

Overview

The M16C/6S group of single-chip microcomputers are built using the high-performance silicon gate CMOS process using a M16C/60 Series CPU core and are packaged in a 64-pin plastic molded LQFP. These single-chip microcomputers operate using sophisticated instructions featuring a high level of instruction efficiency. With 1M bytes of address space, they are capable of executing instructions at high speed. The M16C/6S group are suitable for Power Line Communications (PLC) for home networking included advanced technologies (called IT800) developed by ITRAN Corporations.

Applications

Power Line Communication

-----Table of Contents-----

Overview	1	Timers	77
Memory	9	Timer A	78
Central Processing Unit (CPU)	10	Serial I/O	91
SFR	12	Clock Synchronous serial I/O Mode	100
Reset	18	UART Mode	107
Processor Mode	22	Special Mode	114
Clock Generation Circuit	26	SI/O3 and SI/O4	129
Protection	45	Programmable I/O Ports	134
Interrupts	46	Electrical Characteristics	146
Watchdog Timer	65	Flash Memory Version	157
DMAC	67	IT800AFE (Analog Front End)	180

Specifications written in this manual are believed to be accurate, but are not guaranteed to be entirely free of error. Specifications in this manual may be changed for functional or performance improvements. Please make sure your manual is the latest edition.

Performance Outline

Table 1.1.1 lists performance outline of M16C/6S group.

Table 1.1.1. Performance outline of M16C/6S group

Item		Performance
Number of basic instructions		91 instructions
Shortest instruction execution time		65.1 ns ($f(\text{BCLK}) = 15.36\text{MHz}$, $V_{CC} = 3.0\text{V}$ to 3.6V)
Memory capacity	ROM	96K Byte
	RAM	24K Byte
I/O port		21 ports
Input port	P85	1 bit x 1
Multifunction timer		16 bits x 5 channels (TA0, TA1, TA2, TA3, TA4)
Serial I/O		3 channels (UART0, UART1, UART2) UART, clock synchronous, I ² C bus ¹ (option ²) 2 channels (SI/O3, SI/O4) Clock synchronous SI/O4 is internally connected to IT800
DMAC		2 channels (trigger: 18 sources)
Watchdog timer		15 bits x 1 (with prescaler)
Interrupt		21 internal and 3 external sources, 4 software sources, 7 levels
Clock generation circuit		2 circuits <ul style="list-style-type: none"> • Main clock } (This circuit contains a built-in feedback resistor) • Ring oscillator
Power supply voltage		3.0V to 3.6V
Flash memory	Program/erase voltage	$3.3\text{V} \pm 0.3\text{V}$ ($T_{\text{opr}} = 0$ to 60°C)
	Number of program/erase	100 times
Power consumption		70mA ($V_{CC} = V_{CCA} = 3.3\text{V}$, $f(\text{XIN}) = 5.12\text{MHz}$)
I/O characteristics	I/O withstand voltage	3.6V
	Output current	5mA
Operating ambient temperature		-20 to 85°C
Device configuration		CMOS high performance silicon gate
Package		64-pin plastic mold LQFP

Notes:

1. I²C Bus is a registered trademark of PHILIPS.
2. If you desire this option, please so specify.

Block Diagram and PLC application Outline

Figure 1.1.1 is a block diagram of the M16C/6S group and PLC application Outline.




Figure 1.1.1. Block Diagram of Chip and PLC application Outline

Product List

Tables 1.1.2 list the M16C/6S group product and Figure 1.1.2 shows the type numbers, memory sizes and packages.

Table 1.1.2. Product List (1)

April 2004

Type No.	ROM capacity	RAM capacity	Package type	Remarks
M306S0FA-XXXGP	96K bytes	24K bytes	64P6Q-A	Flash Memory version




Figure 1.1.2. Type No., Memory Size, and Package

Pin Configuration

Figures 1.1.3 show the pin configurations (top view).




Figure 1.1.3. Pin Configuration (Top View)

Table 1.1.3 Pin Description (1)

Pin name	Signal name	I/O type	Function
Vcc, Vss	Power supply input		Apply 3.0V to 3.6V to the Vcc pin. Apply 0V to the Vss pin.
CNVss	CNVss	Input	This is a pin for changing flash memory mode. Usually, connect to Vss.
RESET	Reset input	Input	"L" on this input resets the microcomputer.
XIN	Clock input	Input	These pins are provided for the main clock generating circuit input/output. Connect a ceramic resonator or crystal between the XIN and the XOUT pins. To use an externally derived clock, input it to the XIN pin and leave the XOUT pin open.
XOUT	Clock output	Output	
VCCA	Analog power supply input		This pin is a power supply input of analog circuit. Connect to Vcc.
VSSA	Analog power supply input		This pin is a power supply input of analog circuit. Connect to Vss.
GND/TST	Input for test	Input	This is input pin for test. Connect to Vss.
P15	I/O port P1	Input/output	This is an 1-bit I/O port equivalent to P6. By choosing by the program, it functions as an input pin of INT interrupt.
Vcc25	Power supply		It is the 2.5V power supply pin which is carrying out internal generating. Connect Vcc25 two pins each other and add stabilization capacity.
P60 to P67	I/O port P6	Input/output	This is the 8-bit I/O port of CMOS. It has a direction register for choosing I/O, and is made for every pin in an input port or an output port. An input port can choose the existence of pull-up resistance in a 4-bit unit by the program. It functions as an I/O pin of what is chosen by the program which are therefore UART0 and UART1.
P70, P71, P73, P74, P76	I/O port P7	Input/output	It is an I/O port with a function equivalent to P6 (however, P70 N channel open-drain output). By choosing by the program, it functions as an I/O pin of timers A0 to A3. Moreover, P70 to P73 function also as an I/O pin of UART2.
P80, P81, P83, P84, P85	I/O port P8	Input/output	P80, P81, P83, and P84 are I/O ports with a function equivalent to P6. By choosing by the program, P80 to P81 function as an I/O pin of timer A4, and P83 to P84 functions as an input pin of INT interruption.
	Input port P85	Input	P85 is a port with the common use only for inputs. Pull-up resistance cannot set up this pin. This pin must be pulled-up externally to Vcc.
P90 to P92	I/O port P9	Input/output	It is an I/O port with a function equivalent to P6. It functions as an I/O pin of SI/O3 by choosing by the program.
TS	Output port TS	Output	This is the pin with which IT800 controls ON/OFF of an output to the external transmission AMP at the time of power line communication.
P10	Inner port P10	keep Input	Port for Testing. Please set Direction Register PD1_0 "0" for keeping Input.
P11	Inner port P11	keep Input	Port for Testing. Please set Direction Register PD1_1 "0" for keeping Input.
P40	Inner port P40	Output to IT800	I/O Port for communication between M16C Core and IT800 Modem. Please set Direction Register PD4_0 "1" to Output a signal to IT800. The output signal is connected to TXnRX of IT800 inside of chip.
P41	Inner port P41	Input from IT800	I/O Port for communication between M16C Core and IT800 Modem (Note.1). Please set Direction Register PD4_1 "0" to Input a signal from IT800. The TS signal is input from IT800 inside of chip.
P42	Inner port P42	Output to IT800	I/O Port for communication between M16C Core and IT800 Modem. Please set Direction Register PD4_2 "1" to Output a signal to IT800. The output signal is connected to CLR of IT800 inside of chip.
P53	Inner port P53	Input from IT800	I/O Port for communication between M16C Core and IT800 Modem (Note.1). Please set Direction Register PD5_3 "0" to Input a signal from IT800. The nCD0 signal is input from IT800 inside of chip.
P54	Inner port P54	Input from IT800	I/O Port for communication between M16C Core and IT800 Modem (Note.1). Please set Direction Register PD5_4 "0" to Input a signal from IT800. The nCD1 signal is input from IT800 inside of chip.
P56	Inner port P56	Output to IT800	I/O Port for communication between M16C Core and IT800 Modem. Please set Direction Register PD5_6 "1" to Output a signal to IT800. The output signal is connected to nPHY_RES of IT800 inside of chip.
P82	Inner port P82	Input from IT800	I/O Port for communication between M16C Core and IT800 Modem (Note.1). nINT signal of IT800 is connected to this port inside of chip for carrying out Interrupt function by software.
P95	Inner port P95	Output to IT800	I/O Port for communication between M16C Core and IT800 Modem. This port is connected to DCLK signal of IT800 inside of chip as SI/O4 CLK4 functional Output port by choosing by the program.
P96	Inner port P96	Output to IT800	I/O Port for communication between M16C Core and IT800 Modem. This port is connected to DI signal of IT800 inside of chip as SI/O4 Sout4 functional Output port by choosing by the program.
P97	Inner port P97	Input from IT800	I/O Port for communication between M16C Core and IT800 Modem. This port is connected to DI signal of IT800 inside of chip as SI/O4 Sout4 functional Input port by choosing by the program.

Note 1: In case of Direction Register "1", any signal is not output from M16C to assigned signal of IT800 .
Refer to Programmable I/O Ports pages.

Table 1.1.4 Pin Description (2) (Analog pin)

Pin name	I/O type	Function
PRE-BOUT	Output	This is a pre-amp buffer output.
PRE-INN	Input	This is a pre-amp differential signal input.
PRE-INP	Input	This is a pre-amp differential signal input.
VREF	Input	This is the reference voltage input of amplifier common to channels 1, 2, and 3.
VDCCN	Input	This is a pin for a test. Usually, please carry out a pull-up.
AMP1-IN	Input	This is a channel 1 amplifier input.
AMP1-OUT	Output	This is a channel 1 amplifier output.
AMP2-IN	Input	This is a channel 2 amplifier input.
AMP2-OUT	Output	This is a channel 2 amplifier output.
AMP3-IN	Input	This is a channel 3 amplifier input.
AMP3-OUT	Output	This is a channel 3 amplifier output.
CHI-INP	Input	This is a channel 1 comparator differential input.
CHI-INN	Input	This is a channel 1 comparator differential input.
FB1	Output	This is a channel 1 comparator feedback output.
CH2-INP	Input	This is a channel 2 comparator differential input.
CH2-INN	Input	This is a channel 2 comparator differential input.
FB2	Output	This is a channel 2 comparator feedback output.
CH3-INP	Input	This is a channel 3 comparator differential input.
CH3-INN	Input	This is a channel 3 comparator differential input.
FB3	Output	This is a channel 3 comparator feedback output.
IOUTC	Output	This is the differential current output of DAC.
IOUT	Output	This is the differential current output of DAC.
REXT	Input	This is for external reference resistor of DAC.
IFLT	Input	This is the pin for low path filters of PLL.

Memory

Figure 1.2.1 is a memory map of the M16C/6S group. The address space extends the 1M bytes from address 00000₁₆ to FFFFF₁₆.

The internal ROM is allocated in a lower address direction beginning with address FFFFF₁₆. For example, a 96-Kbyte internal ROM is allocated to the addresses from E8000₁₆ to FFFFF₁₆.

The fixed interrupt vector table is allocated to the addresses from FFFDC₁₆ to FFFFF₁₆. Therefore, store the start address of each interrupt routine here.

The internal RAM is allocated in an upper address direction beginning with address 00400₁₆. For example, a 24-Kbytes internal RAM is allocated to the addresses from 00400₁₆ to 063FF₁₆. In addition to storing data, the internal RAM also stores the stack used when calling subroutines and when interrupts are generated.

The SRF is allocated to the addresses from 00000₁₆ to 003FF₁₆. Peripheral function control registers are located here. Of the SFR, any area which has no functions allocated is reserved for future use and cannot be used by users.

The special page vector table is allocated to the addresses from FFE00₁₆ to FFFDB₁₆. This vector is used by the JMPS or JSRS instruction. For details, refer to the “M16C/60 and M16C/20 Series Software Manual.”




Figure 1.2.1. Memory Map

Central Processing Unit (CPU)

Figure 1.3.1 shows the CPU registers. The CPU has 13 registers. Of these, R0, R1, R2, R3, A0, A1 and FB comprise a register bank. There are two register banks.




Figure 1.3.1. Central Processing Unit Register

(1) Data Registers (R0, R1, R2 and R3)

The R0 register consists of 16 bits, and is used mainly for transfers and arithmetic/logic operations. R1 to R3 are the same as R0.

The R0 register can be separated between high (R0H) and low (R0L) for use as two 8-bit data registers. R1H and R1L are the same as R0H and R0L. Conversely, R2 and R0 can be combined for use as a 32-bit data register (R2R0). R3R1 is the same as R2R0.

(2) Address Registers (A0 and A1)

The register A0 consists of 16 bits, and is used for address register indirect addressing and address register relative addressing. They also are used for transfers and logic/logic operations. A1 is the same as A0.

In some instructions, registers A1 and A0 can be combined for use as a 32-bit address register (A1A0).

(3) Frame Base Register (FB)

FB is configured with 16 bits, and is used for FB relative addressing.

(4) Interrupt Table Register (INTB)

INTB is configured with 20 bits, indicating the start address of an interrupt vector table.

(5) Program Counter (PC)

PC is configured with 20 bits, indicating the address of an instruction to be executed.

(6) User Stack Pointer (USP) and Interrupt Stack Pointer (ISP)

Stack pointer (SP) comes in two types: USP and ISP, each configured with 16 bits.

Your desired type of stack pointer (USP or ISP) can be selected by the U flag of FLG.

(7) Static Base Register (SB)

SB is configured with 16 bits, and is used for SB relative addressing.

(8) Flag Register (FLG)

FLG consists of 11 bits, indicating the CPU status.

- **Carry Flag (C Flag)**

This flag retains a carry, borrow, or shift-out bit that has occurred in the arithmetic/logic unit.

- **Debug Flag (D Flag)**

The D flag is used exclusively for debugging purpose. During normal use, it must be set to "0".

- **Zero Flag (Z Flag)**

This flag is set to "1" when an arithmetic operation resulted in 0; otherwise, it is "0".

- **Sign Flag (S Flag)**

This flag is set to "1" when an arithmetic operation resulted in a negative value; otherwise, it is "0".

- **Register Bank Select Flag (B Flag)**

Register bank 0 is selected when this flag is "0"; register bank 1 is selected when this flag is "1".

- **Overflow Flag (O Flag)**

This flag is set to "1" when the operation resulted in an overflow; otherwise, it is "0".

- **Interrupt Enable Flag (I Flag)**

This flag enables a maskable interrupt.

Maskable interrupts are disabled when the I flag is "0", and are enabled when the I flag is "1". The I flag is cleared to "0" when the interrupt request is accepted.

- **Stack Pointer Select Flag (U Flag)**

ISP is selected when the U flag is "0"; USP is selected when the U flag is "1".

The U flag is cleared to "0" when a hardware interrupt request is accepted or an INT instruction for software interrupt Nos. 0 to 31 is executed.

- **Processor Interrupt Priority Level (IPL)**

IPL is configured with three bits, for specification of up to eight processor interrupt priority levels from level 0 to level 7.

If a requested interrupt has priority greater than IPL, the interrupt is enabled.

- **Reserved Area**

When write to this bit, write "0". When read, its content is indeterminate.

SFR

Address	Register	Symbol	After reset
0000 ₁₆			
0001 ₁₆			
0002 ₁₆			
0003 ₁₆			
0004 ₁₆	Processor mode register 0 (Note 2)	PM0	00000000z(CNVss pin is "L")
0005 ₁₆	Processor mode register 1	PM1	000010002
0006 ₁₆	System clock control register 0	CM0	010010002
0007 ₁₆	System clock control register 1	CM1	001000002
0008 ₁₆			
0009 ₁₆	Address match interrupt enable register	AIER	XXXXXX002
000A ₁₆	Protect register	PRCR	XX0000002
000B ₁₆			
000C ₁₆	Oscillation stop detection register (Note 3)	CM2	0000X0002
000D ₁₆			
000E ₁₆	Watchdog timer start register	WDTS	??16
000F ₁₆	Watchdog timer control register	WDC	00?????2
0010 ₁₆	Address match interrupt register 0	RMAD0	0016
0011 ₁₆			0016
0012 ₁₆			X016
0013 ₁₆			
0014 ₁₆	Address match interrupt register 1	RMAD1	0016
0015 ₁₆			0016
0016 ₁₆			X016
0017 ₁₆			
0018 ₁₆			
0019 ₁₆			
001A ₁₆			
001B ₁₆			
001C ₁₆			
001D ₁₆			
001E ₁₆	Processor mode register 2	PM2	XXX000002
001F ₁₆			
0020 ₁₆	DMA0 source pointer	SAR0	??16
0021 ₁₆			??16
0022 ₁₆			X?16
0023 ₁₆			
0024 ₁₆	DMA0 destination pointer	DAR0	??16
0025 ₁₆			??16
0026 ₁₆			X?16
0027 ₁₆			
0028 ₁₆	DMA0 transfer counter	TCR0	??16
0029 ₁₆			??16
002A ₁₆			
002B ₁₆			
002C ₁₆	DMA0 control register	DM0CON	00000?002
002D ₁₆			
002E ₁₆			
002F ₁₆			
0030 ₁₆	DMA1 source pointer	SAR1	??16
0031 ₁₆			??16
0032 ₁₆			X?16
0033 ₁₆			
0034 ₁₆	DMA1 destination pointer	DAR1	??16
0035 ₁₆			??16
0036 ₁₆			X?16
0037 ₁₆			
0038 ₁₆	DMA1 transfer counter	TCR1	??16
0039 ₁₆			??16
003A ₁₆			
003B ₁₆			
003C ₁₆	DMA1 control register	DM1CON	00000?002
003D ₁₆			
003E ₁₆			
003F ₁₆			

Note 1: The blank areas are reserved and cannot be used by users.

Note 2: The PM00 and PM01 bits do not change at software reset, watchdog timer reset and oscillation stop detection reset.

Note 3: The CM20, CM21, and CM27 bits do not change at oscillation stop detection reset.

X : Nothing is mapped to this bit

? : Undefined

Address	Register	Symbol	After reset
0040 ₁₆			
0041 ₁₆			
0042 ₁₆			
0043 ₁₆			
0044 ₁₆	INT3 interrupt control register	INT3IC	XX00?0002
0045 ₁₆			
0046 ₁₆	UART1 BUS collision detection interrupt control register	U1BCNIC	XXXX?0002
0047 ₁₆	UART0 BUS collision detection interrupt control register	U0BCNIC	XXXX?0002
0048 ₁₆	SI/O4 interrupt control register (S4IC)	S4IC	XX00?0002
0049 ₁₆	SI/O3 interrupt control register	S3IC	XX00?0002
004A ₁₆	UART2 Bus collision detection interrupt control register	BCNIC	XXXX?0002
004B ₁₆	DMA0 interrupt control register	DM0IC	XXXX?0002
004C ₁₆	DMA1 interrupt control register	DM1IC	XXXX?0002
004D ₁₆			
004E ₁₆			
004F ₁₆	UART2 transmit interrupt control register	S2TIC	XXXX?0002
0050 ₁₆	UART2 receive interrupt control register	S2RIC	XXXX?0002
0051 ₁₆	UART0 transmit interrupt control register	S0TIC	XXXX?0002
0052 ₁₆	UART0 receive interrupt control register	S0RIC	XXXX?0002
0053 ₁₆	UART1 transmit interrupt control register	S1TIC	XXXX?0002
0054 ₁₆	UART1 receive interrupt control register	S1RIC	XXXX?0002
0055 ₁₆	Timer A0 interrupt control register	TA0IC	XXXX?0002
0056 ₁₆	Timer A1 interrupt control register	TA1IC	XXXX?0002
0057 ₁₆	Timer A2 interrupt control register	TA2IC	XXXX?0002
0058 ₁₆	Timer A3 interrupt control register	TA3IC	XXXX?0002
0059 ₁₆	Timer A4 interrupt control register	TA4IC	XXXX?0002
005A ₁₆			
005B ₁₆			
005C ₁₆			
005D ₁₆	INT0 interrupt control register	INT0IC	XX00?0002
005E ₁₆	INT1 interrupt control register	INT1IC	XX00?0002
005F ₁₆	INT2 interrupt control register	INT2IC	XX00?0002
0060 ₁₆			
0061 ₁₆			
0062 ₁₆			
0063 ₁₆			
0064 ₁₆			
0065 ₁₆			
0066 ₁₆			
0067 ₁₆			
0068 ₁₆			
0069 ₁₆			
006A ₁₆			
006B ₁₆			
006C ₁₆			
006D ₁₆			
006E ₁₆			
006F ₁₆			
0070 ₁₆			
0071 ₁₆			
0072 ₁₆			
0073 ₁₆			
0074 ₁₆			
0075 ₁₆			
0076 ₁₆			
0077 ₁₆			
0078 ₁₆			
0079 ₁₆			
007A ₁₆			
007B ₁₆			
007C ₁₆			
007D ₁₆			
007E ₁₆			
007F ₁₆			

Note :The blank areas are reserved and cannot be used by users.

X : Nothing is mapped to this bit

? : Undefined

Address	Register	Symbol	After reset
0080 ₁₆			
0081 ₁₆			
0082 ₁₆			
0083 ₁₆			
0084 ₁₆			
0085 ₁₆			
0086 ₁₆			
~			~
01B0 ₁₆			
01B1 ₁₆			
01B2 ₁₆			
01B3 ₁₆			
01B4 ₁₆			
01B5 ₁₆	Flash memory control register 1 (Note 2)	FMR1	0?00??0?2
01B6 ₁₆			
01B7 ₁₆	Flash memory control register 0 (Note 2)	FMR0	??0000012
01B8 ₁₆	Address match interrupt register 2	RMAD2	00 ₁₆
01B9 ₁₆			00 ₁₆
01BA ₁₆			X0 ₁₆
01BB ₁₆	Address match interrupt enable register 2	AIER2	XXXXXX002
01BC ₁₆	Address match interrupt register 3	RMAD3	00 ₁₆
01BD ₁₆			00 ₁₆
01BE ₁₆			X0 ₁₆
01BF ₁₆			
~			~
0250 ₁₆			
0251 ₁₆			
0252 ₁₆			
0253 ₁₆			
0254 ₁₆			
0255 ₁₆			
0256 ₁₆			
0257 ₁₆			
0258 ₁₆			
0259 ₁₆			
025A ₁₆			
025B ₁₆			
025C ₁₆			
025D ₁₆			
025E ₁₆	Peripheral clock select register	PCLKR	000000112
025F ₁₆			
~			~
0330 ₁₆			
0331 ₁₆			
0332 ₁₆			
0333 ₁₆			
0334 ₁₆			
0335 ₁₆			
0336 ₁₆			
0337 ₁₆			
0338 ₁₆			
0339 ₁₆			
033A ₁₆			
033B ₁₆			
033C ₁₆			
033D ₁₆			
033E ₁₆			
033F ₁₆			

Note 1: The blank areas are reserved and cannot be used by users.

Note 2: This register is included in the flash memory version.

X : Nothing is mapped to this bit

? : Undefined

Address	Register	Symbol	After reset
0340 ₁₆			
0341 ₁₆			
0342 ₁₆			
0343 ₁₆			
0344 ₁₆			
0345 ₁₆			
0346 ₁₆			
0347 ₁₆			
0348 ₁₆			
0349 ₁₆			
034A ₁₆			
034B ₁₆			
034C ₁₆			
034D ₁₆			
034E ₁₆			
034F ₁₆			
0350 ₁₆			
0351 ₁₆			
0352 ₁₆			
0353 ₁₆			
0354 ₁₆			
0355 ₁₆			
0356 ₁₆			
0357 ₁₆			
0358 ₁₆			
0359 ₁₆			
035A ₁₆			
035B ₁₆			
035C ₁₆			
035D ₁₆			
035E ₁₆	Interrupt cause select register 2	IFSR2A	00XXXXXX ₂
035F ₁₆	Interrupt cause select register	IFSR	00 ₁₆
0360 ₁₆	SI/O3 transmit/receive register	S3TRR	?? ₁₆
0361 ₁₆			
0362 ₁₆	SI/O3 control register	S3C	01000000 ₂
0363 ₁₆	SI/O3 bit rate generator	S3BRG	?? ₁₆
0364 ₁₆	SI/O4 transmit/receive register	S4TRR	?? ₁₆
0365 ₁₆			
0366 ₁₆	SI/O4 control register	S4C	01000000 ₂
0367 ₁₆	SI/O4 bit rate generator	S4BRG	?? ₁₆
0368 ₁₆			
0369 ₁₆			
036A ₁₆			
036B ₁₆			
036C ₁₆	UART0 special mode register 4	U0SMR4	00 ₁₆
036D ₁₆	UART0 special mode register 3	U0SMR3	000X0X0X ₂
036E ₁₆	UART0 special mode register 2	U0SMR2	X0000000 ₂
036F ₁₆	UART0 special mode register	U0SMR	X0000000 ₂
0370 ₁₆	UART1 special mode register 4	U1SMR4	00 ₁₆
0371 ₁₆	UART1 special mode register 3	U1SMR3	000X0X0X ₂
0372 ₁₆	UART1 special mode register 2	U1SMR2	X0000000 ₂
0373 ₁₆	UART1 special mode register	U1SMR	X0000000 ₂
0374 ₁₆	UART2 special mode register 4	U2SMR4	00 ₁₆
0375 ₁₆	UART2 special mode register 3	U2SMR3	000X0X0X ₂
0376 ₁₆	UART2 special mode register 2	U2SMR2	X0000000 ₂
0377 ₁₆	UART2 special mode register	U2SMR	X0000000 ₂
0378 ₁₆	UART2 transmit/receive mode register	U2MR	00 ₁₆
0379 ₁₆	UART2 bit rate generator	U2BRG	?? ₁₆
037A ₁₆	UART2 transmit buffer register	U2TB	??????? ₂
037B ₁₆			XXXXXXXX? ₂
037C ₁₆	UART2 transmit/receive control register 0	U2C0	00001000 ₂
037D ₁₆	UART2 transmit/receive control register 1	U2C1	00000010 ₂
037E ₁₆	UART2 receive buffer register	U2RB	??????? ₂
037F ₁₆			?????XX ₂

Note : The blank areas are reserved and cannot be used by users.

X : Nothing is mapped to this bit

? : Undefined

Address	Register	Symbol	After reset
0380 ₁₆	Count start flag	TABSR	00 ₁₆
0381 ₁₆			
0382 ₁₆	One-shot start flag	ONSF	00 ₁₆
0383 ₁₆	Trigger select register	TRGSR	00 ₁₆
0384 ₁₆	Up-down flag	UDF	00 ₁₆
0385 ₁₆			
0386 ₁₆	Timer A0 register	TA0	?? ₁₆
0387 ₁₆			?? ₁₆
0388 ₁₆	Timer A1 register	TA1	?? ₁₆
0389 ₁₆			?? ₁₆
038A ₁₆	Timer A2 register	TA2	?? ₁₆
038B ₁₆			?? ₁₆
038C ₁₆	Timer A3 register	TA3	?? ₁₆
038D ₁₆			?? ₁₆
038E ₁₆	Timer A4 register	TA4	?? ₁₆
038F ₁₆			?? ₁₆
0390 ₁₆			
0391 ₁₆			
0392 ₁₆			
0393 ₁₆			
0394 ₁₆			
0395 ₁₆			
0396 ₁₆	Timer A0 mode register	TA0MR	00 ₁₆
0397 ₁₆	Timer A1 mode register	TA1MR	00 ₁₆
0398 ₁₆	Timer A2 mode register	TA2MR	00 ₁₆
0399 ₁₆	Timer A3 mode register	TA3MR	00 ₁₆
039A ₁₆	Timer A4 mode register	TA4MR	00 ₁₆
039B ₁₆			
039C ₁₆			
039D ₁₆			
039E ₁₆			
039F ₁₆			
03A0 ₁₆	UART0 transmit/receive mode register	U0MR	00 ₁₆
03A1 ₁₆	UART0 bit rate generator	U0BRG	?? ₁₆
03A2 ₁₆	UART0 transmit buffer register	U0TB	???????2
03A3 ₁₆			XXXXXXXX?2
03A4 ₁₆	UART0 transmit/receive control register 0	U0C0	000010002
03A5 ₁₆	UART0 transmit/receive control register 1	U0C1	000000102
03A6 ₁₆	UART0 receive buffer register	U0RB	???????2
03A7 ₁₆			?????XX?2
03A8 ₁₆	UART1 transmit/receive mode register	U1MR	00 ₁₆
03A9 ₁₆	UART1 bit rate generator	U1BRG	?? ₁₆
03AA ₁₆	UART1 transmit buffer register	U1TB	???????2
03AB ₁₆			XXXXXXXX?2
03AC ₁₆	UART1 transmit/receive control register 0	U1C0	000010002
03AD ₁₆	UART1 transmit/receive control register 1	U1C1	000000102
03AE ₁₆	UART1 receive buffer register	U1RB	???????2
03AF ₁₆			?????XX?2
03B0 ₁₆	UART transmit/receive control register 2	UCON	X00000002
03B1 ₁₆			
03B2 ₁₆			
03B3 ₁₆			
03B4 ₁₆			
03B5 ₁₆			
03B6 ₁₆			
03B7 ₁₆			
03B8 ₁₆	DMA0 request cause select register	DM0SL	00 ₁₆
03B9 ₁₆			
03BA ₁₆	DMA1 request cause select register	DM1SL	00 ₁₆
03BB ₁₆			
03BC ₁₆			
03BD ₁₆			
03BE ₁₆			
03BF ₁₆			

Note : The blank areas are reserved and cannot be used by users.

X : Nothing is mapped to this bit

? : Undefined

Address	Register	Symbol	After reset
03C0 ₁₆			
03C1 ₁₆			
03C2 ₁₆			
03C3 ₁₆			
03C4 ₁₆			
03C5 ₁₆			
03C6 ₁₆			
03C7 ₁₆			
03C8 ₁₆			
03C9 ₁₆			
03CA ₁₆			
03CB ₁₆			
03CC ₁₆			
03CD ₁₆			
03CE ₁₆			
03CF ₁₆			
03D0 ₁₆			
03D1 ₁₆			
03D2 ₁₆			
03D3 ₁₆			
03D4 ₁₆			
03D5 ₁₆			
03D6 ₁₆			
03D7 ₁₆			
03D8 ₁₆			
03D9 ₁₆			
03DA ₁₆			
03DB ₁₆			
03DC ₁₆			
03DD ₁₆			
03DE ₁₆			
03DF ₁₆			
03E0 ₁₆			
03E1 ₁₆	Port P1 register	P1	?? ₁₆
03E2 ₁₆			
03E3 ₁₆	Port P1 direction register	PD1	00 ₁₆
03E4 ₁₆			
03E5 ₁₆			
03E6 ₁₆			
03E7 ₁₆			
03E8 ₁₆	Port P4 register	P4	?? ₁₆
03E9 ₁₆	Port P5 register	P5	?? ₁₆
03EA ₁₆	Port P4 direction register	PD4	00 ₁₆
03EB ₁₆	Port P5 direction register	PD5	00 ₁₆
03EC ₁₆	Port P6 register	P6	?? ₁₆
03ED ₁₆	Port P7 register	P7	?? ₁₆
03EE ₁₆	Port P6 direction register	PD6	00 ₁₆
03EF ₁₆	Port P7 direction register	PD7	00 ₁₆
03F0 ₁₆	Port P8 register	P8	?? ₁₆
03F1 ₁₆	Port P9 register	P9	?? ₁₆
03F2 ₁₆	Port P8 direction register	PD8	00X00000 ₂
03F3 ₁₆	Port P9 direction register	PD9	00 ₁₆
03F4 ₁₆			
03F5 ₁₆			
03F6 ₁₆			
03F7 ₁₆			
03F8 ₁₆			
03F9 ₁₆			
03FA ₁₆			
03FB ₁₆			
03FC ₁₆	Pull-up control register 0	PUR0	00 ₁₆
03FD ₁₆	Pull-up control register 1	PUR1	00000000 ₂
03FE ₁₆	Pull-up control register 2	PUR2	00 ₁₆
03FF ₁₆	Port control register	PCR	00 ₁₆

Note 1: The blank areas are reserved and cannot be used by users.

X : Nothing is mapped to this bit

? : Undefined

Reset

There are four types of resets: a hardware reset, a software reset, an watchdog timer reset, and an oscillation stop detection reset.

Hardware Reset

A reset is applied using the $\overline{\text{RESET}}$ pin. When an “L” signal is applied to the $\overline{\text{RESET}}$ pin while the power supply voltage is within the recommended operating condition, the pins are initialized (see Table 1.5.1). The oscillation circuit is initialized and the main clock starts oscillating. When the input level at the $\overline{\text{RESET}}$ pin is released from “L” to “H”, the CPU and SFR are initialized, and the program is executed starting from the address indicated by the reset vector. The internal RAM is not initialized. If the $\overline{\text{RESET}}$ pin is pulled “L” while writing to the internal RAM, the internal RAM becomes indeterminate.

Figure 1.5.1 shows the example reset circuit. Figure 1.5.2 shows the reset sequence. Table 1.5.1 shows the statuses of the other pins while the $\overline{\text{RESET}}$ pin is “L”. Figure 1.5.3 shows the CPU register status after reset. Refer to “SFR” for SFR status after reset.

1. When the power supply is stable

- (1) Apply an “L” signal to the $\overline{\text{RESET}}$ pin.
- (2) Supply a clock for 20 cycles or more to the XIN pin.
- (3) Apply an “H” signal to the $\overline{\text{RESET}}$ pin.

2. Power on

- (1) Apply an “L” signal to the $\overline{\text{RESET}}$ pin.
- (2) Let the power supply voltage increase until it meets the recommended operating condition.
- (3) Wait $t_d(\text{P-R})$ or more until the internal power supply stabilizes.
- (4) Supply a clock for 20 cycles or more to the XIN pin.
- (5) Apply an “H” signal to the $\overline{\text{RESET}}$ pin.

Software Reset

When the PM03 bit in the PM0 register is set to “1” (microcomputer reset), the microcomputer has its pins, CPU, and SFR initialized. Then the program is executed starting from the address indicated by the reset vector.

Select the main clock for the CPU clock source, and set the PM03 bit to “1” with main clock oscillation satisfactorily stable.

At software reset, some SFR's are not initialized. Refer to “SFR”. Also, since the PM01 to PM00 bits in the PM0 register are not initialized, the processor mode remains unchanged.




Figure 1.5.1. Example Reset Circuit

Watchdog Timer Reset

Where the PM12 bit in the PM1 register is “1” (reset when watchdog timer underflows), the microcomputer initializes its pins, CPU and SFR if the watchdog timer underflows. Then the program is executed starting from the address indicated by the reset vector.

At watchdog timer reset, some SFR's are not initialized. Refer to “SFR”. Also, since the PM01 to PM00 bits in the PM0 register are not initialized, the processor mode remains unchanged.

Oscillation Stop Detection Reset

Where the CM27 bit in the CM2 register is “0” (reset at oscillation stop detection), the microcomputer initializes its pins, CPU and SFR, coming to a halt if it detects main clock oscillation circuit stop. Refer to the section “oscillation stop, re-oscillation detection function”.

At oscillation stop detection reset, some SFR's are not initialized. Refer to the section “SFR”. Also, since the PM01 to PM00 bits in the PM0 register are not initialized, the processor mode remains unchanged.



**Figure 1.5.2. Reset Sequence**

Table 1.5.1. Pin Status When $\overline{\text{RESET}}$ Pin Level is “L”

Pin name	Status
	CNVss = Vss
P15, P60 to P67, P70, P71, P73, P74, P76, P80, P81, P83, P84, P85, P90 to P92, TS	Input port

**Figure 1.5.3. CPU Register Status After Rreset**

Processor Mode

(1) Setting Processor Modes

Processor mode is available only: single-chip mode.

Processor mode is set by using the CNVSS pin and the PM01 to PM00 bits in the PM0 register.

Table 1.6.2 shows the processor mode after hardware reset. Table 1.6.3 shows the PM01 to PM00 bit set values and processor modes. For setting Single-chip mode, CNVSS should be kept Vss level. And PM01 to PM00 of PM0 register should be set "00."

Table 1.6.1. Processor Mode After Hardware Reset

CNVSS pin input level	Processor mode
Vss	Single-chip mode
Vcc	Flash Memory Mode

Table 1.6.2. PM01 to PM00 Bits Set Values and Processor Modes

PM01 to PM00 bits	Processor modes
002	Single-chip mode
012	
102	Must not be set
112	

Figure 1.6.4 show the memory map in single chip mode.

(3) Setting PLC Mode

PLC mode is simply set by putting P15 High level during RESET.





Figure 1.6.1. PLC mode by P15 simply setting

Table 1.6.3.

	min	typ	max
TR	40us	—	—
Tset up	5us	—	—
THOLD	5us	—	—

Processor mode register 0 (Note 1)



Symbol
PM0

Address
0004₁₆

After reset (Note 2)
00000000₂ (CNVss pin = "L")
00000011₂ (CNVss pin = "H")

Bit symbol	Bit name	Function	RW
PM00	Processor mode bit (Note 2)	b1 b0 0 0: Single-chip mode 0 1: Must not be set 1 0: Must not be set 1 1: Must not be set	RW
PM01			RW
—— (b2)	Nothing is assigned. When write, set to “0”. When read, its content is indeterminate.		——
PM03	Software reset bit	Setting this bit to “1” resets the microcomputer. When read, its content is “0”.	RW
—— (b7-b4)	Nothing is assigned. When write, set to “0”. When read, their contents are indeterminate.		——

Note 1: Write to this register after setting the PRC1 bit in the PRCR register to "1" (write enable).

Note 2: The PM01 to PM00 bits do not change at software reset, watchdog timer reset and oscillation stop detection reset.

Figure 1.6.2. PM0 Register

Processor mode register 1 (Note 1)



Symbol
PM1

Address
0005₁₆

After reset
0X001000₂

Bit symbol	Bit name	Function	RW
(b0)	Reserved bit	Should be set to "0".	RW
(b2)	Nothing is assigned. When write, set to "0". When read, its content is indeterminate.		—
PM12	Watchdog timer function select bit	0 : Watchdog timer interrupt 1 : Watchdog timer reset (Note 2)	RW
PM13	Internal reserved area expansion bit	Should be set to "1".	RW
(b5-b4)	Nothing is assigned. When write, set to "0". When read, its content is indeterminate.		—
(b6)	Reserved bit	Should be set to "0".	RW
PM17	Wait bit (Note 3)	0 : No wait state 1 : With wait state (1 wait)	RW

Note 1: Write to this register after setting the PRC1 bit in the PRCR register to "1" (write enable).

Note 2: PM12 bit is set to "1" by writing a "1" in a program. (Writing a "0" has no effect.)

Note 3: When PM17 bit is set to "1" (with wait state), one wait state is inserted when accessing the internal RAM, internal ROM, or an external area.

Figure 1.6.3. PM1 Register




Figure 1.6.4. Memory Map in Single Chip Mode

Clock Generation Circuit

The clock generation circuit contains two oscillator circuits as follows:

- (1) Main clock oscillation circuit
- (2) Ring oscillator (oscillation stop detect function)

Table 1.7.1 lists the clock generation circuit specifications. Figure 1.7.1 shows the clock generation circuit. Figures 1.7.2 to 1.7.6 show the clock-related registers.

Table 1.7.1. Clock Generation Circuit Specifications

Item	Main clock oscillation circuit	Ring oscillator
Use of clock	<ul style="list-style-type: none"> • CPU clock source • Peripheral function clock source 	<ul style="list-style-type: none"> • CPU clock source • Peripheral function clock source
Clock frequency	5.12 MHz	About 1 MHz
Usable oscillator	<ul style="list-style-type: none"> • Crystal oscillator (Note 1) 	_____
Pins to connect oscillator	XIN, XOUT	_____
Oscillation stop, restart function	No	Presence
Oscillator status after reset	Oscillating	Stopped
Other	Externally derived clock can be input	_____

Note. Operating frequency must be 5.12 MHz, overall accuracy must be less than 150 ppm.





Figure 1.7.1. Clock Generation Circuit

System clock control register 0 (Notes 1 and 4)



Symbol
CM0

Address
0006₁₆

After reset
01001000₂

Bit symbol	Bit name	Function	RW
(b1-b0)	Nothing is assigned. When write, set to "0". When read, its content is indeterminate.		—
CM02	WAIT peripheral function clock stop bit (Note 3)	0 : Do not stop peripheral function clock in wait mode 1 : Stop peripheral function clock in wait mode	RW
(b4-b3)	Nothing is assigned. When write, set to "0". When read, its content is indeterminate.		—
(b5)	Reserved bit	Should be set to "0".	RW
CM06	Main clock division select bit 0 (Notes 5, 13)	0 : CM16 and CM17 valid 1 : Division by 8 mode	RW
(b7)	Reserved bit	Should be set to "0".	RW

Note 1: Write to this register after setting the PRC0 bit of PRCR register to "1" (write enable).

Note 2: When entering stop mode from high or middle speed mode, ring oscillator mode or ring oscillator low power mode, the CM06 bit is set to "1" (divide-by-8 mode).

Note 3: When the PM21 bit of PM2 register is set to "1" (clock modification disable), writing to the CM02 bits has no effect.

Note 4: To use the main clock as the clock source for the CPU clock, follow the procedure below.

- (1) Wait until td(M-L) elapses or the main clock oscillation stabilizes, whichever is longer.
- (2) Set the CM21 to "0".

Note 5: During ring oscillator low power dissipation mode, the divide-by-n value can be selected using the CM06 and CM17 to CM16 bits. To return to high or middle speed mode, however, set the CM06 bit to "1", before selecting the desired mode.

Figure 1.7.2. CM0 Register




Figure 1.7.3. CM1 Register

Oscillation stop detection register (Note 1)

<div><div><div>b7</div><div>b6</div><div>b5</div><div>b4</div><div>b3</div><div>b2</div><div>b1</div><div>b0</div></div><div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div><div><div><div>X</div><div>0</div><div>0</div><div></div><div></div><div></div><div></div><div></div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div></div></div></div></div>								Symbol CM2	Address 000C16	After reset 0X0000002(Note 10)	
<div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div></div></div></div>								Bit symbol	Bit name	Function	RW
<div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div></div></div></div>								CM20	Oscillation stop, re-oscillation detection bit (Notes 7, 8, 9, 10)	0: Oscillation stop, re-oscillation detection function disabled 1: Oscillation stop, re-oscillation detection function enabled	RW
<div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div></div></div></div>								CM21	System clock select bit 2 (Notes 2, 3, 6, 10)	0: Main clock (Ring oscillator turned off) 1: Ring oscillator clock (Ring oscillator oscillating)	RW
<div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div></div></div></div>								CM22	Oscillation stop, re-oscillation detection flag (Note 4)	0: Main clock stop, re-oscillation not detected 1: Main clock stop, re-oscillation detected	RW
<div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div></div></div></div>								CM23	XIN monitor flag (Note 5)	0: Main clock oscillating 1: Main clock turned off	RO
<div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div></div></div></div>								— (b5-b4)	Reserved bit	Must set to “0”	RW
<div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div></div></div></div>								— (b6)	Nothing is assigned. When write, set to “0”. When read, its content is indeterminate.		—
<div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div></div></div></div>								CM27	Operation select bit (when an oscillation stop, re-oscillation is detected) (Note 10)	0: Oscillation stop detection reset 1: Oscillation stop, re-oscillation detection interrupt	RW

Note 1: Write to this register after setting the PRC0 bit of PRCR register to "1" (write enable).

Note 2: When the CM20 bit is "1" (oscillation stop, re-oscillation detection function enabled), the CM27 bit is "1" (oscillation stop, re-oscillation detection interrupt), and the CPU clock source is the main clock, the CM21 bit is set to "1" (ring oscillator clock) if the main clock stop is detected.

Note 3: If the CM20 bit is "1" and the CM23 bit is "1" (main clock turned off), do not set the CM21 bit to "0".

Note 4: This bit becomes "1" at main clock stop detection and main clock re-oscillation detection. When this bit changes from "0" to "1", there arise oscillation stop, re-oscillation detection interrupt. Use this register to discriminate the causes for oscillation stop, re-oscillation detection interrupt and watchdog timer interrupt in the interrupt processing program. By writing "0" in the program, this bit becomes "0". (Even when "1" is written in the program, no change is identified for the bit. Also, this bit is not set to "0" where there occur oscillation stop, re-oscillation detection interrupt.) When the CM22 bit is "1", no oscillation stop, re-oscillation detection interrupt occur even if oscillation stop or re-oscillation is detected.

Note 5: Read the CM23 bit in an oscillation stop, re-oscillation detection interrupt handling routine to determine the main clock status.

Note 6: Effective when the CM07 bit of CM0 register is "0".

Note 7: When the PM21 bit of PM2 register is "1" (clock modification disabled), writing to the CM20 bit has no effect.

Note 8: Set the CM20 bit to "0" (disable) before entering stop mode. After exiting stop mode, set the CM20 bit back to "1" (enable).

Note 9: Set the CM20 bit to "0" (disable) before setting the CM05 bit of CM0 register.

Note 10: The CM20, CM21 and CM27 bits do not change at oscillation stop detection reset.

Figure 1.7.4. CM2 Register

Peripheral clock select register (Note)

b7	b6	b5	b4	b3	b2	b1	b0
0	0	0	0	0	0		

Symbol
PCLKRAddress
025E₁₆When reset
00000011₂

Bit symbol	Bit name	Function	RW
PCLK0	Timers A, B clock select bit (Clock source for the timers A, B, and the dead time timer)	0 : f ₂ 1 : f ₁	RW
PCLK1	SI/O clock select bit (Clock source for UART0 to UART2, SI/O3, SI/O4)	0 : f ₂ SI/O 1 : f ₁ SI/O	RW
— (b7-b2)	Reserved bit	Must set to "0"	RW

Note: Write to this register after setting the PRC0 bit of PRCR register to "1" (write enable).

Processor mode register 2 (Note 1)

b7	b6	b5	b4	b3	b2	b1	b0
×	×	×	0	0			×

Symbol
PM2Address
001E₁₆After reset
XXX00000₂

Bit symbol	Bit name	Function	RW
— (b0)	Nothing is assigned. When write, set to "0". When read, its content is indeterminate.		—
PM21	System clock protective bit (Note 2, Note 3)	0 : Clock is protected by PRCR register 1 : Clock modification disabled	RW
PM22	WDT count source protective bit (Note 2, Note 4)	0 : CPU clock is used for the watchdog timer count source 1 : Ring oscillator clock is used for the watchdog timer count source	RW
— (b4-b3)	Reserved bit	Must set to "0"	RW
— (b7-b5)	Nothing is assigned. When write, set to "0". When read, its content is indeterminate.		—

Note 1: Write to this register after setting the PRC1 bit of PRCR register to "1" (write enable).

Note 2: Once this bit is set to "1", it cannot be cleared to "0" in a program.

Note 3: Setting the PM21 bit to "1" results in the following conditions:

- The BCLK is not halted by executing the WAIT instruction.
- Writing to the following bits has no effect.
 - CM02 bit of CM0 register
 - CM05 bit of CM0 register (main clock is not halted)
 - CM07 bit of CM0 register
 - CM10 bit of CM1 register (stop mode is not entered)
 - CM11 bit of CM1 register
 - CM20 bit of CM2 register (oscillation stop, re-oscillation detection function settings do not change)

Note 4: Setting the PM22 bit to "1" results in the following conditions:

- The ring oscillator starts oscillating, and the ring oscillator clock becomes the watchdog timer count source.
- The CM10 bit of CM1 register is disabled against write. (Writing a "1" has no effect, nor is stop mode entered.)
- The watchdog timer does not stop when in wait mode or hold state.

Figure 1.7.5. PCLKR Register and PM2 Register

The following describes the clocks generated by the clock generation circuit.

(1) Main Clock

Main clock is supplied by IT800 with a tripled clock of XIN (main clock oscillator).

This clock is used as the clock source for the CPU and peripheral function clocks. The main clock oscillator circuit is configured by connecting a resonator between the XIN and XOUT pins. The main clock oscillator circuit contains a feedback resistor. The main clock oscillator circuit may also be configured by feeding an externally generated clock to the XIN pin. Figure 1.7.6 shows the examples of main clock connection circuit.

After reset, the main clock divided by 8 is selected for the CPU clock.

Even if Xin input stops, main clock oscillator does not stop.

During stop mode, all clocks of internal M16C core including the main clock are turned off. Refer to "power control".




Figure 1.7.6. Examples of Main Clock Connection Circuit

(3) Ring Oscillator Clock

This clock, approximately 1 MHz, is supplied by a ring oscillator. This clock is used as the clock source for the CPU and peripheral function clocks. In addition, if the PM22 bit of PM2 register is "1" (ring oscillator clock for the watchdog timer count source), this clock is used as the count source for the watchdog timer. After reset, the ring oscillator clock is turned off. It is turned on by setting the CM21 bit of CM2 register to "1" (ring oscillator clock), and is used as the clock source for the CPU and peripheral function clocks, in place of the main clock.

CPU Clock and Peripheral Function Clock

Two type clocks: CPU clock to operate the CPU and peripheral function clocks to operate the peripheral functions.

(1) CPU Clock and BCLK

These are operating clocks for the CPU and watchdog timer.

The clock source for the CPU clock can be chosen to be the main clock, or ring oscillator clock.

If the main clock or ring oscillator clock is selected as the clock source for the CPU clock, the selected clock source can be divided by 1 (undivided), 2, 4, 8 or 16 to produce the CPU clock. Use the CM06 bit in CM0 register and the CM17 to CM16 bits in CM1 register to select the divide-by-n value.

After reset, the main clock divided by 8 provides the CPU clock.

Note that when entering stop mode from high or middle speed mode, ring oscillator mode or low power ring oscillator mode, the CM06 bit of CM0 register is set to "1" (divide-by-8 mode).

(2) Peripheral Function Clock(f_1 , f_2 , f_8 , f_{32} , f_{1SIO} , f_{2SIO} , f_{8SIO} , f_{32SIO})

These are operating clocks for the peripheral functions.

Of these, f_i ($i = 1, 2, 8, 32$) and f_{iSIO} are derived from the main clock, or ring oscillator clock by dividing them by i . The clock f_i is used for timers A, and f_{iSIO} is used for serial I/O.

When the WAIT instruction is executed after setting the CM02 bit of CM0 register to "1" (peripheral function clock turned off during wait mode), or when the microcomputer is in low power dissipation mode, the f_i , and f_{iSIO} clocks are turned off.

Power Control

There are three power control modes. For convenience' sake, all modes other than wait and stop modes are referred to as normal operation mode here.

(1) Normal Operation Mode

Normal operation mode is further classified into three modes.

In normal operation mode, because the CPU clock and the peripheral function clocks both are on, the CPU and the peripheral functions are operating. Power control is exercised by controlling the CPU clock frequency. The higher the CPU clock frequency, the greater the processing capability. The lower the CPU clock frequency, the smaller the power consumption in the chip. If the unnecessary oscillator circuits are turned off, the power consumption is further reduced.

Before the clock sources for the CPU clock can be switched over, the new clock source to which switched must be oscillating stably. If the new clock source is the main clock, allow a sufficient wait time in a program until it becomes oscillating stably.

Where the CPU clock source is changed from the ring oscillator to the main clock, change the operation mode to the medium speed mode (divided by 8 mode) after the clock was divided by 8 (the CM06 bit of CM0 register was set to "1") in the ring oscillator mode.

- **High-speed Mode**

The main clock divided by 1 provides the CPU clock.

- **Medium-speed Mode**

The main clock divided by 2, 4, 8 or 16 provides the CPU clock.

- **Ring Oscillator Mode**

The ring oscillator clock divided by 1 (undivided), 2, 4, 8 or 16 provides the CPU clock. The ring oscillator clock is also the clock source for the peripheral function clocks.

Table 1.7.2. Setting Clock Related Bit and Modes

Modes		CM2 register CM21	CM1 register CM17, CM16	CM0 register CM06
High-speed mode		0	002	0
Midium-speed mode	divided by 2	0	012	0
	divided by 4	0	102	0
	divided by 8	0	—	1
	divided by 16	0	112	0
Ring oscillator mode	divided by 1	1	002	0
	divided by 2	1	012	0
	divided by 4	1	102	0
	divided by 8	1	—	1
	divided by 16	1	112	0

Note: The divide-by-n value can be selected the same way as in ring oscillator mode.

(2) Wait Mode

In wait mode, the CPU clock is turned off, so are the CPU (because operated by the CPU clock) and the watchdog timer. However, if the PM22 bit of PM2 register is “1” (ring oscillator clock for the watchdog timer count source), the watchdog timer remains active. Because the main clock, and ring oscillator clock are on, the peripheral functions using these clocks keep operating.

• Peripheral Function Clock Stop Function

If the CM02 bit is “1” (peripheral function clocks turned off during wait mode), the f₁, f₂, f₈, f₃₂, f_{1SIO}, f_{8SIO}, and f_{32SIO} clocks are turned off when in wait mode, with the power consumption reduced that much.

• Entering Wait Mode

The microcomputer is placed into wait mode by executing the WAIT instruction.

• Pin Status During Wait Mode

Table 1.7.3 lists pin status during wait mode

• Exiting Wait Mode

The microcomputer is moved out of wait mode by a hardware reset or peripheral function interrupt.

If the microcomputer is to be moved out of exit wait mode by a hardware reset, set the peripheral function interrupt priority ILVL2 to ILVL0 bits to “0002” (interrupts disabled) before executing the WAIT instruction.

The peripheral function interrupts are affected by the CM02 bit. If CM02 bit is “0” (peripheral function clocks not turned off during wait mode), all peripheral function interrupts can be used to exit wait mode. If CM02 bit is “1” (peripheral function clocks turned off during wait mode), the peripheral functions using the peripheral function clocks stop operating, so that only the peripheral functions clocked by external signals can be used to exit wait mode.

Table 1.7.4 lists the interrupts to exit wait mode.

Table 1.7.3. Pin Status During Wait Mode

Pin	Status
I/O ports	Retains status before wait mode

Table 1.7.4. Interrupts to Exit Wait Mode

Interrupt	CM02=0	CM02=1
Serial I/O interrupt	Can be used when operating with internal or external clock	Can be used when operating with external clock
Timer A interrupt	Can be used in all modes	Can be used in event counter mode
$\overline{\text{INT}}$ interrupt	Can be used	Can be used

If the microcomputer is to be moved out of wait mode by a peripheral function interrupt, set up the following before executing the WAIT instruction.

1. In the ILVL2 to ILVL0 bits of interrupt control register, set the interrupt priority level of the peripheral function interrupt to be used to exit wait mode.
Also, for all of the peripheral function interrupts not used to exit wait mode, set the ILVL2 to ILVL0 bits to "0002" (interrupt disable).
2. Set the I flag to "1".
3. Enable the peripheral function whose interrupt is to be used to exit wait mode.
In this case, when an interrupt request is generated and the CPU clock is thereby turned on, an interrupt routine is executed.

The CPU clock turned on when exiting wait mode by a peripheral function interrupt is the same CPU clock that was on when the WAIT instruction was executed.

(3) Stop Mode

In stop mode, all oscillator circuits are turned off, so are the CPU clock and the peripheral function clocks. Therefore, the CPU and the peripheral functions clocked by these clocks stop operating. The least amount of power is consumed in this mode. If the voltage applied to Vcc pins is V_{RAM} or more, the internal RAM is retained.

However, the peripheral functions clocked by external signals keep operating. The following interrupts can be used to exit stop mode.

- $\overline{\text{INT}}$ interrupt
- Timer A, interrupt (when counting external pulses in event counter mode)
- Serial I/O interrupt (when external clock is selected)

• Entering Stop Mode

The microcomputer is placed into stop mode by setting the CM10 bit of CM1 register to "1" (all clocks turned off). At the same time, the CM06 bit of CM0 register is set to "1" (divide-by-8 mode).

Before entering stop mode, set the CM20 bit to "0" (oscillation stop, re-oscillation detection function disable).

• Pin Status in Stop Mode

Table 1.9.6 lists pin status during stop mode

• Exiting Stop Mode

The microcomputer is moved out of stop mode by a hardware reset or peripheral function interrupt.

If the microcomputer is to be moved out of stop mode by a hardware reset, set the peripheral function interrupt priority ILVL2 to ILVL0 bits to "0002" (interrupts disable) before setting the CM10 bit to "1".

If the microcomputer is to be moved out of stop mode by a peripheral function interrupt, set up the following before setting the CM10 bit to "1".

1. In the ILVL2 to ILVL0 bits of interrupt control register, set the interrupt priority level of the peripheral function interrupt to be used to exit stop mode.

Also, for all of the peripheral function interrupts not used to exit stop mode, set the ILVL2 to ILVL0 bits to "0002".

2. Set the I flag to "1".

3. Enable the peripheral function whose interrupt is to be used to exit stop mode.

In this case, when an interrupt request is generated and the CPU clock is thereby turned on, an interrupt service routine is executed.

Which CPU clock will be used after exiting stop mode by a peripheral function is determined by the CPU clock that was on when the microcomputer was placed into stop mode as follows:

If the CPU clock before entering stop mode was derived from the main clock: main clock divide-by-8

If the CPU clock before entering stop mode was derived from the ring oscillator clock: ring oscillator clock divide-by-8

Table 1.7.5. Pin Status in Stop Mode

Pin	Status
I/O ports	Retains status before stop mode

Figure 1.7.7 shows the state transition from normal operation mode to stop mode and wait mode. Figure 1.7.8 shows the state transition in normal operation mode.

Table 1.7.6 shows a state transition matrix describing allowed transition and setting. The vertical line shows current state and horizontal line shows state after transition.




Figure 1.7.7. State Transition to Stop Mode and Wait Mode




Figure 1.7.8. State Transition in Normal Mode

Table 1.7.6. Allowed Transition and Setting

		State after transition			
		High-speed mode, middle-speed mode	Ring oscillator mode	Stop mode	Wait mode
Current state	High-speed mode, middle-speed mode	See Table A	(7)	(8) ¹	(9)
	Ring oscillator mode	(6) ²	See Table A	(8) ¹	(9)
	Stop mode	(10) ³	(10) ³	--	--
	Wait mode	(10)	(10)		

--: Cannot transit

Table 1. State Transition with Main Clock Division Ratio in High- or Middle-speed Mode, Ring Oscillator Mode, and Ring Oscillator Low Power Dissipation Mode

		State after transition				
		No division	Divided by 2	Divided by 4	Divided by 8	Divided by 16
Current state	No division					
	Divided by 2	(1)		(3)	(5)	(4)
	Divided by 4	(1)	(2)		(5)	(4)
	Divided by 8	(1)	(2)	(3)		(4)
	Divided by 16	(1)	(2)	(3)	(5)	

Notes:

1. Avoid making a transition when the CM21 bit is set to "1" (oscillation stop, re-oscillation detection function enabled). Set the CM21 bit to "0" (oscillation stop, re-oscillation detection function disabled) before transiting.
2. Set the CM06 bit to "1" (division by 8 mode) before transiting from ring oscillator mode to high- or middle-speed mode.
3. When exiting stop mode, the CM06 bit is set to "1" (division by 8 mode).

Table B. Setting and Operation

	Setting	Operation
(1)	CM06 = 0, CM17 = 0, CM16 = 0	CPU clock no division mode
(2)	CM06 = 0, CM17 = 0, CM16 = 1	CPU clock division by 2 mode
(3)	CM06 = 0, CM17 = 1, CM16 = 0	CPU clock division by 4 mode
(4)	CM06 = 0, CM17 = 1, CM16 = 1	CPU clock division by 16 mode
(5)	CM06 = 1	CPU clock division by 8 mode
(6)	CM21 = 0	Main clock
(7)	CM21 = 1	Ring oscillator clock selected
(8)	CM10 = 1	Transition to stop mode
(9)	wait	Transition to wait mode
(10)	Hardware interrupt	Exit stop mode or wait mode

System Clock Protective Function

When the main clock is selected for the CPU clock source, this function disables the clock against modifications in order to prevent the CPU clock from becoming halted by run-away.

If the PM21 bit of PM2 register is set to "1" (clock modification disabled), the following bits are protected against writes:

- CM02 bit in CM0 register
- CM10, CM11 bits in CM1 register
- CM20 bit in CM2 register

Before the system clock protective function can be used, the following register settings must be made:

- (1) Set the PRC1 bit of PRCR register to "1" (enable writes to PM2 register).
- (2) Set the PM21 bit of PM2 register to "1" (disable clock modification).
- (3) Set the PRC1 bit of PRCR register to "0" (disable writes to PM2 register).

Do not execute the WAIT instruction when the PM21 bit is "1".

Oscillation Stop and Re-oscillation Detect Function

The oscillation stop and re-oscillation detect function is such that main clock oscillation circuit stop and re-oscillation are detected. At oscillation stop, re-oscillation detection, reset or oscillation stop, re-oscillation detection interrupt are generated. Which is to be generated can be selected using the CM27 bit of CM2 register. Main clock oscillator of M16C/6S does not stop even if Xin input stops. Oscillation stop re-oscillation detect circuit does not function.

Protection

In the event that a program runs out of control, this function protects the important registers so that they will not be rewritten easily. Figure 1.8.1 shows the PRCR register. The following lists the registers protected by the PRCR register.

- Registers protected by PRC0 bit: CM0, CM1, CM2, and PCLKR registers
- Registers protected by PRC1 bit: PM0, PM1, PM2 registers
- Registers protected by PRC2 bit: PD9, S3C and S4C registers

Set the PRC2 bit to “1” (write enabled) and then write to any address, and the PRC2 bit will be cleared to “0” (write protected). The registers protected by the PRC2 bit should be changed in the next instruction after setting the PRC2 bit to “1”. Make sure no interrupts or DMA transfers will occur between the instruction in which the PRC2 bit is set to “1” and the next instruction. The PRC0 and PRC1 bits are not automatically cleared to “0” by writing to any address. They can only be cleared in a program.




Figure 1.8.1. PRCR Register

Interrupts

Type of Interrupts

Figure 1.9.1 shows types of interrupts.




Figure 1.9.1. Interrupts

- Maskable Interrupt: An interrupt which can be enabled (disabled) by the interrupt enable flag (I flag) or whose interrupt priority **can be changed** by priority level.
- Non-maskable Interrupt: An interrupt which cannot be enabled (disabled) by the interrupt enable flag (I flag) or whose interrupt priority **cannot be changed** by priority level.

Software Interrupts

A software interrupt occurs when executing certain instructions. Software interrupts are non-maskable interrupts.

- **Undefined Instruction Interrupt**

An undefined instruction interrupt occurs when executing the UND instruction.

- **Overflow Interrupt**

An overflow interrupt occurs when executing the INTO instruction with the O flag set to "1" (the operation resulted in an overflow). The following are instructions whose O flag changes by arithmetic:

ABS, ADC, ADCF, ADD, CMP, DIV, DIVU, DIVX, NEG, RMPA, SBB, SHA, SUB

- **BRK Interrupt**

A BRK interrupt occurs when executing the BRK instruction.

- **INT Instruction Interrupt**

An INT instruction interrupt occurs when executing the INT instruction. Software interrupt Nos. 0 to 63 can be specified for the INT instruction. Because software interrupt Nos. 4 to 31 are assigned to peripheral function interrupts, the same interrupt routine as for peripheral function interrupts can be executed by executing the INT instruction.

In software interrupt Nos. 0 to 31, the U flag is saved to the stack during instruction execution and is cleared to "0" (ISP selected) before executing an interrupt sequence. The U flag is restored from the stack when returning from the interrupt routine. In software interrupt Nos. 32 to 63, the U flag does not change state during instruction execution, and the SP then selected is used.

Hardware Interrupts

Hardware interrupts are classified into two types — special interrupts and peripheral function interrupts.

(1) Special Interrupts

Special interrupts are non-maskable interrupts.

- **DBC Interrupt**

Do not normally use this interrupt because it is provided exclusively for use by development support tools.

- **Watchdog Timer Interrupt**

Generated by the watchdog timer. Once a watchdog timer interrupt is generated, be sure to initialize the watchdog timer. For details about the watchdog timer, refer to the section "watchdog timer".

- **Oscillation Stop and Re-oscillation Detection Interrupt**

Generated by the oscillation stop and re-oscillation detection function. For details about the oscillation stop detection function, refer to the section "clock generating circuit".

- **Single-step Interrupt**

Do not normally use this interrupt because it is provided exclusively for use by development support tools.

- **Address Match Interrupt**

An address match interrupt is generated immediately before executing the instruction at the address indicated by the RMAD0 to RMAD3 register that corresponds to one of the AIER register's AIER0 or AIER1 bit or the AIER2 register's AIER20 or AIER21 bit which is "1" (address match interrupt enabled). For details about the address match interrupt, refer to the section "address match interrupt".

(2) Peripheral Function Interrupts

Peripheral function interrupts are maskable interrupts and generated by the microcomputer's internal functions. The interrupt sources for peripheral function interrupts are listed in Table 1.9.2. For details about the peripheral functions, refer to the description of each peripheral function in this manual.

Interrupts and Interrupt Vector

One interrupt vector consists of 4 bytes. Set the start address of each interrupt routine in the respective interrupt vectors. When an interrupt request is accepted, the CPU branches to the address set in the corresponding interrupt vector. Figure 1.9.2 shows the interrupt vector.




Figure 1.9.2. Interrupt Vector

• Fixed Vector Tables

The fixed vector tables are allocated to the addresses from FFFDC₁₆ to FFFFF₁₆. Table 1.9.1 lists the fixed vector tables. In the flash memory version of microcomputer, the vector addresses (H) of fixed vectors are used by the ID code check function. For details, refer to the section "flash memory rewrite disabling function".

Table 1.9.1. Fixed Vector Tables

Interrupt source	Vector table addresses Address (L) to address (H)	Remarks	Reference
Undefined instruction	FFFD _{C16} to FFFD _{F16}	Interrupt on UND instruction	M16C/60, M16C/20 serise software maual
Overflow	FFFE ₀₁₆ to FFFE ₃₁₆	Interrupt on INTO instruction	
BRK instruction	FFFE ₄₁₆ to FFFE ₇₁₆	If the contents of address FFFE ₇₁₆ is FF ₁₆ , program execution starts from the address shown by the vector in the relocatable vector table.	
Address match	FFFE ₈₁₆ to FFFEB ₁₆		Address match interrupt
Single step (Note)	FFFE _{C16} to FFFE _{F16}		
Watchdog timer Oscillation stop and re-oscillation detection	FFFF ₀₁₆ to FFFF ₃₁₆		Watchdog timer Clock generating circuit
DBC (Note)	FFFF ₄₁₆ to FFFF ₇₁₆		
— (Reserved)	FFFF ₈₁₆ to FFFF _{B16}		
Reset	FFFF _{C16} to FFFF _{F16}		Reset

Note: Do not normally use this interrupt because it is provided exclusively for use by development support tools.

• Relocatable Vector Tables

The 256 bytes beginning with the start address set in the INTB register comprise a relocatable vector table area. Table 1.9.2 lists the relocatable vector tables. Setting an even address in the INTB register results in the interrupt sequence being executed faster than in the case of odd addresses.

Table 1.9.2. Relocatable Vector Tables

Interrupt source	Vector address (Note 1) Address (L) to address (H)	Software interrupt number	Reference
BRK instruction (Note 5)	+0 to +3 (0000 ₁₆ to 0003 ₁₆)	0	M16C/60, M16C/20 series software manual
——— (Reserved)		1 to 3	
INT3	+16 to +19 (0010 ₁₆ to 0013 ₁₆)	4	INT interrupt
——— (Reserved)	+20 to +23 (0014 ₁₆ to 0017 ₁₆)	5	
Timer B4, UART1 bus collision detect (Note 4)	+24 to +27 (0018 ₁₆ to 001B ₁₆)	6	Timer Serial I/O
Timer B3, UART0 bus collision detect (Note 4)	+28 to +31 (001C ₁₆ to 001F ₁₆)	7	
SI/O4, INT5 (Note 2)	+32 to +35 (0020 ₁₆ to 0023 ₁₆)	8	INT interrupt Serial I/O
SI/O3, INT4 (Note 2)	+36 to +39 (0024 ₁₆ to 0027 ₁₆)	9	
UART 2 bus collision detection	+40 to +43 (0028 ₁₆ to 002B ₁₆)	10	Serial I/O
DMA0	+44 to +47 (002C ₁₆ to 002F ₁₆)	11	DMAC
DMA1	+48 to +51 (0030 ₁₆ to 0033 ₁₆)	12	
——— (Reserved)	+52 to +55 (0034 ₁₆ to 0037 ₁₆)	13	
——— (Reserved)	+56 to +59 (0038 ₁₆ to 003B ₁₆)	14	
UART2 transmit, NACK2 (Note 3)	+60 to +63 (003C ₁₆ to 003F ₁₆)	15	Serial I/O
UART2 receive, ACK2 (Note 3)	+64 to +67 (0040 ₁₆ to 0043 ₁₆)	16	
UART0 transmit, NACK0 (Note 3)	+68 to +71 (0044 ₁₆ to 0047 ₁₆)	17	
UART0 receive, ACK0 (Note 3)	+72 to +75 (0048 ₁₆ to 004B ₁₆)	18	
UART1 transmit, NACK1 (Note 3)	+76 to +79 (004C ₁₆ to 004F ₁₆)	19	
UART1 receive, ACK1 (Note 3)	+80 to +83 (0050 ₁₆ to 0053 ₁₆)	20	
Timer A0	+84 to +87 (0054 ₁₆ to 0057 ₁₆)	21	Timer
Timer A1	+88 to +91 (0058 ₁₆ to 005B ₁₆)	22	
Timer A2	+92 to +95 (005C ₁₆ to 005F ₁₆)	23	
Timer A3	+96 to +99 (0060 ₁₆ to 0063 ₁₆)	24	
Timer A4	+100 to +103 (0064 ₁₆ to 0067 ₁₆)	25	
——— (Reserved)	+104 to +107 (0068 ₁₆ to 006B ₁₆)	26	
——— (Reserved)	+108 to +111 (006C ₁₆ to 006F ₁₆)	27	
——— (Reserved)	+112 to +115 (0070 ₁₆ to 0073 ₁₆)	28	
INT0	+116 to +119 (0074 ₁₆ to 0077 ₁₆)	29	INT interrupt
INT1	+120 to +123 (0078 ₁₆ to 007B ₁₆)	30	
INT2	+124 to +127 (007C ₁₆ to 007F ₁₆)	31	
Software interrupt (Note 5)	+128 to +131 (0080 ₁₆ to 0083 ₁₆) to +252 to +255 (00FC ₁₆ to 00FF ₁₆)	32 to 63	M16C/60, M16C/20 series software manual

Note 1: Address relative to address in INTB.

Note 2: Set the IFSR register's IFSR6 and IFSR7 bits "0".

Note 3: During I²C mode, NACK and ACK interrupts comprise the interrupt source.

Note 4: Set the IFSR2A register's IFSR26 and IFSR27 bits "1".

Note 5: These interrupts cannot be disabled using the I flag.

Interrupt Control


The following describes how to enable/disable the maskable interrupts, and how to set the priority in which order they are accepted. What is explained here does not apply to nonmaskable interrupts.

Use the FLG register's I flag, IPL, and each interrupt control register's ILVL2 to ILVL0 bits to enable/disable the maskable interrupts. Whether an interrupt is requested is indicated by the IR bit in each interrupt control register.

Figure 1.9.3 shows the interrupt control registers.

Interrupt control register (Note 2)

Symbol	Address	After reset
U1BCNIC (Note 3)	0046 ₁₆	XXXXX0002
U0BCNIC (Note 3)	0047 ₁₆	XXXXX0002
BCNIC	004A ₁₆	XXXXX0002
DM0IC, DM1IC	004B ₁₆ , 004C ₁₆	XXXXX0002
S0TIC to S2TIC	0051 ₁₆ , 0053 ₁₆ , 004F ₁₆	XXXXX0002
S0RIC to S2RIC	0052 ₁₆ , 0054 ₁₆ , 0050 ₁₆	XXXXX0002
TA0IC to TA4IC	0055 ₁₆ to 0059 ₁₆	XXXXX0002




Bit symbol	Bit name	Function	RW
ILVL0	Interrupt priority level select bit	b2 b1 b0 0 0 0 : Level 0 (interrupt disabled) 0 0 1 : Level 1 0 1 0 : Level 2 0 1 1 : Level 3 1 0 0 : Level 4 1 0 1 : Level 5 1 1 0 : Level 6 1 1 1 : Level 7	RW
ILVL1			RW
ILVL2			RW
IR		0 : Interrupt not requested 1 : Interrupt requested	RW (Note 1)
— (b7-b4)	No functions are assigned. When writing to these bits, write "0". The values in these bits when read are indeterminate.		—

Note 1: This bit can only be reset by writing "0" (Do not write "1").

Note 2: To rewrite the interrupt control registers, do so at a point that does not generate the interrupt request for that register. For details, see the precautions for interrupts.

Note 3: Use the IFSR2A register to select.

Symbol	Address	After reset
INT3IC	0044 ₁₆	XX00X0002
S4IC	0048 ₁₆	XX00X0002
S3IC	0049 ₁₆	XX00X0002
INT0IC to INT2IC	005D ₁₆ to 005F ₁₆	XX00X0002



Bit symbol	Bit name	Function	RW
ILVL0	Interrupt priority level select bit	b2 b1 b0 0 0 0 : Level 0 (interrupt disabled) 0 0 1 : Level 1 0 1 0 : Level 2 0 1 1 : Level 3 1 0 0 : Level 4 1 0 1 : Level 5 1 1 0 : Level 6 1 1 1 : Level 7	RW
ILVL1			RW
ILVL2			RW
IR		0: Interrupt not requested 1: Interrupt requested	RW (Note 1)
POL	Polarity select bit	0 : Selects falling edge (Notes 3, 4) 1 : Selects rising edge	RW
—	Reserved bit	Must always be set to "0"	RW
— (b7-b6)	No functions are assigned. When writing to these bits, write "0". The values in these bits when read are indeterminate.		RW

Note 1: This bit can only be reset by writing "0" (Do not write "1").

Note 2: To rewrite the interrupt control register, do so at a point that does not generate the interrupt request for that register. For details, see the precautions for interrupts.

Note 3: If the IFSR register's IFSRi bit (i = 0 to 5) is "1" (both edges), set the INTiIC register's POL bit to "0" (falling edge).

Note 4: Set the S3IC or S4IC register's POL bit to "0" (falling edge) when the IFSR register's IFSR6 bit = 0 (SI/O3 selected) or IFSR7 bit = 0 (SI/O4 selected), respectively.

Figure 1.9.3. Interrupt Control Registers

I Flag

The I flag enables or disables the maskable interrupt. Setting the I flag to “1” (= enabled) enables the maskable interrupt. Setting the I flag to “0” (= disabled) disables all maskable interrupts.

IR Bit

The IR bit is set to “1” (= interrupt requested) when an interrupt request is generated. Then, when the interrupt request is accepted and the CPU branches to the corresponding interrupt vector, the IR bit is cleared to “0” (= interrupt not requested).

The IR bit can be cleared to “0” in a program. Note that do not write “1” to this bit.

ILVL2 to ILVL0 Bits and IPL

Interrupt priority levels can be set using the ILVL2 to ILVL0 bits.

Table 1.9.3 shows the settings of interrupt priority levels and Table 1.9.4 shows the interrupt priority levels enabled by the IPL.

The following are conditions under which an interrupt is accepted:

- I flag = “1”
- IR bit = “1”
- interrupt priority level > IPL

The I flag, IR bit, ILVL2 to ILVL0 bits and IPL are independent of each other. In no case do they affect one another.

Table 1.9.3. Settings of Interrupt Priority Levels


ILVL2 to ILVL0 bits	Interrupt priority level	Priority order
0002	Level 0 (interrupt disabled)	———
0012	Level 1	<div style="text-align: center;"> Low  High </div>
0102	Level 2	
0112	Level 3	
1002	Level 4	
1012	Level 5	
1102	Level 6	
1112	Level 7	

Table 1.9.4. Interrupt Priority Levels Enabled by IPL

IPL	Enabled interrupt priority levels
0002	Interrupt levels 1 and above are enabled
0012	Interrupt levels 2 and above are enabled
0102	Interrupt levels 3 and above are enabled
0112	Interrupt levels 4 and above are enabled
1002	Interrupt levels 5 and above are enabled
1012	Interrupt levels 6 and above are enabled
1102	Interrupt levels 7 and above are enabled
1112	All maskable interrupts are disabled

Interrupt Sequence

An interrupt sequence — what are performed over a period from the instant an interrupt is accepted to the instant the interrupt routine is executed — is described here.

If an interrupt occurs during execution of an instruction, the processor determines its priority when the execution of the instruction is completed, and transfers control to the interrupt sequence from the next cycle. If an interrupt occurs during execution of either the SMOVB, SMOVF, SSTR or RMPA instruction, the processor temporarily suspends the instruction being executed, and transfers control to the interrupt sequence.

The CPU behavior during the interrupt sequence is described below. Figure 1.9.4 shows time required for executing the interrupt sequence.

- (1) The CPU gets interrupt information (interrupt number and interrupt request priority level) by reading the address 000016. Then it clears the IR bit for the corresponding interrupt to “0” (interrupt not requested).
- (2) The FLG register immediately before entering the interrupt sequence is saved to the CPU’s internal temporary register^(Note 1).
- (3) The I, D and U flags in the FLG register become as follows:
 The I flag is cleared to “0” (interrupts disabled).
 The D flag is cleared to “0” (single-step interrupt disabled).
 The U flag is cleared to “0” (ISP selected).
 However, the U flag does not change state if an INT instruction for software interrupt Nos. 32 to 63 is executed.
- (4) The CPU’s internal temporary register ^(Note 1) is saved to the stack.
- (5) The PC is saved to the stack.
- (6) The interrupt priority level of the accepted interrupt is set in the IPL.
- (7) The start address of the relevant interrupt routine set in the interrupt vector is stored in the PC.

After the interrupt sequence is completed, the processor resumes executing instructions from the start address of the interrupt routine.

Note: This register cannot be used by user.




Figure 1.9.4. Time Required for Executing Interrupt Sequence

Interrupt Response Time

Figure 1.9.5 shows the interrupt response time. The interrupt response or interrupt acknowledge time denotes a time from when an interrupt request is generated till when the first instruction in the interrupt routine is executed. Specifically, it consists of a time from when an interrupt request is generated till when the instruction then executing is completed ((a) in Figure 1.9.5) and a time during which the interrupt sequence is executed ((b) in Figure 1.9.5).




Figure 1.9.5. Interrupt response time

Variation of IPL when Interrupt Request is Accepted

When a maskable interrupt request is accepted, the interrupt priority level of the accepted interrupt is set in the IPL.

When a software interrupt or special interrupt request is accepted, one of the interrupt priority levels listed in Table 1.9.5 is set in the IPL. Shown in Table 1.9.5 are the IPL values of software and special interrupts when they are accepted.

Table 1.9.5. IPL Level That is Set to IPL When A Software or Special Interrupt Is Accepted

Interrupt sources	Level that is set to IPL
Watchdog timer	7
Software, address match, $\overline{\text{DBC}}$, single-step	Not changed

Saving Registers

In the interrupt sequence, the FLG register and PC are saved to the stack.

At this time, the 4 high-order bits of the PC and the 4 high-order (IPL) and 8 low-order bits of the FLG register, 16 bits in total, are saved to the stack first. Next, the 16 low-order bits of the PC are saved. Figure 1.9.6 shows the stack status before and after an interrupt request is accepted.

The other necessary registers must be saved in a program at the beginning of the interrupt routine. Use the PUSHM instruction, and all registers except SP can be saved with a single instruction.




Figure 1.9.6. Stack Status Before and After Acceptance of Interrupt Request

The operation of saving registers carried out in the interrupt sequence is dependent on whether the SP^(Note), at the time of acceptance of an interrupt request, is even or odd. If the stack pointer ^(Note) is even, the FLG register and the PC are saved, 16 bits at a time. If odd, they are saved in two steps, 8 bits at a time. Figure 1.9.7 shows the operation of the saving registers.

Note: When any INT instruction in software numbers 32 to 63 has been executed, this is the SP indicated by the U flag. Otherwise, it is the ISP.




Figure 1.9.7. Operation of Saving Register

Returning from an Interrupt Routine

The FLG register and PC in the state in which they were immediately before entering the interrupt sequence are restored from the stack by executing the REIT instruction at the end of the interrupt routine. Thereafter the CPU returns to the program which was being executed before accepting the interrupt request.

Return the other registers saved by a program within the interrupt routine using the POPM or similar instruction before executing the REIT instruction.

Interrupt Priority

If two or more interrupt requests are generated while executing one instruction, the interrupt request that has the highest priority is accepted.

For maskable interrupts (peripheral functions), any desired priority level can be selected using the ILVL2 to ILVL0 bits. However, if two or more maskable interrupts have the same priority level, their interrupt priority is resolved by hardware, with the highest priority interrupt accepted.

The watchdog timer and other special interrupts have their priority levels set in hardware. Figure 1.9.8 shows the priorities of hardware interrupts.

Software interrupts are not affected by the interrupt priority. If an instruction is executed, control branches invariably to the interrupt routine.

Reset > $\overline{\text{DBC}}$ > WDT > Peripheral function > Single step > Address match

Figure 1.9.8. Hardware Interrupt Priority

Interrupt Priority Resolution Circuit

The interrupt priority resolution circuit is used to select the interrupt with the highest priority among those requested.

Figure 1.9.9 shows the circuit that judges the interrupt priority level.




Figure 1.9.9. Interrupts Priority Select Circuit

INT Interrupt

INT_i interrupt (i=0 to 3) is triggered by the edges of external inputs. The edge polarity is selected using the IFSR register's IFSR_i bit.

Figure 1.9.10 shows the IFSR and IFSR2A registers.




Figure 1.9.10. IFSR Register and IFSR2A Register

Address Match Interrupt

An address match interrupt is generated immediately before executing the instruction at the address indicated by the RMADi register (i=0 to 3). Set the start address of any instruction in the RMADi register. Use the AIER register's AIER0 and AIER1 bits and the AIER2 register's AIER20 and AIER21 bits to enable or disable the interrupt. Note that the address match interrupt is unaffected by the I flag and IPL. For address match interrupts, the value of the PC that is saved to the stack area varies depending on the instruction being executed. Figure 1.9.11 shows the instruction just before execution and address stored in the stack when there occurs interruption.

Note that when using the external data bus in width of 8 bits, the address match interrupt cannot be used for external area.

Figure 1.9.12 shows the AIER, AIER2, and RMAD0 to RMAD3 registers.

(1) Instructions in which the "return destination + 2" address is stored in the stack when address match interrupt occurs

- 16-bit operation code
- Instruction shown below among 8-bit operation code instructions

ADD.B:S	#IMM8,dest	SUB.B:S	#IMM8,dest	AND.B:S	#IMM8,dest
OR.B:S	#IMM8,dest	MOV.B:S	#IMM8,dest	STZ.B:S	#IMM8,dest
STNZ.B:S	#IMM8,dest	STZX.B:S	#IMM81,#IMM82,dest		
CMP.B:S	#IMM8,dest	PUSHM	src	POPM	dest
JMPS	#IMM8	JSRS	#IMM8		
MOV.B:S	#IMM,dest	(However, dest = A0 or A1)			

(2) Instructions in which the "return destination + 1" address is stored in the stack when address match interrupt occurs

- Instructions other than the above

Figure 1.9.11. Instruction Just Before Execution and Address Stored in Stack When There Occurs Interrupts

Table 1.9.6. Relationship Between Address Match Interrupt Sources and Associated Registers

Address match interrupt sources	Address match interrupt enable bit	Address match interrupt register
Address match interrupt 0	AIER0	RMAD0
Address match interrupt 1	AIER1	RMAD1
Address match interrupt 2	AIER20	RMAD2
Address match interrupt 3	AIER21	RMAD3




Figure 1.9.12. AIER Register, AIER2 Register and RMAD0 to RMAD3 Registers

Precautions for Interrupts

(1) Reading Address 00000₁₆

- Do not read the address 00000₁₆ in a program. When a maskable interrupt request is accepted, the CPU reads interrupt information (interrupt number and interrupt request priority level) from the address 00000₁₆ during the interrupt sequence. At this time, the IR bit for the accepted interrupt is cleared to "0". If the address 00000₁₆ is read in a program, the IR bit for the interrupt which has the highest priority among the enabled interrupts is cleared to "0". This causes a problem that the interrupt is canceled, or an unexpected interrupt is generated.

(2) SP Setting

- Set any value in the SP before accepting an interrupt. The SP is cleared to '0000₁₆' after reset. Therefore, if an interrupt is accepted before setting any value in the SP, the program may go out of control.

(3) $\overline{\text{INT}}$ Interrupt

- Either an "L" level or an "H" level of at least 250 ns width is necessary for the signal input to the $\overline{\text{INT}}$ through $\overline{\text{INT}}_3$ pins regardless of the CPU clock.
- When the polarity of the $\overline{\text{INT}}_0$ to $\overline{\text{INT}}_3$ pins is changed, the IR bit is sometimes set to "1" (=interrupt requested). After changing the polarity, set the IR bit to "0" (=interrupt not requested). Figure 1.9.12 shows the procedure for changing the $\overline{\text{INT}}$ interrupt generate factor.

(4) Watchdog Timer Interrupt

- Initialize the watchdog timer after the watchdog timer interrupt occurs.




Figure 1.9.13. Switching Procedure for $\overline{\text{INT}}$ Interrupt Request

(5) Modifying Interrupt Control Register

- Each interrupt control register can only be modified while no interrupt requests corresponding to that register are generated. If interrupt requests managed by any interrupt control register are likely to occur, disable the interrupts before modifying the register. A sample program is shown below.

To modify any interrupt control register after disabling interrupts, be careful with the instructions used.

Modifying other than the IR bit

If an interrupt request corresponding to that register is generated while executing the instruction, the IR bit may not be set to "1" (= interrupt requested), with the result that the interrupt request is ignored. If this presents a problem, use the following instructions to modify the register.

Instructions to use: AND, OR, BCLR, BSET

Modifying the IR bit

Even when the IR bit is cleared to "0" (= interrupt not requested), it may not actually be cleared to "0" depending on the instruction used. Therefore, use the MOV instruction to clear the IR bit.

Example 1:

```
INT_SWITCH1:
  FCLR  I           ; Disable interrupts.
  AND.B #00h, 0055h ; Set the TA0IC register to "0016".
  NOP                    ; Four NOP instructions are required when using HOLD function.
  NOP
  FSET  I           ; Enable interrupts.
```

Example 2:

```
INT_SWITCH2:
  FCLR  I           ; Disable interrupts.
  AND.B #00h, 0055h ; Set the TA0IC register to "0016".
  MOV.W MEM, R0     ; Dummy read.
  FSET  I           ; Enable interrupts.
```

Example 3:

```
INT_SWITCH3:
  PUSHC FLG         ; Push Flag register on to stack
  FCLR  I           ; Disable interrupts.
  AND.B #00h, 0055h ; Set the TA0IC register to "0016".
  POPC  FLG         ; Enable interrupts.
```

Why the FSET I instruction is preceded by two NOP instructions (four when using HOLD function) in Example 1 and why the FSET I instruction is preceded by a dummy read in Example 2

This is to prevent the I flag from being set to "1" before writing to the interrupt control register for reasons of the instruction queue buffer.

Watchdog Timer

The watchdog timer is the function of detecting when the program is out of control. Therefore, we recommend using the watchdog timer to improve reliability of a system. The watchdog timer contains a 15-bit counter which counts down the clock derived by dividing the CPU clock using the prescaler. Whether to generate a watchdog timer interrupt request or apply a watchdog timer reset as an operation to be performed when the watchdog timer underflows after reaching the terminal count can be selected using the PM12 bit of PM1 register. The PM12 bit can only be set to "1" (reset). Once this bit is set to "1", it cannot be set to "0" (watchdog timer interrupt) in a program.

The pin, CPU and SFR initialized where the monitor timer underflows when the PM12 bit is "1" are the same as in software reset.

When the main clock is selected for CPU clock, the divide-by-N value for the prescaler can be chosen to be 16 or 128. If a sub-clock is selected for CPU clock, the divide-by-N value for the prescaler is always 2 no matter how the WDC7 bit is set. The period of watchdog timer can be calculated as given below. The period of watchdog timer is, however, subject to an error due to the prescaler.

With main clock chosen for CPU clock

$$\text{Watchdog timer period} = \frac{\text{Prescaler dividing (16 or 128) X Watchdog timer count (32768)}}{\text{CPU clock}}$$

With sub-clock chosen for CPU clock

$$\text{Watchdog timer period} = \frac{\text{Prescaler dividing (2) X Watchdog timer count (32768)}}{\text{CPU clock}}$$

For example, when CPU clock = 16 MHz and the divide-by-N value for the prescaler= 16, the watchdog timer period is approx. 32.8 ms.

The watchdog timer is initialized by writing to the WDTS register. The prescaler is initialized after reset. Note that the watchdog timer and the prescaler both are inactive after reset, so that the watchdog timer is activated to start counting by writing to the WDTS register.

In stop mode, wait mode and hold state, the watchdog timer and prescaler are stopped. Counting is resumed from the held value when the modes or state are released.

Figure 1.10.1 shows the block diagram of the watchdog timer. Figure 1.10.2 shows the watchdog timer-related registers.

- Count source protective mode

In this mode, a ring oscillator clock is used for the watchdog timer count source. The watchdog timer can be kept being clocked even when CPU clock stops as a result of run-away.

Before this mode can be used, the following register settings are required:

- (1) Set the PRC1 bit of PRCR register to "1" (enable writes to PM1 and PM2 registers).
- (2) Set the PM12 bit of PM1 register to "1" (reset when the watchdog timer underflows).
- (3) Set the PM22 bit of PM2 register to "1" (ring oscillator clock used for the watchdog timer count source).
- (4) Set the PRC1 bit of PRCR register to "0" (disable writes to PM1 and PM2 registers).
- (5) Write to the WDTS register (watchdog timer starts counting).

Setting the PM22 bit to “1” results in the following conditions

- The ring oscillator starts oscillating, and the ring oscillator clock becomes the watchdog timer count source.
- The CM10 bit of CM1 register is disabled against write. (Writing a “1” has no effect, nor is stop mode entered.)
- The watchdog timer does not stop when in wait mode.




Figure 1.10.1. Watchdog Timer Block Diagram




Figure 1.10.2. WDC Register and WDTS Register

DMAC

The DMAC (Direct Memory Access Controller) allows data to be transferred without the CPU intervention. Two DMAC channels are included. Each time a DMA request occurs, the DMAC transfers one (8 or 16-bit) data from the source address to the destination address. The DMAC uses the same data bus as used by the CPU. Because the DMAC has higher priority of bus control than the CPU and because it makes use of a cycle steal method, it can transfer one word (16 bits) or one byte (8 bits) of data within a very short time after a DMA request is generated. Figure 1.11.1 shows the block diagram of the DMAC. Table 1.11.1 shows the DMAC specifications. Figures 1.11.2 to 1.11.4 show the DMAC-related registers.




Figure 1.11.1. DMAC Block Diagram

A DMA request is generated by a write to the DMiSL register ($i = 0-1$)'s DSR bit, as well as by an interrupt request which is generated by any function specified by the DMiSL register's DMS and DSEL3–DSEL0 bits. However, unlike in the case of interrupt requests, DMA requests are not affected by the I flag and the interrupt control register, so that even when interrupt requests are disabled and no interrupt request can be accepted, DMA requests are always accepted. Furthermore, because the DMAC does not affect interrupts, the interrupt control register's IR bit does not change state due to a DMA transfer.

A data transfer is initiated each time a DMA request is generated when the DMiCON register's DMAE bit = "1" (DMA enabled). However, if the cycle in which a DMA request is generated is faster than the DMA transfer cycle, the number of transfer requests generated and the number of times data is transferred may not match. For details, refer to "DMA Requests".


Table 1.11.1. DMAC Specifications

Item		Specification
No. of channels		2 (cycle steal method)
Transfer memory space		<ul style="list-style-type: none"> • From any address in the 1M bytes space to a fixed address • From a fixed address to any address in the 1M bytes space • From a fixed address to a fixed address
Maximum No. of bytes transferred		128K bytes (with 16-bit transfers) or 64K bytes (with 8-bit transfers)
DMA request factors (Note 1, Note 2)		Falling edge of $\overline{\text{INT0}}$ or $\overline{\text{INT1}}$ Both edge of $\overline{\text{INT0}}$ or $\overline{\text{INT1}}$ Timer A0 to timer A4 interrupt requests UART0 transfer, UART0 reception interrupt requests UART1 transfer, UART1 reception interrupt requests UART2 transfer, UART2 reception interrupt requests SI/O3, SI/O4 interrupt requests Software triggers
Channel priority		DMA0 > DMA1 (DMA0 takes precedence)
Transfer unit		8 bits or 16 bits
Transfer address direction		forward or fixed (The source and destination addresses cannot both be in the forward direction.)
Transfer mode	•Single transfer	Transfer is completed when the DMA _i transfer counter ($i = 0-1$) underflows after reaching the terminal count.
	•Repeat transfer	When the DMA _i transfer counter underflows, it is reloaded with the value of the DMA _i transfer counter reload register and a DMA transfer is continued with it.
DMA interrupt request generation timing		When the DMA _i transfer counter underflowed
DMA startup		Data transfer is initiated each time a DMA request is generated when the DMA _i CON register's DMAE bit = "1" (enabled).
DMA shutdown	•Single transfer	<ul style="list-style-type: none"> • When the DMAE bit is set to "0" (disabled) • After the DMA_i transfer counter underflows
	•Repeat transfer	When the DMAE bit is set to "0" (disabled)
Reload timing for forward address pointer and transfer counter		When a data transfer is started after setting the DMAE bit to "1" (enabled), the forward address pointer is reloaded with the value of the SAR _i or the DAR _i pointer whichever is specified to be in the forward direction and the DMA _i transfer counter is reloaded with the value of the DMA _i transfer counter reload register.

Notes:

1. DMA transfer is not effective to any interrupt. DMA transfer is affected neither by the I flag nor by the interrupt control register.
2. The selectable causes of DMA requests differ with each channel.
3. Make sure that no DMAC-related registers (addresses 002016–003F16) are accessed by the DMAC.

DMA0 request cause select register





Note: The causes of DMA0 requests can be selected by a combination of DMS bit and DSEL3 to DSEL0 bits in the manner described below.

DSEL3 to DSEL0	DMS=0(basic cause of request)	DMS=1(extended cause of request)
0 0 0 0 ₂	Falling edge of INT0 pin	—
0 0 0 1 ₂	Software trigger	—
0 0 1 0 ₂	Timer A0	—
0 0 1 1 ₂	Timer A1	—
0 1 0 0 ₂	Timer A2	—
0 1 0 1 ₂	Timer A3	—
0 1 1 0 ₂	Timer A4	Two edges of INT0 pin
0 1 1 1 ₂	—	—
1 0 0 0 ₂	—	—
1 0 0 1 ₂	—	—
1 0 1 0 ₂	UART0 transmit	—
1 0 1 1 ₂	UART0 receive	—
1 1 0 0 ₂	UART2 transmit	—
1 1 0 1 ₂	UART2 receive	—
1 1 1 0 ₂	—	—
1 1 1 1 ₂	UART1 transmit	—

Figure 1.11.2. DM0SL Register

DMA1 request cause select register

								Symbol DM1SL	Address 03BA ₁₆	After reset 00 ₁₆	
								Bit symbol	Bit name	Function	RW
								DSEL0	DMA request cause select bit	Refer to note	RW
								DSEL1			RW
								DSEL2			RW
								DSEL3			RW
								— (b5-b4)	Nothing is assigned. When write, set to "0". When read, its content is "0".		—
								DMS	DMA request cause expansion select bit	0: Basic cause of request 1: Extended cause of request	RW
DSR	Software DMA request bit	A DMA request is generated by setting this bit to "1" when the DMS bit is "0" (basic cause) and the DSEL3 to DSEL0 bits are "00012" (software trigger). The value of this bit when read is "0" .	RW								

Note: The causes of DMA1 requests can be selected by a combination of DMS bit and DSEL3 to DSEL0 bits in the manner described below.

DSEL3 to DSEL0	DMS=0(basic cause of request)	DMS=1(extended cause of request)
0 0 0 0 ₂	Falling edge of INT1 pin	—
0 0 0 1 ₂	Software trigger	—
0 0 1 0 ₂	Timer A0	—
0 0 1 1 ₂	Timer A1	—
0 1 0 0 ₂	Timer A2	—
0 1 0 1 ₂	Timer A3	SI/O3
0 1 1 0 ₂	Timer A4	SI/O4
0 1 1 1 ₂	—	Two edges of INT1
1 0 0 0 ₂	—	—
1 0 0 1 ₂	—	—
1 0 1 0 ₂	UART0 transmit	—
1 0 1 1 ₂	UART0 receive/ACK0	—
1 1 0 0 ₂	UART2 transmit	—
1 1 0 1 ₂	UART2 receive/ACK2	—
1 1 1 0 ₂	—	—
1 1 1 1 ₂	UART1 receive/ACK1	—

DMAi control register(i=0,1)

b7	b6	b5	b4	b3	b2	b1	b0	Symbol	Address	After reset
								DM0CON	002C ₁₆	00000X00 ₂
								DM1CON	003C ₁₆	00000X00 ₂


Bit symbol	Bit name	Function	RW
DMBIT	Transfer unit bit select bit	0 : 16 bits 1 : 8 bits	RW
DMASL	Repeat transfer mode select bit	0 : Single transfer 1 : Repeat transfer	RW
DMAS	DMA request bit	0 : DMA not requested 1 : DMA requested	RW (Note 1)
DMAE	DMA enable bit	0 : Disabled 1 : Enabled	RW
DSD	Source address direction select bit (Note 2)	0 : Fixed 1 : Forward	RW
DAD	Destination address direction select bit (Note 2)	0 : Fixed 1 : Forward	RW
— (b7-b6)	Nothing is assigned. When write, set to “0”. When read, its content is “0”.		—

Note 1: The DMAS bit can be set to "0" by writing "0" in a program (This bit remains unchanged even if "1" is written).

Note 2: At least one of the DAD and DSD bits must be "0" (address direction fixed).


Figure 1.11.3. DM1SL Register, DM0CON Register, and DM1CON Registers

DMAi source pointer (i = 0, 1) (Note)



Note: If the DSD bit of DMiCON register is "0" (fixed), this register can only be written to when the DMAE bit of DMiCON register is "0" (DMA disabled).
 If the DSD bit is "1" (forward direction), this register can be written to at any time.
 If the DSD bit is "1" and the DMAE bit is "1" (DMA enabled), the DMAi forward address pointer can be read from this register. Otherwise, the value written to it can be read.

DMAi destination pointer (i = 0, 1)(Note)



Note: If the DAD bit of DMiCON register is "0" (fixed), this register can only be written to when the DMAE bit of DMiCON register is "0" (DMA disabled).
 If the DAD bit is "1" (forward direction), this register can be written to at any time.
 If the DAD bit is "1" and the DMAE bit is "1" (DMA enabled), the DMAi forward address pointer can be read from this register. Otherwise, the value written to it can be read.

DMAi transfer counter (i = 0, 1)




Figure 1.11.4. SAR0, SAR1, DAR0, DAR1, TCR0, and TCR1 Registers

1. Transfer Cycles

The transfer cycle consists of a memory or SFR read (source read) bus cycle and a write (destination write) bus cycle. The number of read and write bus cycles is affected by the source and destination addresses of transfer. Furthermore, the bus cycle itself is extended by a software wait or $\overline{\text{RDY}}$ signal.

(a) Effect of Source and Destination Addresses

If the transfer unit and data bus both are 16 bits and the source address of transfer begins with an odd address, the source read cycle consists of one more bus cycle than when the source address of transfer begins with an even address.


Similarly, if the transfer unit and data bus both are 16 bits and the destination address of transfer begins with an odd address, the destination write cycle consists of one more bus cycle than when the destination address of transfer begins with an even address.

(b) Effect of Software Wait


For memory or SFR accesses in which one or more software wait states are inserted, the number of bus cycles required for that access increases by an amount equal to software wait states.

Figure 1.11.5 shows the example of the cycles for a source read. For convenience, the destination write cycle is shown as one cycle and the source read cycles for the different conditions are shown. In reality, the destination write cycle is subject to the same conditions as the source read cycle, with the transfer cycle changing accordingly. When calculating transfer cycles, take into consideration each condition for the source read and the destination write cycle, respectively. For example, when data is transferred in 16 bit units using an 8-bit bus ((2) in Figure 1.11.5), two source read bus cycles and two destination write bus cycles are required.


(1) When the transfer unit is 8 or 16 bits and the source of transfer is an even address




(2) When the transfer unit is 16 bits and the source address of transfer is an odd address



(3) When the source read cycle under condition (1) has one wait state inserted



(4) When the source read cycle under condition (2) has one wait state inserted



Note: The same timing changes occur with the respective conditions at the destination as at the source.

Figure 1.11.5. Transfer Cycles for Source Read

2. DMA Transfer Cycles

Any combination of even or odd transfer read and write addresses is possible. Table 1.11.2 shows the number of DMA transfer cycles. Table 1.11.3 shows the Coefficient j, k.

The number of DMAC transfer cycles can be calculated as follows:

$$\text{No. of transfer cycles per transfer unit} = \text{No. of read cycles} \times j + \text{No. of write cycles} \times k$$

Table 1.11.2. DMA Transfer Cycles

Transfer unit	Access address	No. of read cycles	No. of write cycles
8-bit transfers (DMBIT= "1")	Even	1	1
	Odd	1	1
16-bit transfers (DMBIT= "0")	Even	1	1
	Odd	2	2

Table 1.11.3. Coefficient j, k

	Internal ROM, RAM		SFR	
	No wait	With wait	1-wait ²	2-wait ²
j	1	2	2	3
k	1	2	2	3

Notes:

1. Depends on the set value of CSE register
2. Depends on the set value of PM20 bit in F

3. DMA Enable

When a data transfer starts after setting the DMAE bit in DMiCON register (i = 0, 1) to "1" (enabled), the DMAC operates as follows:

- (1) Reload the forward address pointer with the SARi register value when the DSD bit in DMiCON register is "1" (forward) or the DARi register value when the DAD bit of DMiCON register is "1" (forward).
- (2) Reload the DMAi transfer counter with the DMAi transfer counter reload register value.

If the DMAE bit is set to "1" again while it remains set, the DMAC performs the above operation. However, if a DMA request may occur simultaneously when the DMAE bit is being written, follow the steps below.

Step 1: Write "1" to the DMAE bit and DMAS bit in DMiCON register simultaneously.

Step 2: Make sure that the DMAi is in an initial state as described above (1) and (2) in a program.

If the DMAi is not in an initial state, the above steps should be repeated.

4. DMA Request

The DMAC can generate a DMA request as triggered by the cause of request that is selected with the DMS and DSEL3 to DSEL0 bits of DMiSL register (i = 0, 1) on either channel. Table 1.13.4 shows the timing at which the DMAS bit changes state.

Whenever a DMA request is generated, the DMAS bit is set to "1" (DMA requested) regardless of whether or not the DMAE bit is set. If the DMAE bit was set to "1" (enabled) when this occurred, the DMAS bit is set to "0" (DMA not requested) immediately before a data transfer starts. This bit cannot be set to "1" in a program (it can only be set to "0").

The DMAS bit may be set to "1" when the DMS or the DSEL3 to DSEL0 bits change state. Therefore, always be sure to set the DMAS bit to "0" after changing the DMS or the DSEL3 to DSEL0 bits.

Because if the DMAE bit is "1", a data transfer starts immediately after a DMA request is generated, the DMAS bit in almost all cases is "0" when read in a program. Read the DMAE bit to determine whether the DMAC is enabled.

Table 1.11.4. Timing at Which the DMAS Bit Changes State

DMA factor	DMAS bit of the DMiCON register	
	Timing at which the bit is set to "1"	Timing at which the bit is set to "0"
Software trigger	When the DSR bit of DMiCON register is set to "1"	<ul style="list-style-type: none"> • Immediately before a data transfer starts • When set by writing "0" in a program
Peripheral function	When the interrupt control register for the peripheral function that is selected by the DSEL3 to DSEL0 and DMS bits of DMiCON register has its IR bit set to "1"	

Channel Priority and DMA Transfer Timing

If both DMA0 and DMA1 are enabled and DMA transfer request signals from DMA0 and DMA1 are detected active in the same sampling period (one period from a falling edge to the next falling edge of BCLK), the DMAS bit on each channel is set to “1” (DMA requested) at the same time. In this case, the DMA requests are arbitrated according to the channel priority, DMA0 > DMA1. The following describes DMAC operation when DMA0 and DMA1 requests are detected active in the same sampling period. Figure 1.11.6 shows an example of DMA transfer effected by external factors.

In Figure 1.11.6, because DMA0 and DMA1 requests occurred at the same time, DMA0 which has higher channel priority is accepted first and a DMA transfer on it starts. When DMA0 finishes one transfer unit, it relinquishes control of the bus to the CPU, and when the CPU finishes one bus access, DMA1 starts a transfer next and after completion of one transfer unit, returns control of the bus to the CPU.

Note that because there is only one DMAS bit on each channel, the number of times DMA is requested cannot be counted. Therefore, even if multiple DMA requests occurred before gaining control of the bus as in the case of DMA1 in Figure 1.11.6, the DMAS bit is set to “0” when control of the bus is gained and after completion of one transfer unit, control of the bus is returned to the CPU.




Figure 1.11.6. DMA Transfer by External Factors

Timers

Five 16-bit timers, each capable of operating independently of the others. The count source for each timer acts as a clock, to control such timer operations as counting, reloading, etc. Figures 1.12.1 show block diagrams of timer A.




Figure 1.12.1. Timer A Configuration

Timer A

Figure 1.12.2 shows a block diagram of the timer A. Figures 1.12.3 to 1.12.5 show registers related to the timer A.

The timer A supports the following four modes. Except in event counter mode, timers A0 to A4 all have the same function. Use the TMOD1 to TMOD0 bits of TAI_iMR register (i = 0 to 4) to select the desired mode.

- **Timer mode:** The timer counts an internal count source.
- **Event counter mode:** The timer counts pulses from an external device or overflows and underflows of other timers.
- **One-shot timer mode:** The timer outputs a pulse only once before it reaches the minimum count “0000₁₆.”
- **Pulse width modulation (PWM) mode:** The timer outputs pulses in a given width successively.




Figure 1.12.2. Timer A Block Diagram




Figure 1.12.3. TA0MR to TA4MR Registers

Timer Ai register (i= 0 to 4) (Note 1)

<div style="display: flex; justify-content: space-around;"> <div style="text-align: center;">(b15) b7</div> <div style="text-align: center;">(b8) b0 b7</div> </div> <div style="border: 1px solid black; width: 100px; height: 15px; margin: 5px auto;"></div>		Symbol	Address	After reset
		TA0	0387 ₁₆ , 0386 ₁₆	Indeterminate
		TA1	0389 ₁₆ , 0388 ₁₆	Indeterminate
		TA2	038B ₁₆ , 038A ₁₆	Indeterminate
		TA3	038D ₁₆ , 038C ₁₆	Indeterminate
		TA4	038F ₁₆ , 038E ₁₆	Indeterminate

Mode	Function	Setting range	RW
Timer mode	Divide the count source by n + 1 where n = set value	0000 ₁₆ to FFFF ₁₆	RW
Event counter mode	Divide the count source by FFFF ₁₆ – n + 1 where n = set value when counting up or by n + 1 when counting down (Note 5)	0000 ₁₆ to FFFF ₁₆	RW
One-shot timer mode	Divide the count source by n where n = set value and cause the timer to stop	0000 ₁₆ to FFFF ₁₆ (Notes 2, 4)	WO
Pulse width modulation mode (16-bit PWM)	Modify the pulse width as follows: PWM period: $(2^{16} - 1) / f_j$ High level PWM pulse width: n / f_j where n = set value, f_j = count source frequency	0000 ₁₆ to FFFE ₁₆ (Note 3, 4)	WO
Pulse width modulation mode (8-bit PWM)	Modify the pulse width as follows: PWM period: $(2^8 - 1) \times (m + 1) / f_j$ High level PWM pulse width: $(m + 1)n / f_j$ where n = high-order address set value, m = low-order address set value, f_j = count source frequency	00 ₁₆ to FE ₁₆ (High-order address) 00 ₁₆ to FF ₁₆ (Low-order address) (Note 3, 4)	WO

Note 1: The register must be accessed in 16 bit units.

Note 2: If the TAI register is set to '0000₁₆', the counter does not work and timer Ai interrupt requests are not generated either. Furthermore, if "pulse output" is selected, no pulses are output from the TAIOUT pin.

Note 3: If the TAI register is set to '0000₁₆', the pulse width modulator does not work, the output level on the TAIOUT pin remains low, and timer Ai interrupt requests are not generated either. The same applies when the 8 high-order bits of the timer TAI register are set to '0016' while operating as an 8-bit pulse width modulator.

Note 4: Use the MOV instruction to write to the TAI register.

Note 5: The timer counts pulses from an external device or overflows or underflows in other timers.

Count start flag

Count start flag		Symbol TABS	Address 0380 ₁₆	After reset 00 ₁₆
<div><div><div>b7</div><div>b6</div><div>b5</div><div>b4</div><div>b3</div><div>b2</div><div>b1</div><div>b0</div></div><div><div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div></div></div>				

Up/down flag (Note 1)

<div style="display: flex; justify-content: space-around;"> <div style="text-align: center;">b7 b6 b5 b4 b3 b2 b1 b0</div> <div style="border: 1px solid black; width: 100px; height: 15px; position: relative;"> <div style="position: absolute; top: 0; left: 0; width: 100%; height: 100%; background: repeating-linear-gradient(45deg, transparent, transparent 2px, black 2px, black 4px);"></div> </div> </div>		Symbol	Address	After reset
		UDF	0384 ₁₆	00 ₁₆

Bit symbol	Bit name	Function	RW
TA0UD	Timer A0 up/down flag	0 : Down count 1 : Up count Enabled by setting the TAIMR register's MR2 bit to "0" (= switching source in UDF register) during event counter mode.	RW
TA1UD	Timer A1 up/down flag		RW
TA2UD	Timer A2 up/down flag		RW
TA3UD	Timer A3 up/down flag		RW
TA4UD	Timer A4 up/down flag		RW
TA2P	Timer A2 two-phase pulse signal processing select bit	0 : two-phase pulse signal processing disabled 1 : two-phase pulse signal processing enabled (Notes 2, 3)	WO
TA3P	Timer A3 two-phase pulse signal processing select bit		WO
TA4P	Timer A4 two-phase pulse signal processing select bit		WO

Note 1: Use MOV instruction to write to this register.

Note 2: Make sure the port direction bits for the TA2 IN to TA4I N and TA2 OUT to TA4 OUT pins are set to "0" (input mode).

Note 3: When not using the two-phase pulse signal processing function, set the corresponding bit to "0" (TA2P and TA3P must be set "0").

Figure 1.12.4. TA0 to TA4 Registers, TABSR Register, and UDF Register




Figure 1.12.5. ONSF Register, TRGSR Register, and CPSRF Register

1. Timer Mode

In timer mode, the timer counts a count source generated internally (see Table 1.12.1). Figure 1.12.6 shows TAIiMR register in timer mode.

Table 1.12.1. Specifications in Timer Mode

Item	Specification
Count source	f ₁ , f ₂ , f ₈ , f ₃₂
Count operation	<ul style="list-style-type: none"> Down-count When the timer underflows, it reloads the reload register contents and continues counting
Divide ratio	1/(n+1) n: set value of TAIiMR register (i= 0 to 4) 0000 ₁₆ to FFFF ₁₆
Count start condition	Set TAIiS bit of TABSR register to "1" (= start counting)
Count stop condition	Set TAIiS bit to "0" (= stop counting)
Interrupt request generation timing	Timer underflow
TAiIN pin function	I/O port or gate input i≠2, 3
TAiOUT pin function	I/O port or pulse output
Read from timer	Count value can be read by reading TAIi register
Write to timer	<ul style="list-style-type: none"> When not counting and until the 1st count source is input after counting start Value written to TAIi register is written to both reload register and counter When counting (after 1st count source input) Value written to TAIi register is written to only reload register (Transferred to counter when reloaded next)
Select function	<ul style="list-style-type: none"> Gate function Counting can be started and stopped by an input signal to TAIiIN pin Pulse output function Whenever the timer underflows, the output polarity of TAIiOUT pin is inverted. When not counting, the pin outputs a low.




Figure 1.12.6. Timer Ai Mode Register in Timer Mode

2. Event Counter Mode

In event counter mode, the timer counts pulses from an external device or overflows and underflows of other timers. Timer A4 can count two-phase external signals. Table 1.12.2 lists specifications in event counter mode (when not processing two-phase pulse signal). Table 1.12.3 lists specifications in event counter mode (when processing two-phase pulse signal with the timer A4). Figure 1.12.7 shows TAI_{MR} register in event counter mode (when not processing two-phase pulse signal). Figure 1.12.8 shows TA4MR registers in event counter mode (when processing two-phase pulse signal with the timer A4).

Table 1.12.2. Specifications in Event Counter Mode (when not processing two-phase pulse signal)

Item	Specification
Count source	<ul style="list-style-type: none"> External signals input to TAI_{IN} pin (i=0 to 4) (effective edge can be selected in program) timer A_j (j=i-1, except j=4 if i=0) overflows or underflows, timer A_k (k=i+1, except k=0 if i=4) overflows or underflows
Count operation	<ul style="list-style-type: none"> Up-count or down-count can be selected by external signal or program When the timer overflows or underflows, it reloads the reload register contents and continues counting. When operating in free-running mode, the timer continues counting without reloading.
Divided ratio	$1 / (FFFF_{16} - n + 1)$ for up-count $1 / (n + 1)$ for down-count n : set value of TAI register 0000 ₁₆ to FFFF ₁₆
Count start condition	Set TAI _S bit of TABSR register to "1" (= start counting)
Count stop condition	Set TAI _S bit to "0" (= stop counting)
Interrupt request generation timing	Timer overflow or underflow
TAI _{IN} pin function	I/O port or count source input i≠2, 3
TAI _{OUT} pin function	I/O port, pulse output, or up/down-count select input
Read from timer	Count value can be read by reading TAI register
Write to timer	<ul style="list-style-type: none"> When not counting and until the 1st count source is input after counting start Value written to TAI register is written to both reload register and counter When counting (after 1st count source input) Value written to TAI register is written to only reload register (Transferred to counter when reloaded next)
Select function	<ul style="list-style-type: none"> Free-run count function Even when the timer overflows or underflows, the reload register content is not reloaded to it Pulse output function Whenever the timer underflows or underflows, the output polarity of TAI_{OUT} pin is inverted . When not counting, the pin outputs a low.

Timer Ai mode register (i=0 to 4)
(When not using two-phase pulse signal processing)

b7	b6	b5	b4	b3	b2	b1	b0	Symbol TA0MR to TA4MR	Address 0396 ₁₆ to 039A ₁₆	After reset 00 ₁₆
		0				0	1			

Note 1: During event counter mode, the count source can be selected using the ONSF and TRGSR registers.

Note 2: TA0OUT pin is N-channel open drain output.

Note 3: Effective when the TAiGH and TAiGL bits of ONSF or TRGSR register are '002' (TAiIN pin input).

Note 4: Count down when input on TAiOUT pin is low or count up when input on that pin is high. The port direction bit for TAiOUT pin must be set to "0" (= input mode).

Figure 1.12.7. TAIiMR Register in Event Counter Mode (when not using two-phase pulse signal processing)

Table 1.12.3. Specifications in Event Counter Mode (when processing two-phase pulse signal with timer A4)

Item	Specification
Count source	• Two-phase pulse signals input to TAI _{IN} or TAI _{OUT} pins (i = 4)
Count operation	<ul style="list-style-type: none"> • Up-count or down-count can be selected by two-phase pulse signal • When the timer overflows or underflows, it reloads the reload register contents and continues counting. When operating in free-running mode, the timer continues counting without reloading.
Divide ratio	$1/(FFFF_{16} - n + 1)$ for up-count $1/(n + 1)$ for down-count n : set value of TAI register 0000 ₁₆ to FFFF ₁₆
Count start condition	Set TAI _S bit of TABSR register to "1" (= start counting)
Count stop condition	Set TAI _S bit to "0" (= stop counting)
Interrupt request generation timing	Timer overflow or underflow
TAI _{IN} pin function	Two-phase pulse input
TAI _{OUT} pin function	Two-phase pulse input
Read from timer	Count value can be read by reading timer A4 register
Write to timer	<ul style="list-style-type: none"> • When not counting and until the 1st count source is input after counting start Value written to TAI register is written to both reload register and counter • When counting (after 1st count source input) Value written to TAI register is written to reload register (Transferred to counter when reloaded next)
Select function	<ul style="list-style-type: none"> • Multiply-by-4 processing operation (timer A4) <p>If the phase relationship is such that TAK_{IN}(k=4) pin goes "H" when the input signal on TAK_{OUT} pin is "H", the timer counts up rising and falling edges on TAK_{OUT} and TAK_{IN} pins. If the phase relationship is such that TAK_{IN} pin goes "L" when the input signal on TAK_{OUT} pin is "H", the timer counts down rising and falling edges on TAK_{OUT} and TAK_{IN} pins.</p>





Figure 1.12.8. TA4MR Registers in Event Counter Mode (when using two-phase pulse signal processing with timer A4)

3. One-shot Timer Mode

In one-shot timer mode, the timer is activated only once by one trigger. (See Table 1.12.4.) When the trigger occurs, the timer starts up and continues operating for a given period. Figure 1.12.9 shows the TAI_{MR} register in one-shot timer mode.

Table 1.12.4. Specifications in One-shot Timer Mode

Item	Specification
Count source	f1, f2, f8, f32
Count operation	<ul style="list-style-type: none"> Down-count When the counter reaches 0000₁₆, it stops counting after reloading a new value If a trigger occurs when counting, the timer reloads a new count and restarts counting
Divide ratio	$1/n$ n : set value of TAI register 0000 ₁₆ to FFFF ₁₆ However, the counter does not work if the divide-by- n value is set to 0000 ₁₆ .
Count start condition	TAI _S bit of TABSR register = "1" (start counting) and one of the following triggers occurs. <ul style="list-style-type: none"> External trigger input from the TAI_{IN} pin timer A_j ($j=i-1$, except $j=4$ if $i=0$) overflow or underflow, timer A_k ($k=i+1$, except $k=0$ if $i=4$) overflow or underflow The TAI_{OS} bit of ONSF register is set to "1" (= timer starts)
Count stop condition	<ul style="list-style-type: none"> When the counter is reloaded after reaching "0000₁₆" TAI_S bit is set to "0" (= stop counting)
Interrupt request generation timing	When the counter reaches "0000 ₁₆ "
TAI _{IN} pin function	I/O port or trigger input
TAI _{OUT} pin function	I/O port or pulse output
Read from timer	An indeterminate value is read by reading TAI register
Write to timer	<ul style="list-style-type: none"> When not counting and until the 1st count source is input after counting start Value written to TAI register is written to both reload register and counter When counting (after 1st count source input) Value written to TAI register is written to only reload register (Transferred to counter when reloaded next)
Select function	<ul style="list-style-type: none"> Pulse output function The timer outputs a low when not counting and a high when counting.

Figure 1.12.9. TA_iMR Register in One-shot Timer Mode

4. Pulse Width Modulation (PWM) Mode

In PWM mode, the timer outputs pulses of a given width in succession (see Table 1.12.5). The counter functions as either 16-bit pulse width modulator or 8-bit pulse width modulator. Figure 1.12.10 shows TAI_{MR} register in pulse width modulation mode. Figures 1.12.11 and 1.12.12 show examples of how a 16-bit pulse width modulator operates and how an 8-bit pulse width modulator operates.

Table 1.12.5. Specifications in PWM Mode

Item	Specification
Count source	f ₁ , f ₂ , f ₈ , f ₃₂
Count operation	<ul style="list-style-type: none"> Down-count (operating as an 8-bit or a 16-bit pulse width modulator) The timer reloads a new value at a rising edge of PWM pulse and continues counting The timer is not affected by a trigger that occurs during counting
16-bit PWM	<ul style="list-style-type: none"> High level width n / f_j n: set value of TAI register ($i=0$ to 4) Cycle time $(2^{16}-1) / f_j$ fixed f_j: count source frequency (f₁, f₂, f₈, f₃₂)
8-bit PWM	<ul style="list-style-type: none"> High level width $n \times (m+1) / f_j$ n: set value of TAI_{MR} register high-order address Cycle time $(2^8-1) \times (m+1) / f_j$ m: set value of TAI_{MR} register low-order address
Count start condition	<ul style="list-style-type: none"> External trigger input from the TAI_{IN} pin timer A_j ($j=i-1$, except $j=4$ if $i=0$) overflow or underflow, timer A_k ($k=i+1$, except $k=0$ if $i=4$) overflow or underflow TAIS bit of TABSR register is set to "1" (= start counting)
Count stop condition	TAIS bit is set to "0" (= stop counting)
Interrupt request generation timing	PWM pulse goes "L"
TAI _{IN} pin function	I/O port or trigger input
TAI _{OUT} pin function	Pulse output
Read from timer	An indeterminate value is read by reading TAI register
Write to timer	<ul style="list-style-type: none"> When not counting and until the 1st count source is input after counting start Value written to TAI register is written to both reload register and counter When counting (after 1st count source input) Value written to TAI register is written to only reload register (Transferred to counter when reloaded next)




Figure 1.12.10. TAIiMR Register in PWM Mode




Figure 1.12.11. Example of 16-bit Pulse Width Modulator Operation




Figure 1.12.12. Example of 8-bit Pulse Width Modulator Operation

Serial I/O

Serial I/O is configured with five channels: UART0 to UART2, SI/O3 and SI/O4.

UARTi (i=0 to 2)

UARTi each have an exclusive timer to generate a transfer clock, so they operate independently of each other.

Figure 1.13.1 shows the block diagram of UARTi. Figures 1.13.2 shows the block diagram of the UARTi transmit/receive.

UARTi has the following modes:

- Clock synchronous serial I/O mode
- Clock asynchronous serial I/O mode (UART mode).
- Special mode 1 (I²C mode)
- Special mode 2

Figures 1.13.3 to 1.13.8 show the UARTi-related registers.

Refer to tables listing each mode for register setting.




Figure 1.13.1. UARTi Block Diagram





Figure 1.13.2. UARTi Transmit/Receive Unit

UARTi transmit buffer register (i=0 to 2)(Note)




Symbol	Address	After reset
U0TB	03A3 ₁₆ -03A2 ₁₆	Indeterminate
U1TB	03AB ₁₆ -03AA ₁₆	Indeterminate
U2TB	037B ₁₆ -037A ₁₆	Indeterminate

Function	RW
Transmit data	WO
Nothing is assigned. In an attempt to write to these bits, write "0". The value, if read, turns out to be indeterminate.	—

Note: Use MOV instruction to write to this register.

UARTi receive buffer register (i=0 to 2)




Symbol	Address	After reset
U0RB	03A7 ₁₆ -03A6 ₁₆	Indeterminate
U1RB	03AF ₁₆ -03AE ₁₆	Indeterminate
U2RB	037F ₁₆ -037E ₁₆	Indeterminate

Bit symbol	Bit name	Function	RW
—	—	Receive data (D ₇ to D ₀)	RO
(b7-b0)	—	Receive data (D ₈)	RO
(b8)	—	Receive data (D ₈)	RO
—	Nothing is assigned. In an attempt to write to these bits, write "0". The value, if read, turns out to be "0".	—	—
(b10-b9)	Nothing is assigned.	—	—
ABT	Arbitration lost detecting flag (Note 2)	0 : Not detected 1 : Detected	RW
OER	Overrun error flag (Note 1)	0 : No overrun error 1 : Overrun error found	RO
FER	Framing error flag (Note 1)	0 : No framing error 1 : Framing error found	RO
PER	Parity error flag (Note 1)	0 : No parity error 1 : Parity error found	RO
SUM	Error sum flag (Note 1)	0 : No error 1 : Error found	RO

Note 1: When the UiMR register's SMD2 to SMD0 bits = "000₂" (serial I/O disabled) or the UiC1 register's RE bit = "0" (reception disabled), all of the SUM, PER, FER and OER bits are set to "0" (no error). The SUM bit is set to "0" (no error) when all of the PER, FER and OER bits = "0" (no error). Also, the PER and FER bits are set to "0" by reading the lower byte of the UiRB register.

Note 2: The ABT bit is set to "0" by writing "0" in a program. (Writing "1" has no effect.)

UARTi bit rate generator (i=0 to 2)(Notes 1, 2)



Symbol	Address	After reset
U0BRG	03A1 ₁₆	Indeterminate
U1BRG	03A9 ₁₆	Indeterminate
U2BRG	0379 ₁₆	Indeterminate

Function	Setting range	RW
Assuming that set value = n, UiBRG divides the count source by n + 1	00 ₁₆ to FF ₁₆	WO

Note 1: Write to this register while serial I/O is neither transmitting nor receiving.

Note 2: Use MOV instruction to write to this register.

Figure 1.13.3. U0TB to U2TB Register, U0RB to U2RB Register, and U0BRG to U2BRG Register

UARTi transmit/receive mode register (i=0 to 2)

<div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div> <div>b7b6b5b4b3b2b1b0</div>								Symbol	Address	After reset	
								U0MR to U2MR	03A0 ₁₆ , 03A8 ₁₆ , 0378 ₁₆	00 ₁₆	
								Bit symbol	Bit name	Function	RW
								SMD0	Serial I/O mode select bit (Note 2)	b2 b1 b0 0 0 0 : Serial I/O disabled 0 0 1 : Clock synchronous serial I/O mode 0 1 0 : I ² C mode (Note 3) 1 0 0 : UART mode transfer data 7 bits long 1 0 1 : UART mode transfer data 8 bits long 1 1 0 : UART mode transfer data 9 bits long Must not be set except above	RW
								SMD1			RW
								SMD2			RW
								CKDIR	Internal/external clock select bit	0 : Internal clock 1 : External clock (Note 1) (Note 4)	RW
								STPS	Stop bit length select bit	0 : One stop bit 1 : Two stop bits	RW
								PRY	Odd/even parity select bit	Effective when PRYE = 1 0 : Odd parity 1 : Even parity	RW
								PRYE	Parity enable bit	0 : Parity disabled 1 : Parity enabled	RW
								IOPOL	TxD, RxD I/O polarity reverse bit	0 : No reverse 1 : Reverse	RW

Note 1: Set the corresponding port direction bit for each CLKi pin to "0" (input mode).

Note 2: To receive data, set the corresponding port direction bit for each RxDi pin to "0" (input mode).

Note 3: Set the corresponding port direction bit for SCL and SDA pins to "0" (input mode).

Note 4: Set "0" to select internal clock of UART2.

UARTi transmit/receive control register 0 (i=0 to 2)

<div><div></div><div></div><div></div><div></div><div></div><div></div><div></div><div></div></div>								Symbol	Address	After reset	
								U0C0 to U2C0	03A4 ₁₆ , 03AC ₁₆ , 037C ₁₆	00001000 ₂	
								Bit symbol	Bit name	Function	RW
								CLK0	BRG count source select bit	b1 b0 0 0 : f _{1SIO} or f _{2SIO} is selected 0 1 : f _{8SIO} is selected 1 0 : f _{32SIO} is selected 1 1 : Must not be set	RW
								CLK1			RW
								CRS	CTS/RTS function select bit (Note 4)	Effective when CRD = 0 0 : CTS function is selected (Note 1) 1 : RTS function is selected	RW
								TXEPT	Transmit register empty flag	0 : Data present in transmit register (during transmission) 1 : No data present in transmit register (transmission completed)	RO
								CRD	CTS/RTS disable bit	0 : CTS/RTS function enabled 1 : CTS/RTS function disabled (P60, P64 and P73 can be used as I/O ports)	RW
								NCH	Data output select bit (Note 2)	0 : TxDi/SDAi and SCLi pins are CMOS output 1 : TxDi/SDAi and SCLi pins are N-channel open-drain output	RW
								CKPOL	CLK polarity select bit	0 : Transmit data is output at falling edge of transfer clock and receive data is input at rising edge 1 : Transmit data is output at rising edge of transfer clock and receive data is input at falling edge	RW
								UFORM	Transfer format select bit (Note 3)	0 : LSB first 1 : MSB first	RW

Note 1: Set the corresponding port direction bit for each CTSi pin to "0" (input mode).

Note 2: TxD2/SDA2 are N-channel open-drain output. Cannot be set to the CMOS output. NCH bit of U2C0 register is effective in an output set up of SCL2 pin.

Note 3: Effective for clock synchronous serial I/O mode and UART mode transfer data 8 bits long.

Note 4: CTS1/RTS1 can be used when the UCON register's CLKMD1 bit = "0" (only CLK1 output) and the UCON register's RCSP bit = "0" (CTS0/RTS0 not separated).

Figure 1.13.4. U0MR to U2MR Register and U0C0 to U2C0 Register


UARTi transmit/receive control register 1 (i=0, 1)



Symbol Address After reset
 U0C1, U1C1 03A5₁₆, 03AD₁₆ 00000010₂

Bit symbol	Bit name	Function	RW
TE	Transmit enable bit	0 : Transmission disabled 1 : Transmission enabled	RW
TI	Transmit buffer empty flag	0 : Data present in UiTB register 1 : No data present in UiTB register	RO
RE	Receive enable bit	0 : Reception disabled 1 : Reception enabled	RW
RI	Receive complete flag	0 : No data present in UiRB register 1 : Data present in UiRB register	RO
— (b5-b4)	Nothing is assigned. When write, set "0". When read, these contents are "0".		—
UiLCH	Data logic select bit	0 : No reverse 1 : Reverse	RW
UiERE	Error signal output enable bit	0 : Output disabled 1 : Output enabled	RW

UART2 transmit/receive control register 1




Symbol Address After reset
 U2C1 037D₁₆ 00000010₂

Bit symbol	Bit name	Function	RW
TE	Transmit enable bit	0 : Transmission disabled 1 : Transmission enabled	RW
TI	Transmit buffer empty flag	0 : Data present in U2TB register 1 : No data present in U2TB register	RO
RE	Receive enable bit	0 : Reception disabled 1 : Reception enabled	RW
RI	Receive complete flag	0 : No data present in U2RB register 1 : Data present in U2RB register	RO
U2IRS	UART2 transmit interrupt cause select bit	0 : Transmit buffer empty (TI = 1) 1 : Transmit is completed (TXEPT = 1)	RW
U2RRM	UART2 continuous receive mode enable bit	0 : Continuous receive mode disabled 1 : Continuous receive mode enabled	RW
U2LCH	Data logic select bit	0 : No reverse 1 : Reverse	RW
U2ERE	Error signal output enable bit	0 : Output disabled 1 : Output enabled	RW

Figure 1.13.5. U0C1 to U2C1 Registers

UART transmit/receive control register 2



Symbol
UCON


Address
03B0₁₆

After reset
X0000000₂

Bit symbol	Bit name	Function	RW
U0IRS	UART0 transmit interrupt cause select bit	0 : Transmit buffer empty (TI = 1) 1 : Transmission completed (TXEPT = 1)	RW
U1IRS	UART1 transmit interrupt cause select bit	0 : Transmit buffer empty (TI = 1) 1 : Transmission completed (TXEPT = 1)	RW
U0RRM	UART0 continuous receive mode enable bit	0 : Continuous receive mode disabled 1 : Continuous receive mode enable	RW
U1RRM	UART1 continuous receive mode enable bit	0 : Continuous receive mode disabled 1 : Continuous receive mode enabled	RW
CLKMD0	UART1 CLK/CLKS select bit 0	Effective when CLKMD1 = "1" 0 : Clock output from CLK1 1 : Clock output from CLKS1	RW
CLKMD1	UART1 CLK/CLKS select bit 1 (Note)	0 : CLK output is only CLK1 1 : Transfer clock output from multiple pins function selected	RW
RCSP	Separate UART0 CTS/RTS bit	0 : CTS/RTS shared pin 1 : CTS/RTS separated (CTS ₀ supplied from the P64 pin)	RW
— (b7)	Nothing is assigned. When write, set "0". When read, its content is indeterminate.		—

Note: When using multiple transfer clock output pins, make sure the following conditions are met:
U1MR register's CKDIR bit = "0" (internal clock)

UART2 special mode register (i=0 to 2)



Symbol
U0SMR to U2SMR

Address
036F₁₆, 0373₁₆, 0377₁₆


After reset
X0000000₂

Bit symbol	Bit name	Function	RW
IICM	I ² C mode select bit	0 : Other than I ² C mode 1 : I ² C mode	RW
ABC	Arbitration lost detecting flag control bit	0 : Update per bit 1 : Update per byte	RW
BBS	Bus busy flag	0 : STOP condition detected 1 : START condition detected (busy)	RW (Note1)
— (b3-b6)	Reserved bit	Set to "0"	RW
— (b7)	Nothing is assigned. When write, set "0". When read, its content is indeterminate.		—

Note 1: The BBS bit is set to "0" by writing "0" in a program. (Writing "1" has no effect.).

Figure 1.13.6. UCON Register and U0SMR to U2SMR Registers


UARTi special mode register 2 (i=0 to 2)



Symbol Address After reset
U0SMR2 to U2SMR2 036E₁₆, 0372₁₆, 0376₁₆ X0000000₂

Bit symbol	Bit name	Function	RW
IICM2	I ² C mode select bit 2	Refer to Table 1.16.4	RW
CSC	Clock-synchronous bit	0 : Disabled 1 : Enabled	RW
SWC	SCL wait output bit	0 : Disabled 1 : Enabled	RW
ALS	SDA output stop bit	0 : Disabled 1 : Enabled	RW
STAC	UARTi initialization bit	0 : Disabled 1 : Enabled	RW
SWC2	SCL wait output bit 2	0 : Transfer clock 1 : 0 output	RW
SDHI	SDA output disable bit	0 : Enabled 1 : Disabled (high impedance)	RW
— (b7)	Nothing is assigned. When write, set "0". When read, its content is indeterminate.		—

UARTi special mode register 3 (i=0 to 2)



Symbol Address After reset
U0SMR3 to U2SMR3 036D₁₆, 0371₁₆, 0375₁₆ 000X0X0X₂


Bit symbol	Bit name	Function	RW
— (b0)	Nothing is assigned. When write, set "0". When read, its content is indeterminate.		—
CKPH	Clock phase set bit	0 : Without clock delay 1 : With clock delay	RW
— (b2)	Nothing is assigned. When write, set "0". When read, its content is indeterminate.		—
NODC	Clock output select bit	0 : CLKi is CMOS output 1 : CLKi is N-channel open drain output	RW
— (b4)	Nothing is assigned. When write, set "0". When read, its content is indeterminate.		—
DL0	SDAi digital delay setup bit (Note 1, Note 2)	b7 b6 b5 0 0 0 : Without delay 0 0 1 : 1 to 2 cycle(s) of UiBRG count source 0 1 0 : 2 to 3 cycles of UiBRG count source 0 1 1 : 3 to 4 cycles of UiBRG count source 1 0 0 : 4 to 5 cycles of UiBRG count source 1 0 1 : 5 to 6 cycles of UiBRG count source 1 1 0 : 6 to 7 cycles of UiBRG count source 1 1 1 : 7 to 8 cycles of UiBRG count source	RW
DL1			RW
DL2			RW

Note 1 : The DL2 to DL0 bits are used to generate a delay in SDAi output by digital means during I²C mode. In other than I²C mode, set these bits to "0002" (no delay).

Note 2 : The amount of delay varies with the load on SCLi and SDAi pins. Also, when using an external clock, the amount of delay increases by about 100 ns.

Figure 1.13.7. U0SMR2 to U2SMR2 Registers and U0SMR3 to U2SMR3 Registers

UARTi special mode register 4 (i=0 to 2)



Symbol
U0SMR4 to U2SMR4

Address
036C₁₆, 0370₁₆, 0374₁₆

After reset
00₁₆

Bit symbol	Bit name	Function	RW
STAREQ	Start condition generate bit (Note)	0 : Clear 1 : Start	RW
RSTAREQ	Restart condition generate bit (Note)	0 : Clear 1 : Start	RW
STPREQ	Stop condition generate bit (Note)	0 : Clear 1 : Start	RW
STSPSEL	SCL, SDA output select bit	0 : Start and stop conditions not output 1 : Start and stop conditions output	RW
ACKD	ACK data bit	0 : ACK 1 : NACK	RW
ACKC	ACK data output enable bit	0 : Serial I/O data output 1 : ACK data output	RW
SCLHI	SCL output stop enable bit	0 : Disabled 1 : Enabled	RW
SWC9	SCL wait bit 3	0 : SCL "L" hold disabled 1 : SCL "L" hold enabled	RW

Note: Set to "0" when each condition is generated.

Figure 1.13.8. U0SMR4 to U2SMR4 Registers

Clock Synchronous serial I/O Mode

The clock synchronous serial I/O mode uses a transfer clock to transmit and receive data. Table 1.14.1 lists the specifications of the clock synchronous serial I/O mode. Table 1.14.2 lists the registers used in clock synchronous serial I/O mode and the register values set. UART2 is not available in this mode.

Table 1.14.1. Clock Synchronous Serial I/O Mode Specifications

Item	Specification
Transfer data format	<ul style="list-style-type: none"> Transfer data length: 8 bits
Transfer clock	<ul style="list-style-type: none"> UiMR(i=0 to 1) register's CKDIR bit = "0" (internal clock) : $f_j / 2(n+1)$ $f_j = f_{1SIO}, f_{2SIO}, f_{8SIO}, f_{32SIO}$. n: Setting value of UiBRG register 0016 to FF16 CKDIR bit = "1" (external clock) : Input from CLKi pin
Transmission, reception control	<ul style="list-style-type: none"> Selectable from CTS function, RTS function or CTS/RTS function disable
Transmission start condition	<ul style="list-style-type: none"> Before transmission can start, the following requirements must be met (Note 1) <ul style="list-style-type: none"> The TE bit of UiC1 register= 1 (transmission enabled) The TI bit of UiC1 register = 0 (data present in UiTB register) If CTS function is selected, input on the CTSi pin = "L"
Reception start condition	<ul style="list-style-type: none"> Before reception can start, the following requirements must be met (Note 1) <ul style="list-style-type: none"> The RE bit of UiC1 register= 1 (reception enabled) The TE bit of UiC1 register= 1 (transmission enabled) The TI bit of UiC1 register= 0 (data present in the UiTB register)
Interrupt request generation timing	<ul style="list-style-type: none"> For transmission, one of the following conditions can be selected <ul style="list-style-type: none"> The UiIRS bit (Note 3) = 0 (transmit buffer empty): when transferring data from the UiTB register to the UARTi transmit register (at start of transmission) The UiIRS bit = 1 (transfer completed): when the serial I/O finished sending data from the UARTi transmit register For reception <ul style="list-style-type: none"> When transferring data from the UARTi receive register to the UiRB register (at completion of reception)
Error detection	<ul style="list-style-type: none"> Overrun error (Note 2) <ul style="list-style-type: none"> This error occurs if the serial I/O started receiving the next data before reading the UiRB register and received the 7th bit of the next data
Select function	<ul style="list-style-type: none"> CLK polarity selection <ul style="list-style-type: none"> Transfer data input/output can be chosen to occur synchronously with the rising or the falling edge of the transfer clock LSB first, MSB first selection <ul style="list-style-type: none"> Whether to start sending/receiving data beginning with bit 0 or beginning with bit 7 can be selected Continuous receive mode selection <ul style="list-style-type: none"> Reception is enabled immediately by reading the UiRB register Switching serial data logic <ul style="list-style-type: none"> This function reverses the logic value of the transmit/receive data Transfer clock output from multiple pins selection (UART1) <ul style="list-style-type: none"> The output pin can be selected in a program from two UART1 transfer clock pins that have been set Separate CTS/RTS pins (UART0) <ul style="list-style-type: none"> CTS0 and RTS0 are input/output from separate pins

Note 1: When an external clock is selected, the conditions must be met while if the UiC0 register's CKPOL bit = "0" (transmit data output at the falling edge and the receive data taken in at the rising edge of the transfer clock), the external clock is in the high state; if the UiC0 register's CKPOL bit = "1" (transmit data output at the rising edge and the receive data taken in at the falling edge of the transfer clock), the external clock is in the low state.

Note 2: If an overrun error occurs, the value of UiRB register will be indeterminate. The IR bit of SiRIC register does not change.

Note 3: The U0IRS and U1IRS bits respectively are the UCON register bits 0 and 1.

Table 1. 14. 2. Registers to Be Used and Settings in Clock Synchronous Serial I/O Mode

Register	Bit	Function
UiTB(Note3)	0 to 7	Set transmission data
UiRB(Note3)	0 to 7	Reception data can be read
	OER	Overrun error flag
UiBRG	0 to 7	Set a transfer rate
UiMR(Note3)	SMD2 to SMD0	Set to "0012"
	CKDIR	Select the internal clock or external clock
	IOPOL	Set to "0"
UiC0	CLK1 to CLK0	Select the count source for the UiBRG register
	CRS	Select CTS or RTS to use
	TXEPT	Transmit register empty flag
	CRD	Enable or disable the CTS or RTS function
	NCH	Select TxDi pin output mode
	CKPOL	Select the transfer clock polarity
	UFORM	Select the LSB first or MSB first
UiC1	TE	Set this bit to "1" to enable transmission/reception
	TI	Transmit buffer empty flag
	RE	Set this bit to "1" to enable reception
	RI	Reception complete flag
	U2IRS (Note 1)	Select the source of UART2 transmit interrupt
	U2RRM (Note 1)	Set this bit to "1" to use continuous receive mode
	UiLCH	Set this bit to "1" to use inverted data logic
	UiERE	Set to "0"
UiSMR	0 to 7	Set to "0"
UiSMR2	0 to 7	Set to "0"
UiSMR3	0 to 2	Set to "0"
	NODC	Select clock output mode
	4 to 7	Set to "0"
UiSMR4	0 to 7	Set to "0"
UCON	U0IRS, U1IRS	Select the source of UART0/UART1 transmit interrupt
	U0RRM, U1RRM	Set this bit to "1" to use continuous receive mode
	CLKMD0	Select the transfer clock output pin when CLKMD1 = 1
	CLKMD1	Set this bit to "1" to output UART1 transfer clock from two pins
	RCSP	Set this bit to "1" to accept as input the UART0 CTS ₀ signal from the P64 pin
	7	Set to "0"

Note 1: Set the U0C1 and U1C1 register bit 4 and bit 5 to "0". The U0IRS, U1IRS, U0RRM and U1RRM bits are in the UCON register.

Note 2: Not all register bits are described above. Set those bits to "0" when writing to the registers in clock synchronous serial I/O mode.

i=0 to 1

Table 1.14.3 lists the functions of the input/output pins during clock synchronous serial I/O mode. Table 1.14.3 shows pin functions for the case where the multiple transfer clock output pin select function is deselected. Table 1.14.4 lists the P64 pin functions during clock synchronous serial I/O mode. Note that for a period from when the UARTi operation mode is selected to when transfer starts, the TxDi pin outputs an “H”. (If the N-channel open-drain output is selected, this pin is in a high-impedance state.)

Table 1.14.3. Pin Functions (When Not Select Multiple Transfer Clock Output Pin Function)

Pin name	Function	Method of selection
TxDi (i = 0 to 2) (P63, P67)	Serial data output	(Outputs dummy data when performing reception only)
RxDi (P62, P66)	Serial data input	PD6 register's PD6_2 bit=0, PD6_6 bit=0 (Can be used as an input port when performing transmission only)
CLKi (P61, P65)	Transfer clock output	UiMR register's CKDIR bit=0
	Transfer clock input	UiMR register's CKDIR bit=1 PD6 register's PD6_1 bit=0, PD6_5 bit=0
CTS $\overline{\text{i}}$ /RTS $\overline{\text{i}}$ (P60, P64)	CTS input	UiC0 register's CRD bit=0 UiC0 register's CRS bit=0 PD6 register's PD6_0 bit=0, PD6_4 bit=0
	RTS output	UiC0 register's CRD bit=0 UiC0 register's CRS bit=1
	I/O port	UiC0 register's CRD bit=1

Table 1.14.4. P64 Pin Functions


Pin function	Bit set value					
	U1C0 register		UCON register			PD6 register
	CRD	CRS	RCSP	CLKMD1	CLKMD0	PD6_4
P64	1	—	0	0	—	Input: 0, Output: 1
CTS $\overline{\text{1}}$	0	0	0	0	—	0
RTS $\overline{\text{1}}$	0	1	0	0	—	—
CTS $\overline{\text{0}}$ (Note1)	0	0	1	0	—	0
CLKS $\overline{\text{1}}$	—	—	—	1(Note 2)	1	—

Note 1: In addition to this, set the U0C0 register's CRD bit to “0” (CTS $\overline{\text{0}}$ /RTS $\overline{\text{0}}$ enabled) and the U0C0 register's CRS bit to “1” (RTS $\overline{\text{0}}$ selected).

Note 2: When the CLKMD1 bit = 1 and the CLKMD0 bit = 0, the following logic levels are output:

- High if the U1C0 register's CLKPOL bit = 0
- Low if the U1C0 register's CLKPOL bit = 1


(1) Example of transmit timing (when internal clock is selected)



The above timing diagram applies to the case where the register bits are set as follows:

- UIMR register CKDIR bit = 0 (internal clock)
- UIC0 register CRD bit = 0 (CTS/RTS enabled), CRS bit = 0 (CTS selected)
- UIC0 register CKPOL bit = 0 (transmit data output at the falling edge and receive data taken in at the rising edge of the transfer clock)
- UIRS bit = 0 (an interrupt request occurs when the transmit buffer becomes empty): U0IRS bit is the UCON register bit 0, U1IRS bit is the UCON register bit 1, and U2IRS bit is the U2C1 register bit 4

(2) Example of receive timing (when external clock is selected)



The above timing diagram applies to the case where the register bits are set as follows:

- UIMR register CKDIR bit = 1 (external clock)
- UIC0 register CRD bit = 0 (CTS/RTS enabled), CRS bit = 1 (RTS selected)
- UIC0 register CKPOL bit = 0 (transmit data output at the falling edge and receive data taken in at the rising edge of the transfer clock)

f_{EXT} : frequency of external clock

Make sure the following conditions are met when input to the CLKi pin before receiving data is high:

- UIC0 register TE bit = 1 (transmit enabled)
- UIC0 register RE bit = 1 (Receive enabled)
- Write dummy data to the UiTb register

Figure 1.14.1. Transmit and Receive Operation

(a) CLK Polarity Select Function

Use the UiC0 register ($i = 0$ to 1)'s CKPOL bit to select the transfer clock polarity. Figure 1.14.2 shows the polarity of the transfer clock.




Figure 1.14.2. Transfer Clock Polarity

(b) LSB First/MSB First Select Function

Use the UiC0 register ($i = 0$ to 1)'s UFORM bit to select the transfer format. Figure 1.14.3 shows the transfer format.




Figure 1.14.3. Transfer Format

(c) Continuous Receive Mode

When the UiRRM bit ($i = 0$ to 1) = 1 (continuous receive mode), the UiC1 register's TI bit is set to "1" (data present in the UiTB register) by reading the UiRB register. In this case, i.e., UiRRM bit = 1, do not write dummy data to the UiTB register in a program. The U0RRM and U1RRM bits are the UCON register bit 2 and bit 3, respectively.

(d) Serial Data Logic Switching Function

When the UiC1 register ($i = 0$ to 1)'s UiLCH bit = 1 (reverse), the data written to the UiTB register has its logic reversed before being transmitted. Similarly, the received data has its logic reversed when read from the UiRB register. Figure 1.14.4 shows serial data logic.




Figure 1.14.4. Serial Data Logic Switching

(e) Transfer Clock Output From Multiple Pins (UART1)

Use the UCON register's CLKMD1 to CLKMD0 bits to select one of the two transfer clock output pins. (See Figure 1.14.5.) This function can be used when the selected transfer clock for UART1 is an internal clock.




Figure 1.14.5. Transfer Clock Output From Multiple Pins

(f) $\overline{\text{CTS}}/\overline{\text{RTS}}$ Separate Function (UART0)

This function separates $\overline{\text{CTS}}_0/\overline{\text{RTS}}_0$, outputs $\overline{\text{RTS}}_0$ from the P60 pin, and accepts as input the $\overline{\text{CTS}}_0$ from the P64 pin. To use this function, set the register bits as shown below.

- U0C0 register's CRD bit = 0 (enables UART0 $\overline{\text{CTS}}/\overline{\text{RTS}}$)
- U0C0 register's CRS bit = 1 (outputs UART0 $\overline{\text{RTS}}$)
- U1C0 register's CRD bit = 0 (enables UART1 $\overline{\text{CTS}}/\overline{\text{RTS}}$)
- U1C0 register's CRS bit = 0 (inputs UART1 $\overline{\text{CTS}}$)
- UCON register's RCSP bit = 1 (inputs $\overline{\text{CTS}}_0$ from the P64 pin)
- UCON register's CLKMD1 bit = 0 (CLKS1 not used)

Note that when using the $\overline{\text{CTS}}/\overline{\text{RTS}}$ separate function, UART1 $\overline{\text{CTS}}/\overline{\text{RTS}}$ separate function cannot be used.




Figure 1.14.6. $\overline{\text{CTS}}/\overline{\text{RTS}}$ Separat Function

Clock Asynchronous Serial I/O (UART) Mode

The UART mode allows transmitting and receiving data after setting the desired transfer rate and transfer data format. Tables 1.15.1 lists the specifications of the UART mode.

Table 1.15.1. UART Mode Specifications

Item	Specification
Transfer data format	<ul style="list-style-type: none"> • Character bit (transfer data): Selectable from 7, 8 or 9 bits • Start bit: 1 bit • Parity bit: Selectable from odd, even, or none • Stop bit: Selectable from 1 or 2 bits
Transfer clock	<ul style="list-style-type: none"> • UiMR(i=0 to 2) register's CKDIR bit = 0 (internal clock) : $f_j / 16(n+1)$ $f_j = f_{1SIO}, f_{2SIO}, f_{8SIO}, f_{32SIO}$. n: Setting value of UiBRG register 00₁₆ to FF₁₆ • CKDIR bit = "1" (external clock) : $f_{EXT}/16(n+1)$ (Note 3) f_{EXT}: Input from CLKi pin. n: Setting value of UiBRG register 00₁₆ to FF₁₆
Transmission, reception control	<ul style="list-style-type: none"> • Selectable from CTS function, RTS function or CTS/RTS function disable
Transmission start condition	<ul style="list-style-type: none"> • Before transmission can start, the following requirements must be met <ul style="list-style-type: none"> – The TE bit of UiC1 register= 1 (transmission enabled) – The TI bit of UiC1 register = 0 (data present in UiTB register) – If CTS function is selected, input on the CTSi pin = "L"
Reception start condition	<ul style="list-style-type: none"> • Before reception can start, the following requirements must be met <ul style="list-style-type: none"> – The RE bit of UiC1 register= 1 (reception enabled) – Start bit detection
Interrupt request generation timing	<ul style="list-style-type: none"> • For transmission, one of the following conditions can be selected <ul style="list-style-type: none"> – The UiIRS bit (Note 2) = 0 (transmit buffer empty): when transferring data from the UiTB register to the UARTi transmit register (at start of transmission) – The UiIRS bit =1 (transfer completed): when the serial I/O finished sending data from the UARTi transmit register • For reception <ul style="list-style-type: none"> When transferring data from the UARTi receive register to the UiRB register (at completion of reception)
Error detection	<ul style="list-style-type: none"> • Overrun error (Note 1) This error occurs if the serial I/O started receiving the next data before reading the UiRB register and received the bit one before the last stop bit of the next data • Framing error This error occurs when the number of stop bits set is not detected • Parity error This error occurs when if parity is enabled, the number of 1's in parity and character bits does not match the number of 1's set • Error sum flag This flag is set (= 1) when any of the overrun, framing, and parity errors is encountered
Select function	<ul style="list-style-type: none"> • LSB first, MSB first selection Whether to start sending/receiving data beginning with bit 0 or beginning with bit 7 can be selected • Serial data logic switch This function reverses the logic of the transmit/receive data. The start and stop bits are not reversed. • Tx/D, Rx/D I/O polarity switch This function reverses the polarities of the Tx/D pin output and Rx/D pin input. The logic levels of all I/O data is reversed. • Separate CTS/RTS pins (UART0) CTS0 and RTS0 are input/output from separate pins

Note 1: If an overrun error occurs, the value of UiRB register will be indeterminate. The IR bit of SiRIC register does not change.

Note 2: The U0IRS and U1IRS bits respectively are the UCON register bits 0 and 1; the U2IRS bit is the U2C1 register bit 4.

Note 3: CKDIR of U2MR must be set "0" to select internal clock.

Table 1. 15. 2. Registers to Be Used and Settings in UART Mode

Register	Bit	Function
UiTB	0 to 8	Set transmission data (Note 1)
UiRB	0 to 8	Reception data can be read (Note 1)
	OER, FER, PER, SUM	Error flag
UiBRG	---	Set a transfer rate
UiMR	SMD2 to SMD0	Set these bits to '1002' when transfer data is 7 bits long Set these bits to '1012' when transfer data is 8 bits long Set these bits to '1102' when transfer data is 9 bits long
	CKDIR	Select the internal clock or external clock
	STPS	Select the stop bit
	PRY, PRYE	Select whether parity is included and whether odd or even
	IOPOL	Select the TxD/RxD input/output polarity
UiC0	CLK0, CLK1	Select the count source for the UiBRG register
	CRS	Select CTS or RTS to use
	TXEPT	Transmit register empty flag
	CRD	Enable or disable the CTS or RTS function
	NCH	Select TxDi pin output mode (Note 2)
	CKPOL	Set to "0"
	UFORM	LSB first or MSB first can be selected when transfer data is 8 bits long. Set this bit to "0" when transfer data is 7 or 9 bits long.
UiC1	TE	Set this bit to "1" to enable transmission
	TI	Transmit buffer empty flag
	RE	Set this bit to "1" to enable reception
	RI	Reception complete flag
	U2IRS (Note 2)	Select the source of UART2 transmit interrupt
	U2RRM (Note 2)	Set to "0"
	UiLCH	Set this bit to "1" to use inverted data logic
	UiERE	Set to "0"
UiSMR	0 to 7	Set to "0"
UiSMR2	0 to 7	Set to "0"
UiSMR3	0 to 7	Set to "0"
UiSMR4	0 to 7	Set to "0"
UCON	U0IRS, U1IRS	Select the source of UART0/UART1 transmit interrupt
	U0RRM, U1RRM	Set to "0"
	CLKMD0	Invalid because CLKMD1 = 0
	CLKMD1	Set to "0"
	RCSP	Set this bit to "1" to accept as input the UART0 CTS ₀ signal from the P64 pin
	7	Set to "0"

Note 1: The bits used for transmit/receive data are as follows: Bit 0 to bit 6 when transfer data is 7 bits long; bit 0 to bit 7 when transfer data is 8 bits long; bit 0 to bit 8 when transfer data is 9 bits long.

Note 2: Set the U0C1 and U1C1 registers bit 4 to bit 5 to "0". The U0IRS, U1IRS, U0RRM and U1RRM bits are included in the UCON register.

Note 3: TxD2 pin is N channel open-drain output. Set the U2C0 register's NCH bit to "0".

i=0 to 2

Table 1.15.3 lists the functions of the input/output pins during UART mode. Table 1.15.4 lists the P64 pin functions during UART mode. Note that for a period from when the UARTi operation mode is selected to when transfer starts, the TxDi pin outputs an “H”. (If the N-channel open-drain output is selected, this pin is in a high-impedance state.)

Table 1.15.3. I/O Pin Functions


Pin name	Function	Method of selection
TxDi (i = 0 to 2) (P63, P67, P70)	Serial data output	(Outputs dummy data when performing reception only)
RxDi (P62, P66, P71)	Serial data input	PD6 register's PD6_2 bit=0, PD6_6 bit=0, PD7 register's PD7_1 bit=0 (Can be used as an input port when performing transmission only)
CLKi (P61, P65)	Input/output port	UiMR register's CKDIR bit=0
	Transfer clock input	UiMR register's CKDIR bit=1 PD6 register's PD6_1 bit=0, PD6_5 bit=0, PD7 register's PD7_2 bit=0
$\overline{\text{CTS}}_i/\text{RTS}_i$ (P60, P64, P73)	$\overline{\text{CTS}}$ input	UiC0 register's CRD bit=0 UiC0 register's CRS bit=0 PD6 register's PD6_0 bit=0, PD6_4 bit=0, PD7 register's PD7_3 bit=0
	RTS output	UiC0 register's CRD bit=0 UiC0 register's CRS bit=1
	Input/output port	UiC0 register's CRD bit=1

Table 1.15.4. P64 Pin Functions

Pin function	Bit set value				
	U1C0 register		UCON register		PD6 register
	CRD	CRS	RCSP	CLKMD1	PD6_4
P64	1	—	0	0	Input: 0, Output: 1
$\overline{\text{CTS}}_1$	0	0	0	0	0
RTS_1	0	1	0	0	—
$\overline{\text{CTS}}_0$ (Note)	0	0	1	0	0

Note: In addition to this, set the U0C0 register's CRD bit to “0” ($\overline{\text{CTS}}_0/\text{RTS}_0$ enabled) and the U0C0 register's CRS bit to “1” (RTS_0 selected).

(1) Example of transmit timing when transfer data is 8 bits long (parity enabled, one stop bit)




The above timing diagram applies to the case where the register bits are set as follows:

- UIMR register PRYE bit = 1 (parity enabled)
- UIMR register STPS bit = 0 (1 stop bit)
- UIC0 register CRD bit = 0 (CTS/RTS enabled), CRS bit = 0 (CTS selected)
- UIRS bit = 1 (an interrupt request occurs when transmit completed):
U0IRS bit is the UCON register bit 0, U1IRS bit is the UCON register bit 1, and U2IRS bit is the U2C1 register bit 4

$$T_c = 16(n+1) / f_j \text{ or } 16(n+1) / f_{EXT}$$

f_j : frequency of UiBRG count source (f1SIO, f2SIO, f8SIO, f32SIO)
 f_{EXT} : frequency of UiBRG count source (external clock)
 n : value set to UiBRG
 i : 0 to 2

(2) Example of transmit timing when transfer data is 9 bits long (parity disabled, two stop bits)



The above timing diagram applies to the case where the register bits are set as follows:

- UIMR register PRYE bit = 0 (parity disabled)
- UIMR register STPS bit = 1 (2 stop bits)
- UIC0 register CRD bit = 1 (CTS/RTS disabled)
- UIRS bit = 0 (an interrupt request occurs when transmit buffer becomes empty):
U0IRS bit is the UCON register bit 0, U1IRS bit is the UCON register bit 1, and U2IRS bit is the U2C1 register bit 4

$$T_c = 16(n+1) / f_j \text{ or } 16(n+1) / f_{EXT}$$

f_j : frequency of UiBRG count source (f1SIO, f2SIO, f8SIO, f32SIO)
 f_{EXT} : frequency of UiBRG count source (external clock)
 n : value set to UiBRG
 i : 0 to 2

Figure 1.15.1. Transmit Operation

- Example of receive timing when transfer data is 8 bits long (parity disabled, one stop bit)





Figure 1.15.2. Receive Operation


(a) LSB First/MSB First Select Function

As shown in Figure 1.15.3, use the UiC0 register's UFORM bit to select the transfer format. This function is valid when transfer data is 8 bits long.

(1) When UiC0 register's UFORM bit = 0 (LSB first)



(2) When UiC0 register's UFORM bit = 1 (MSB first)



Note: This applies to the case where the UiC0 register's CKPOL bit = 0 (transmit data output at the falling edge and the receive data taken in at the rising edge of the transfer clock), the UiC1 register's UiLCH bit = 0 (no reverse), UiMR register's STPS bit = 0 (1 stop bit) and UiMR register's PRYE bit = 1 (parity enabled).

ST : Start bit
P : Parity bit
SP : Stop bit
i = 0 to 2

Figure 1.15.3. Transfer Format

(b) Serial Data Logic Switching Function

The data written to the UiTB register has its logic reversed before being transmitted. Similarly, the received data has its logic reversed when read from the UiRB register. Figure 1.15.4 shows serial data logic.




Figure 1.15.4. Serial Data Logic Switching

(c) TxD and RxD I/O Polarity Inverse Function

This function inverses the polarities of the TxDi pin output and RxDi pin input. The logic levels of all input/output data (including the start, stop and parity bits) are inverted. Figure 1.15.5 shows the TxD pin output and RxD pin input polarity inverse.




Figure 1.15.5. TxD and RxD I/O Polarity Inverse

(d) $\overline{\text{CTS}}/\overline{\text{RTS}}$ Separate Function (UART0)

This function separates $\overline{\text{CTS}}_0/\overline{\text{RTS}}_0$, outputs $\overline{\text{RTS}}_0$ from the P60 pin, and accepts as input the $\overline{\text{CTS}}_0$ from the P64 pin. To use this function, set the register bits as shown below.

- U0C0 register's CRD bit = 0 (enables UART0 $\overline{\text{CTS}}/\overline{\text{RTS}}$)
- U0C0 register's CRS bit = 1 (outputs UART0 $\overline{\text{RTS}}$)
- U1C0 register's CRD bit = 0 (enables UART1 $\overline{\text{CTS}}/\overline{\text{RTS}}$)
- U1C0 register's CRS bit = 0 (inputs UART1 $\overline{\text{CTS}}$)
- UCON register's RCSP bit = 1 (inputs $\overline{\text{CTS}}_0$ from the P64 pin)
- UCON register's CLKMD1 bit = 0 (CLKS1 not used)

Note that when using the $\overline{\text{CTS}}/\overline{\text{RTS}}$ separate function, UART1 $\overline{\text{CTS}}/\overline{\text{RTS}}$ separate function cannot be used.




Figure 1.15.6. $\overline{\text{CTS}}/\overline{\text{RTS}}$ Separate Function

Special Mode 1 (I²C mode)

I²C mode is provided for use as a simplified I²C interface compatible mode. Table 1.16.1 lists the specifications of the I²C mode. Table 1.16.2 lists the registers used in the I²C mode and the register values set. Figure 1.16.1 shows the block diagram for I²C mode. Figure 1.16.2 shows SCLi timing.

As shown in Table 1.16.3, the microcomputer is placed in I²C mode by setting the SMD2 to SMD0 bits to '0102' and the IICM bit to "1". Because SDAi transmit output has a delay circuit attached, SDAi output does not change state until SCLi goes low and remains stably low.

Table 1.16.1. I²C Mode Specifications

Item	Specification
Transfer data format	<ul style="list-style-type: none"> Transfer data length: 8 bits
Transfer clock	<ul style="list-style-type: none"> During master <ul style="list-style-type: none"> UiMR(i=0 to 2) register's CKDIR bit = "0" (internal clock) : $f_j / 2(n+1)$ $f_j = f_{1SIO}, f_{2SIO}, f_{8SIO}, f_{32SIO}$. n: Setting value of UiBRG register 0016 to FF16 During slave <ul style="list-style-type: none"> CKDIR bit = "1" (external clock) : Input from CLKi pin
Transmission start condition	<ul style="list-style-type: none"> Before transmission can start, the following requirements must be met (Note 1) <ul style="list-style-type: none"> The TE bit of UiC1 register= 1 (transmission enabled) The TI bit of UiC1 register = 0 (data present in UiTB register)
Reception start condition	<ul style="list-style-type: none"> Before reception can start, the following requirements must be met (Note 1) <ul style="list-style-type: none"> The RE bit of UiC1 register= 1 (reception enabled) The TE bit of UiC1 register= 1 (transmission enabled) The TI bit of UiC1 register= 0 (data present in the UiTB register)
Interrupt request generation timing	When start or stop condition is detected, acknowledge undetected, and acknowledge detected
Error detection	<ul style="list-style-type: none"> Overrun error (Note 2) <ul style="list-style-type: none"> This error occurs if the serial I/O started receiving the next data before reading the UiRB register and received the 8th bit of the next data
Select function	<ul style="list-style-type: none"> Arbitration lost <ul style="list-style-type: none"> Timing at which the UiRB register's ABT bit is updated can be selected SDAi digital delay <ul style="list-style-type: none"> No digital delay or a delay of 2 to 8 UiBRG count source clock cycles selectable Clock phase setting <ul style="list-style-type: none"> With or without clock delay selectable

Note 1: When an external clock is selected, the conditions must be met while the external clock is in the high state.

Note 2: If an overrun error occurs, the value of UiRB register will be indeterminate. The IR bit of SiRIC register does not change.




Figure 1.16.1. I²C Mode Block Diagram

Table 1. 16. 2. Registers to Be Used and Settings in I²C Mode (1) (Continued)

Register	Bit	Function	
		Master	Slave
UiTB ³	0 to 7	Set transmission data	Set transmission data
UiRB ³	0 to 7	Reception data can be read	Reception data can be read
	8	ACK or NACK is set in this bit	ACK or NACK is set in this bit
	ABT	Arbitration lost detection flag	Invalid
	OER	Overrun error flag	Overrun error flag
UiBRG	---	Set a transfer rate	Invalid
UiMR ³	SMD2 to SMD0	Set to '0102'	Set to '0102'
	CKDIR	Set to "0"	Set to "1"
	IOPOL	Set to "0"	Set to "0"
UiC0	CLK1, CLK0	Select the count source for the UiBRG register	Invalid
	CRS	Invalid because CRD = 1	Invalid because CRD = 1
	TXEPT	Transmit buffer empty flag	Transmit buffer empty flag
	CRD	Set to "1"	Set to "1"
	NCH	Set to "1" ²	Set to "1" ²
	CKPOL	Set to "0"	Set to "0"
	UFORM	Set to "1"	Set to "1"
UiC1	TE	Set this bit to "1" to enable transmission	Set this bit to "1" to enable transmission
	TI	Transmit buffer empty flag	Transmit buffer empty flag
	RE	Set this bit to "1" to enable reception	Set this bit to "1" to enable reception
	RI	Reception complete flag	Reception complete flag
	U2IRS ¹	Invalid	Invalid
	U2RRM ¹ , UiLCH, UiERE	Set to "0"	Set to "0"
UiSMR	IICM	Set to "1"	Set to "1"
	ABC	Select the timing at which arbitration-lost is detected	Invalid
	BBS	Bus busy flag	Bus busy flag
	3 to 7	Set to "0"	Set to "0"
UiSMR2	IICM2	Refer to Table 1.16.4.	Refer to Table 1.16.4.
	CSC	Set this bit to "1" to enable clock synchronization	Set to "0"
	SWC	Set this bit to "1" to have SCLi output fixed to "L" at the falling edge of the 9th bit of clock	Set this bit to "1" to have SCLi output fixed to "L" at the falling edge of the 9th bit of clock
	ALS	Set this bit to "1" to have SDAi output stopped when arbitration-lost is detected	Set to "0"
	STAC	Set to "0"	Set this bit to "1" to initialize UAR _{Ti} at start condition detection
	SWC2	Set this bit to "1" to have SCLi output forcibly pulled low	Set this bit to "1" to have SCLi output forcibly pulled low
	SDHI	Set this bit to "1" to disable SDAi output	Set this bit to "1" to disable SDAi output
	7	Set to "0"	Set to "0"
UiSMR3	0, 2, 4 and NODC	Set to "0"	Set to "0"
	CKPH	Refer to Table 1.16.4	Refer to Table 1.16.4
	DL2 to DL0	Set the amount of SDAi digital delay	Set the amount of SDAi digital delay

i=0 to 2

Notes:

1. Set the U0C1 and U1C1 register bit 4 and bit 5 to "0". The U0IRS, U1IRS, U0RRM and U1RRM bits are in the UCON register.
2. TxD2 pin is N channel open-drain output. Set the NCH bit in the U2C0 register to "0".
3. Not all register bits are described above. Set those bits to "0" when writing to the registers in I²C mode.

Table 1. 16. 3. Registers to Be Used and Settings in I²C Mode (2) (Continued)

Register	Bit	Function	
		Master	Slave
UiSMR4	STAREQ	Set this bit to "1" to generate start condition	Set to "0"
	RSTAREQ	Set this bit to "1" to generate restart condition	Set to "0"
	STPREQ	Set this bit to "1" to generate stop condition	Set to "0"
	STSPSEL	Set this bit to "1" to output each condition	Set to "0"
	ACKD	Select ACK or NACK	Select ACK or NACK
	ACKC	Set this bit to "1" to output ACK data	Set this bit to "1" to output ACK data
	SCLHI	Set this bit to "1" to have SCLi output stopped when stop condition is detected	Set to "0"
	SWC9	Set to "0"	Set this bit to "1" to set the SCLi to "L" hold at the falling edge of the 9th bit of clock
IFSR2A	IFSR26, ISFR27	Set to "1"	Set to "1"
UCON	U0IRS, U1IRS	Invalid	Invalid
	2 to 7	Set to "0"	Set to "0"

i=0 to 2

Table 1.16.4. I²C Mode Functions

Function	Clock synchronous serial I/O mode (SMD2 to SMD0 = 0012, IICM = 0)	I ² C mode (SMD2 to SMD0 = 0102, IICM = 1)			
		IICM2 = 0 (NACK/ACK interrupt)		IICM2 = 1 (UART transmit/ receive interrupt)	
		CKPH = 0 (No clock delay)	CKPH = 1 (Clock delay)	CKPH = 0 (No clock delay)	CKPH = 1 (Clock delay)
Factor of interrupt number 6, 7 and 10 (Note 1)(Refer to Fig 1.16.2)	—————	Start condition detection or stop condition detection (Refer to Fig 1.20.4)			
Factor of interrupt number 15, 17 and 19 (Note 1)(Refer to Fig 1.16.2)	UARTi transmission Transmission started or completed (selected by UiIRS)	No acknowledgment detection (NACK) Rising edge of SCLi 9th bit	UARTi transmission Rising edge of SCLi 9th bit	UARTi transmission Falling edge of SCLi 9th bit	UARTi transmission Falling edge of SCLi 9th bit
Factor of interrupt number 16, 18 and 20 (Note 1)(Refer to Fig 1.16.2)	UARTi reception When 8th bit received CKPOL = 0 (rising edge) CKPOL = 1 (falling edge)	Acknowledgment detection (ACK) Rising edge of SCLi 9th bit	UARTi transmission Falling edge of SCLi 9th bit		
Timing for transferring data from the UART reception shift register to the UiRB register	CKPOL = 0 (rising edge) CKPOL = 1 (falling edge)	Rising edge of SCLi 9th bit	Falling edge of SCLi 9th bit	Falling and rising edges of SCLi 9th bit	
UARTi transmission output delay	Not delayed	Delayed			
Functions of P63, P67 and P70 pins	TxDi output	SDAi input/output			
Functions of P62, P66 and P71 pins	RxDi input	SCLi input/output			
Functions of P61, P65 and P72 pins	CLKi input or output selected	————— (Cannot be used in I ² C mode)			
Noise filter width	15ns	200ns			
Read RxDi and SCLi pin levels	Possible when the corresponding port direction bit = 0	Always possible no matter how the corresponding port direction bit is set			
Initial value of TxDi and SDAi outputs	CKPOL = 0 (H) CKPOL = 1 (L)	The value set in the port register before setting I ² C mode (Note 2)			
Initial and end values of SCLi	—————	H	L	H	L
DMA1 factor (Refer to Fig 1.16.2)	UARTi reception	Acknowledgment detection (ACK)	UARTi reception Falling edge of SCLi 9th bit		
Store received data	1st to 8th bits are stored in UiRB register bit 0 to bit 7	1st to 8th bits are stored in UiRB register bit 7 to bit 0	1st to 7th bits are stored in UiRB register bit 6 to bit 0, with 8th bit stored in UiRB register bit 8		1st to 8th bits are stored in UiRB register bit 7 to bit 0 (Note 3)
Read received data	UiRB register status is read directly as is				Read UiRB register Bit 6 to bit 0 as bit 7 to bit 1, and bit 8 as bit 0 (Note 4)

i = 0 to 2

Note 1: To change the interrupt sources from one to another, follow the procedure described below.


1. Disable the interrupt of the corresponding interrupt number to be changed.
2. Change interrupt sources from one to another.
3. Set the IR bit for the corresponding interrupt number to 0 (no interrupt request).
4. Set the IPL2 to IPL0 bits for the corresponding interrupt number.

Note 2: Set the initial value of SDAi output while the UiMR register's SMD2 to SMD0 bits = '000 2' (serial I/O disabled).


Note 3: Second data transfer to UiRB register (Rising edge of SCLi 9th bit)

Note 4: First data transfer to UiRB register (Falling edge of SCLi 9th bit)


(1) IICM2= 0 (ACK and NACK interrupts), CKPH= 0 (no clock delay)




(2) IICM2= 0, CKPH= 1 (clock delay)



(3) IICM2= 1 (UART transmit/receive interrupt), CKPH= 0



(4) IICM2= 1, CKPH= 1



i=0 to 2

This diagram applies to the case where the following condition is met.
 • UiMR register CKDIR bit = 0 (Slave selected)

Figure 1.16.2. Transfer to UiRB Register and Interrupt Timing

• Detection of Start and Stop Condition

Whether a start or a stop condition has been detected is determined.

A start condition-detected interrupt request is generated when the SDAi pin changes state from high to low while the SCLi pin is in the high state. A stop condition-detected interrupt request is generated when the SDAi pin changes state from low to high while the SCLi pin is in the high state.

Because the start and stop condition-detected interrupts share the interrupt control register and vector, check the UiSMR register's BBS bit to determine which interrupt source is requesting the interrupt.




Figure 1.16.3. Detection of Start and Stop Condition

• Output of Start and Stop Condition

A start condition is generated by setting the UiSMR4 register ($i = 0$ to 2)'s STAREQ bit to "1" (start).

A restart condition is generated by setting the UiSMR4 register's RSTAREQ bit to "1" (start).

A stop condition is generated by setting the UiSMR4 register's STPREQ bit to "1" (start).

A start condition is output by setting the STAREQ bit to "1" and then the UiSMR4 register's STSPSEL bit to "1" (start). Similarly, a restart condition is output by setting the RSTAREQ bit to "1" and then the STSPSEL bit to "1", and a stop condition is output by setting the STPREQ bit to "1" and then the STSPSEL bit to "1".


Table 1.16.5 and Figure 1.16.4 show the functions of the STSPSEL.

If start, stop and restart conditions are to be output, make sure no interrupts will occur between the instruction that sets the STAREQ, STPREQ or RSTAREQ bit to "1" and the instruction that sets the STSPSEL bit to "1".

Also, if a start condition is to be output, make sure the STAREQ bit is set to "1" before setting the STSPSEL bit to "1".

Table 1.16.5. STSPSEL Bit Functions

Function	STSPSEL = 0	STSPSEL = 1
Output of SCLi and SDAi pins	Output of transfer clock and data Output of start/stop condition is accomplished by a program using ports (not automatically generated in hardware)	Output of a start/stop condition according to the STAREQ, RSTAREQ and STPREQ bit
Star/stop condition interrupt request generation timing	Start/stop condition detection	Finish generating start/stop condition

**Figure 1.16.4. STSPSEL Bit Functions**

- **Arbitration**

Unmatching of the transmit data and SDAi pin input data is checked synchronously with the rising edge of SCLi. Use the UiSMR register's ABC bit to select the timing at which the UiRB register's ABT bit is updated. If the ABC bit = 0 (updated bitwise), the ABT bit is set to "1" at the same time unmatching is detected during check, and is cleared to "0" when not detected. In cases when the ABC bit is set to "1", if unmatching is detected even once during check, the ABT bit is set to "1" (unmatching detected) at the falling edge of the clock pulse of 9th bit. If the ABT bit needs to be updated byte-wise, clear the ABT bit to "0" (undetected) after detecting acknowledge in the first byte, before transferring the next byte.

Setting the UiSMR2 register's ALS bit to "1" (SDA output stop enabled) causes arbitration-lost to occur, in which case the SDAi pin is placed in the high-impedance state at the same time the ABT bit is set to "1" (unmatching detected).

• Transfer Clock

Data is transmitted/received using a transfer clock like the one shown in Figure 1.16.4.

The UiSMR2 register's CSC bit is used to synchronize the internally generated clock (internal SCLi) and an external clock supplied to the SCLi pin. In cases when the CSC bit is set to "1" (clock synchronization enabled), if a falling edge on the SCLi pin is detected while the internal SCLi is high, the internal SCLi goes low, at which time the UiBRG register value is reloaded with and starts counting in the low-level interval. If the internal SCLi changes state from low to high while the SCLi pin is low, counting stops, and when the SCLi pin goes high, counting restarts.

In this way, the UARTi transfer clock is comprised of the logical product of the internal SCLi and SCLi pin signal. The transfer clock works from a half period before the falling edge of the internal SCLi 1st bit to the rising edge of the 9th bit. To use this function, select an internal clock for the transfer clock. The UiSMR2 register's SWC bit allows to select whether the SCLi pin should be fixed to or freed from low-level output at the falling edge of the 9th clock pulse.

If the UiSMR4 register's SCLHI bit is set to "1" (enabled), SCLi output is turned off (placed in the high-impedance state) when a stop condition is detected.

Setting the UiSMR2 register's SWC2 bit = 1 (0 output) makes it possible to forcibly output a low-level signal from the SCLi pin even while sending or receiving data. Clearing the SWC2 bit to "0" (transfer clock) allows the transfer clock to be output from or supplied to the SCLi pin, instead of outputting a low-level signal.

If the UiSMR4 register's SWC9 bit is set to "1" (SCL hold low enabled) when the UiSMR3 register's CKPH bit = 1, the SCLi pin is fixed to low-level output at the falling edge of the clock pulse next to the ninth. Setting the SWC9 bit = 0 (SCL hold low disabled) frees the SCLi pin from low-level output.

• SDA Output

The data written to the UiTB register bit 7 to bit 0 (D7 to D0) is sequentially output beginning with D7. The ninth bit (D8) is ACK or NACK.

The initial value of SDAi transmit output can only be set when IICM = 1 (I²C mode) and the UiMR register's SMD2 to SMD0 bits = '0002' (serial I/O disabled).

The UiSMR3 register's DL2 to DL0 bits allow to add no delays or a delay of 2 to 8 UiBRG count source clock cycles to SDAi output.

Setting the UiSMR2 register's SDHI bit = 1 (SDA output disabled) forcibly places the SDAi pin in the high-impedance state. Do not write to the SDHI bit synchronously with the rising edge of the UARTi transfer clock. This is because the ABT bit may inadvertently be set to "1" (detected).

• SDA Input

When the IICM2 bit = 0, the 1st to 8th bits (D7 to D0) of received data are stored in the UiRB register bit 7 to bit 0. The 9th bit (D8) is ACK or NACK.

When the IICM2 bit = 1, the 1st to 7th bits (D7 to D1) of received data are stored in the UiRB register bit 6 to bit 0 and the 8th bit (D0) is stored in the UiRB register bit 8. Even when the IICM2 bit = 1, providing the CKPH bit = 1, the same data as when the IICM2 bit = 0 can be read out by reading the UiRB register after the rising edge of the corresponding clock pulse of 9th bit.

- **ACK and NACK**

If the STSPSEL bit in the UiSMR4 register is set to “0” (start and stop conditions not generated) and the ACKC bit in the UiSMR4 register is set to “1” (ACK data output), the value of the ACKD bit in the UiSMR4 register is output from the SDAi pin.

If the IICM2 bit = 0, a NACK interrupt request is generated if the SDAi pin remains high at the rising edge of the 9th bit of transmit clock pulse. An ACK interrupt request is generated if the SDAi pin is low at the rising edge of the 9th bit of transmit clock pulse.

If ACKi is selected for the cause of DMA1 request, a DMA transfer can be activated by detection of an acknowledge.

- **Initialization of Transmission/Reception**

If a start condition is detected while the STAC bit = 1 (UARTi initialization enabled), the serial I/O operates as described below.

- The transmit shift register is initialized, and the content of the UiTB register is transferred to the transmit shift register. In this way, the serial I/O starts sending data synchronously with the next clock pulse applied. However, the UARTi output value does not change state and remains the same as when a start condition was detected until the first bit of data is output synchronously with the input clock.
- The receive shift register is initialized, and the serial I/O starts receiving data synchronously with the next clock pulse applied.
- The SWC bit is set to “1” (SCL wait output enabled). Consequently, the SCLi pin is pulled low at the falling edge of the ninth clock pulse.

Note that when UARTi transmission/reception is started using this function, the TI does not change state. Note also that when using this function, the selected transfer clock should be an external clock.

Special Mode 2

Multiple slaves can be serially communicated from one master. Synchronous clock polarity and phase are selectable. Table 1.16.6 lists the specifications of Special Mode 2. Table 1.16.7 lists the registers used in Special Mode 2 and the register values set. Figure 1.16.5 shows communication control example for Special Mode 2. UART2 is not available in this mode.

Table 1.16.6. Special Mode 2 Specifications

Item	Specification
Transfer data format	<ul style="list-style-type: none"> Transfer data length: 8 bits
Transfer clock	<ul style="list-style-type: none"> Master mode $UiMR(i=0 \text{ to } 1)$ register's CKDIR bit = "0" (internal clock) : $fj / 2(n+1)$ $fj = f1SIO, f2SIO, f8SIO, f32SIO$. n: Setting value of UiBRG register 0016 to FF16 Slave mode CKDIR bit = "1" (external clock selected) : Input from CLKi pin
Transmit/receive control	Controlled by input/output ports
Transmission start condition	<ul style="list-style-type: none"> Before transmission can start, the following requirements must be met (Note 1) <ul style="list-style-type: none"> The TE bit of UiC1 register= 1 (transmission enabled) The TI bit of UiC1 register = 0 (data present in UiTB register)
Reception start condition	<ul style="list-style-type: none"> Before reception can start, the following requirements must be met (Note 1) <ul style="list-style-type: none"> The RE bit of UiC1 register= 1 (reception enabled) The TE bit of UiC1 register= 1 (transmission enabled) The TI bit of UiC1 register= 0 (data present in the UiTB register)
Interrupt request generation timing	<ul style="list-style-type: none"> For transmission, one of the following conditions can be selected <ul style="list-style-type: none"> The UiIRS bit of UiC1 register = 0 (transmit buffer empty): when transferring data from the UiTB register to the UAR<i>Ti</i> transmit register (at start of transmission) The UiIRS bit =1 (transfer completed): when the serial I/O finished sending data from the UAR<i>Ti</i> transmit register For reception When transferring data from the UAR<i>Ti</i> receive register to the UiRB register (at completion of reception)
Error detection	<ul style="list-style-type: none"> Overrun error (Note 2) This error occurs if the serial I/O started receiving the next data before reading the UiRB register and received the 7th bit of the next data
Select function	<ul style="list-style-type: none"> Clock phase setting Selectable from four combinations of transfer clock polarities and phases

Note 1: When an external clock is selected, the conditions must be met while if the UiC0 register's CKPOL bit = "0" (transmit data output at the falling edge and the receive data taken in at the rising edge of the transfer clock), the external clock is in the high state; if the UiC0 register's CKPOL bit = "1" (transmit data output at the rising edge and the receive data taken in at the falling edge of the transfer clock), the external clock is in the low state.

Note 2: If an overrun error occurs, the value of UiRB register will be indeterminate. The IR bit of SiRIC register does not change.




Figure 1.16.5. Serial Bus Communication Control Example (UART0)

Table 1. 16. 7. Registers to Be Used and Settings in Special Mode 2

Register	Bit	Function
UiTB(Note2)	0 to 7	Set transmission data
UiRB(Note2)	0 to 7	Reception data can be read
	OER	Overrun error flag
UiBRG	0 to 7	Set a transfer rate
UiMR(Note2)	SMD2 to SMD0	Set to '0012'
	CKDIR	Set this bit to "0" for master mode or "1" for slave mode
	IOPOL	Set to "0"
UiC0	CLK1, CLK0	Select the count source for the UiBRG register
	CRS	Invalid because CRD = 1
	TXEPT	Transmit register empty flag
	CRD	Set to "1"
	NCH	Select TxDi pin output format
	CKPOL	Clock phases can be set in combination with the UiSMR3 register's CKPH bit
	UFORM	Set to "0"
UiC1	TE	Set this bit to "1" to enable transmission
	TI	Transmit buffer empty flag
	RE	Set this bit to "1" to enable reception
	RI	Reception complete flag
	U2IRS (Note 1)	Select UART2 transmit interrupt cause
	U2RRM(Note 1), U2LCH, UiERE	Set to "0"
UiSMR	0 to 7	Set to "0"
UiSMR2	0 to 7	Set to "0"
UiSMR3	CKPH	Clock phases can be set in combination with the UiC0 register's CKPOL bit
	NODC	Set to "0"
	0, 2, 4 to 7	Set to "0"
UiSMR4	0 to 7	Set to "0"
UCON	U0IRS, U1IRS	Select UART0 and UART1 transmit interrupt cause
	U0RRM, U1RRM	Set to "0"
	CLKMD0	Invalid because CLKMD1 = 0
	CLKMD1, RCSP, 7	Set to "0"

Note 1: Set the U0C0 and U1C1 register bit 4 and bit 5 to "0". The U0IRS, U1IRS, U0RRM and U1RRM bits are in the UCON register.

Note 2: Not all register bits are described above. Set those bits to "0" when writing to the registers in Special Mode 2.

i = 0 to 1

• Clock Phase Setting Function

One of four combinations of transfer clock phases and polarities can be selected using the UiSMR3 register's CKPH bit and the UiC0 register's CKPOL bit.

Make sure the transfer clock polarity and phase are the same for the master and slaves to be communicated.

(a) Master (Internal Clock)

Figure 1.16.6 shows the transmission and reception timing in master (internal clock).

(b) Slave (External Clock)

Figure 1.16.7 shows the transmission and reception timing (CKPH=0) in slave (external clock) while

Figure 1.16.8 shows the transmission and reception timing (CKPH=1) in slave (external clock).




Figure 1.16.6. Transmission and Reception Timing in Master Mode (Internal Clock)




Figure 1.16.7. Transmission and Reception Timing (CKPH=0) in Slave Mode (External Clock)




Figure 1.16.8. Transmission and Reception Timing (CKPH=1) in Slave Mode (External Clock)

SI/O3 and SI/O4

SI/O3 and SI/O4 are exclusive clock-synchronous serial I/Os.

Figure 1.17.1 shows the block diagram of SI/O3 and SI/O4, and Figure 1.17.2 shows the SI/O3 and SI/O4-related registers. SI/O4 is directly connected to IT800 internally.

Table 1.17.1 shows the specifications of SI/O3 and SI/O4.





Figure 1.17.1. SI/O3 and SI/O4 Block Diagram

S I/Oi control register (i = 3, 4) (Note 1)



Symbol	Address	After reset
S3C	0362 ₁₆	0100000 ₁₆
S4C	0366 ₁₆	0100000 ₁₆

Bit symbol	Bit name	Description	RW
SMi0	Internal synchronous clock select bit	b1 b0 0 0 : Selecting f1SIO or f2SIO	RW
SMi1		0 1 : Selecting f8SIO 1 0 : Selecting f32SIO 1 1 : Must not be set.	RW
SMi2	Souti output disable bit (Note 4)	0 : Souti output 1 : Souti output disable(high impedance)	RW
SMi3	S I/Oi port select bit	0 : Input/output port 1 : Souti output, CLKi function	RW
SMi4	CLK polarity select bit	0 : Transmit data is output at falling edge of transfer clock and receive data is input at rising edge 1 : Transmit data is output at rising edge of transfer clock and receive data is input at falling edge	RW
SMi5	Transfer direction select bit	0 : LSB first 1 : MSB first	RW
SMi6	Synchronous clock select bit	0 : External clock (Note 2) 1 : Internal clock (Note 3)	RW
SMi7	Souti initial value set bit	Effective when SMI3 = 0 0 : "L" output 1 : "H" output	RW


Note 1: Make sure this register is written to by the next instruction after setting the PRCR register's PRC2 bit to "1" (write enable).

Note 2: Set the SMI3 bit to "1" (Souti output, CLKi function).

Note 3: Set the SMI3 bit to "1" and the corresponding port direction bit to "0" (input mode).

Note 4: Effective when SMI3 bit = 1.

SI/Oi bit rate generator (i = 3, 4) (Notes 1, 2)




Symbol	Address	After reset
S3BRG	0363 ₁₆	Indeterminate
S4BRG	0367 ₁₆	Indeterminate

Description	Setting range	RW
Assuming that set value = n, BRGi divides the count source by n + 1	00 ₁₆ to FF ₁₆	WO

Note 1: Write to this register while serial I/O is neither transmitting nor receiving.

Note 2: Use MOV instruction to write to this register.

SI/Oi transmit/receive register (i = 3, 4) (Note 1, 2)



Symbol	Address	After reset
S3TRR	0360 ₁₆	Indeterminate
S4TRR	0364 ₁₆	Indeterminate

Description	RW
Transmission/reception starts by writing transmit data to this register. After transmission/reception finishes, reception data can be read by reading this register.	RW

Note 1: Write to this register while serial I/O is neither transmitting nor receiving.

Note 2: To receive data, set the corresponding port direction bit for Sini to "0" (input mode).

Figure 1.17.2. S3C and S4C Registers, S3BRG and S4BRG Registers, and S3TRR and S4TRR Registers

Table 1.17.1. SI/O3 and SI/O4 Specifications

Item	Specification
Transfer data format	<ul style="list-style-type: none"> Transfer data length: 8 bits
Transfer clock	<ul style="list-style-type: none"> SiC (i=3, 4) register's SMi6 bit = "1" (internal clock) : $f_j / 2(n+1)$ $f_j = f_{1SIO}, f_{8SIO}, f_{32SIO}$. n=Setting value of SiBRG register 0016 to FF16. SMi6 bit = "0" (external clock) : Input from CLKi pin (Note 1)
Transmission/reception start condition	<ul style="list-style-type: none"> Before transmission/reception can start, the following requirements must be met Write transmit data to the SiTRR register (Notes 2, 3)
Interrupt request generation timing	<ul style="list-style-type: none"> When SiC register's SMi4 bit = 0 The rising edge of the last transfer clock pulse (Note 4) When SMi4 = 1 The falling edge of the last transfer clock pulse (Note 4)
CLKi pin function	I/O port, transfer clock input, transfer clock output
SOUTi pin function	I/O port, transmit data output, high-impedance
SINi pin function	I/O port, receive data input
Select function	<ul style="list-style-type: none"> LSB first or MSB first selection Whether to start sending/receiving data beginning with bit 0 or beginning with bit 7 can be selected Function for setting an SOUTi initial value set function When the SiC register's SMi6 bit = 0 (external clock), the SOUTi pin output level while not transmitting can be selected. CLK polarity selection Whether transmit data is output/input timing at the rising edge or falling edge of transfer clock can be selected.

Note 1: To set the SiC register's SMi6 bit to "0" (external clock), follow the procedure described below.

- If the SiC register's SMi4 bit = 0, write transmit data to the SiTRR register while input on the CLKi pin is high. The same applies when rewriting the SiC register's SMi7 bit.
- If the SMi4 bit = 1, write transmit data to the SiTRR register while input on the CLKi pin is low. The same applies when rewriting the SMi7 bit.
- Because shift operation continues as long as the transfer clock is supplied to the SI/Oi circuit, stop the transfer clock after supplying eight pulses. If the SMi6 bit = 1 (internal clock), the transfer clock automatically stops.

Note 2: Unlike UART0 to UART2, SI/Oi (i = 3 to 4) is not separated between the transfer register and buffer. Therefore, do not write the next transmit data to the SiTRR register during transmission.

Note 3: When the SiC register's SMi6 bit = 1 (internal clock), SOUTi retains the last data for a 1/2 transfer clock period after completion of transfer and, thereafter, goes to a high-impedance state. However, if transmit data is written to the SiTRR register during this period, SOUTi immediately goes to a high-impedance state, with the data hold time thereby reduced.

Note 4: When the SiC register's SMi6 bit = 1 (internal clock), the transfer clock stops in the high state if the SMi4 bit = 0, or stops in the low state if the SMi4 bit = 1.

(a) SI/Oi Operation Timing

Figure 1.17.3 shows the SI/Oi operation timing




Figure 1.17.3. SI/Oi Operation Timing

(b) CLK Polarity Selection

The SiC register's SMi4 bit allows selection of the polarity of the transfer clock. Figure 1.17.4 shows the polarity of the transfer clock.




Figure 1.17.4. Polarity of Transfer Clock

(c) Functions for Setting an SOUTi Initial Value

If the SiC register's SMi6 bit = 0 (external clock), the SOUTi pin output can be fixed high or low when not transferring. Figure 1.17.5 shows the timing chart for setting an SOUTi initial value and how to set it.




Figure 1.17.5. SOUTi's Initial Value Setting

Programmable I/O Ports

The programmable input/output ports (hereafter referred to simply as “I/O ports”) consist of 26 lines P1, P4 to P9 (except P85). Each port can be set for input or output every line by using a direction register, and can also be chosen to be or not be pulled high every 4 lines. P85 is an input-only port and does not have a pull-up resistor. Port P85 shares the pin with $\overline{\text{NMI}}$, so that the $\overline{\text{NMI}}$ input level can be read from the P8 register P8_5 bit.

Figures 1.18.1 to 1.18.4 show the I/O ports. Figure 1.18.5 shows the I/O pins.

Each pin functions as an I/O port, a peripheral function input/output.

For details on how to set peripheral functions, refer to each functional description in this manual. If any pin is used as a peripheral function input, set the direction bit for that pin to “0” (input mode). Any pin used as an output pin for peripheral functions is directed for output no matter how the corresponding direction bit is set.

(1) Port Pi Direction Register (PDi Register, i = 0 to 13)

Figure 1.18.6 shows the direction registers.

This register selects whether the I/O port is to be used for input or output. The bits in this register correspond one for one to each port.

No direction register bit for P85 is available.

(2) Port Pi Register (Pi Register, i = 1, 4 to 9)

Figure 1.18.7 show the Pi registers.

Data input/output to and from external devices are accomplished by reading and writing to the Pi register. The Pi register consists of a port latch to hold the input/output data and a circuit to read the pin status. For ports set for input mode, the input level of the pin can be read by reading the corresponding Pi register, and data can be written to the port latch by writing to the Pi register.

For ports set for output mode, the port latch can be read by reading the corresponding Pi register, and data can be written to the port latch by writing to the Pi register. The data written to the port latch is output from the pin. The bits in the Pi register correspond one for one to each port.

(3) Pull-up Control Register 0 to Pull-up Control Register 2 (PUR0 to PUR2 Registers)

Figure 1.18.8 shows the PUR0 to PUR2 registers.

The PUR0 to PUR2 register bits can be used to select whether or not to pull the corresponding port high in 4 bit units. The port chosen to be pulled high has a pull-up resistor connected to it when the direction bit is set for input mode.

(4) Port Control Register

Figure 1.18.9 shows the port control register.

When the P1 register is read after setting the PCR register's PCR0 bit to “1”, the corresponding port latch can be read no matter how the PD1 register is set.




Figure 1.18.1. I/O Ports (1)




Figure 1.18.2. I/O Ports (2)




Figure 1.18.3. I/O Ports (3)




Figure 1.18.4. I/O Ports (4)





Figure 1.18.5. I/O Pins

Port Pi direction register (i=1, 4 to 7 and 9) (Note 1)

Symbol	Address	After reset
PD1	03E3 ₁₆	00 ₁₆
PD4 to PD7	03EA ₁₆ , 03EB ₁₆ , 03EE ₁₆ , 03EF ₁₆	00 ₁₆
PD9	03F3 ₁₆	00 ₁₆




Bit symbol	Bit name	Function	RW
PDi_0	Port P _{i0} direction bit	0 : Input mode (Functions as an input port) 1 : Output mode (Functions as an output port) (i = 0 to 7 and 9 to 13)	RW
PDi_1	Port P _{i1} direction bit		RW
PDi_2	Port P _{i2} direction bit		RW
PDi_3	Port P _{i3} direction bit		RW
PDi_4	Port P _{i4} direction bit		RW
PDi_5	Port P _{i5} direction bit		RW
PDi_6	Port P _{i6} direction bit		RW
PDi_7	Port P _{i7} direction bit		RW

Note 1: Make sure the PD9 register is written to by the next instruction after setting the PRCR register's PRC2 bit to "1" (write enabled).

Note 2: Set PD1_0 and PD1_1 bits to "0."

Port P8 direction register



Symbol	Address	After reset
PD8	03F2 ₁₆	00X00000 ₂

Bit symbol	Bit name	Function	RW
PD8_0	Port P8 ₀ direction bit	0 : Input mode (Functions as an input port) 1 : Output mode (Functions as an output port)	RW
PD8_1	Port P8 ₁ direction bit		RW
PD8_2	Port P8 ₂ direction bit		RW
PD8_3	Port P8 ₃ direction bit		RW
PD8_4	Port P8 ₄ direction bit		RW
— (b5)	Nothing is assigned. In an attempt to write to this bit, write "0". The value, if read, turns out to be indeterminate.		—
PD8_6	Port P8 ₆ direction bit	0 : Input mode (Functions as an input port) 1 : Output mode (Functions as an output port)	RW
PD8_7	Port P8 ₇ direction bit		RW

Figure 1.18.6. PD1, PD4 to PD9 Registers

Port Pi register (i=1, 4 to 7 and 9)

								Symbol	Address	(Note 2)	After reset
b7	b6	b5	b4	b3	b2	b1	b0	P1	03E116		Indeterminate
								P4 to P7	03E816, 03E916, 03EC16, 03ED16		Indeterminate
								P9	03F116		Indeterminate

Bit symbol	Bit name	Function	RW
Pi_0	Port Pio bit	The pin level on any I/O port which is set for input mode can be read by reading the corresponding bit in this register.	RW
Pi_1	Port Pi1 bit		RW
Pi_2	Port Pi2 bit		RW
Pi_3	Port Pi3 bit	The pin level on any I/O port which is set for output mode can be controlled by writing to the corresponding bit in this register	RW
Pi_4	Port Pi4 bit		RW
Pi_5	Port Pis bit		RW
Pi_6	Port Pie bit		RW
Pi_7	Port Piz bit		RW
		0 : "L" level	
		1 : "H" level (Note 1)	
		(i = 0 to 7 and 9 to 13)	

Note 1: Since P7₀ is N-channel open drain ports, the data is high-impedance.

Note 2: Set P1_0 and P1_1 bits to "0."


Port P8 register

								Symbol	Address	After reset
b7	b6	b5	b4	b3	b2	b1	b0	P8	03F016	Indeterminate

Bit symbol	Bit name	Function	RW
P8_0	Port P80 bit	The pin level on any I/O port which is set for input mode can be read by reading the corresponding bit in this register.	RW
P8_1	Port P81 bit		RW
P8_2	Port P82 bit		RW
P8_3	Port P83 bit	The pin level on any I/O port which is set for output mode can be controlled by writing to the corresponding bit in this register (except for P8 ₅)	RW
P8_4	Port P84 bit		RW
P8_5	Port P85 bit		RO
P8_6	Port P86 bit		RW
P8_7	Port P87 bit		RW
		0 : "L" level	
		1 : "H" level	

Figure 1.18.7. P1, P4 to P9

Pull-up control register 0 (Note 1)

Symbol
PUR0Address
03FC₁₆After reset
00₁₆

Bit symbol	Bit name	Function	RW
(b2-b0)	Nothing is assigned. When write, set to "0". When read, its content is indeterminate.		—
PU03	P14 to P17 pull-up	0 : Not pulled high 1 : Pulled high (Note 2)	RW
(b7-b4)	Nothing is assigned. When write, set to "0". When read, its content is indeterminate.		—

Note 1: During memory extension and microprocessor modes, the pins are not pulled high although their corresponding register contents can be modified.

Note 2: The pin for which this bit is "1" (pulled high) and the direction bit is "0" (input mode) is pulled high.

Pull-up control register 1

Symbol
PUR1Address
03FD₁₆After reset(Note 5)
00000000₂
00000010₂

Bit symbol	Bit name	Function	RW
(b3-b0)	Nothing is assigned. When write, set to "0". When read, its content is indeterminate.		—
PU14	P60 to P63 pull-up	0 : Not pulled high 1 : Pulled high (Note 3)	RW
PU15	P64 to P67 pull-up		RW
PU16	P72 to P73 pull-up (Note 1)		RW
PU17	P74 to P77 pull-up		RW

Note 1: The P70 and P71 pins do not have pull-ups.

Note 2: During memory extension and microprocessor modes, the pins are not pulled high although the contents of these bits can be modified.

Note 3: The pin for which this bit is "1" (pulled high) and the direction bit is "0" (input mode) is pulled high.

Note 4: If the PM01 to PM00 bits are set to "012" (memory expansion mode) or "112" (microprocessor mode) in a program during single-chip mode, the PU11 bit becomes "1".


Note 5: The values after hardware reset 1 and 2 are as follows:

- 00000000₂ when input on CNVss pin is "L"
- 00000010₂ when input on CNVss pin is "H"

The values after software reset, watchdog timer reset and oscillation stop detection reset are as follows:

- 00000000₂ when PM 01 to PM00 bits of PM0 register are "002" (single-chip mode)
- 00000010₂ when PM 01 to PM00 bits of PM0 register are "012" (memory expansion mode) or "112" (microprocessor mode)

Pull-up control register 2

Symbol
PUR2Address
03FE₁₆After reset
00₁₆

Bit symbol	Bit name	Function	RW
PU20	P80 to P83 pull-up	0 : Not pulled high 1 : Pulled high (Note 1)	RW
PU21	P84 to P87 pull-up (Note 2)		RW
PU22	P90 to P93 pull-up		RW
—— (b7-b3)	Nothing is assigned. In an attempt to write to these bits, write "0". The value, if read, turns out to be "0".		——

Note 1: The pin for which this bit is "1" (pulled high) and the direction bit is "0" (input mode) is pulled high.

Note 2: The P85 pin does not have pull-up.

Figure 1.18.8. PUR0 to PUR2 Registers





Figure 1.18.9. PCR Register

Table 1.18.1. Unassigned Pin Handling in Single-chip Mode

Pin name	Connection
Ports P1, P6 to P9 (excluding P85)	After setting for input mode, connect every pin to V _{SS} via a resistor(pull-down); or after setting for output mode, leave these pins open.
XOUT (Note 1)	Open
P85	Connect via resistor to V _{CC} (pull-up)
V _{CCA}	Connect to V _{CC}
V _{SSA}	Connect to V _{SS}

Note 1: With external clock input to X_{IN} pin.

**Figure 1.18.10. Unassigned Pins Handling**

Electrical Characteristics

Table 1.19.1. Absolute Maximum Ratings

Symbol	Parameter		Condition	Rated value	Unit
V _{cc}	Supply voltage		V _{cc} =V _{ccA}	-0.3 to 4.2	V
V _{ccA}	Analog supply voltage		V _{cc} =V _{ccA}	-0.3 to 4.2	V
V _i	Input voltage	RESET, CNV _{ss} P6 ₀ to P6 ₇ , P7 ₁ , P7 ₃ , P7 ₄ , P7 ₆ , P8 ₀ to P8 ₅ , P9 ₀ to P9 ₂ , X _{IN}		-0.3 to V _{cc} +0.3	V
		P7 ₀		-0.3 to 6.5	V
V _o	Output voltage	P6 ₀ to P6 ₇ , P7 ₁ , P7 ₃ , P7 ₄ , P7 ₆ , P8 ₀ to P8 ₄ , P9 ₀ to P9 ₂ , X _{OUT} , TS		-0.3 to V _{cc1} +0.3	V
		P7 ₀		-0.3 to 6.5	V
P _d	Power dissipation			500	mW
T _{opr}	Operating ambient temperature			-20 to 85	°C
T _{stg}	Storage temperature			-65 to 150	°C

Table 1.19.2. Recommended Operating Conditions (Note 1)

Symbol	Parameter		Standard			Unit
			Min.	Typ.	Max.	
V _{CC}	Supply voltage		3.0	3.3	3.6	V
V _{CCA}	Analog supply voltage			V _{CC}		V
V _{SS}	Supply voltage			0		V
V _{SSA}	Analog supply voltage			0		V
V _{IH}	HIGH input voltage	P60 to P67, P71, P73, P74, P76, P80 to P84, P90 to P92 X _{IN} , RESET, CNV _{SS}	0.8V _{CC1}		V _{CC1}	V
		P70	0.8V _{CC1}		6.5	V
V _{IL}	LOW input voltage	P60 to P67, P70, P71, P73, P74, P76, P80 to P84, P90 to P92 X _{IN} , RESET, CNV _{SS}	0		0.2V _{CC1}	V
I _{OH (peak)}	HIGH peak output current	P60 to P67, P71, P73, P74, P76, P80 to P84, P90 to P92, TS			-10.0	mA
I _{OH (avg)}	HIGH average output current	P60 to P67, P71, P73, P74, P76, P80 to P84, P90 to P92, TS			-5.0	mA
I _{OL (peak)}	LOW peak output current	P60 to P67, P70, P71, P73, P74, P76, P80 to P84, P90 to P92, TS			10.0	mA
I _{OL (avg)}	LOW average output current	P60 to P67, P70, P71, P73, P74, P76, P80 to P84, P90 to P92, TS			5.0	mA
f (X _{IN})	Main clock input oscillation frequency (Note 4)	V _{CC} =3.0 to 3.6V		5.12		MHz
f (Ring)	Ring oscillation frequency			1		MHz
f (BCLK)	CPU operation clock			15.36		MHz
T _{SU(PLL)}	PLL frequency synthesizer stabilization wait time	V _{CC} =3.0V			50	ms

Note 1: Referenced to V_{CC} = 3.0 to 3.6V at T_{opr} = -20 to 85 °C unless otherwise specified.

Note 2: The mean output current is the mean value within 100ms.

Note 3: The total I_{OL} (peak) for all ports must be 80mA max, the total I_{OH} (peak) for all ports must be -40mA max.

Table 1.19.3. Flash Memory Version Electrical Characteristics (Note 1)

Parameter	Standard			Unit
	Min.	Typ.	Max	
Word program time		30	200	μs
Block erase time		1	4	s
Erase all unlocked blocks time		1 X n	4 X n	s
Lock bit program time		30	200	μs

Note 1: Referenced to V_{CC} = 3.0 to 3.6V at T_{opr} = 0 to 60 °C unless otherwise specified.

Note 2: n denotes the number of block erases.

**Table 1.19.4. Flash Memory Version Program/Erase Voltage and Read Operation Voltage Characteristics
(at T_{opr} = 0 to 60°C)**

Flash program, erase voltage	Flash read operation voltage
V _{CC} = 3.3 V ± 0.3 V	V _{CC} = 3.0 to 3.6 V

Table 1.19.5. Power Supply Circuit Timing Characteristics

Symbol	Parameter	Measuring condition	Standard			Unit
			Min.	Typ.	Max.	
td(P-R)	Time for internal power supply stabilization during powering-on	$V_{CC} = 3.0$ to $3.6V$			2	ms
td(R-S)	STOP release time				150	μs
td(M-L)	Time for internal power supply stabilization when main clock oscillation starts				50	μs


Note : When $V_{CC1} = 5V$ 

Table 1.19.6. Electrical Characteristics (Note)

Symbol	Parameter		Measuring condition	Standard			Unit
				Min.	Typ.	Max.	
V _{OH}	HIGH output voltage	P6 ₀ to P6 ₇ , P7 ₁ , P7 ₃ , P7 ₄ , P7 ₆ , P8 ₀ to P8 ₄ , P9 ₀ to P9 ₂ , TS	I _{OH} = -1mA	V _{CC} -0.5		V _{CC}	V
V _{OH}	HIGH output voltage	X _{OUT}	I _{OH} = -0.1mA	V _{CC} -0.5		V _{CC}	V
V _{OL}	LOW output voltage	P6 ₀ to P6 ₇ , P7 ₁ , P7 ₃ , P7 ₄ , P7 ₆ , P8 ₀ to P8 ₄ , P9 ₀ to P9 ₂ , TS	I _{OL} = 1mA			0.5	V
V _{OL}	LOW output voltage	X _{OUT}	I _{OL} = 0.1mA			0.5	V
V _{T+} -V _{T-}	Hysteresis	TA0IN, TA1IN, TA4IN, INT1 to INT3, CTS0 to CT5, SCL, SDA, CLK0 to CLK4, TA4OUT, RxD0 to RxD2, S _N 3		0.2		0.8	V
V _{T+} -V _{T-}	Hysteresis	RESET		0.2	(0.7)	1.8	V
I _{IH}	HIGH input current	P6 ₀ to P6 ₇ , P7 ₀ , P7 ₁ , P7 ₃ , P7 ₄ , P7 ₆ , P8 ₀ to P8 ₄ , P9 ₀ to P9 ₂ X _{IN} , RESET, CNVss	V _I = 3V			4.0	μA
I _{IL}	LOW input current	P6 ₀ to P6 ₇ , P7 ₀ , P7 ₁ , P7 ₃ , P7 ₄ , P7 ₆ , P8 ₀ to P8 ₄ , P9 ₀ to P9 ₂ X _{IN} , RESET, CNVss	V _I = 0V			-4.0	μA
R _{PULLUP}	Pull-up resistance	P6 ₀ to P6 ₇ , P7 ₁ , P7 ₃ , P7 ₄ , P7 ₆ , P8 ₀ to P8 ₄ , P9 ₀ to P9 ₂	V _I = 0V	66	160	500	kΩ
R _{IXIN}	Feedback resistance	X _{IN}			3.0		MΩ

Note : Referenced to V_{CC}=3.0 to 3.6V, V_{SS}=0V at T_{opr} = -20 to 85 °C, f(BCLK)=15.36 MHz unless otherwise specified.

Table 1.19.7. Electrical Characteristics (2) (Note 1)

Symbol	Parameter		Measuring condition		Standard			Unit
					Min.	Typ.	Max.	
I _{cc}	Power supply current (V _{CC} =2.7 to 3.6V)	In single-chip mode, the output pins are open and other pins are V _{SS}	Flash memory	f(BCLK)=15.36 MHz, No division		70		mA
			Flash memory Program	f(BCLK)=10MHz, V _{CC1} =3.0V		TBD		mA
			Flash memory Erase	f(BCLK)=10MHz, V _{CC1} =3.0V		TBD		mA

Note 1: Referenced to V_{CC}=3.0 to 3.6V, V_{SS}=0V at Topr = -20 to 85 °C, f(BCLK)=15.36MHz unless otherwise specified.

Timing Requirements**($V_{CC} = 3V$, $V_{SS} = 0V$, at $T_{opr} = -20$ to $85^{\circ}C$ unless otherwise specified)****Table 1.19.8. External Clock Input**

Symbol	Parameter	Standard		Unit
		Min.	Max.	
t_c	External clock input cycle time	195.3		ns
$t_{w(H)}$	External clock input HIGH pulse width	80		ns
$t_{w(L)}$	External clock input LOW pulse width	80		ns
t_r	External clock rise time		18	ns
t_f	External clock fall time		18	ns

Timing Requirements(V_{CC} = 3V, V_{SS} = 0V, at T_{opr} = – 20 to 85°C unless otherwise specified)**Table 1.19.9. Timer A Input (Counter Input in Event Counter Mode)**

Symbol	Parameter	Standard		Unit
		Min.	Max.	
t _c (TA)	TAiN input cycle time	150		ns
t _w (TAH)	TAiN input HIGH pulse width	60		ns
t _w (TAL)	TAiN input LOW pulse width	60		ns

Table 1.19.10. Timer A Input (Gating Input in Timer Mode)

Symbol	Parameter	Standard		Unit
		Min.	Max.	
t _c (TA)	TAiN input cycle time	600		ns
t _w (TAH)	TAiN input HIGH pulse width	300		ns
t _w (TAL)	TAiN input LOW pulse width	300		ns

Table 1.19.11. Timer A Input (External Trigger Input in One-shot Timer Mode)

Symbol	Parameter	Standard		Unit
		Min.	Max.	
t _c (TA)	TAiN input cycle time	300		ns
t _w (TAH)	TAiN input HIGH pulse width	150		ns
t _w (TAL)	TAiN input LOW pulse width	150		ns

Table 1.19.12. Timer A Input (External Trigger Input in Pulse Width Modulation Mode)

Symbol	Parameter	Standard		Unit
		Min.	Max.	
t _w (TAH)	TAiN input HIGH pulse width	150		ns
t _w (TAL)	TAiN input LOW pulse width	150		ns

Table 1.19.13. Timer A Input (Counter Increment/decrement Input in Event Counter Mode)

Symbol	Parameter	Standard		Unit
		Min.	Max.	
t _c (UP)	TAiOUT input cycle time	3000		ns
t _w (UPH)	TAiOUT input HIGH pulse width	1500		ns
t _w (UPL)	TAiOUT input LOW pulse width	1500		ns
t _{su} (UP-TiN)	TAiOUT input setup time	600		ns
t _h (TiN-UP)	TAiOUT input hold time	600		ns

Table 1.19.14. Timer A Input (Two-phase Pulse Input in Event Counter Mode)

Symbol	Parameter	Standard		Unit
		Min.	Max.	
t _c (TA)	TAiN input cycle time	2		μs
t _{su} (TAiN-TAOUT)	TAiOUT input setup time	500		ns
t _{su} (TAOUT-TAiN)	TAiN input setup time	500		ns

Timing Requirements**(V_{CC} = 3V, V_{SS} = 0V, at T_{opr} = – 20 to 85°C unless otherwise specified)****Table 1.19.15. Serial I/O**

Symbol	Parameter	Standard		Unit
		Min.	Max.	
t _c (CK)	CLKi input cycle time	300		ns
t _w (CKH)	CLKi input HIGH pulse width	150		ns
t _w (CKL)	CLKi input LOW pulse width	150		ns
t _d (C-Q)	TxDi output delay time		160	ns
t _h (C-Q)	TxDi hold time	0		ns
t _{su} (D-C)	RxDi input setup time	100		ns
t _h (C-D)	RxDi input hold time	90		ns

Table 1.19.16. External Interrupt INTi Input

Symbol	Parameter	Standard		Unit
		Min.	Max.	
t _w (INH)	INTi input HIGH pulse width	380		ns
t _w (INL)	INTi input LOW pulse width	380		ns




Figure 1.19.1. Timing Diagram (1)




Figure 1.19.2. Timing Diagram (2)

Flash Memory Version

Flash Memory Performance

The flash memory version has three modes—CPU rewrite, standard serial input/output, and parallel input/output modes—in which its internal flash memory can be operated on.

Note: About the parallel writer of exclusive use, there is no schedule of development at the present time.

Table 1.20.1 shows the outline performance of flash memory version (see Table 1.1.1 for the items not listed in Table 1.20.1.).

Table 1.20.1. Flash Memory Version Specifications

Item		Specification
Flash memory operating mode		3 modes (CPU rewrite, standard serial I/O, parallel I/O)
Erase block	User ROM area	See Figure 1.20.1
	Boot ROM area	1 block (4 Kbytes) (Note 1)
Method for program		In units of word
Method for erasure		Block erase
Program, erase control method		Program and erase controlled by software command
Protect method		Two 8 Kbyte user blocks by register lock bit (FMR02)
Number of commands		5 commands
Number of program and erasure		100 times
Data Retention		10 years
ROM code protection		Parallel I/O and standard serial I/O modes are supported.

Note 1: The boot ROM area contains a standard serial I/O mode rewrite control program which is stored in it when shipped from the factory. This area can only be rewritten in parallel input/output mode.

Table 1.20.2. Flash Memory Rewrite Modes Overview

Flash memory rewrite mode	CPU rewrite mode	Standard serial I/O mode
Function	The user ROM area is rewritten by executing software commands from the CPU. EW0 mode: Can be rewritten in any area other than the flash memory EW1 mode: Can be rewritten in the flash memory	The user ROM area is rewritten by using a dedicated serial programmer. Standard serial I/O mode 1: Clock sync serial I/O Standard serial I/O mode 2: UART
Areas which can be rewritten	User ROM area	User ROM area
Operation mode	Single chip mode Memory expansion mode (EW0 mode) Boot mode (EW0 mode)	Boot mode
ROM programmer	None	Serial programmer

1. Memory Map

The ROM in the flash memory version is separated between a user ROM area and a boot ROM area. Figure 1.20.1 shows the block diagram of flash memory.

The user ROM area is divided into several blocks, so that memory can be erased one block at a time. The user ROM area can be rewritten in all of CPU rewrite, standard serial input/output, and parallel input/output modes.

The boot ROM area is located at addresses that overlap the user ROM area, and can only be rewritten in parallel input/output mode.




Figure 1.20.1. Flash Memory Block Diagram

Boot Mode

After a hardware reset which is performed by applying a high-level signal to the CNVss and P15 pins, the microcomputer is placed in boot mode, thereby executing the program in the boot ROM area.

The boot ROM area contains a standard serial input/output mode based rewrite control program which was stored in it when shipped from the factory.

Functions To Prevent Flash Memory from Rewriting

To prevent the flash memory from being read or rewritten easily, parallel input/output mode has a ROM code protect and standard serial input/output mode has an ID code check function.

• ROM Code Protect Function

The ROM code protect function inhibits the flash memory from being read or rewritten during parallel input/output mode. Figure 1.20.2 shows the ROMCP register.

The ROMCP register is located in the user ROM area. The ROMCP1 bit consists of two bits. The ROM code protect function is enabled by clearing one or both of two ROMCP1 bits to "0" when the ROMCR bits are not '002,' with the flash memory thereby protected against reading or rewriting. Conversely, when the ROMCR bits are '002' (ROM code protect removed), the flash memory can be read or rewritten. Once the ROM code protect function is enabled, the ROMCR bits cannot be changed during parallel input/output mode. Therefore, use standard serial input/output or other modes to rewrite the flash memory.

• ID Code Check Function

Use this function in standard serial input/output mode. Unless the flash memory is blank, the ID codes sent from the programmer and the ID codes written in the flash memory are compared to see if they match. If the ID codes do not match, the commands sent from the programmer are not accepted. The ID code consists of 8-bit data, the areas of which, beginning with the first byte, are 0FFFD₁₆, 0FFFE₃₁₆, 0FFFEB₁₆, 0FFFEF₁₆, 0FFFF₃₁₆, 0FFFF₇₁₆, and 0FFFFB₁₆. Prepare a program in which the ID codes are preset at these addresses and write it in the flash memory.




Figure 1.20.2. ROMCP Register




Figure 1.20.3. Address for ID Code Stored

CPU Rewrite Mode

In CPU rewrite mode, the user ROM area can be rewritten by executing software commands from the CPU. Therefore, the user ROM area can be rewritten directly while the microcomputer is mounted on-board without having to use a ROM programmer, etc.

In CPU rewrite mode, only the user ROM area shown in Figure 1.20.1 can be rewritten and the boot ROM area cannot be rewritten. Make sure the Program and the Block Erase commands are executed only on each block in the user ROM area.

During CPU rewrite mode, the user ROM area can be operated on in either Erase Write 0 (EW0) mode or Erase Write 1 (EW1) mode. Table 1.21.1 lists the differences between Erase Write 0 (EW0) and Erase Write 1 (EW1) modes.

Table 1.21.1. EW0 Mode and EW1 Mode

Item	EW0 mode	EW1 mode
Operation mode	• Single chip mode	Single chip mode
Areas in which a rewrite control program can be located	• User ROM area	User ROM area
Areas in which a rewrite control program can be executed	Must be transferred to any area other than the flash memory (e.g., RAM) before being executed	Can be executed directly in the user ROM area
Areas which can be rewritten	User ROM area	User ROM area However, this does not include the area in which a rewrite control program exists
Software command limitations	None	<ul style="list-style-type: none"> • Program, Block Erase command Cannot be executed on any block in which a rewrite control program exists • Read Status Register command Cannot be executed
Modes after Program or Erase	Read Status Register mode	Read Array mode
CPU status during Auto Write and Auto Erase	Operating	Hold state (I/O ports retain the state in which they were before the command was executed) ^(Note)
Flash memory status detection	<ul style="list-style-type: none"> • Read the FMR0 register's FMR00, FMR06, and FMR07 bits in a program • Execute the Read Status Register command to read the status register's SR7, SR5, and SR4 flags. 	Read the FMR0 register's FMR00, FMR06, and FMR07 bits in a program

Note: Make sure no interrupts (except NMI and watchdog timer interrupts) and DMA transfers will occur.

- **EW0 Mode**

The microcomputer is placed in CPU rewrite mode by setting the FMR0 register's FMR01 bit to "1" (CPU rewrite mode enabled), ready to accept commands. In this case, because the FMR1 register's FMR11 bit = 0, EW0 mode is selected. The FMR01 bit can be set to "1" by writing "0" and then "1" in succession. Use software commands to control program and erase operations. Read the FMR0 register or status register to check the status of program or erase operation at completion.

- **EW1 Mode**

EW1 mode is selected by setting FMR11 bit to "1" (by writing "0" and then "1" in succession) after setting the FMR01 bit to "1" (by writing "0" and then "1" in succession).

Read the FMR0 register to check the status of program or erase operation at completion. The status register cannot be read during EW1 mode.

Figure 1.21.2 shows the FMR0 and FMR1 registers.

FMR00 Bit

This bit indicates the operating status of the flash memory. The bit is “0” when the Program or Erase is running; otherwise, the bit is “1”.

FMR01 Bit

The microcomputer is made ready to accept commands by setting the FMR01 bit to “1” (CPU rewrite mode).

FMR02 Bit

When FMR02 bit is “0” (rewriting is disable), block 0 and block 1 do not receive the command of a program and block erase.

FMSTP Bit

This bit is provided for initializing the flash memory control circuits, as well as for reducing the amount of current consumed in the flash memory. The internal flash memory is disabled against access by setting the FMSTP bit to “1”. Therefore, the FMSTP bit must be written to by a program in other than the flash memory.

In the following cases, set the FMSTP bit to “1”:

- When flash memory access resulted in an error while erasing or programming in EW0 mode (FMR00 bit not reset to “1” (ready))
- When entering low power mode or ring low power mode

FMR06 Bit

This is a read-only bit indicating the status of auto program operation. The bit is set to “1” when a program error occurs; otherwise, it is cleared to “0”. For details, refer to the description of the full status check.

FMR07 Bit

This is a read-only bit indicating the status of auto erase operation. The bit is set to “1” when an erase error occurs; otherwise, it is cleared to “0”. For details, refer to the description of the full status check.

Figure 1.21.3 and 1.21.4 show the setting and resetting of EW0 mode and EW1 mode, respectively.

FMR11 Bit

Setting this bit to “1” places the microcomputer in EW1 mode.




Figure 1.21.2. FIDR Register and FMR0 and FMR1 Registers





Figure 1.21.3. Setting and Resetting of EW0 Mode

EW1 mode operation procedure



Note 1: Select 10 MHz or less for CPU clock using the CM0 register's CM06 bit and CM1 register's CM17 to 6 bits. Also, set the PM1 register's PM17 bit to "1" (with wait state).

Note 2: To set the FMR01 bit to "1", write "0" and then "1" in succession. Make sure no interrupts or no DMA transfers will occur before writing "1" after writing "0". Write to the FMR01 bit from a program in other than the flash memory. Also write only when the NMI pin is "H" level.

Figure 1.21.4. Setting and Resetting of EW1 Mode

Precautions on CPU Rewrite Mode

Described below are the precautions to be observed when rewriting the flash memory in CPU rewrite mode.

(1) Operation Speed

Before entering CPU rewrite mode (EW0 or EW1 mode), select 10 MHz or less for BCLK using the CM06 bit in the CM0 register and the CM17 to CM16 bits in the CM1 register. Also, set the PM17 bit in the PM1 register to "1" (with wait state).

(2) Instructions to Prevent from Using

The following instructions cannot be used in EW0 mode because the flash memory's internal data is referenced: UND instruction, INTO instruction, JMPs instruction, JSRS instruction, and BRK instruction.

(3) Interrupts

EW0 Mode

- Any interrupt which has a vector in the variable vector table can be used providing that its vector is transferred into the RAM area.
- The $\overline{\text{NMI}}$ and watchdog timer interrupts can be used because the FMR0 register and FMR1 register are initialized when one of those interrupts occurs. The jump addresses for those interrupt service routines should be set in the fixed vector table.

Because the rewrite operation is halted when a $\overline{\text{NMI}}$ or watchdog timer interrupt occurs, the rewrite program must be executed again after exiting the interrupt service routine.

- The address match interrupt cannot be used because the flash memory's internal data is referenced.

EW1 Mode

- Make sure that any interrupt which has a vector in the variable vector table or address match interrupt will not be accepted during the auto program or auto erase period.
- Avoid using watchdog timer interrupts.
- The WDT interrupt can be used because the FMR0 register and FMR1 register are initialized when this interrupt occurs. The jump address for the interrupt service routine should be set in the fixed vector table.

Because the rewrite operation is halted when a WDT interrupt occurs, the rewrite program must be executed again after exiting the interrupt service routine.

(4) How to Access

To set the FMR01, FMR02, or FMR11 bit to "1", write "0" and then "1" in succession. This is necessary to ensure that no interrupts or DMA transfers will occur before writing "1" after writing "0".

(5) Writing in the User ROM Space

EW0 Mode

- If the power supply voltage drops while rewriting any block in which the rewrite control program is stored, a problem may occur that the rewrite control program is not correctly rewritten and, consequently, the flash memory becomes unable to be rewritten thereafter. In this case, standard serial I/O or parallel I/O mode should be used.

EW1 Mode

- Avoid rewriting any block in which the rewrite control program is stored.

(6) DMA Transfer

In EW1 mode, make sure that no DMA transfers will occur while the FMR0 register's FMR00 bit = 0 (during the auto program or auto erase period).

(7) Writing Command and Data

Write the command code and data at even addresses.

(8) Wait Mode

When shifting to wait mode, set the FMR01 bit to "0" (CPU rewrite mode disabled) before executing the WAIT instruction.

(9) Stop Mode

When shifting to stop mode, the following settings are required:

- Set the FMR01 bit to "0" (CPU rewrite mode disabled) and disable DMA transfers before setting the CM10 bit to "1" (stop mode).
- Execute the JMP.B instruction subsequent to the instruction which sets the CM10 bit to "1" (stop mode)

```
Example program    BSET      0, CM1      ; Stop mode
                   JMP.B     L1
```

L1:

Program after returning from stop mode

Software Commands

Software commands are described below. The command code and data must be read and written in 16-bit units, to and from even addresses in the user ROM area. When writing command code, the 8 high-order bits (D₁₅–D₈) are ignored.

Table 1.21.2. Software Commands

Command	First bus cycle			Second bus cycle		
	Mode	Address	Data (D ₀ to D ₇)	Mode	Address	Data (D ₀ to D ₇)
Read array	Write	X	xxFF ₁₆			
Read status register	Write	X	xx70 ₁₆	Read	X	SRD
Clear status register	Write	X	xx50 ₁₆			
Program	Write	WA	xx40 ₁₆	Write	WA	WD
Block erase	Write	X	xx20 ₁₆	Write	BA	xxD0 ₁₆

SRD: Status register data (D₇ to D₀)

WA: Write address (Make sure the address value specified in the the first bus cycle is the same even address as the write address specified in the second bus cycle.)

WD: Write data (16 bits)

BA: Uppermost block address (even address, however)

X: Any even address in the user ROM area

x: High-order 8 bits of command code (ignored)

Read Array Command (FF₁₆)

This command reads the flash memory.

Writing 'xxFF₁₆' in the first bus cycle places the microcomputer in read array mode. Enter the read address in the next or subsequent bus cycles, and the content of the specified address can be read in 16-bit units.

Because the microcomputer remains in read array mode until another command is written, the contents of multiple addresses can be read in succession.

However, when you use Read array command immediately after a program command, please read data in the following procedure.

- (1) FF₁₆, FF₁₆, FF₁₆, and FF₁₆ are written to 4 arbitrary continuous addresses.
- (2) The head address of (1) is specified in Read array mode.
- (3) (2) is repeated until the read value and FFFF₁₆ are in agreement.
- (4) The head address +2 of (1) is specified.
- (5) (4) is repeated until the read value and FFFF₁₆ are in agreement.
- (6) Arbitrary addresses are specified.

Read Status Register Command (70₁₆)

This command reads the status register.

Write 'xx70₁₆' in the first bus cycle, and the status register can be read in the second bus cycle. (Refer to "Status Register.") When reading the status register too, specify an even address in the user ROM area.

Do not execute this command in EW1 mode.

Clear Status Register Command (50₁₆)

This command clears the status register to "0".

Write 'xx50₁₆' in the first bus cycle, and the FMR06 to FMR07 bits in the FMR0 register and SR4 to SR5 in the status register will be cleared to "0".

Program Command (40₁₆)

This command writes data to the flash memory in 1 word (2 byte) units.

Write 'xx40₁₆' in the first bus cycle and write data to the write address in the second bus cycle, and an auto program operation (data program and verify) will start. Make sure the address value specified in the first bus cycle is the same even address as the write address specified in the second bus cycle.

Check the FMR00 bit in the FMR0 register to see if auto programming has finished. The FMR00 bit is "0" during auto programming and set to "1" when auto programming is completed.

Check the FMR06 bit in the FMR0 register after auto programming has finished, and the result of auto programming can be known. (Refer to "Full Status Check.")

Writing over already programmed addresses is inhibited.

Moreover, when FMR02 bit of FMR0 register is "0" (rewriting is disable), the program command to block 0 and block 1 is not received. Just behind a program command, when you execute commands other than a program command, please make it the address value which was specified by the 2nd bus cycle of a program command and which writes in and specifies the same address as an address by the 1st bus cycle of the following command.

In EW1 mode, do not execute this command on any address at which the rewrite control program is located.

In EW0 mode, the microcomputer goes to read status register mode at the same time auto programming starts, making it possible to read the status register. The status register bit 7 (SR7) is cleared to "0" at the same time auto programming starts, and set back to "1" when auto programming finishes. In this case, the microcomputer remains in read status register mode until a read command is written next. The result of auto programming can be known by reading the status register after auto programming has finished.




Figure 1.21.5. Program Command

Block Erase

Write 'xx2016' in the first bus cycle and write 'xxD016' to the uppermost address of a block (even address, however) in the second bus cycle, and an auto erase operation (erase and verify) will start. Check the FMR0 register's FMR00 bit to see if auto erasing has finished.

The FMR00 bit is "0" during auto erasing and set to "1" when auto erasing is completed.

Check the FMR0 register's FMR07 bit after auto erasing has finished, and the result of auto erasing can be known. (Refer to "Full Status Check.")

Moreover, when FMR02 bit of FMR0 register is "0" (rewriting is disable), the block erase command to block 0 and block 1 is not received.

Figure 1.21.6 shows an example of a block erase flowchart.

Each block can be protected against erasing by a lock bit. (Refer to "Data Protect Function.")

Writing over already programmed addresses is inhibited.

In EW1 mode, do not execute this command on any address at which the rewrite control program is located.

In EW0 mode, the microcomputer goes to read status register mode at the same time auto erasing starts, making it possible to read the status register. The status register bit 7 (SR7) is cleared to "0" at the same time auto erasing starts, and set back to "1" when auto erasing finishes. In this case, the microcomputer remains in read status register mode until the Read Array or Read Lock Bit Status command is written next.




Figure 1.21.6. Block Erase Command

Status Register

The status register indicates the operating status of the flash memory and whether an erase or programming operation terminated normally or in error. The status of the status register can be known by reading the FMR0 register's FMR00, FMR06, and FMR07 bits.

Table 1.21.3 shows the status register.

In EW0 mode, the status register can be read in the following cases:

- (1) When a given even address in the user ROM area is read after writing the Read Status Register command
- (2) When a given even address in the user ROM area is read after executing the Program, Block Erase, Erase All Unlocked Block, or Lock Bit Program command but before executing the Read Array command.

Sequencer Status (SR7 and FMR00 Bits)

The sequence status indicates the operating status of the flash memory. SR7 = 0 (busy) during auto programming and auto erase is set to "1" (ready) at the same time the operation finishes.

Erase Status (SR5 and FMR07 Bits)

Refer to "Full Status Check."

Program Status (SR4 and FMR06 Bits)

Refer to "Full Status Check."

Table 1.21.3. Status Register

- D0 to D7: Indicates the data bus which is read out when the Read Status Register command is executed.

Status register bit	FMR0 register bit	Status name	Contents		Value after reset
			"0"	"1"	
SR7 (D7)	FMR00	Sequencer status	Busy	Ready	1
SR6 (D6)	——	Reserved	-	-	——
SR5 (D5)	FMR07	Erase status	Terminated normally	Terminated in error	0
SR4 (D4)	FMR06	Program status	Terminated normally	Terminated in error	0
SR3 (D3)	——	Reserved	-	-	——
SR2 (D2)	——	Reserved	-	-	——
SR1 (D1)	——	Reserved	-	-	——
SR0 (D0)	——	Reserved	-	-	——

- The FMR07 bit (SR5) and FMR06 bit (SR4) are cleared to "0" by executing the Clear Status Register command.
- When the FMR07 bit (SR5) or FMR06 bit (SR4) = 1, the Program and Block Erase are not accepted.

Full Status Check

When an error occurs, the FMR0 register's FMR06 to FMR07 bits are set to "1", indicating occurrence of each specific error. Therefore, execution results can be verified by checking these status bits (full status check). Table 1.21.4 lists errors and FMR0 register status. Figure 1.21.7 shows a full status check flowchart and the action to be taken when each error occurs.

Table 1.21.4. Errors and FMR0 Register Status

FRM00 register (status register) status		Error	Error occurrence condition
FMR07 (SR5)	FMR06 (SR4)		
1	1	Command sequence error	<ul style="list-style-type: none"> When any command is not written correctly When invalid data was written other than those that can be written in the second bus cycle of the Block Erase command (i.e., other than 'xxD016' or 'xxFF16') (Note 1)
1	0	Erase error	<ul style="list-style-type: none"> When the Block Erase was executed but the blocks were not automatically erased correctly
0	1	Program error	<ul style="list-style-type: none"> When the Program command was executed but the blocks were not automatically programmed correctly.

Note 1: Writing "xxFF16" in the second bus cycle of these commands places the microcomputer in read array mode, and the command code written in the first bus cycle is nullified.




Figure 1.21.7. Full Status Check and Handling Procedure for Each Error

Standard Serial I/O Mode

The standard serial I/O mode inputs and outputs the software commands, addresses and data needed to operate (read, program, erase, etc.) the internal flash memory using the serial I/O port UART1. The serial I/O mode transfers the data serially in 8-bit units.

In the standard serial I/O mode the CPU executes a control program for flash memory rewrite (using the CPU's rewrite mode), rewrite data input and so forth. It is started when both the P15 (CE) pin and the CNVss pin are in "H" level after the reset is released. (In normal operation mode, set CNVss pin to "L" level.)

This control program is written in the boot ROM area when the product is shipped.

There are actually two standard serial I/O modes: mode 1, which is clock synchronized, and mode 2, which is asynchronous. Standard serial I/O switches between mode 1 (clock synchronous) and mode 2 (clock asynchronous) depending on the level of CLK1 pin when the reset is released.

To use standard serial I/O mode 1 (clock synchronous), set the CLK1 pin to "H" level and release the reset. The operation uses the four UART1 pins CLK1, RxD1, TxD1 and RTS1 (BUSY). The CLK1 pin is the transfer clock input pin through which an external transfer clock is input. The TxD1 pin is for CMOS output. The RTS1 (BUSY) pin outputs an "L" level when ready for reception and an "H" level when reception starts. In mode 1, be sure the TxD1 (P67) pin is at high before reset being deasserted.

To use standard serial I/O mode 2 (clock asynchronous), set the CLK1 pin to "L" level and release the reset. The operation uses the two UART1 pins RxD1 and TxD1.

In standard serial input/output mode, the user ROM area can be rewritten while the microcomputer is mounted on-board by using a serial programmer suitable for the M16C/62P group. For more information about serial programmers, contact the manufacturer of your serial programmer. For details on how to use, refer to the user's manual included with your serial programmer.

Table 1.22.1 lists pin functions (flash memory standard serial input/output mode). Figures 1.22.1 to 1.22.2 show pin connections for serial input/output mode.

ID Code Check Function

This function determines whether the ID codes sent from the serial programmer and those written in the flash memory match. (Refer to the description of the functions to inhibit rewriting flash memory version.)

Table 1.22.1. Functional explanation of pin (flash memory standard serial I/O mode)

Pin	Signal name	I/O	Description
Vcc,Vss	Power supply input		Apply the voltage guaranteed for Program and Erase to Vcc pin. Apply 0 V to Vss pin.
CNVss	CNVss	I	Connect to Vcc pin.
RESET	Reset input	I	Reset input pin. While RESET pin is "L" level, input a 20 cycle or longer clock to XIN pin.
XIN	Clock input	I	Connect a ceramic resonator or crystal oscillator between XIN and XOUT pins. To input an externally generated clock, input it to XIN pin and open XOUT pin.
XOUT	Clock output	O	
VDCCN			Input "H" level signal.
VCCA, VssA	Analog power supply input	I	Please connect AVcc to Vcc and connect AVss to Vss.
VREF	Standard voltage input	I	Input the standard voltage of a preamplifier and an operational amplifier.
P60 to P63	Input port P6	I	Input "H" or "L" level signal or open.
P64/RTS1	BUSY output	O	Standard serial I/O mode 1: BUSY signal output pin Standard serial I/O mode 2: Monitors the boot program operation check signal output pin.
P65/CLK1	SCLK input	I	Standard serial I/O mode 1: Serial clock input pin Standard serial I/O mode 2: Input "L."
P66/RxD1	RxD input	I	Serial data input pin.
P67/TxD1	TxD output	O	Serial data output pin. (Note 1)
P70, P71, P73, P74, P76	Input port P7	I	Input "H" or "L" level signal or open.
P80, P81, P83, P84, P85	Input port P8	I	Input "H" or "L" level signal or open.
P15	CE input	I	Input "H" level signal.
P90 to P92	Input port P11	I	Input "H" or "L" level signal or open.

Note 1: When using standard serial input/output mode 1, the TxD pin must be held high while the RESET pin is pulled low. Therefore, connect this pin to Vcc1 via a resistor. Because this pin is directed for data output after reset, adjust the pull-up resistance value in the system so that data transfers will not be affected.

Example of Circuit Application in the Standard Serial I/O Mode

Figure 1.22.1 and 1.22.2 show example of circuit application in standard serial I/O mode 1 and mode 2, respectively. Refer to the user's manual for serial writer to handle pins controlled by a serial writer.





Figure 1.22.1. Circuit Application in Standard Serial I/O Mode 1

**Figure 1.22.2. Circuit Application in Standard Serial I/o Mode 2**

ROM Code Protect Function

The ROM code protect function inhibits the flash memory from being read or rewritten. (Refer to the description of the functions to inhibit rewriting flash memory version.)

IT800AFE (Analog Front End)

1. The block diagram of analog front end

Analog front end (AFE) part is the circuit located between M16C/6S and a power line, and M16C/6S build in DAC, preamplifier, and ADC. There are the following two signal circuits in AFE.

(1)Transmitting circuit:It drives with the signal from the logic of M16C/6S inside, and this is consists of DAC with a differential output, Output filter for spectrum adjustment, Differential line driver amplifier and line coupling circuit which drive power line.

(2)Receiving circuit:This is consists of Line coupling circuit, Differential preamplifier, Input filter group and ADC. Line coupling circuit is common to both transmission and reception.




Fig.1.23.1 Analog Front End circuit block diagram

(1)Transmitting circuit

The characteristic required for transmitting course is as follows.

- (a)A suitable output signal level is obtained to the load of rating
- (b)It has the frequency characteristic to maximum zone width of 400kHz
- (c)The signal level outside a zone:It is less than each regulation

This system assumes operation in the following three fundamental signal zones.

- (a)The U.S., Japan:100k to 400kHz
- (b)Europe in door:95k to 125kHz(CENELEC B Band)
- (c)Europe out door:20k to 80kHz(CENELEC A Band)

It is necessary to perform the change of a signal zone by change of adjustment of change of the configuration of IT800, the analog filter to a signal zone, or output electric power, and the output impedance of the line driver stage (notes).

Note. Please refer to the following standard and style about the conditions outside a signal level or a zone.

- (a)The U.S.:FCC standard, part 15
- (b)Europe:CENELEC standard, EN 50065-1
- (c)Japan:ARIB

About DAC (Digital to Analog Converter)

DAC of built-in in M16C/6S is current output type 10 bit DAC. The standard level of output current can be set up by the external resistance linked to a built-in standard power supply. A DAC circuit and a load circuit are shown in Fig. 1.23.2. The typical characteristic is shown in Table 1.23.1.




Fig.1.23.2 DAC (Digital to Analog Converter)

Table.1.23.1 DAC Electrical Characteristics (Vdd=3.3±0.3V, Ta=-20°C to 85°C unless otherwise specified)

Parameter	Symbol	Condition	Electrical Characteristics			Unit
			Min	Typ	Max	
Standard voltage	Vref	Rext=2.1kΩ		0.3		V
Standard current	Iref	Rext=2.1kΩ		0.14		mA
External standard register	Rext			2.1		kΩ
DAC output register	Rout/Routc	Rext=2.1kΩ			2.0	kΩ
Full-scale current	IFULL	Rext=2.1kΩ	0.9	1	1.1	mA
Maximum output voltage	Voutmax	Rout/Routc=2.1kΩ			Vdd-1	V

In the circumference of a DAC circuit, it is cautious of the following point and a constant is set up.

(a) Full-scale output current of DAC

Although the current by which DAC is outputted to a pin (Iout/Ioutc) according to the change width of an internal bit changes, total is fixed and serves as full-scale output current (IFULL). This IFULL can be set up by the following formula.

$$IFULL = 2131 / R_{ext}(\text{mA})$$

The unit of R_{ext} is

Since about 1mA of an IFULL value is the optimal value, R_{ext} is 2.1k .

DAC is total and Iout/Ioutc changes between 0 to IFULL at 1024 steps by the full range for a change width of 10 bits.

The value of Iout/Ioutc is expressed with the following formula if the step value which converted the 10-bit binary input into decimal is set to d. (d=0 to 1023)

$$I_{out} = IFULL / 1023 * d$$

$$I_{outc} = IFULL / 1023 * (1023 - d)$$

(b) About DAC load resistance

Resistance (R_{out}/R_{outc}) is connected to a DAC output pin. In this resistance, signal voltage occurs by the current (Iout/Ioutc) which flows, respectively. In order to maintain the linearity of Iout/Ioutc, it is necessary to set up R_{out}/R_{outc} so that this potential may not exceed maximum 2V. Since Iout/Ioutc is mostly set to one half of IFULL(s) at the time of a non-signal (balanced state), the signal voltage (V_{out}/V_{outc}) of a DAC output pin is set to below:

$$V_{out} = R_{out} \times I_{out}$$

$$V_{outc} = R_{outc} \times I_{outc}$$

Since the recommendation value of V_{out}/V_{outc} at the time of a non-signal is about 1V, in $R_{ext}=2.1k$, R_{out}/R_{outc} serves as 2.1k .

The capacitor (C_{out}/C_{outc}) for output filters cuts the high frequency ingredient of DAC, and sets it up on balance with necessary zone frequency.

(2)Receiving circuit

(a)Preamplifier

A preamplifier circuit consists of two CMOS operational amplifiers as shown in Fig. 3, the first opamp is connected as gain stage with gain of 20dB and the second opamp is connected as a voltage follower for driving of external filter.




Fig. 1.23.3 Consists of Preamp circuit

Table.1.23.2 Preamp Electrical Characteristics (Ta=-25°C unless otherwise specified)

Parameter	Symbol	Condition	Electrical Characteristics			Unit
			Min	Typ	Max	
Standard voltage	Vdd		3.0	3.3	3.6	V
Input off-set voltage	Vof				15	mV
Open loop gain	Gvo	No-load	70			dB
Gain band width	BW	Gvo=0dB	5			MHz
Common mode input range	CMIR	DC to 1MHz	0.7		Vdd-0.7	V
Common mode rejection ratio	CMRR	DC to 1MHz	40			dB
Power supply rejection ratio	PSRR	DC to 1MHz	30			dB

(b)ADC (Analog to Digital Converter)

The output of the channel filter (maximum of three) connected outside is connected to 1 bit ADC which consists of an operational amplifier and a comparator.

M16C/6S build in ADC of three equivalent performances. The circuit of one ADC has composition shown in the following figure.




Fig.1.23.4 ADC block diagram

Three ADC use all three by the signal zone to be used. The constant of a filter is set up as shown in the following table.

Table.1.23.3 The example of an ADC part constant setting

Parts	Application characteristic	C1	C2	C3	Unit
Capacitor	FCC/ARIB	33	22	10	pF
	CECLEC-B	33	—	—	pF
Parts	Application characteristic	R1	R2	R3	Unit
Register	FCC/ARIB	10	10	12	k
	CECLEC-B	10	—	—	k

REVISION HISTORY

M16C/6S Group

Rev. No.	Revision Description	Rev. date
1.00	First Edition of PDF File	Jun 25, 2003
2.00	<p>P1 L7 is changed.</p> <p>P2 T1.1.1 is changed.</p> <p>P3 F1.1.1 is changed.</p> <p>P4 T1.1.2 is changed.</p> <p>P5 F1.1.2 is changed.</p> <p>P7 T1.1.3 is changed.</p> <p>P8 T1.1.4 is changed.</p> <p>P9 L5 and F1.2.1 are changed.</p> <p>P12 Table of register is changed.</p> <p>P14 Table of register is changed.</p> <p>P15 Table of register is changed.</p> <p>P20 F1.5.2 is changed.</p> <p>P24 F1.6.1 is changed.</p> <p>P25 F1.6.2 is changed.</p> <p>P26 F1.6.3 is changed.</p> <p>P27 L2 and F1.7.1 are changed.</p> <p>P29 F1.7.2 is changed.</p> <p>P30 F1.7.3 is changed.</p> <p>P33 L4 to L5 and F1.7.6 are changed.</p> <p>P36 L5 is changed.</p> <p>P37 T1.7.2 is changed.</p> <p>P42 F1.7.8 is changed.</p> <p>P43 T1.7.6 is changed.</p> <p>P45 T1.7.7 is changed.</p> <p>P52 T1.9.2 is changed.</p> <p>P54 T1.9.3 is changed.</p> <p>P62 L2 is changed.</p> <p>P83 F1.12.5 is changed.</p> <p>P84 F1.12.6 is changed.</p> <p>P85 L3 and T1.12.2 are changed.</p> <p>P88 F1.12.8 is changed.</p> <p>P90 F1.12.9 is changed.</p> <p>P92 F1.12.10 is changed.</p> <p>P94 L13 is changed.</p> <p>P95 F1.13.1 is changed.</p> <p>P100 F1.13.6 is changed.</p> <p>P107 F1.14.2 and F1.14.3 are changed.</p> <p>P119 T1.16.2 is changed.</p>	Aug 18, 2003

Rev. No.	Revision Description	Rev. date
2.00	<p>P121 T1.16.4 is changed.</p> <p>P127 T1.16.6 is changed.</p> <p>P128 F1.16.5 is changed.</p> <p>– Special Mode 3 is delated.</p> <p>P139 L10 to L11 and L17 to L19 and L21 and L30 to L32 and L38 to L40 are changed.</p> <p>P140 F1.18.1 is changed.</p> <p>P141 F1.18.2 is changed.</p> <p>P143 F1.18.4 is changed.</p> <p>P147 F1.18.8 is changed.</p> <p>P149 T1.18.1 is changed.</p> <p>P151 T1.19.1 is changed.</p> <p>P152 T1.19.2 is changed.</p> <p>P153 T1.19.4 is changed.</p> <p>P154 T1.19.5 is changed.</p> <p>P155 T1.19.6 is changed.</p> <p>P157 L2 and T1.19.8 are changed.</p> <p>P158 L2 is changed.</p> <p>P159 L2 is changed.</p> <p>P162 L3 to L4 are delated. T1.20.2 is changed.</p> <p>P163 1.Memory Map is changed. F1.20.1 is changed.</p> <p>P164 Boot Mode is changed.</p> <p>P166 L5 and T1.21.1 are changed.</p> <p>P168 is changed.</p> <p>P169 F1.21.2 is changed.</p> <p>P170 F1.21.3 is changed.</p> <p>P171 F1.21.4 is changed.</p> <p>P174 T1.21.2 is changed. Read Array Command is changed.</p> <p>P175 Program Command is changed.</p> <p>P176 Block Erase is changed.</p> <p>P177 Sequencer Status and T1.21.3 are changed.</p> <p>P178 T1.21.4 is changed.</p> <p>P179 F1.21.7 is changed.</p> <p>P181 T1.22.1 is changed.</p> <p>P182 F1.22.1 is changed.</p> <p>P183 F1.22.2 is changed.</p> <p>P184 Parallel I/O Mode and User ROM and Boot ROM Areas are delated.</p>	Aug 18, 2003

Rev. No.	Revision Description	Rev. date
2.01	<p>P3 L1 to L2 are changed. F1.1.1 is changed.</p> <p>P7 T1.1.3 is changed.</p> <p>P22 L3 to L4 are changed.</p> <p>P23 (3) Setting PLC Mode is changed. T1.6.4 and F1.6.1 and F1.6.2 are changed.</p> <p>P141 F1.18.4 is changed.</p> <p>P143 F1.18.6 is changed.</p> <p>P144 F1.18.7 is changed.</p> <p>P178 Standard Serial I/O Mode is changed.</p>	Oct 27, 2003
3.00	<p>P1 Table of Contents is changed.</p> <p>P2 T1.1.1 is changed.</p> <p>P4 T1.1.2 is changed.</p> <p>P5 F1.1.2 is changed.</p> <p>P6 F1.1.3 is changed.</p> <p>P7 T1.1.3 is changed.</p> <p>P9 F1.2.1 is changed.</p> <p>P22 Text is changed. T1.6.1 is delated.</p> <p>P23 Text is changed. T1.6.4 and F1.6.2 are delated. Table name of T1.6.3 is added.</p> <p>P26 T1.7.1 is changed.</p> <p>P27 F1.7.1 is changed.</p> <p>P32 Text is changed. F1.7.6 is changed.</p> <p>P33 Text is changed.</p> <p>P36 Text is changed.</p> <p>P37 T1.7.4 is changed.</p> <p>P38 Text is changed.</p> <p>P44 T1.7.7, F1.7.9 and text are delated.</p> <p>P45 Text is changed.</p> <p>P46 F1.9.1 is changed.</p> <p>P48 Text is changed (NMI Interrupt is delated.)</p> <p>P49 T1.9.1 is changed.</p> <p>P55 T1.9.5 is changed.</p> <p>P58 F.1.9.8 is changed.</p> <p>P59 F.1.9.9 is changed.</p> <p>BetweenP60 to P61 Text is delated (NMI Interrupt is delated.)</p> <p>P63 Text is delated (NMI Interrupt is delated.)</p> <p>P79 F.1.12.4 is changed.</p> <p>P137 Text is changed.</p> <p>P140 F.1.18.3 is changed.</p> <p>P147 T.1.18.1 is changed.</p> <p>P148 F.1.18.10 is changed.</p> <p>P149 T.1.19.1 is changed.</p> <p>P150 T.1.19.2 is changed. Deletion of a voltage desplay of a header.</p> <p>P151 Deletion of a voltage desplay of a header.</p> <p>P152 Deletion of a voltage desplay of a header.</p>	Jul 22, 2004

Rev. No.	Revision Description	Rev. date
3.00	<p>P153 T.1.19.6 is changed. Deletion of a voltage display of a header.</p> <p>P154 T.1.19.7 is changed. Deletion of a voltage display of a header.</p> <p>P155 Deletion of a voltage display of a header.</p> <p>P156 Deletion of a voltage display of a header.</p> <p>P157 T.1.19.15 is changed.</p> <p>P163 T.1.20.3 is changed.</p> <p>P167 T.1.21.2 is changed.</p> <p>P168 T.1.21.3 is changed.</p> <p>P169 T.1.21.4 is changed.</p> <p>P170 Text is changed.</p> <p>P180 IT800AFE (Analog Front End) is added.</p> <p>P181 F.1.23.2 is changed.</p> <p>P183 Text is changed. T.1.23.2 is changed.</p> <p>P184 F.1.23.4 is changed.</p>	Jul 22, 2004

Renesas Technology Corp. Sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs!

1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage.
Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party.
2. Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.
The information described here may contain technical inaccuracies or typographical errors.
Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (<http://www.renesas.com>).
4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corp. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
5. Renesas Technology Corp. semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials.
7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.



RENESAS SALES OFFICES

<http://www.renesas.com>

Renesas Technology America, Inc.
450 Holger Way, San Jose, CA 95134-1368, U.S.A
Tel: <1> (408) 382-7500 Fax: <1> (408) 382-7501

Renesas Technology Europe Limited.
Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, United Kingdom
Tel: <44> (1628) 585 100, Fax: <44> (1628) 585 900

Renesas Technology Europe GmbH
Dornacher Str. 3, D-85622 Feldkirchen, Germany
Tel: <49> (89) 380 70 0, Fax: <49> (89) 929 30 11

Renesas Technology Hong Kong Ltd.
7/F., North Tower, World Finance Centre, Harbour City, Canton Road, Hong Kong
Tel: <852> 2265-6688, Fax: <852> 2375-6836

Renesas Technology Taiwan Co., Ltd.
FL 10, #99, Fu-Hsing N. Rd., Taipei, Taiwan
Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology (Shanghai) Co., Ltd.
26/F., Ruijin Building, No.205 Maoming Road (S), Shanghai 200020, China
Tel: <86> (21) 6472-1001, Fax: <86> (21) 6415-2952

Renesas Technology Singapore Pte. Ltd.
1, Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632
Tel: <65> 6213-0200, Fax: <65> 6278-8001