

LT1027 Precision 5V Reference

### FEATURES

- Very Low Drift: 2ppm/°C Max TC
- Pin Compatible with LT1021-5, REF-02, (PDIP Package)
- Output Sources 15mA, Sinks 10mA
- Excellent Transient Response Suitable for A-to-D Reference Inputs
- Noise Reduction Pin
- Excellent Long Term Stability
- Less Than 1ppm <sub>P-P</sub> Noise (0.1Hz to 10Hz)

### **APPLICATIONS**

- A-to-D and D-to-A Converters
- Digital Voltmeters
- Reference Standard
- Precision Current Source

### DESCRIPTION

The LT<sup>®</sup>1027 is a precision reference with extra-low drift, superior accuracy, excellent line and load regulation and low output impedance at high frequency. This device is intended for use in 12- to 16-bit A-to-D and D-to-A systems where demanding accuracy requirements must be met without the use of power hungry, heated substrate references. The fast settling output recovers quickly from load transients such as those presented by A-to-D converter reference inputs. The LT1027 brings together both outstanding accuracy and temperature coefficient specifications.

The LT1027 reference is based on LTC's proprietary advanced subsurface Zener bipolar process which eliminates noise and stability problems associated with surface breakdown devices.

C, LTC and LT are registered trademarks of Linear Technology Corporation.

### TYPICAL APPLICATION

Supplying V<sub>REF</sub> and V<sub>CC</sub> to the LTC<sup>®</sup>1290 12-bit ADC



#### **Output Voltage**



sn1027 1027fcs



### ABSOLUTE MAXIMUM RATINGS (Note 1)

Operating Temperature Range	
LT1027C	0°C to 70°C
LT1027M (OBSOLETE)	–55°C to 125°C
Storage Temperature Range	
All Devices	-65°C to 150°C
Lead Temperature (Soldering, 10 sec).	300°C

### PACKAGE/ORDER INFORMATION



\*Connected internally. Do not connect external circuitry to these pins. Consult LTC Marketing for parts specified with wider operating temperature ranges.

# **ELECTRICAL CHARACTERISTICS** The $\bullet$ denotes specifications which apply over the full operating temperature range otherwise specifications are at T<sub>A</sub> = 25°C. V<sub>IN</sub> = 10V, I<sub>LOAD</sub> = 0, unless otherwise specified.

SYMBOL	PARAMETER	CONDITIONS		MIN	ТҮР	MAX	UNITS
V <sub>OUT</sub>	Output Voltage (Note 2)	LT1027A LT1027B, C, D LT1027E		4.9990 4.9975 4.9950	5.000 5.000 5.000	5.0010 5.0025 5.0050	V
TCV <sub>OUT</sub>	Output Voltage Temperature Coefficient (Note 3)	LT1027A, B LT1027C LT1027D LT1027E	•		1 2 2 3	2 3 5 7.5	ppm/°C

sn1027 1027fcs



**ELECTRICAL CHARACTERISTICS** The  $\bullet$  denotes specifications which apply over the full operating temperature range otherwise specifications are at T<sub>A</sub> = 25°C. V<sub>IN</sub> = 10V, I<sub>LOAD</sub> = 0, unless otherwise specified.

SYMBOL	PARAMETER	CONDITIONS		MIN	ТҮР	MAX	UNITS
	Line Regulation (Note 4)	$8V \le V_{IN} \le 10V$	•		6	12 25	ppm/V ppm/V
		$10V \le V_{IN} \le 40V$	•		3	6 8	ppm/V ppm/V
	Load Regulation (Notes 4, 6)	Sourcing Current $0 \le I_{OUT} \le 15 \text{mA}$	•	-8 -10	-3	6 8	ppm/mA ppm/mA
		Sinking Current $0 \ge I_{OUT} \ge -10mA$	•		30	120	ppm/mA
	Supply Current		•		2.2	3.1 3.5	mA mA
	V <sub>TRIM</sub> Adjust Range		•	±30	±50		mV
e <sub>n</sub>	Output Noise (Note 5)	$0.1$ Hz $\leq f \leq 10$ Hz			3		μV <sub>P-P</sub>
		$10Hz \le f \le 1kHz$			2.0	6.0	μV <sub>RMS</sub>
	Temperature Hysteresis	H package; $\Delta T = 25^{\circ}C$			10		ppm
	Long Term Stability	H package			20		ppm/month

Note 1: Absolute Maximum Ratings are those values beyond which the life of the part may be impaired.

Note 2: Output voltage is measured immediately after turn-on. Changes due to chip warm-up are typically less than 0.005%.

Note 3: Temperature coefficient is determined by the "box" method in which the maximum  $\Delta V_{OUT}$  over the temperature range is divided by  $\Delta T$ .

Note 4: Line and load regulation measurements are done on a pulse basis. Output voltage changes due to die temperature change must be taken into account separately. Package thermal resistance is 150°C/W for TO-5 (H), 130°C/W for PDIP (N8), and 180°C/W for plastic SO (SO-8).

Note 5: RMS noise is measured with an 8-pole bandpass filter with a center frequency of 30Hz and a Q of 1.5. The filter output is then rectified and integrated for a fixed time period, resulting in an average, as opposed to RMS voltage. A correction factor is used to convert average to RMS. This value is then used to obtain RMS noise voltage in the 10Hz to 1000Hz frequency band. This test also screens for low frequency "popcorn" noise within the bandwidth of the filter. Consult factory for 100% 0.1Hz to 10Hz noise testing.

Note 6: Devices typically exhibit a slight negative DC output impedance of  $-0.015\Omega$ . This compensates for PC trace resistance, improving regulation at the load.

### TYPICAL PERFORMANCE CHARACTERISTICS



#### **Output Impedance vs Frequency**



#### **Output Voltage**





sn1027 1027fcs

### **TYPICAL PERFORMANCE CHARACTERISTICS**

V<sub>OUT</sub> 1V/DIV

### Start-Up and Turn-Off (No Load) V<sub>OUT</sub> 1V/DIV 10V 1027 G04 1µs/DIV

Start-Up and Turn-Off

10V

 $R_{L} = 1k, C_{L} = 4.7 \mu F$ 

500µs/DIV

1027 GO







1027 G09



1027 G07

**Line Regulation** 





0.1Hz to 10Hz Output Noise Filtering = 1 zero at 0.1Hz 2 poles at 10Hz





sn1027 1027fcs





**Output Settling Time (Sourcing)** 

I<sub>OUT</sub> (mA)







CHANGE IN OUTPUT VOLTAGE (µV)

### APPLICATIONS INFORMATION

#### Effect of Reference Drift on System Accuracy

A large portion of the temperature drift error budget in many systems is the system reference voltage. Figure 1 indicates the maximum temperature coefficient allowable if the reference is to contribute no more than 0.5LSB error to the overall system performance. The example shown is a 12-bit system designed to operate over a temperature range from 25°C to 65°C. Assuming the system calibration is performed at 25°C, the temperature span is 40°C. It can be seen from the graph that the temperature coefficient of the reference must be no worse than 3ppm/°C if it is to contribute less than 0.5LSB error. For this reason, the LT1027 has been optimized for low drift.



Figure 1. Maximum Allowable Reference Drift

### **Trimming Output Voltage**

The LT1027 has an adjustment pin for trimming output voltage. The impedance of the  $V_{ADJ}$  pin is about  $20 k\Omega$  with an open-circuit voltage of 2.5V. A  $\pm 30 mV$  guaranteed trim range is achievable by tying the  $V_{ADJ}$  pin to the wiper of a 10k potentiometer connecting between the output and ground. Trimming output voltage does not affect the TC of the device.

### **Noise Reduction**

The positive input of the internal scaling amplifier is brought out as the Noise Reduction (NR) pin. Connecting a  $1\mu$ F Mylar capacitor between this pin and ground will reduce the wideband noise of the LT1027 from  $2.0\mu$ V<sub>RMS</sub>

to approximately  $1.2\mu V_{RMS}$  in a 10Hz to 1kHz bandwidth. Transient response is not affected by this capacitor. Startup settling time will increase to several milliseconds due to the  $7k\Omega$  impedance looking into the NR pin. The capacitor *must* be a low leakage type. Electrolytics are *not* suitable for this application. Just 100nA leakage current will result in a 150ppm error in output voltage. This pin is the most sensitive pin on the device. For maximum protection a guard ring is recommended. The ring should be driven from a resistive divider from V<sub>OUT</sub> set to 4.4V (the open-circuit voltage on the NR pin).

### **Transient Response**

The LT1027 has been optimized for transient response. Settling time is under  $2\mu$ s when an AC-coupled 10mA load transient is applied to the output. The LT1027 achieves fast settling by using a class B NPN/PNP output stage. When sinking current, the device may oscillate with capacitive loads greater than 100pF. The LT1027 is stable with all capacitive loads when at no DC load or when sourcing current, although for best settling time either no output bypass capactor or a  $4.7\mu$ F tantalum unit is recommended. An  $0.1\mu$ F ceramic output capacitor will *maximize output ringing* and is *not* recommended.

### **Kelvin Connections**

Although the LT1027 does not have true force-sense capability, proper hook-up can improve line loss and ground loop problems significantly. Since the ground pin of the LT1027 carries only 2mA, it can be used as a low-side sense line, greatly reducing ground loop problems on the low side of the reference. The  $V_{OUT}$  pin should be close to the load or connected via a heavy trace as the resistance of this trace directly affects load regulation. It is important to remember that a 1.22mV drop due to trace resistance is equivalent to a 1LSB error in a 5V<sub>FS</sub>, 12-bit system.

The circuits in Figures 2 and 3 illustrate proper hook-up to minimize errors due to ground loops and line losses. Losses in the output lead can be further reduced by adding a PNP boost transistor if load current is 5mA or higher. R2 can be added to further reduce current in the output sense load.



### **APPLICATIONS INFORMATION**



Figure 2. Standard Hook-Up



\*OPTIONAL-REDUCES CURRENT IN OUTPUT SENSE LEAD



### **TYPICAL APPLICATIONS**



#### **Operating 5V Reference from 5V Supply**



sn1027 1027fcs



## 6

### **EQUIVALENT SCHEMATIC**



### PACKAGE DESCRIPTION





Information furnished by Linear Technology Corporation is believed to be accurate and reliable. However, no responsibility is assumed for its use. Linear Technology Corporation makes no representation that the interconnection of its circuits as described herein will not infringe on existing patent rights.

### PACKAGE DESCRIPTION



N8 Package

\*THESE DIMENSIONS DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS. MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED 0.010 INCH (0.254mm)





### **RELATED PARTS**

PART NUMBER	DESCRIPTION	COMMENTS
LT1019	Precision Series Bandgap Reference, 0.05%, 5ppm/°C Drift	2.5V, 4.5V, 5V, 10V Outputs; Industrial, Military Grades Available
LT1021	Precision Buried Zener Diode Reference, 0.5%, 5ppm/°C Drift	5V, 7V, 10V Outputs; 8-Pin PDIP, SO, TO-5 Packages; Military Grades Available
LT1236	Precision Series Reference, 0.05%, 5ppm/°C Drift	5V, 10V Outputs; 8-Pin PDIP, SO Packages; Industrial Grade Available
LT1460	Micropower Precision Series Bandgap Reference, 0.075%, 10ppm/°C Drift	2.5V, 5V, 10V Outputs; 8-Pin PDIP, SO, MSOP; TO-92 and SOT-23 Packages
LT1461	Low Dropout 3ppm/°C Drift, 0.04% Series Reference	2.5V, SO-8 Package
LT1798	Low Dropout, Micropower Reference	2.5V, 3V, 4.096V, 5V, Adjustable in SO-8

sn1027 1027fcs



LT/CPI 1101 1.5K REV C • PRINTED IN USA UINEAR TECHNOLOGY © LINEAR TECHNOLOGY CORPORATION 1992