

To all our customers

---

## **Regarding the change of names mentioned in the document, such as Hitachi Electric and Hitachi XX, to Renesas Technology Corp.**

---

The semiconductor operations of Mitsubishi Electric and Hitachi were transferred to Renesas Technology Corporation on April 1st 2003. These operations include microcomputer, logic, analog and discrete devices, and memory chips other than DRAMs (flash memory, SRAMs etc.) Accordingly, although Hitachi, Hitachi, Ltd., Hitachi Semiconductors, and other Hitachi brand names are mentioned in the document, these names have in fact all been changed to Renesas Technology Corp. Thank you for your understanding. Except for our corporate trademark, logo and corporate statement, no changes whatsoever have been made to the contents of the document, and these changes do not constitute any alteration to the contents of the document itself.

Renesas Technology Home Page: <http://www.renesas.com>

Renesas Technology Corp.  
Customer Support Dept.  
April 1, 2003

## Cautions

Keep safety first in your circuit designs!

1. Renesas Technology Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage.

Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corporation product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corporation or a third party.
2. Renesas Technology Corporation assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corporation or an authorized Renesas Technology Corporation product distributor for the latest product information before purchasing a product listed herein.  
The information described here may contain technical inaccuracies or typographical errors. Renesas Technology Corporation assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.  
Please also pay attention to information published by Renesas Technology Corporation by various means, including the Renesas Technology Corporation Semiconductor home page (<http://www.renesas.com>).
4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corporation assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
5. Renesas Technology Corporation semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corporation or an authorized Renesas Technology Corporation product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
6. The prior written approval of Renesas Technology Corporation is necessary to reprint or reproduce in whole or in part these materials.
7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.  
Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
8. Please contact Renesas Technology Corporation for further details on these materials or the products contained therein.

# BRC144EMP Series

NPN Built-in Resistor Transistor MPAK Series  
Inverter, Driver, Switching

**RENESAS**


ADE-208-1443B (Z)

Rev.2  
Sep. 2001

## Features

- Built-in Resistor Type
- Simplifies Circuit Design
- Reduces Board Space
- Complementary pair with BRA144EMP series

## Outline



Note: Marking is shown in below.

Device	Marking	R1 (k $\Omega$ )	R2 (k $\Omega$ )
BRC144EMP	BG	47	47
BRC124EMP	DG	22	22
BRC114EMP	FG	10	10
BRC143EMP	HG	4.7	4.7
BRC123EMP	KG	2.2	2.2

# BRC144EMP Series

## Absolute Maximum Ratings

(Ta = 25°C)


Item		Symbol	Ratings	Unit
Supply voltage		$V_{cc}$	50	V
Input voltage	BRC144EMP	$V_i$	-10 to +40	V
	BRC124EMP		-10 to +30	
	BRC114EMP		-10 to +20	
	BRC143EMP		-10 to +15	
	BRC123EMP		-10 to +12	
Output current		$I_o$	100	mA
Total power dissipation		$P_T^{*1}$	200	mW
Junction temperature		$T_j$	150	°C
Storage temperature		$T_{stg}$	-55 to +150	°C

\*Value on the glass epoxy board. (10 mm × 10 mm × 0.7 mm)






## Electrical Characteristics

(Ta = 25°C)






Item		Symbol	Min	Typ	Max	Unit	Test conditions
Input on voltage	BRC144EMP	$V_{I(on)}$	1.5	—	4.5	V	$V_{CC} = 0.3 \text{ V}$ , $I_O = 5 \text{ mA}$
	BRC124EMP		1.3	—	3.0		
	BRC114EMP		1.2	—	2.4		
	BRC143EMP		1.1	—	2.0		
	BRC123EMP		1.1	—	1.8		
Input off voltage	BRC144EMP	$V_{I(off)}$	1.0	—	1.5	V	$V_{CC} = 5 \text{ V}$ , $I_O = 100 \mu\text{A}$
	BRC124EMP		1.0	—	1.5		
	BRC114EMP		1.0	—	1.5		
	BRC143EMP		1.0	—	1.5		
	BRC123EMP		1.0	—	1.5		
Output saturation voltage		$V_{O(on)}$	—	—	0.3	V	$I_O = 10 \text{ mA}$ , $I_I = 0.5 \text{ mA}$
Output cutoff current		$I_{O(off)}$	—	—	0.5	$\mu\text{A}$	$V_{CC} = 50 \text{ V}$ , $I_I = 0$
DC current transfer ratio	BRC144EMP	$G_i$	70	—	—		$V_{CC} = 5 \text{ V}$ , $I_O = 5 \text{ mA}$
	BRC124EMP		56	—	—		
	BRC114EMP		30	—	—		
	BRC143EMP		20	—	—		$V_{CC} = 5 \text{ V}$ , $I_O = 10 \text{ mA}$
	BRC123EMP		20	—	—		$V_{CC} = 5 \text{ V}$ , $I_O = 20 \text{ mA}$
Input resistance	BRC144EMP	$R_1$	33	47	61	$\text{k}\Omega$	
	BRC124EMP		15	22	28		
	BRC114EMP		7	10	13		
	BRC143EMP		3.3	4.7	6.1		
	BRC123EMP		1.5	2.2	2.8		
Resistance ratio		$R_1/R_2$	0.8	1.0	1.2		



Main Characteristics (BRC144EMP)








## Main Characteristics (BRC124EMP)















Main Characteristics (BRC114EMP)



## Main Characteristics (BRC143EMP)



Main Characteristics (BRC123EMP)



## Taping Specification


There are two different size reels in MPAK packaging.

Packing to “Left” direction

Purchasing Identification Code


Standard Reel 3000 pcs/reel: Type No. + Mark **TL**

Large Reel 12000 pcs/reel: Type No. + Mark **UL**



Package Dimensions


Unit: mm



Hitachi Code	MPAK
JEDEC	—
EIAJ	Conforms
Mass (reference value)	0.011 g

Footprint

MPAK



## Disclaimer

1. Hitachi neither warrants nor grants licenses of any rights of Hitachi's or any third party's patent, copyright, trademark, or other intellectual property rights for information contained in this document. Hitachi bears no responsibility for problems that may arise with third party's rights, including intellectual property rights, in connection with use of the information contained in this document.
2. Products and product specifications may be subject to change without notice. Confirm that you have received the latest product standards or specifications before final design, purchase or use.
3. Hitachi makes every attempt to ensure that its products are of high quality and reliability. However, contact Hitachi's sales office before using the product in an application that demands especially high quality and reliability or where its failure or malfunction may directly threaten human life or cause risk of bodily injury, such as aerospace, aeronautics, nuclear power, combustion control, transportation, traffic, safety equipment or medical equipment for life support.
4. Design your application so that the product is used within the ranges guaranteed by Hitachi particularly for maximum rating, operating supply voltage range, heat radiation characteristics, installation conditions and other characteristics. Hitachi bears no responsibility for failure or damage when used beyond the guaranteed ranges. Even within the guaranteed ranges, consider normally foreseeable failure rates or failure modes in semiconductor devices and employ systemic measures such as fail-safes, so that the equipment incorporating Hitachi product does not cause bodily injury, fire or other consequential damage due to operation of the Hitachi product.
5. This product is not designed to be radiation resistant.
6. No one is permitted to reproduce or duplicate, in any form, the whole or part of this document without written approval from Hitachi.
7. Contact Hitachi's sales office for any questions regarding this document or Hitachi semiconductor products.

## Sales Offices

# HITACHI

### Hitachi, Ltd.

Semiconductor & Integrated Circuits  
Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan  
Tel: (03) 3270-2111 Fax: (03) 3270-5109

URL <http://www.hitachisemiconductor.com/>

### For further information write to:

Hitachi Semiconductor (America) Inc. 179 East Tasman Drive San Jose, CA 95134 Tel: <1> (408) 433-1990 Fax: <1> (408) 433-0223	Hitachi Europe Ltd. Electronic Components Group Whitebrook Park Lower Cookham Road Maidenhead Berkshire SL6 8YA, United Kingdom Tel: <44> (1628) 585000 Fax: <44> (1628) 585200	Hitachi Asia Ltd. Hitachi Tower 16 Collyer Quay #20-00 Singapore 049318 Tel : <65>-538-6533/538-8577 Fax : <65>-538-6933/538-3877 URL : <a href="http://semiconductor.hitachi.com.sg">http://semiconductor.hitachi.com.sg</a>	Hitachi Asia (Hong Kong) Ltd. Group III (Electronic Components) 7/F., North Tower World Finance Centre, Harbour City, Canton Road Tsim Sha Tsui, Kowloon Hong Kong Tel : <852>-(2)-735-9218 Fax : <852>-(2)-730-0281 URL : <a href="http://semiconductor.hitachi.com.hk">http://semiconductor.hitachi.com.hk</a>
	Hitachi Europe GmbH Electronic Components Group Dornacher Straße 3 D-85622 Feldkirchen Postfach 201, D-85619 Feldkirchen Germany Tel: <49> (89) 9 9180-0 Fax: <49> (89) 9 29 30 00	Hitachi Asia Ltd. (Taipei Branch Office) 4/F, No. 167, Tun Hwa North Road Hung-Kuo Building Taipei (105), Taiwan Tel : <886>-(2)-2718-3666 Fax : <886>-(2)-2718-8180 Telex : 23222 HAS-TP URL : <a href="http://www.hitachi.com.tw">http://www.hitachi.com.tw</a>	

Copyright © Hitachi, Ltd., 2001. All rights reserved. Printed in Japan.

Colophon 5.0