

FEATURES

High Speed 12-Bit Monolithic D/A Converters

AD565A/AD566A*

FUNCTIONAL BLOCK DIAGRAMS

Single Chip Construction Very High Speed Settling to 1/2 LSB AD565A: 250 ns max AD566A: 350 ns max Full-Scale Switching Time: 30 ns Guaranteed for Operation with ±12 V (565A) Supplies, with -12 V Supply (AD566A) **Linearity Guaranteed Overtemperature** 1/2 LSB max (K, T Grades) **Monotonicity Guaranteed Overtemperature** Low Power: AD566A = 180 mW max; AD565A = 225 mW max Use with On-Board High Stability Reference (AD565A) or with External Reference (AD566A) Low Cost MIL-STD-883-Compliant Versions Available

PRODUCT DESCRIPTION

The AD565A and AD566A are fast 12-bit digital-to-analog converters that incorporate the latest advances in analog circuit design to achieve high speeds at low cost.

The AD565A and AD566A use 12 precision, high speed bipolar current-steering switches, a control amplifier, and a laser-trimmed thin-film resistor network to produce a very fast, high accuracy analog output current. The AD565A also includes a buried Zener reference that features low noise, long-term stability, and temperature drift characteristics comparable to the best discrete reference diodes.

The combination of performance and flexibility in the AD565A and AD566A has resulted from major innovations in circuit design, an important new high speed bipolar process, and continuing advances in laser-wafer-trimming techniques (LWT). The AD565A and AD566A have a 10%–90% full-scale transition time less than 35 ns and settle to within $\pm 1/2$ LSB in 250 ns max (350 ns for AD566A). Both are laser-trimmed at the wafer level to $\pm 1/8$ LSB typical linearity and are specified to $\pm 1/4$ LSB max error (K and T grades) at $\pm 25^{\circ}$ C. High speed and accuracy make the AD565A and AD566A the ideal choice for high speed display drivers as well as for fast analog-to-digital converters.

The laser trimming process that provides the excellent linearity is also used to trim both the absolute value and the temperature coefficient of the reference of the AD565A, resulting in a typical full-scale gain TC of 10 ppm/°C. When tighter TC performance is required or when a system reference is available, the AD566A may be used with an external reference.

*Covered by Patent Numbers: 3,803,590; RE 28,633; 4,213,806; 4,136,349; 4,020,486; 3,747,088.

REV. E

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices.



AD565A and AD566A are available in four performance grades. The J and K grades are specified for use over the 0°C to +70°C temperature range while the S and T grades are specified for the -55°C to +125°C range. The D grades are all packaged in a 24-lead, hermetically sealed, ceramic, dual-in-line package. The JR grade is packaged in a 28-lead plastic SOIC.

PRODUCT HIGHLIGHTS

- 1. The wide output compliance range of the AD565A and AD566A are ideally suited for fast, low noise, accurate voltage output configurations without an output amplifier.
- 2. The devices incorporate a newly developed, fully differential, nonsaturating precision current switching cell structure that combines the dc accuracy and stability first developed in the AD562/AD563 with very fast switching times and an optimally damped settling characteristic.
- 3. The devices also contain SiCr thin-film application resistors that can be used with an external op amp to provide a precision voltage output or as input resistors for a successiveapproximation A/D converter. The resistors are matched to the internal ladder network to guarantee a low gain temperature coefficient and are laser-trimmed for minimum full-scale and bipolar offset errors.
- 4. The AD565A and AD566A are available in versions compliant with MIL-STD-883. Refer to the Analog Devices *Military Products Databook* or current /883B data sheet for detailed specifications.

One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106, U.S.A. Tel: 781/329-4700 www.analog.com Fax: 781/326-8703 © Analog Devices, Inc., 2002

AD565A—SPECIFICATIONS ($T_A = 25^{\circ}C$, $V_{CC} = 15 V$, $V_{EE} = 15 V$, unless otherwise noted.)

		AD565AJ			AD565AK		
Parameter	Min	Тур	Max	Min	Тур	Max	Unit
DATA INPUTS ¹ (Pins 13 to 24)							
TTL or 5 V CMOS							
Input Voltage							
Bit ON Logic "1"	2.0		5.5	2.0		5.5	V
Bit OFF Logic "0" Logic Current (Each Bit)			0.8			0.8	v
Bit ON Logic "1"		120	300		120	300	цА
Bit OFF Logic "0"		35	100		35	100	μΑ
RESOLUTION			12			12	Bits
Current							
Unipolar (All Bits On)	-1.6	-2.0	-2.4	-1.6	-2.0	-2.4	mA
Bipolar (All Bits On or Off)	±0.8	± 1.0	±1.2	±0.8	± 1.0	±1.2	mA
Resistance (Exclusive of Span Resistors)	6	8	10	6	8	10	kΩ
Offset		0.01	0.05		0.01	0.05	0/ of E.C. Downer
Unipolar Bipolar (Figure 3, P2 = 50 O Fixed)		0.01	0.05		0.01	0.05	% of F.S. Range
Capacitance		25	0.15		25	0.1	pF
Compliance Voltage							F -
T_{MIN} to T_{MAX}	-1.5		+10	-1.5		+10	V
ACCURACY (Error Relative to							
Full Scale) 25°C		$\pm 1/4$	$\pm 1/2$		$\pm 1/8$	±0.35	LSB
T T		(0.006)	(0.012)		(0.003)	(0.0084)	% of F.S. Range
T _{MIN} to T _{MAX}		$\pm 1/2$	$\pm 3/4$		$\pm 1/4$	$\pm 1/2$	LSB
		(0.012)	(0.018)		(0.000)	(0.012)	70 01 F.S. Kalige
25°C		+1/2	+3/4		+1/4	+1/2	ISB
TMIN TO TMAX	ΜΟΝΟΤΟ	NICITY GUA	RANTEED	MONOTON		RANTEED	LSD
TEMPERATURE COEFFICIENTS							
With Internal Reference							
Unipolar Zero		1	2		1	2	ppm/°C
Bipolar Zero		5	10		5	10	ppm/°C
Gain (Full Scale)		15	50		10	20	ppm/°C
Differential Nonlinearity		2			2		ppm/°C
SETTLING TIME TO 1/2 LSB All Bits ON-to-OFF or OFF-to-ON		250	400		250	400	ns
FULL-SCALE TRANSITION							
10% to 90% Delay plus Rise Time		15	30		15	30	ns
90% to 10% Delay plus Fall Time		30	50		30	50	ns
TEMPERATURE RANGE							
Operating	0		+70	0		+70	°C
Storage	-65		+150	-65		+150	°C
POWER REQUIREMENTS		_	_		-	_	
V_{CC} , +11.4 to +16.5 V dc		3	5		3	5	mA
$v_{\rm EE}$, -11.4 to -10.5 v dc		-12	-18		-12	-18	IIIA
POWER SUPPLY GAIN SENSITIVITY ² $V = \pm 11.4$ to ± 16.5 V dc		3	10		3	10	norm of $\mathbf{F} \mathbf{S} / \frac{0}{4}$
$V_{CC} = -11.4$ to -16.5 V dc		15	25		15	25	ppm of F.S./%
PROGRAMMABLE OUTPUT RANGES							FF
(See Figures 2, 3, 4)		0 to +5			0 to +5		V
		-2.5 to +2.5			-2.5 to +2.5	5	V
		0 to +10			0 to +10		V
		-5 to +5			-5 to +5		V
		-10 to $+10$			-10 to $+10$		V
EXTERNAL ADJUSTMENTS							
Resistor for R2 (Figure 2)		+0.1	+0.25		+0.1	+0.25	% of F.S. Range
Bipolar Zero Error with Fixed		20.1	_0.25		20.1	-0.25	70 01 1 .0. Tunge
50 Ω Resistor for R1 (Figure 3)		± 0.05	±0.15		± 0.05	± 0.1	% of F.S. Range
Gain Adjustment Range (Figure 2)	±0.25			±0.25			% of F.S. Range
Bipolar Zero Adjustment Range	±0.15			±0.15			% of F.S. Range
REFERENCE INPUT	1.5	20	25	1.5	20	25	10
Input Impedance	15	20	25	15	20	25	K55
REFERENCE OUTPUT	0.00	10.00	10.10	0.00	10.00	10.10	V
Vullage Current (Available for External Loads) ³	1.5	2.5	10.10	9.90	2.5	10.10	w mA
POWER DISSIPATION		2.5	345		225	345	mW
		223	747		443	747	111 W

NOTES ¹The digital inputs are guaranteed but not tested over the operating temperature range. ²The power supply gain sensitivity is tested in reference to a V_{CC} , V_{EE} of ±15 V dc. ³For operation at elevated temperatures, the reference cannot supply current for external loads. It, therefore, should be buffered if additional loads are to be supplied. Specifications subject to change without notice.

		AD565AS			AD565AT		
Parameter	Min	Тур	Max	Min	Тур	Max	Unit
DATA INPUTS ¹ (Pins 13 to 24)							
TTL or 5 V CMOS							
Bit ON Logic "1"	2.0		5.5	2.0		5.5	V
Bit OFF Logic "0"			0.8	2.00		0.8	v
Logic Current (Each Bit)							
Bit ON Logic "1" Bit OFF Logic "0"		120	300		120	300	μΑ
		55	100		55	100	 D:t-
RESOLUTION			12			12	Bits
OUTPUT							
Unipolar (All Bits On)	-1.6	-2.0	-2.4	-1.6	-2.0	-2.4	mA
Bipolar (All Bits On or Off)	±0.8	± 1.0	±1.2	±0.8	± 1.0	±1.2	mA
Resistance (Exclusive of Span Resistors)	6	8	10	6	8	10	kΩ
Utiset		0.01	0.05		0.01	0.05	% of FS Pange
Bipolar (Figure 3, R2 = 50 Ω Fixed)		0.05	0.05		0.01	0.03	% of F.S. Range
Capacitance		25			25		pF
Compliance Voltage							
T _{MIN} to T _{MAX}	-1.5		+10	-1.5		+10	V
ACCURACY (Error Relative to					110		I OD
Full Scale) 25°C		$\pm 1/4$	$\pm 1/2$		$\pm 1/8$	± 0.35	LSB % of E.S. Panga
TMIN to TMAN		(0.000) +1/2	$\pm 3/4$		(0.003) +1/4	$\pm 1/2$	LSB
		(0.012)	(0.018)		(0.006)	(0.012)	% of F.S. Range
DIFFERENTIAL NONLINEARITY							
25°C		$\pm 1/2$	±3/4		$\pm 1/4$	±1/2	LSB
T _{MIN} to T _{MAX}	MONO	FONICITY G	UARANTEED	MONOT	CONICITY GU	ARANTEED	
TEMPERATURE COEFFICIENTS							
Unipolar Zero		1	2		1	2	nnm/°C
Bipolar Zero		5	10		5	10	ppm/°C
Gain (Full Scale)		15	30		10	15	ppm/°C
Differential Nonlinearity		2			2		ppm/°C
SETTLING TIME TO 1/2 LSB			400			100	
All Bits ON-to-OFF or OFF-to-ON		250	400		250	400	ns
FULL-SCALE TRANSITION		15	20		15	20	20
90% to 10% Delay plus Fall Time		30	50		30	50	115
TEMPERATURE RANGE		50			50	30	
Operating	-55		+125	-55		+125	°C
Storage	-65		+150	-65		+150	°C
POWER REQUIREMENTS							
V_{CC} , +11.4 to +16.5 V dc		3	5		3	5	mA
$V_{\rm EE}$, -11.4 to -16.5 V dc		-12	-18		-12	-18	mA
POWER SUPPLY GAIN SENSITIVITY ²		2	10		2	10	mass of $\mathbf{E} \mathbf{S} / 0 /$
$V_{CC} = -11.4$ to -16.5 V dc		15	25		15	25	ppm of $F.S./\%$
PROGRAMMABLE OUTPUT RANGES							
(See Figures 2, 3, 4)		0 to +5			0 to +5		V
		-2.5 to +2	.5		-2.5 to +2.5	5	V
		0 to +10			0 to $+10$		V
		-5 to $+5$			-5 to $+5$		V
EXTERNAL ADDISTMENTS		10 10 110	,		10 10 110		¥
Gain Error with Fixed 50 Ω							
Resistor for R2 (Figure 2)		± 0.1	±0.25		± 0.1	±0.25	% of F.S. Range
Bipolar Zero Error with Fixed		10.05			10.25		
50Ω Resistor for R1 (Figure 3)	+0.25	± 0.05	±0.15	+0.25	±0.05	±0.1	% of F.S. Range
Bipolar Zero Adjustment Range	± 0.25 ± 0.15			± 0.25 ± 0.15			% of F.S. Range
REFERENCE INPUT							,
Input Impedance	15	20	25	15	20	25	kΩ
REFERENCE OUTPUT							
Voltage	9.90	10.00	10.10	9.90	10.00	10.10	V
Current (Available for External Loads) ³	1.5	2.5		1.5	2.5		mA
POWER DISSIPATION		225	345		225	345	mW

Specifications shown in **boldface** are tested on all production units at final electrical test. Results from those tests are used to calculate outgoing quality levels. All min and max specifications are guaranteed, although only those shown in **boldface** are tested on all production units.

Specification subject to change without notice.

AD566A—**SPECIFICATIONS**($T_A = 25^{\circ}C$, $V_{EE} = -15$ V, unless otherwise noted)

		AD566AJ			AD566AK		
Parameter	Min	Тур	Max	Min	Тур	Max	Unit
DATA INPUTS ¹ (Pins 13 to 24)							
Input Voltage							
Bit ON Logic "1"	2.0		5.5	2.0		5.5	V
Bit OFF Logic "0" Logic Current (Each Bit)	0		0.8	0		0.8	V
Bit ON Logic "1"		120	300		120	300	μΑ
Bit OFF Logic "0"		35	100		35	100	μΑ
RESOLUTION			12			12	Bits
Current							
Unipolar (All Bits On)	-1.6	-2.0	-2.4	-1.6	-2.0	-2.4	mA
Bipolar (All Bits On or Off) Resistance (Exclusive of Span Resistore)	±0.8	±1.0	± 1.2	± 0.8	±1.0	±1.2	mA kO
Offset	0	0	10	0	0	10	K52
Unipolar (Adjustable to Zero per Figure 3) Bipolar (Figure 4, R1 and R2 = 50 Ω Fixed) Capacitance		0.01 0.05 25	0.05 0.15		0.01 0.05 25	0.05 0.1	% of F.S. Range % of F.S. Range pF
Compliance Voltage							1
T _{MIN} to T _{MAX}	-1.5		+10	-1.5		+10	V
Full Scale) 25°C		$\pm 1/4$	±1/2		$\pm 1/8$	±0.35	LSB
		(0.006)	(0.012)		(0.003)	(0.0084)	% of F.S. Range
T_{MIN} to T_{MAX}		$\pm 1/2$	$\pm 3/4$		$\pm 1/4$	$\pm 1/2$	LSB % of F.S. Range
DIFFERENTIAL NONLINEARITY		(0.012)	(0.013)		(0.000)	(0:012)	70 01 1 .0. Kalige
25°C	wawa	±1/2	±3/4	MONOTO	$\pm 1/4$	±1/2	LSB
T _{MIN} to T _{MAX}	MONO	TONICITY GU	JARANTEED	MONOTO	DNICITY GUA	RANTEED	
TEMPERATURE COEFFICIENTS Unipolar Zero		1	2		1	2	ppm/°C
Bipolar Zero		5	10		5	10	ppm/°C
Gain (Full Scale)		7	10		3	5	ppm/°C
ETTI NC TIME TO 1/2 LSP		2			2		ppm/°C
All Bits ON-to-OFF or OFF-to-ON		250	350		250	350	ns
FULL-SCALE TRANSITION							
10% to 90% Delay plus Rise Time		15	30		15	30	ns
90% to 10% Delay plus Fail Time		30	50		30	50	IIS
V_{EE} , -11.4 to -16.5 V dc		-12	-18		-12	-18	mA
POWER SUPPLY GAIN SENSITIVITY ²							
$V_{EE} = -11.4$ to -16.5 V dc		15	25		15	25	ppm of F.S./%
PROGRAMMABLE OUTPUT RANGES		0 ± 5			0 ± 5		V
(see Figures 5, 4, 5)		-2.5 to $+2$.5		-2.5 to $+2$.5	vV
		0 to +10			0 to +10		V
		-5 to $+5-10$ to $+10$)		-5 to $+5-10$ to $+10$	n	V V
EXTERNAL ADJUSTMENTS		10 10 11	<u>, </u>		10 10 11	<u> </u>	•
Gain Error with Fixed 50 Ω							
Resistor for R2 (Figure 3) Bipolar Zero Error with Fixed		± 0.1	±0.25		± 0.1	±0.25	% of F.S. Range
50 Ω Resistor for R1 (Figure 4)		± 0.05	±0.15		± 0.05	±0.1	% of F.S. Range
Gain Adjustment Range (Figure 3)	±0.25			±0.25			% of F.S. Range
Bipolar Zero Adjustment Kange	±0.15			±0.15			% of F.S. Range
Input Impedance	15	20	25	15	20	25	kΩ
POWER DISSIPATION		180	300		180	300	mW
MULTIPLYING MODE PERFORMANCE (All Models)							
Quadrants Reference Voltage		Two (2): H	Bipolar Operatio	n at Digital Ir	nput Only		
Accuracy		$10 \text{ Bits } (\pm 0)$	0.05% of Reduc	ed F.S.) for 1	V dc Reference	Voltage	
Reference Feedthrough (Unipolar Mode,				1		_	
All Bits OFF, and I V to 10 V [p-p], Sine Wave Erequency for 1/2 I SB [p-p] Feedthrough)		40					kHz typ
Output Slew Rate 10%–90%		5					mA/μs
90%-10%		1					mA/μs
Step Change in Reference Voltage)		1.5 µs to 0	.01% F.S.				
CONTROL AMPLIFIER							
Full Power Bandwidth		300					kHz
Small-Signal Closed-Loop Bandwidth		1.8					MHz

NOTES ¹The digital input levels are guaranteed but not tested over the temperature range. ²The power supply gain sensitivity is tested in reference to a V_{EE} of -1.5 V dc.

Specifications subject to change without notice.

		AD566AS			AD566AT		
Parameter	Min	Тур	Max	Min	Тур	Max	Unit
DATA INPUTS ¹ (Pins 13 to 24)							
Input Voltage							
Bit ON Logic "1"	2.0		5.5	2.0		5.5	V
Logic Current (Each Bit)	0		0.8	0		0.8	v
Bit ON Logic "1"		120	300		+120	300	μΑ
Bit OFF Logic "0"		35	100		+35	100	μΑ
RESOLUTION			12			12	Bits
Current							
Unipolar (All Bits On)	-1.6	-2.0	-2.4	-1.6	-2.0	-2.4	mA
Bipolar (All Bits On or Off) Resistance (Exclusive of Span Resistors)	±0.8	± 1.0	± 1.2	±0.8	± 1.0	±1.2	mA kO
Offset		0	10	0	0	10	K22
Unipolar (Adjustable to Zero per Figure 3)		0.01	0.05		0.01	0.05	% of F.S. Range
Supplar (Figure 4, KI and $KZ = 50 \Omega$ Fixed) Capacitance		25	0.15		25	0.1	pF
Compliance Voltage							
T _{MIN} to T _{MAX}	-1.5		+10	-1.5		+10	V
ACCURACY (Error Relative to Full Scale) 25°C		+1/4	+1/2		+1/8	+0.35	LSB
		(0.006)	(0.012)		(0.003)	(0.0084)	% of F.S. Range
T _{MIN} to T _{MAX}		$\pm 1/2$	$\pm 3/4$		$\pm 1/4$	$\pm 1/2$	LSB
		(0.012)	(0.018)		(0.006)	(0.012)	% of F.S. Kange
25°C		$\pm 1/2$	±3/4		$\pm 1/4$	$\pm 1/2$	LSB
T _{MIN} to T _{MAX}	MONO1	CONICITY GU	JARANTEED	MONOT	ONICITY GUA	ARANTEED	
TEMPERATURE COEFFICIENTS							
Unipolar Zero Binolar Zero		1	2		1	2	ppm/°C
Gain (Full Scale)		7	10		3	5	ppm/°C
Differential Nonlinearity		2			2		ppm/°C
SETTLING TIME TO 1/2 LSB		250	250		250	250	
All Bits ON-to-OFF of OFF-to-ON		250	300		250	300	ns
10% to 90% Delay plus Rise Time		15	30		15	30	ns
90% to 10% Delay plus Fall Time		30	50		30	50	ns
POWER REQUIREMENTS							
$V_{\rm EE}$, -11.4 to -16.5 V dc		-12	-18		-12	-18	mA
POWER SUPPLY GAIN SENSITIVITY ² $V_{TT} = -11.4$ to -16.5 V dc		15	25		15	25	nnm of F S /%
PROGRAMMARI E OLITPUT RANGES		15	23		15	23	ppin or 1.3.770
(see Figures 3, 4, 5)		0 to +5			0 to +5		v
		-2.5 to $+2$	2.5		-2.5 to $+2$.5	V
		0 to +10 -5 to +5			0 to +10 -5 to +5		
		-10 to +1	0		-10 to $+10$)	V V
EXTERNAL ADJUSTMENTS							
Gain Error with Fixed 50 Ω		+0.1	+0.25		+0.1	+0.25	% of ES Range
Bipolar Zero Error with Fixed		±0.1	±0.25		±0.1	±0.25	70 01 17.5. Range
50 Ω Resistor for R1 (Figure 4)	10.05	± 0.05	±0.15	10.05	± 0.05	±0.1	% of F.S. Range
Gain Adjustment Range (Figure 3) Bipolar Zero Adjustment Range	± 0.25 ± 0.15			± 0.25 ± 0.15			% of F.S. Range
REFERENCE INPUT	_0115						, o of Fior Funge
Input Impedance	15	20	25	15	20	25	kΩ
POWER DISSIPATION		180	300		180	300	mW
MULTIPLYING MODE PERFORMANCE (All Models)							
Quadrants Reference Voltage		Two (2):	Bipolar Operatio	n at Digital I	Input Only		
Accuracy		$10 \text{ Bits } (\pm$	0.05% of Reduc	ed F.S.) for	1 V dc Referenc	e Voltage	
Reference Feedthrough (Unipolar Mode,				1		-	
All Bits OFF, and I V to 10 V [p-p], Sine Wave Frequency for 1/2 I SB [p-p] Feedthrough)		40					kHz typ
Output Slew Rate 10%–90%		5					mA/μs
90%-10%		1					mA/μs
Step Change in Reference Voltage)		1.5 µs to (0.01% F.S.				
CONTROL AMPLIFIER		- p					
Full Power Bandwidth		300					kHz
Small-Signal Closed-Loop Bandwidth		1.8					MHz

Specifications shown in **boldface** are tested on all production units at final electrical test. Results from those tests are used to calculate outgoing quality levels. All min and max specifications are guaranteed, although only those shown in **boldface** are tested on all production units.

Specification subject to change without notice.

ABSOLUTE MAXIMUM RATINGS

V_{CC} to Power Ground
V_{EE} to Power Ground (AD565A) 0 V to -18 V
Voltage on DAC Output (Pin 9)3 V to +12 V
Digital Inputs (Pins 13 to 24) to
Power Ground
REF IN to Reference Ground $\dots \dots \dots \pm 12$ V
Bipolar Offset to Reference Ground ±12 V
10 V Span R to Reference Ground $\dots \pm 12$ V
20 V Span R to Reference Ground $\dots \pm 24$ V
REF OUT (AD565A) Indefinite Short to Power Ground
Momentary Short to V _{CC}
Power Dissipation 1000 mW

GROUNDING RULES

The AD565A and AD566A use separate reference and power grounds to allow optimum connections for low noise and high speed performance. These grounds should be tied together at one point, usually the device power ground. The separate ground returns minimize current flow in low level signal paths. In this way, logic return currents are not summed into the same return path with analog signals.

AD565A ORDERING GUIDE

Model ¹	Max Gain T.C. (ppm of F.S./°C)	Temperature Range	Linearity Error Max @ +25°C	Package Options ²
AD565AJD	50	0°C to +70°C	±1/2 LSB	Ceramic (D-24)
AD565AJR	50	0° C to $+70^{\circ}$ C	$\pm 1/2$ LSB	SOIC (RW-28)
AD565AKD	20	0° C to $+70^{\circ}$ C	$\pm 1/4$ LSB	Ceramic (D-24)
AD565ASD	30	–55°C to +125°C	±1/2 LSB	Ceramic (D-24)
AD565ATD	15	–55°C to +125°C	$\pm 1/4$ LSB	Ceramic (D-24)

NOTES

¹For details on grade and package offerings screened in accordance with MIL-STD-883, refer to the Analog Devices *Military Products Databook* or current/883B data sheet. ²D = Ceramic DIP, R = SOIC.

AD566A ORDERING GUIDE

Model ¹	Max Gain T.C. (ppm of F.S./°C)	Linearity Temperature Range	Error Max @ +25°C	Package Option ²	
AD566AJD	10	0°C to +70°C	±1/2 LSB	Ceramic (D-24	
AD566AKD	3	0°C to +70°C	$\pm 1/4$ LSB	Ceramic (D-24)	
AD566ASD	10	–55°C to +125°C	$\pm 1/2$ LSB	Ceramic (D-24)	
AD566ATD	3	–55°C to +125°C	$\pm 1/4$ LSB	Ceramic (D-24)	

NOTES

¹For details on grade and package offerings screened in accordance with MIL-STD-883, refer to the Analog Devices *Military Products Databook* or current/883B data sheet. ²D = Ceramic DIP.

CAUTION _

ESD (electrostatic discharge) sensitive device. Electrostatic charges as high as 4000 V readily accumulate on the human body and test equipment and can discharge without detection. Although the AD565A/AD566A features proprietary ESD protection circuitry, permanent damage may occur on devices subjected to high energy electrostatic discharges. Therefore, proper ESD precautions are recommended to avoid performance degradation or loss of functionality.



PIN CONFIGURATIONS







CONNECTING THE AD565A FOR BUFFERED VOLTAGE OUTPUT

The standard current-to-voltage conversion connections using an operational amplifier are shown in Figures 1, 2, and 3 with the preferred trimming techniques. If a low offset operational amplifier (OP77, AD741L, OP07) is used, excellent performance can be obtained in many situations without trimming (an op amp with less than 0.5 mV max offset voltage should be used to keep offset errors below 1/2 LSB). If a 50 Ω fixed resistor is substituted for the 100 Ω trimmer, unipolar zero is typically within ±1/2 LSB (plus op amp offset) and full-scale accuracy is within 0.1% (0.25% max). Substituting a 50 Ω resistor for the 100 Ω bipolar offset trimmer gives a bipolar zero error typically within ±2 LSB (0.05%).

The AD509 is recommended for buffered voltage-output applications that require a settling time to $\pm 1/2$ LSB of 1 μ s. The feedback capacitor is shown with the optimum value for each application; this capacitor is required to compensate for the 25 pF DAC output capacitance.

FIGURE 1. UNIPOLAR CONFIGURATION

This configuration provides a unipolar 0 V to 10 V output range. In this mode, the bipolar terminal, Pin 8, should be grounded if not used for trimming.



Figure 1. 0 V to 10 V Unipolar Voltage Output

STEP I . . . ZERO ADJUST

Turn all bits OFF and adjust zero trimmer R1 until the output reads 0.000 V (1 LSB = 2.44 mV). In most cases, this trim is not needed, but Pin 8 should then be connected to Pin 12.

STEP II . . . GAIN ADJUST

Turn all bits ON and adjust 100Ω gain trimmer R2 until the output is 9.9976 V. (Full scale is adjusted to 1 LSB less than nominal full scale of 10.000 V.) If a 10.2375 V full scale is desired (exactly 2.5 mV/bit), insert a 120Ω resistor in series with the gain resistor at Pin 10 to the op amp output.

FIGURE 2. BIPOLAR CONFIGURATION

This configuration provides a bipolar output voltage from -5.000 V to +4.9976 V, with positive full scale occurring with all bits ON (all 1s).



Figure 2. ±5 V Bipolar Voltage Output

STEP I . . . OFFSET ADJUST

Turn OFF all bits. Adjust 100Ω trimmer R1 to give -5.000 V output.

STEP II . . . GAIN ADJUST

Turn ON all bits. Adjust 100 Ω gain trimmer R2 to give a reading of +4.9976 V.

Please note that it is not necessary to trim the op amp to obtain full accuracy at room temperature. In most bipolar situations, an op amp trim is unnecessary unless the untrimmed offset drift of the op amp is excessive.

FIGURE 3. OTHER VOLTAGE RANGES

The AD565A can also be easily configured for a unipolar 0 V to +5 V range or ± 2.5 V and ± 10 V bipolar ranges by using the additional 5 k Ω application resistor provided at the 20 V span R terminal, Pin 11. For a 5 V span (0 V to +5 V, or ± 2.5 V), the two 5 k Ω resistors are used in parallel by shorting Pin 11 to Pin 9 and connecting Pin 10 to the op amp output and the bipolar offset either to ground for unipolar or to REF OUT for the bipolar offset either to ground for unipolar or to REF OUT for the bipolar range. For the ± 10 V range (20 V span) use the 5 k Ω resistors in series by connecting only Pin 11 to the op amp output and the bipolar offset connected as shown. The ± 10 V option is shown in Figure 3.



Figure 3. ±10 V Voltage Output

CONNECTING THE AD566A FOR BUFFERED VOLTAGE OUTPUT

The standard current-to-voltage conversion connections using an operational amplifier are shown in Figures 4, 5, and 6 with the preferred trimming techniques. If a low offset operational amplifier (OP77, AD741L, OP07) is used, excellent performance can be obtained in many situations without trimming (an op amp with less than 0.5 mV max offset voltage should be used to keep offset errors below 1/2 LSB). If a 50 Ω fixed resistor is substituted for the 100 Ω trimmer, unipolar zero typically is within ±1/2 LSB (plus op amp offset), and full-scale accuracy is within 0.1% (0.25% max). Substituting a 50 Ω resistor for the 100 Ω bipolar offset trimmer gives a bipolar zero error typically within ±2 LSB (0.05%).

The AD509 is recommended for buffered voltage-output applications that require a settling time to $\pm 1/2$ LSB of 1 µs. The feedback capacitor is shown with the optimum value for each application; this capacitor is required to compensate for the 25 pF DAC output capacitance.

FIGURE 4. UNIPOLAR CONFIGURATION

This configuration provides a unipolar 0 V to 10 V output range. In this mode, the bipolar terminal, Pin 7, should be grounded if not used for trimming.



Figure 4. 0 V to 10 V Unipolar Voltage Output

STEP I . . . ZERO ADJUST

Turn all bits OFF and adjust zero trimmer, R1, until the output reads 0.000 V (1 LSB = 2.44 mV). In most cases, this trim is not needed, but Pin 7 should then be connected to Pin 12.

STEP II . . . GAIN ADJUST

Turn all bits ON and adjust 100Ω gain trimmer, R2, until the output is 9.9976 V. (Full scale is adjusted to 1 LSB less than nominal full scale of 10.000 V.) If a 10.2375 V full scale is desired (exactly 2.5 mV/bit), insert a 120 Ω resistor in series with the gain resistor at Pin 10 to the op amp output.

FIGURE 5. BIPOLAR CONFIGURATION

This configuration provides a bipolar output voltage from -5.000 V to +4.9976 V, with positive full scale occurring with all bits ON (all 1s).



Figure 5. ±5 V Bipolar Voltage Output

STEP I . . . OFFSET ADJUST

Turn OFF all bits. Adjust $100 \,\Omega$ trimmer R1 to give -5.000 output V.

STEP II . . . GAIN ADJUST

Turn ON all bits. Adjust 100Ω gain trimmer R2 to give a reading of +4.9976 V.

Please note that it is not necessary to trim the op amp to obtain full accuracy at room temperature. In most bipolar situations, an op amp trim is unnecessary unless the untrimmed offset drift of the op amp is excessive.

FIGURE 6. OTHER VOLTAGE RANGES

The AD566A can also be easily configured for a unipolar 0 V to +5 V range or ± 2.5 V and ± 10 V bipolar ranges by using the additional 5 k Ω application resistor provided at the 20 V span R terminal, Pin 11. For a 5 V span (0 V to +5 V or ± 2.5 V), the two 5 k Ω resistors are used in parallel by shorting Pin 11 to Pin 9 and connecting Pin 10 to the op amp output and the bipolar offset resistor either to ground for unipolar or to V_{REF} for the bipolar range. For the ± 10 V range (20 V span), use the 5 k Ω resistors in series by connecting only Pin 11 to the op amp output and the bipolar offset resistor offset connected as shown. The ± 10 V option is shown in Figure 6.



* THE PARALLEL COMBINATION OF THE BIPOLAR OFFSET RESISTOR AND R3 ESTABLISHES A CURRENT TO BALANCE THE MSB CURRENT. THE EFFECT OF TEMPERATURE COEFFICIENT MISMATCH BETWEEN THE BIPOLAR RESISTOR COMBINATION AND DAC RESISTORS IS EXPANDED ON PREVIOUS PAGE.

Figure 6. ±10 V Voltage Output

Table I.	Digital Input Codes	
----------	----------------------------	--

DIGITAL INPUT MSB LSB	Straight Binary	ANALOG OUTPUT Offset Binary	Twos Complement*
$\begin{array}{c} 0 \ 0 \ 0 \ 0 \ 0 \ 0 \ 0 \ 0 \ 0 \ 0 $	Zero	-FS	Zero
	Mid Scale – 1 LSB	Zero - 1 LSB	+FS – 1 LSB
	+1/2 FS	Zero	–FS
	+FS – 1 LSB	+FS - 1 LSB	Zero – 1 LSB

*Inverts the MSB of the offset binary code with an external inverter to obtain twos complement.

OUTLINE DIMENSIONS

24-Lead Side-Brazed Solder Lid Ceramic DIP [DIP/SB] (D-24)

Dimensions shown in inches and (millimeters)



CONTROLLING DIMENSIONS ARE IN INCHES; MILLIMETER DIMENSIONS (IN PARENTHESES) ARE ROUNDED-OFF INCH EQUIVALENTS FOR REFERENCE ONLY AND ARE NOT APPROPRIATE FOR USE IN DESIGN

28-Lead Standard Small Outline Package [SOIC] Wide Body

(RW-28)

Dimensions shown in millimeters and (inches)



CONTROLLING DIMENSIONS ARE IN MILLIMETERS; INCH DIMENSIONS (IN PARENTHESES) ARE ROUNDED-OFF MILLIMETER EQUIVALENTS FOR REFERENCE ONLY AND ARE NOT APPROPRIATE FOR USE IN DESIGN

Revision History

Location	Page
10/02—Data Sheet changed from REV. D to REV. E.	
Edits to SPECIFICATIONS	