Dual port SuperSpeed USB 3.0 redriver Rev. 2 — 19 June 2013

Product data sheet

General description 1.

The PTN36242L is a dual port SuperSpeed USB 3.0 redriver IC that enhances signal quality by performing receive equalization on the deteriorated input signal followed by transmit de-emphasis maximizing system link performance. With its superior differential signal conditioning and enhancement capability, the device delivers significant flexibility and performance scaling for various systems with different PCB trace and cable channel conditions and still benefit from optimum power consumption.

The PTN36242L is a dual port device that supports data signaling rate of 5 Gbit/s through each channel. PTN36242L has four channels (two ports): one port has two channels. Port 1 has A1 and B1 channels and Port 2 has A2 and B2 channels. The data flow of one channel is facing the USB host and another channel is facing the USB peripheral or device. Each channel consists of a high-speed Transmit (Tx) differential lane and a high-speed Receive (Rx) differential lane.

The PTN36242L has built-in advanced power management capability that enables significant power saving under various different USB 3.0 Low-power modes (U2/U3). It detects LFPS signaling and link electrical conditions and can dynamically activate/de-activate internal circuitry and logic. The device performs these actions without host software intervention and conserves power.

The PTN36242L is powered from a 3.3 V supply and it is available in HVQFN32 $3 \text{ mm} \times 6 \text{ mm} \times 0.85 \text{ mm}$ package with 0.4 mm pitch.

Features and benefits 2.

- Supports USB 3.0 specification (SuperSpeed only)
- Support of two ports (Port 1 has A1 and B1 channels; Port 2 has A2 and B2 channels)
- Each channel supports a receive equalizer and a transmit de-emphasis function
- Selectable receive equalization on each channel to recover from InterSymbol Interference (ISI) and high-frequency losses, with the ability to choose equalization gain settings per channel
- Selectable transmit de-emphasis and output swing on each channel delivers pre-compensation suited to channel conditions
- Integrated termination resistors provide impedance matching on both transmit and receive paths
- Automatic receiver termination indication and detection
- Low active power: 743 mW/225 mA (typical) for both ports with Vos = 1000 mV; equalization = 6 dB; de-emphasis = -3.5 dB and V_{DD} = 3.3 V



Dual port SuperSpeed USB 3.0 redriver

- Power-saving states:
 - ♦ 60 mW/20 mA (typical) when in U2/U3 states
 - 26 mW/8 mA (typical) when no connection detected
 - \blacklozenge 0.5 mW/150 μA (typical) when in deep power-saving state
- Hot plug capable
- Power supply: 3.3 V ± 10 %
- HVQFN32 3 mm × 6 mm × 0.85 mm package with 0.4 mm pitch, exposed center pad for thermal relief and electrical ground
- ESD: 8 kV HBM, 1 kV CDM for high-speed pins
- Operating temperature range: 0 °C to 85 °C

3. Applications

- Notebook/netbook/net top platforms
- Docking stations
- Desktop and AIO platforms
- Server and storage platforms
- USB 3.0 peripherals such as consumer/storage devices, printers, or USB 3.0 capable hubs/repeaters

4. System context diagrams



The system context diagrams in Figure 1 illustrate PTN36242L usage.

Ordering information 5.

able 1. Ordering information								
Type number	Topside	Package	Package					
	mark	Name	Description	Version				
PTN36242LBS	36242L	HVQFN32	plastic thermal enhanced very thin quad flat package; no leads; 32 terminals; body $3 \times 6 \times 0.85$ mm ^[1]	SOT1185-1				

[1] Maximum package height is 1 mm.

5.1 Ordering options

Table 2.	Orde	ring options		
Type num	ber	Orderable part number	Package	Packing method

Type number	Orderable part number	Package	Packing method	Minimum order quantity	Temperature
PTN36242LBS	PTN36242LBS,518	HVQFN32	Reel 13" Q1/T1 *standard mark SMD dry pack	5000	$T_{amb} = 0 \ ^{\circ}C \ to \ 85 \ ^{\circ}C$

Dual port SuperSpeed USB 3.0 redriver

6. Block diagram



Dual port SuperSpeed USB 3.0 redriver

7. Pinning information

7.1 Pinning



7.2 Pin description

Table 3.	Pin description			
Symbol	Pin	Туре	Description	
High-spe	ed differe	ential signals	i	
A1IN+	26	self-biasing differential input	Differential signal from SuperSpeed USB 3.0 transmitter. A1IN+ makes a differential pair with A1IN–. The input to this pin must be AC-coupled externally.	
A1IN-	27	self-biasing differential input	Differential signal from SuperSpeed USB 3.0 transmitter. A1IN– makes a differential pair with A1IN+. The input to this pin must be AC-coupled externally.	
B1OUT+	23	self-biasing differential output	Differential signal to SuperSpeed USB 3.0 receiver. B1OUT+ makes a differential pair with B1OUT–. The output of this pin must be AC-coupled externally.	
B1OUT-	24	self-biasing differential output	Differential signal to SuperSpeed USB 3.0 receiver. B1OUT– makes a differential pair with B1OUT+. The output of this pin must be AC-coupled externally.	
A1OUT+	2	self-biasing differential output	Differential signal to SuperSpeed USB 3.0 receiver. A1OUT+ makes a differential pair with A1OUT–. The output of this pin must be AC-coupled externally.	

Dual port SuperSpeed USB 3.0 redriver

Table 3.	Fin de		
Symbol	Pin	Туре	Description
A1OUT-	1	self-biasing differential output	Differential signal to SuperSpeed USB 3.0 receiver. A1OUT– makes a differential pair with A1OUT+. The output of this pin must be AC-coupled externally.
B1IN+	5	self-biasing differential input	Differential signal from SuperSpeed USB 3.0 transmitter. B1IN+ makes a differential pair with B1IN–. The input to this pin must be AC-coupled externally.
B1IN-	4	self-biasing differential input	Differential signal from SuperSpeed USB 3.0 transmitter. B1IN- makes a differential pair with B1IN+. The input to this pin must be AC-coupled externally.
A2IN+	20	self-biasing differential input	Differential signal from SuperSpeed USB 3.0 transmitter. A2IN+ makes a differential pair with A2IN–. The input to this pin must be AC-coupled externally.
A2IN-	21	self-biasing differential input	Differential signal from SuperSpeed USB 3.0 transmitter. A2IN- makes a differential pair with A2IN+. The input to this pin must be AC-coupled externally.
B2OUT+	17	self-biasing differential output	Differential signal to SuperSpeed USB 3.0 receiver. B2OUT+ makes a differential pair with B2OUT–. The output of this pin must be AC-coupled externally.
B2OUT-	18	self-biasing differential output	Differential signal to SuperSpeed USB 3.0 receiver. B2OUT– makes a differential pair with B2OUT+. The output of this pin must be AC-coupled externally.
A2OUT+	8	self-biasing differential output	Differential signal to SuperSpeed USB 3.0 receiver. A2OUT+ makes a differential pair with A2OUT The output of this pin must be AC-coupled externally.
A2OUT-	7	self-biasing differential output	Differential signal to SuperSpeed USB 3.0 receiver. A2OUT– makes a differential pair with A2OUT+. The output of this pin must be AC-coupled externally.
B2IN+	11	self-biasing differential input	Differential signal from SuperSpeed USB 3.0 transmitter. B2IN+ makes a differential pair with B2IN–. The input to this pin must be AC-coupled externally.
B2IN-	10	self-biasing differential input	Differential signal from SuperSpeed USB 3.0 transmitter. B2IN- makes a differential pair with B2IN+. The input to this pin must be AC-coupled externally.
Control a	nd conf	iguration sign	als
CE	12	CMOS	Chip Enable input (active HIGH); internally pulled-up.
		input	If CE is LOW, then the device is in deep power-saving state even if supply rail is ON. For the device to be able to operate, the CE pin must be HIGH.



When TEST = HIGH, device is in Test mode, otherwise the

TEST

22

CMOS

Dual port SuperSpeed USB 3.0 redriver

Table 3.	Pin descriptioncontinued					
Symbol	Pin	Туре	Description			
OS	30	Analog	External resistor for output swing adjustment. This pin shall be left open, internally generated bias current will be used and the output is at default swing setting.			
			This pin shall be connected to a 4.99 k Ω resistor to GND. The output swing will be at the default value with reference to the external resistor.			
			For output swing of 1000 mV, leave OS pin open or use resistor of 4.99 $k\Omega.$			
			For output swing of 1100 mV, short OS pin to ground through a 3.75 $k\Omega$ resistor.			
			For output swing of 900 mV, short OS pin to ground through a 6.25 $k\Omega$ resistor.			
AEQ0 AEQ1	32 31	CMOS input	Equalizer control for channel A of port 1 and port 2. Internally pulled down through 50 $k\Omega$ resistor.			
	-		[AEQ1, AEQ0] =			
			00: 9 dB			
			01: 3 dB			
			10: 6 dB			
			11: 7.5 dB			
ADE0 ADE1	29	CMOS	Programmable output de-emphasis level setting for channel A			
	28	8 Input	resistor.			
			[ADE1, ADE0] =			
			00: -3.5 dB			
			01: 0 dB			
			10: –7 dB			
			11: –5 dB			
BEQ0	13	CMOS	Equalizer control for channel B of port 1 and port 2. Internally			
BEQ1	14	input				
			00: 9 dB			
			01: 3 dB			
			10: 6 dB			
			11: 7.5 dB			
BDE0	15	CMOS	Programmable output de-emphasis level setting for channel B			
BDE1	16	input	of port 1 and port 2. Internally pulled down through 50 k Ω resistor			
			[BDE1. BDE0] =			
			00: –3.5 dB			
			01: 0 dB			
			10: –7 dB			
			11: –5 dB			
Supply v	oltage					
V _{DD}	9, 25	Power	3.3 V supply.			

PTN36242L Product data sheet

Table 3.	Pin descriptioncontinued				
Symbol	Pin	Туре	Description		
Ground c	onnectio	ns			
GND	3, 19, 6	Ground	Ground supply (0 V).		
GND	center pad	Ground	the center pad must be connected to GND plane for both electrical grounding and thermal relief.		

8. Functional description

Refer to Figure 2 "Block diagram of PTN36242L".

PTN36242L is a dual port SuperSpeed USB 3.0 redriver meant to be used for signal integrity enhancement on various platforms — notebooks, docking station, desktop, AIO, peripheral devices, etc. With its high fidelity differential signal conditioning capability and wide configurability, this chip is flexible enough for use under various system environments.

The following sections describe the individual block functions and capabilities of the device in more detail.

8.1 Receive equalization

On the high-speed signal path, the device performs receive equalization providing frequency selective gain to configuration pins AEQ0, AEQ1, BEQ0 and BEQ1 setting. Table 4 lists the configuration options available in this device.

	, Dianie Dy consideration options
AEQ1/AEQ0, BEQ1/BEQ0	SuperSpeed USB 3.0 signal equalization gain at 2.5 GHz
LL	9 dB
LH	3 dB
HL	6 dB
HH	7.5 dB

Table 4. AEQ0/AEQ1 (channel A), BEQ0/BEQ1 (channel B) configuration options

8.2 Transmit de-emphasis

The PTN36242L device enhances High Frequency (HF) signal content further by performing de-emphasis on the high-speed signals. In addition, the device provides flat frequency gain by boosting output signal. Both flat and frequency selective gains prepare the system to cover up for losses further down the link. <u>Table 5</u> lists de-emphasis configuration options of PTN36242L.

Table 5. ADE0/ADE1 (channel A), BDE0/BDE1 (channel B) configuration options

ADE1/ADE0, BDE1/BDE0	SuperSpeed USB 3.0 signal de-emphasis gain
LL	–3.5 dB
LH	0
HL	–7 dB
НН	–5 dB

Figure 4 illustrates de-emphasis as a function of time.

Product data sheet

PTN36242L



8.3 Device states and power management

PTN36242L has implemented an advanced power management scheme that operates in tune with USB 3.0 bus electrical condition. Though the device does not decode USB power management commands (related to USB 3.0 U1/U2/U3 transitions) exchanged between USB 3.0 host and peripheral/device, it relies on bus electrical conditions to decide to be in one of the following states:

- Active state wherein device is fully operational, USB data is transported on port 1 and port 2. In this state, USB connection exists, but there is no need for Receive Termination detection.
- **Power-saving** state wherein the channels A1, A2, B1 and B2 are kept enabled. In this state, squelching, LFPS detection and/or Receive termination detection circuitry are active. Based on USB connection, there are 2 possibilities:
 - No USB connection:

Receive Termination detection circuitry keeps polling periodically.

DC common-mode voltage level is not maintained.

- When USB connection exists and when the link is in USB 3.0 U2/U3 mode:

Receive Termination detection circuitry keeps polling periodically.

DC Common mode voltage level is maintained.

- **Deep power-saving** or **Shutdown state** wherein the channel is in Deep power-saving/Shutdown condition enabling significant power saving.
 - DC common-mode voltage level is not maintained.
 - Tx and Rx terminations are put to high-impedance condition.
 - Transitioning to Active state would take several tens of milliseconds.

When CE is LOW, both port 1 and port 2 are put in Deep power-saving state.

The Receive Termination Detection circuitry is implemented as part of a transmitter and detect whether a load device with equivalent DC impedance $Z_{RX DC}$ is present.

Dual port SuperSpeed USB 3.0 redriver

9. Limiting values

Imiting values In accordance with the Absolute Maximum Rating System (IEC 60134).								
Symbol	Parameter	Conditions	Min	Max	Unit			
V _{DD}	supply voltage		<u>[1]</u> –0.3	+4.6	V			
VI	input voltage	3.3 V CMOS inputs	<u>[1]</u> –0.3	$V_{DD} + 0.5$	V			
T _{stg}	storage temperature		-65	+150	°C			
V _{ESD}	electrostatic discharge voltage	HBM for high-speed pins	[2] _	8000	V			
		HBM for control pins	[2] _	4000	V			
		CDM for high-speed pins	<u>[3]</u>	1000	V			
		CDM for control pins	<u>[3]</u>	500	V			

[1] All voltage values (except differential voltages) are with respect to network ground terminal.

[2] Human Body Model: ANSI/EOS/ESD-S5.1-1994, standard for ESD sensitivity testing, Human Body Model -Component level; Electrostatic Discharge Association, Rome, NY, USA.

[3] Charged Device Model; ANSI/EOS/ESD-S5.3.1-1999, standard for ESD sensitivity testing, Charged Device Model - Component level; Electrostatic Discharge Association, Rome, NY, USA.

10. Recommended operating conditions

Table 7.	Operating conditions					
Symbol	Parameter	Conditions	Min	Тур	Max	Unit
V _{DD}	supply voltage	3.3 V supply option	3.0	3.3	3.6	V
VI	input voltage	control and configuration pins (for example, AEQ0, AEQ1, BEQ0, BEQ1, ADE0, ADE1, BDE0, BDE1, CE, TEST)	-	V _{DD}	3.6	V
T _{amb}	ambient temperature	operating in free air	0	-	85	°C

11. Characteristics

11.1 Device characteristics

Table 8.	Device characteristics					
Symbol	Parameter	Conditions	Min	Тур	Max	Unit
t _{startup}	start-up time	supply voltage within operating range to specified operating characteristics	-	-	20	ms
t _{S(HL)}	HIGH to LOW settling time	enable to disable; CE HIGH \rightarrow LOW change to specified operating characteristics; device is supplied with valid supply voltage	-	-	1	ms
t _{s(LH)}	LOW to HIGH settling time	disable to enable; CE LOW \rightarrow HIGH change to specified operating characteristics; device is supplied with valid supply voltage	-	-	20	ms
t _{rcfg}	reconfiguration time	any configuration pin change (from one setting to another setting) to specified operating characteristics; device is supplied with valid supply voltage	-	-	100	ms
t _{PD(dif)}	differential propagation delay	between 50 % level at input and output; see Figure 5	-	-	0.4	ns
t _{idle}	idle time	default wait time to wait before getting into Power-saving state	-	300	400	ms
t _{d(pwrsave-act)}	delay time from power-save to active	time for exiting from Power-saving state and get into Active state; see Figure 7	-	10	-	μS
t _{d(act-idle)}	delay time from active to idle	reaction time for squelch detection circuit and transmitter output buffer; see <u>Figure 6</u>	-	9	14	ns
$t_{d(idle-act)}$	delay time from idle to active	reaction time for squelch detection circuit and transmitter output buffer; see Figure 6	-	5	11	ns
I _{DD}	supply current	Active state; Tx de-emphasis = -3.5 dB; Rx equalization gain = 6 dB; Tx output signal swing (peak-to-peak) = 1000 mV	-	225	-	mA
		U2/U3 Power-saving state	-	20		mA
		no USB connection state	-	8		mA
		Deep power-saving state; CE = LOW	-	150		μA



NXP Semiconductors

PTN36242L

Dual port SuperSpeed USB 3.0 redriver



11.2 Receiver AC/DC characteristics

Table 9. Receiver AC/DC characteristics

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
Z _{RX_DC}	receiver DC common-mode impedance		18	-	30	Ω
Z _{RX_DIFF_DC}	DC differential impedance	RX pair	72	-	120	Ω
Z _{IH}	HIGH-level input impedance	DC input; common-mode	25	-	-	kΩ
V _{RX_DIFFp-p}	differential input peak-to-peak voltage		100	-	1200	mV
V _{RX_DC_CM}	RX DC common mode voltage		-	1.8	-	V
V _{RX_CM_AC_P}	RX AC common-mode voltage	peak	-	-	150	mV
V _{th(i)}	input threshold voltage	differential peak-to-peak value	100	-	-	mV

Dual port SuperSpeed USB 3.0 redriver

11.3 Transmitter AC/DC characteristics

Symbol	Parameter	Conditions	Min	Түр	Мах	Unit
Z _{TX_DC}	transmitter DC common-mode impedance		18	-	30	Ω
Z _{TX_DIFF_DC}	DC differential impedance		72	-	120	Ω
V _{TX_DIFFp-p}	differential peak-to-peak	R _L = 100 Ω				
	output voltage	$OS = 4.99 \text{ k}\Omega \text{ or}$ not connected	800	1000	1200	mV
		OS = 3.75 kΩ	800	1100	1200	mV
		OS = 6.25 kΩ	800	900	1200	mV
V _{TX_DC_CM}	transmitter DC common-mode voltage		-	-	1.8	V
V _{TX_CM_ACpp_ACTIV}	TX AC common-mode peak-to-peak output voltage (active state)	device input fed with differential signal	-	-	100	mV
V _{TX_IDL_DIFF_ACpp}	electrical idle differential peak-to-peak output voltage	when link is in electrical idle	-	-	10	mV
V _{TX_RCV_DETECT}	voltage change allowed during receiver detection	positive voltage swing to sense the receiver termination detection	-	-	600	mV
t _{r(tx)}	transmit rise time	measured using 20 % and 80 % levels; see <u>Figure 8</u>	60	70	80	ps
t _{f(tx)}	transmit fall time	measured using 80 % and 20 % levels; see <u>Figure 8</u>	60	70	80	ps
t _{(r-f)tx}	difference between transmit rise and fall time	measured using 20 % and 80 % levels	-	-	20	ps



Table 10. Transmitter AC/DC characteristics

Dual port SuperSpeed USB 3.0 redriver

11.4 Jitter performance

<u>Table 11</u> provides jitter performance of PTN36242L under a specific set of conditions, illustrated by Figure 9.

Table 11. Jitter performance characteristics

Unit Interval (UI) = 200 ps.

Symbol	Parameter	Conditions		Min	Тур	Max	Unit
t _{jit(o)(p-p)}	peak-to-peak output jitter time	total jitter at test point C	<u>[1]</u>	-	0.14	-	UI
t _{jit(dtrm)(p-p)}	peak-to-peak deterministic jitter time		<u>[1]</u>	-	0.06	-	UI
t _{jit(rndm)(p-p)}	peak-to-peak random jitter time		<u>[1][2]</u>	-	0.08	-	UI

[1] Measured at test point C with K28.5 pattern, V_{ID} = 1000 mV (peak-to-peak), 5 Gbit/s; -3.5 dB de-emphasis from source.

[2] Random jitter calculated as 14.069 times the RMS random jitter for 10^{-12} bit error rate.



11.5 Control inputs

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
V _{IH}	HIGH-level input voltage		$0.65 \times V_{DD(3V3)}$	-	-	V
V _{IL}	LOW-level input voltage		-	-	$0.35 \times V_{DD(3V3)}$	V
I _{LI}	input leakage current	measured with input at $V_{IH(max)}$ and $V_{IL(min)}$ when CE = 0 and excluding OS pin	-	10	-	μΑ

NXP Semiconductors

PTN36242L

Dual port SuperSpeed USB 3.0 redriver

12. Package outline



Fig 10. Package outline SOT1185-1 (HVQFN32)

All information provided in this document is subject to legal disclaimers.

PTN36242L

Dual port SuperSpeed USB 3.0 redriver

13. Soldering of SMD packages

This text provides a very brief insight into a complex technology. A more in-depth account of soldering ICs can be found in Application Note *AN10365 "Surface mount reflow soldering description"*.

13.1 Introduction to soldering

Soldering is one of the most common methods through which packages are attached to Printed Circuit Boards (PCBs), to form electrical circuits. The soldered joint provides both the mechanical and the electrical connection. There is no single soldering method that is ideal for all IC packages. Wave soldering is often preferred when through-hole and Surface Mount Devices (SMDs) are mixed on one printed wiring board; however, it is not suitable for fine pitch SMDs. Reflow soldering is ideal for the small pitches and high densities that come with increased miniaturization.

13.2 Wave and reflow soldering

Wave soldering is a joining technology in which the joints are made by solder coming from a standing wave of liquid solder. The wave soldering process is suitable for the following:

- Through-hole components
- Leaded or leadless SMDs, which are glued to the surface of the printed circuit board

Not all SMDs can be wave soldered. Packages with solder balls, and some leadless packages which have solder lands underneath the body, cannot be wave soldered. Also, leaded SMDs with leads having a pitch smaller than ~0.6 mm cannot be wave soldered, due to an increased probability of bridging.

The reflow soldering process involves applying solder paste to a board, followed by component placement and exposure to a temperature profile. Leaded packages, packages with solder balls, and leadless packages are all reflow solderable.

Key characteristics in both wave and reflow soldering are:

- · Board specifications, including the board finish, solder masks and vias
- Package footprints, including solder thieves and orientation
- · The moisture sensitivity level of the packages
- Package placement
- Inspection and repair
- Lead-free soldering versus SnPb soldering

13.3 Wave soldering

Key characteristics in wave soldering are:

- Process issues, such as application of adhesive and flux, clinching of leads, board transport, the solder wave parameters, and the time during which components are exposed to the wave
- Solder bath specifications, including temperature and impurities

Dual port SuperSpeed USB 3.0 redriver

13.4 Reflow soldering

Key characteristics in reflow soldering are:

- Lead-free versus SnPb soldering; note that a lead-free reflow process usually leads to higher minimum peak temperatures (see <u>Figure 11</u>) than a SnPb process, thus reducing the process window
- Solder paste printing issues including smearing, release, and adjusting the process window for a mix of large and small components on one board
- Reflow temperature profile; this profile includes preheat, reflow (in which the board is heated to the peak temperature) and cooling down. It is imperative that the peak temperature is high enough for the solder to make reliable solder joints (a solder paste characteristic). In addition, the peak temperature must be low enough that the packages and/or boards are not damaged. The peak temperature of the package depends on package thickness and volume and is classified in accordance with Table 13 and 14

Table 13. SnPb eutectic process (from J-STD-020D)

Package thickness (mm)	Package reflow temperature (°C)		
	Volume (mm ³)		
	< 350	≥ 350	
< 2.5	235	220	
≥ 2.5	220	220	

Table 14. Lead-free process (from J-STD-020D)

Package thickness (mm)	Package reflow temperature (°C)				
	Volume (mm ³)				
	< 350	350 to 2000	> 2000		
< 1.6	260	260	260		
1.6 to 2.5	260	250	245		
> 2.5	250	245	245		

Moisture sensitivity precautions, as indicated on the packing, must be respected at all times.

Studies have shown that small packages reach higher temperatures during reflow soldering, see Figure 11.

Dual port SuperSpeed USB 3.0 redriver



For further information on temperature profiles, refer to Application Note *AN10365* "Surface mount reflow soldering description".

14. Abbreviations

Table 15.	Abbreviations
Acronym	Description
AIO	All In One computer platform
CDM	Charged-Device Model
HBM	Human Body Model
I ² C-bus	Inter-Integrated Circuit bus
IC	Integrated Circuit
LFPS	Low Frequency Periodic Sampling
PCB	Printed-Circuit Board
Rx	Receive
SI	Signal Integrity
Tx	Transmit
USB	Universal Serial Bus

19 of 23

15. Revision history

Document ID	Release date	Data sheet status	Change notice	Supersedes	
PTN36242L v.2	20130619	Product data sheet	-	PTN36242L v.1	
Modifications:	• Table 8 "De	vice characteristics", symbol	t _{s(HL)} (HIGH to LOW set	ling time):	
	 Condition 	n corrected from "disable to e	enable" to "enable to disa	able"	
	 Max value corrected from "20 ms" to "1 ms" 				
	 Table 8 "Device characteristics", symbol t_{s(LH)} (LOW to HIGH settling time): 				
	 Condition corrected from "enable to disable" to "disable to enable" 				
	 Max valu 	e corrected from "1 ms" to "2	20 ms"		
	Remark: These	are corrections to document	ation only; there is no ch	ange to device functionality.	
PTN36242L v.1	20130411	Product data sheet	-	-	

20 of 23

Dual port SuperSpeed USB 3.0 redriver

16. Legal information

16.1 Data sheet status

Document status[1][2]	Product status ^[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL http://www.nxp.com.

16.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between NXP Semiconductors and its customer, unless NXP Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the NXP Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

16.3 Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof. Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at http://www.nxp.com/profile/terms, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

PTN36242L

Dual port SuperSpeed USB 3.0 redriver

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Non-automotive qualified products — Unless this data sheet expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond

NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

Translations — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

16.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

17. Contact information

For more information, please visit: http://www.nxp.com

For sales office addresses, please send an email to: salesaddresses@nxp.com

Dual port SuperSpeed USB 3.0 redriver

18. Contents

1	General description 1
2	Features and benefits 1
3	Applications 2
4	System context diagrams 3
5	Ordering information
5.1	Ordering options 4
6	Block diagram
7	Pinning information
7.1	Pinning
7.2	Pin description 6
8	Functional description9
8.1	Receive equalization 9
8.2	Transmit de-emphasis 9
8.3	Device states and power management 10
9	Limiting values 11
10	Recommended operating conditions 11
11	Characteristics 12
11.1	Device characteristics
11.2	Receiver AC/DC characteristics 13
11.3	Transmitter AC/DC characteristics 14
11.4	Jitter performance
11.5	Control inputs
12	Package outline 16
13	Soldering of SMD packages 17
13.1	Introduction to soldering
13.2	Wave and reflow soldering 17
13.3	Peflow soldering
13.4	Abbreviations 19
14	Abbreviations
15	Revision history
10	Legal Information
16.1	Data Sheet Status
16.3	Disclaimers 21
16.4	Trademarks
17	Contact information
18	Contents
-	

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© NXP B.V. 2013.

All rights reserved.

For more information, please visit: http://www.nxp.com For sales office addresses, please send an email to: salesaddresses@nxp.com

Date of release: 19 June 2013 Document identifier: PTN36242L