

**Obsolete Device** 

# **TC820**

## 3-3/4 Digit A/D Converter with Frequency Counter and Logic Probe

#### Features

- Multiple Analog Measurement System
  - Digit A/D Converter
  - Frequency Counter
  - Logic Probe
- Low Noise A/D Converter:
  - Differential Inputs: (1 pA Bias Current)
  - On-Chip 50 ppm/°C Voltage Reference
- Frequency Counter:
  - 4 MHz Maximum Input Frequency
  - Auto-Ranging Over Four Decade Range
- Logic Probe:
  - Two LCD Annunciators
- Buzzer Driver
- 3-3/4 Digit Display with Over Range Indicator
- LCD Display Driver with Built-in Contrast Control
- Data Hold Input for Comparison Measurements
- Low Battery Detect with LCD Annunciator
- Under Range and Over Range Outputs
- On-Chip Buzzer Driver with Control Input
- 40-Lead Plastic DIP, 44-Lead Plastic Flat Pack, or 44-Lead PLCC Packages

#### **General Description**

The TC820 is a 3-3/4 digit, multi-measurement system especially suited for use in portable instruments. It integrates a dual slope A/D converter, auto-ranging frequency counter and logic probe into a single 44-pin surface mount, or 40-pin through hole package. The operates from a single 9V input voltage (battery) and features a built-in battery low flag. Function and decimal point selection are accomplished with simple logic inputs designed for direct connection to an external microcontroller or rotary switch.

#### Package Type:



#### **Typical Applications**





### 1.0 ELECTRICAL CHARACTERISTICS

#### **Absolute Maximum Ratings\***

Supply Voltage (V <sub>DD</sub> to GND)
Analog Input Voltage:
(Either Input) (Note 1) V <sub>DD</sub> to V <sub>SS</sub>
Reference Input Voltage (Either Input) V <sub>DD</sub> to V <sub>SS</sub>
Digital InputsV <sub>DD</sub> to DGND
$V_{\text{DISP}}$
Package Power Dissipation (T <sub>A</sub> – 70°C) (Note 2):
40-Lead Plastic DIP1.23W
44-Lead PLCC1.23W
44-Lead Plastic Flat Package (PQFP)1.00W
Operating Temperature Range:
"C" Devices0°C to +70°C
"E" Devices40°C to +85°C
Storage Temperature Range65°C to +150°C

\*Stresses above those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions above those indicated in the operation sections of the specifications is not implied. Exposure to Absolute Maximum Rating conditions for extended periods may affect device reliability.

### **ELECTRICAL CHARACTERISTICS**

Electrical Characteristics: Unless otherwise specified, $V_{SS} = 9V$ , $T_A = +25^{\circ}C$						
Parameter	Sym	Min	Тур	Max	Units	Test Conditions
Zero Input Reading		-000	±000	+000	Digital Reading	V <sub>IN</sub> = 0V Full Scale = 400 mV
Rollover Error	RE	-1	±0.2	+1	Counts	$V_{IN} = \pm 390 \text{ mV}$ Full Scale = 400 mV
Nonlinearity (Maximum Deviation From Best Straight Line Fit)	NL	-1	±0.2	+1	Count	Full Scale = 400 mV
Ratiometric Reading		1999	1999/2000	2000	—	$V_{IN} = V_{REF}$
Common Mode Rejection Ratio	CMRR	—	50		μ٧/٧	$V_{CM} = \pm 1V, V_{IN} = 0V$ Full Scale = 400 mV ( $V_{FS} = 200 \text{ mV}$ )
Common Mode Voltage Range	VCMR	$V_{SS}$ + 1.5		$V_{DD} - 1$		Input High, Input Low
Noise (P-P Value Not Exceeded 95% of Time)	e <sub>N</sub>		15		μV	V <sub>IN</sub> = 0V Full Scale = 400 mV
Input Leakage Current	I <sub>IN</sub>	—	—		—	$V_{IN} = 0V$
		—	1	10	pА	$T_A = +25^{\circ}C$
		—	20	-	pА	$0^{\circ}C \leq T_{A} \leq +70^{\circ}C$
		_	100	-	pА	$\text{-40°C} \leq \text{T}_{A} \leq \text{+85°C}$
Analog Common Voltage	V <sub>COM</sub>	3.15	3.3	3.45	V	25 kΩ between Common and V <sub>DD</sub> (V <sub>SS</sub> - V <sub>COM</sub> )
Common Voltage Temperature Coefficient	V <sub>CTC</sub>	_	—		_	25 k $\Omega$ Between Common and V_DD
		—	35	50	ppm/°C	$0^{\circ}C \leq T_{A} \leq +70^{\circ}C$
		—	50	-	—	$\text{-40°C} \leq \text{T}_{A} \leq \text{+85°C}$
Zero Reading Drift	TC <sub>ZS</sub>	—	—	-	—	$V_{IN} = 0V$
		—	0.2	_	_	$0^{\circ}C \leq T_A \leq +70^{\circ}C$
		_	1	_	_	$-40^{\circ}C \le T_A \le +85^{\circ}C$
Note A location frames and a			a second day of the set for	and a constant for	Particular A	

Note 1: Input voltages may exceed the supply voltages provided that input current is limited to ±100 μA. Current above this value may result in invalid display readings, but will not destroy the device if limited to ±1 mA.

2: Dissipation ratings assume device is mounted with all leads soldered to printed circuit board.

Electrical Characteristics: Unless otherwise specified, V <sub>SS</sub> = 9V, T <sub>A</sub> = +25°C						
Parameter	Sym	Min	Тур	Max	Units	Test Conditions
Scale Factor Temperature	TC <sub>FS</sub>	—	_	—	_	V <sub>IN</sub> = 399 mV
Coefficient		—	1	5	ppm/°C	$0^{\circ}C \leq T_A \leq +70^{\circ}C$
		_	5	-	ppm/°C	$-40^{\circ}C \le T_A \le +85^{\circ}C$ Ext Ref = 0 ppm/°C
Supply Current	۱ <sub>S</sub>	_	1	1.5	mA	$V_{IN} = 0V$
Peak-to-Peak Backplane Drive Voltage		4.25	4.7	5.3	V	V <sub>S</sub> = 9V V <sub>DISP</sub> = DGND
Buzzer Frequency		—	5	—	kHz	F <sub>OSC</sub> = 40 kHz
Counter TIme-Base Period		—	1	—	Second	F <sub>OSC</sub> = 40 kHz
Low Battery Flag Voltage		6.7	7	7.3	V	$V_{DD}$ to $V_{SS}$
Input Low Voltage	V <sub>IL</sub>	—	_	DGND + 1.5	V	
Input High Voltage	V <sub>IH</sub>	V <sub>DD</sub> – 1.5	—	—	V	
Output Low Voltage, UR, OR Outputs	V <sub>OL</sub>	V <sub>DD</sub> – 1.5	—	DGND + 0.4	V	I <sub>L</sub> = 50 μA
Control Pin Pull-down Current		—	5	—	μA	$V_{IN} = V_{DD}$

### **ELECTRICAL CHARACTERISTICS (CONTINUED)**

Note 1: Input voltages may exceed the supply voltages provided that input current is limited to ±100 μA. Current above this value may result in invalid display readings, but will not destroy the device if limited to ±1 mA.

2: Dissipation ratings assume device is mounted with all leads soldered to printed circuit board.

#### 2.0 PIN DESCRIPTIONS

The descriptions of the pins are listed in Table 2-1.

TABLE 2-1:	PIN FUNCTION TABLE
TABLE 2-1:	PIN FUNCTION TABLE

Pin Number (40-PDIP)	Pin Number (44-PQFP)	Symbol	Description				
1	40	L-E4	LCD segment driver for L ("logic LOW"), polarity, and "e" segment of most significant digit (MSD).				
2	41	AGD4	LCD segme	ent drive for "a	," "g," and "d" segments of MSD.		
3	42	BC4P3	LCD segme	ent drive for "b	" and "c" segments of MSD and de	ecimal point 3.	
4	43	HFE3	LCD segme	ent drive for H	("logic HIGH"), and "f" and "e" seg	ments of third LSD.	
5	44	AGD3	LCD segme	ent drive for "a	," "g," and "d" segments of third LS	SD.	
6	1	BC3P2	LCD segme	ent drive for "b	" and "c" segments of third LSD ar	nd decimal point 2.	
7	2	OFE2	LCD segme	ent drive for "o	ver range," and "f" and "e" segmer	nts of second LSD.	
8	3	AGD2	LCD segme	ent drive for "a	," "g," and "d" segments of second	LSD.	
9	4	BC2P1	LCD segme	ent drive for "b	" and "c" segments of second LSI	D and decimal point 1.	
10	5	PKFE1	LCD segme	ent drive for "h	old peak reading," and "f" and "e"	segments of LSD.	
11	6	AGD1	LCD segme	ent drive for "a	," "g," and "d" segments of LSD.		
12	7	BC1BT	LCD segme	ent drive for "b	" and "c" segments of LSD and "lo	w battery."	
13	8	BP3	LCD backpl	ane #3.			
14	9	BP2	LCD backpl	ane #2.			
15	10	BP1	LCD backpl	ane #1.			
—	11	V <sub>DISP</sub>	Sets peak L compensate	CD drive sign e for temperat	al: V <sub>PEAK</sub> = (V <sub>DD</sub> ) – V <sub>DISP</sub> . V <sub>DISP</sub> r ure variation of LCD crystal thresh	nay also be used to old voltage.	
16	12	DGND	Internal logi	c digital grour	nd, the logic "0" level. Nominally 4.	7V below V <sub>DD</sub> .	
17	13	ANNUNC	Square-way used to con on; connect	Square-wave output at the backplane frequency, synchronized to BP1. ANNUNC can be used to control display annunciators. Connecting an LCD segment to ANNUNC turns it on; connecting it to its backplane turns it off.			
18	14	LOGIC	Logic mode control input. When connected to $V_{DD}$ , the converter is in Logic mode. The LCD displays "OL" and the decimal point inputs control the HIGH and LOW annunciators. When the "low" annunciator is on, the buzzer will also be on. When unconnected or connected to DGND, the is in the Voltage/Frequency Measurement mode. This pin has a 5 µA internal pull-down to DGND.				
19	15	RANGE/ FREQ	Dual purpos will be 200	se input. In Ra counts instead	ange mode, when connected to V <sub>D</sub> d of 2000 counts.	$_{D}$ , the integration time	
20	16	DP0/LO	Dual purpos connecting pull-down to	se input. Decir this pin to V <sub>DI</sub> DGND in Vo	mal point select input for voltage m o will turn on the "low" LCD segme Its mode only. Decimal point logic:	easurements. In logic mode, nt. There is an internal 5 μA	
			DP1	DPQ	Decimal Point Selected		
			0	0	None		
			0	1	DP1		
			1	0	DP2		
			1	1	DP3		
21	17	DP1/HI	Dual purpose input. Decimal point select input for voltage measurements. In Logic mode,				
			connecting this pin to $V_{DD}$ will turn on the "high" LCD segment. There is an internal 5 $\mu$ A pull-down to DGND in Volts mode only.				
22	18	BUZOUT	Buzzer output. Audio frequency, 5kHz, output which drives a piezoelectric buzzer.				
23	19	BUZIN	Buzzer control input. Connecting BUZIN to $V_{DD}$ turns the buzzer on. BUZIN is logically OR'ed (internally) with the "logic level low" input. There is an internal 5 $\mu$ A pull-down to DGND.				

Pin Number (40-PDIP)	Pin Number (44-PQFP)	Symbol	Description	
24	20	FREQ/ VOLTS	Voltage or frequency measurement select input. When unconnected, or connected VOLTS to DGND, the A/D converter function is active. When connected to $V_{DD}$ , the frequency counter function is active. This pin has an internal 5 $\mu$ A pull-down to DGND.	
25	21	PKHOLD	Peak hold input. When connected to $V_{DD}$ , the converter will only update the display if a new conversion value is greater than the preceding value. Thus, the peak reading will be stored and held indefinitely. When unconnected, or connected to DGND, the converter will operate normally. This pin has an internal 5 $\mu$ A pull-down to DGND.	
—	22	UR	Under range output. This output will be HIGH when the digital reading is 380 counts or less.	
—	23	OR	Over range output. This output will be HIGH when the analog signal input is greater than full scale. The LCD will display "OL" when the input is over ranged.	
26	24	V <sub>SS</sub>	Negative supply connection. Connect to negative terminal of 9V battery.	
27	25	COM	Analog circuit ground reference point. Nominally 3.3V below V <sub>DD</sub> .	
28	26	C <sub>REF</sub> +	Positive connection for reference capacitor.	
29	27	C <sub>REF</sub> -	Negative connection for reference capacitor.	
30	28	V <sub>REF</sub> +	High differential reference input connection.	
31	29	V <sub>REF</sub> -	Low differential reference input connection.	
32	30	V <sub>IN</sub> -	Low analog input signal connection.	
33	31	V <sub>IN</sub> +	High analog input signal connection.	
34	32	V <sub>BUFF</sub>	Buffer output. Connect to integration resistor.	
35	33	C <sub>AZ</sub>	Auto-zero capacitor connection.	
36	34	V <sub>INT</sub>	Integrator output. Connect to integration capacitor.	
—	35	EOC/ HOLD	Bi-directional pin. Pulses low (i.e., from V <sub>DD</sub> to DGND) at the end of each conversion. If connected to V <sub>DD</sub> , conversions will continue, but the display is not updated.	
37	36	OSC1	Crystal oscillator (input) connection.	
38	37	OSC2	Crystal oscillator (output) connection.	
39	38	OSC3	RC oscillator connection.	
40	39	V <sub>DD</sub>	LCD segment drive for "a," "g," and "d" segments of MSD.	

TABLE 2-1: PIN FUNCTION TABLE (CONTINUED)

### 3.0 DETAILED DESCRIPTION

The is a 3-3/4 digit measurement system combining an integrating analog-to-digital converter, frequency counter, and logic level tester in a single package. The TC820 supersedes the TC7106 in new designs by improving performance and reducing system cost. The TC820 adds features that are difficult, expensive, or impossible to provide with older A/D converters (see Table 3-1). The high level of integration permits TC820 based instruments to deliver higher performance and more features, while actually reducing parts count. Fabricated in low power CMOS, the TC820 directly drives a 3-3/4 digit (3999 maximum) LCD.

With a maximum range of 3999 counts, the TC820 provides 10 times greater resolution in the 200 mV to 400 mV range than traditional 3-1/2 digit meters. An auto-zero cycle ensures a zero reading with a 0V input. CMOS processing reduces analog input bias current to only 1 pA. Rollover error (the difference in readings for equal magnitude but opposite polarity input signals) is less than  $\pm$ 1 count. Differential reference inputs permit ratiometric measurements for ohms or bridge transducer applications.

The TC820's frequency counter option simplifies design of an instrument well-suited to both analog and digital troubleshooting: voltage, current, and resistance measurements, plus precise frequency measurements to 4MHz (higher frequencies can be measured with an external prescaler), and a simple logic probe. The frequency counter will automatically adjust its range to match the input frequency, over a four-decade range.

Two logic level measurement inputs permit a TC820 based meter to function as a logic probe. When combined with external level shifters, the TC820 will display logic levels on the LCD and also turn on a piezoelectric buzzer when the measured logic level is low.

Other TC820 features simplify instrument design and reduce parts count. On-chip decimal point drivers are included, as is a low battery detection annunciator. A piezoelectric buzzer can be controlled with an external switch or by the logic probe inputs. Two oscillator options are provided: a crystal can be used if high accuracy frequency measurements are desired, or a simple RC option can be used for low-end instruments.

A "peak reading hold" input allows the TC820 to retain the highest A/D or frequency reading. This feature is useful in measuring motor starting current, maximum temperature, and similar applications.

A family of instruments can be created with the TC820. No additional design effort is required to create instruments with 3-3/4 digit resolution.

The TC820 operates from a single 9V battery, with typical power of 10mW. Packages include a 40-lead plastic DIP, 44-lead plastic flat package (PQFP), and 44-lead PLCC.

#### TABLE 3-1: COMPETITIVE EVALUATION

Features Comparison	TC820	7106
3-3/4 Digit Resolution	Yes	No
Auto-Ranging Frequency Counter	Yes	No
Logic Probe	Yes	No
Decimal Point Drive	Yes	No
Peak Reading Hold (Frequency or Voltage)	Yes	No
Display Hold	Yes	No
Simple 10:1 Range Change	Yes	No
Buzzer Drive	Yes	No
Low Battery Detection with Annunciator	Yes	No
Over Range Detection with Annunciator	Yes	No
Low Drift Reference	Yes	No
Under Range/Over Range Logic Output	Yes	No
Input Overload Display	"OL"	"1"
LCD Annunciator Driver	Yes	No
LCD Drive Type	Triplexed	Direct
LCD Pin Connections	15	24
LCD Elements	36	23

#### 3.1 General Theory of Operation

#### 3.1.1 DUAL SLOPE CONVERSION PRINCIPLES

The TC820 analog-to-digital converter operates on the principle of dual slope integration. An understanding of the dual slope conversion technique will aid the user in following the detailed TC820 theory of operation following this section. A conventional dual slope converter measurement cycle has two distinct phases:

- 1. Input Signal Integration.
- 2. Reference Voltage Integration (De-integration).

Referring to Figure 3-1, the unknown input signal to be converted is integrated from zero for a fixed time period  $(t_{INT})$ , measured by counting clock pulses. A constant reference voltage of the opposite polarity is then integrated until the integrator output voltage returns to zero. The reference integration (de-integration) time  $(t_{DEINT})$  is then directly proportional to the unknown input voltage  $(V_{IN})$ .

In a simple dual slope converter, a complete conversion requires the integrator output to "ramp-up" from zero and "ramp-down" back to zero. A simple mathematical equation relates the input signal, reference voltage, and integration time.

#### **EQUATION 3-1:**

$\frac{1}{R_{INT}C_{INT}}\int_{0}^{t_{INT}}V_{IN}(t)dt = \frac{V_{REF}t_{DEINT}}{R_{INT}C_{INT}}$
Where: V <sub>REF</sub> = Reference Voltage t <sub>INT</sub> = Integration Time t <sub>DEINT</sub> = De-integration Time

For a constant V<sub>INT</sub>:

#### **EQUATION 3-2:**







Accuracy in a dual slope converter is unrelated to the integrating resistor and capacitor values as long as they are stable during a measurement cycle. An inherent benefit of the dual slope technique is noise immunity. Noise spikes are integrated or averaged to zero during the integration periods, making integrating ADCs immune to the large conversion errors that plague successive approximation converters in high noise environments. Interfering signals, with frequency components at multiples of the averaging (integrating) period, will be attenuated (Figure 3-2). Integrating ADCs commonly operate with the signal integration period set to a multiple of the 50/60Hz power line period.



FIGURE 3-2: Normal Mode Rejection of Dual Slope Converter.

#### 3.2 Analog Section

In addition to the basic integrate and de-integrate dual slope phases discussed above, the TC820 design incorporates a "zero integrator output" phase and an "auto-zero" phase. These additional phases ensure that the integrator starts at 0V (even after a severe over range conversion), and that all offset voltage errors (buffer amplifier, integrator and comparator) are removed from the conversion. A true digital zero reading is assured without any external adjustments.

A complete conversion consists of four distinct phases:

- 1. Zero Integrator Output.
- 2. Auto-Zero.
- 3. Signal Integrate.
- 4. Reference De-integrate.

#### 3.2.1 ZERO INTEGRATOR OUTPUT PHASE

This phase guarantees that the integrator output is at OV before the system zero phase is entered, ensuring that the true system offset voltages will be compensated for even after an over range conversion. The duration of this phase is 500 counts plus the unused de-integrate counts.

#### 3.2.2 AUTO-ZERO PHASE

During the auto-zero phase, the differential input signal is disconnected from the measurement circuit by opening internal analog switches, and the internal nodes are shorted to Analog Common ( $0V_{REF}$ ) to establish a zero input condition. Additional analog switches close a feedback loop around the integrator and comparator to permit comparator offset voltage error compensation. A voltage established on  $C_{AZ}$  then compensates for internal device offset voltages during the measurement cycle. The auto-zero phase residual is typically 10 µV to 15 mV. The auto-zero duration is 1500 counts.

#### 3.2.3 SIGNAL INTEGRATION PHASE

Upon completion of the auto-zero phase, the auto-zero loop is opened and the internal differential inputs connect to  $V_{IN}$ + and  $V_{IN}$ -. The differential input signal is then integrated for a fixed time period, which is 2000 counts (4000 clock periods). The externally set clock frequency is divided by two before clocking the internal counters.

The integration time period is:

#### **EQUATION 3-3:**

t	4000	
$q_{NT} =$	F <sub>OSC</sub>	

The differential input voltage must be within the device's Common mode range when the converter and measured system share the same power supply common (ground). If the converter and measured system do not share the same power supply common, as in battery powered applications,  $V_{\rm IN}$ - should be tied to analog common.

Polarity is determined at the end of signal integration phase. The sign bit is a "true polarity" indication, in that signals less than 1LSB are correctly determined. This allows precision null detection that is limited only by device noise and auto-zero residual offsets.

#### 3.2.4 REFERENCE INTEGRATE (DE-INTEGRATE) PHASE

The reference capacitor, which was charged during the auto-zero phase, is connected to the input of the integrating amplifier. The internal sign logic ensures the polarity of the reference voltage is always connected in the phase opposite to that of the input voltage. This causes the integrator to ramp back to zero at a constant rate, determined by the reference potential.

The amount of time required ( $t_{DEINT}$ ) for the integrating amplifier to reach zero is directly proportional to the amplitude of the voltage that was put on the integrating capacitor ( $V_{INT}$ ) during the integration phase.

## EQUATION 3-4:

$$t_{DEINT} = \frac{R_{INT}C_{INT}V_{INT}}{V_{REF}}$$

The digital reading displayed by the TC820 is:

Digital Count = 2000  $\frac{V_{IN}+V_{IN}}{V_{REF}}$ 

The oscillator frequency is divided by 2 prior to clocking the internal decade counters. The four-phase measurement cycle takes a total of 8000 (4000) counts or 16,000 clock pulses. The 8000 count phase is independent of input signal magnitude or polarity.

Each phase of the measurement cycle has the following length:

TABLE 3-2:	MEASUREMENT CYCLE
	PHASE LENGTH

Conversion Phase	Counts
1) Auto-Zero	1500
2) Signal Integrate (Notes 1, 2)	2000
3) Reference Integrate	1 to 4001
4) Integrator Output Zero	499 to 4499

- Note 1: This time period is fixed. The integration period for theTC820 is: INT (TC820) =  $4000/F_{OSC}$  = 2000 counts. Where  $F_{OSC}$  is the clock oscillator frequency.
  - 2: Times shown are the RANGE/FREQ at logic low (normal operation). When RANGE/FREQ is logic high, signal integrate times are 200 counts. See Section 3.2.7 "10:1 Range Change".

#### 3.2.5 INPUT OVER RANGE

When the analog input is greater than full scale, the LCD will display "OL" and the "OVER RANGE" LCD annunciator will be on.

#### 3.2.6 PEAK READING HOLD

The TC820 provides the capability of holding the highest (or peak) reading. Connecting the PK HOLD input to  $V_{DD}$  enables the peak hold feature. At the end of each conversion, the contents of the TC820 counter are compared to the contents of the display register. If the new reading is higher than the reading being displayed, the higher reading is transferred to the display register. A "higher" reading is defined as the reading with the higher absolute value.

The peak reading is held in the display register, so the reading will not "droop" or slowly decay with time. The held reading will be retained until a higher reading occurs, the PK HOLD input is disconnected from  $V_{DD}$ , or power is removed.

The peak signal to be measured must be present during the TC820 signal integrate period. The TC820 does not perform transient peak detection of the analog input signal. However, in many cases, such as measuring temperature or electric motor starting current, the TC820 "acquisition time" will not be a limitation. If true peak detection is required, a simple circuit will suffice. See the applications section for details. The peak reading function is also available when the TC820 is in the Frequency Counter mode. The counter auto-ranging feature is disabled when peak reading hold is selected.

#### 3.2.7 10:1 RANGE CHANGE

The analog input full scale range can be changed with the RANGE/FREQ input. Normally, RANGE/FREQ is held low by an internal pull-down. Connecting this pin to  $V_{S^+}$  will increase the full scale voltage by a factor of 10. No external component changes are required.

The RANGE/FREQ input operates by changing the integrate period. When RANGE/FREQ is connected to  $V_{DD}$ , the signal integration phase of the conversion is reduced by a factor of 10 (i.e., from 2000 counts to 200 counts).

For the TC820, the 10:1 range change will result in  $\pm$ 4V full scale. This full scale range will exceed the Common mode range of the input buffer when operating from a 9V battery. If range changing is required for the TC820, a higher supply voltage can be provided, or the input voltage can be divided by 2 externally.

#### 3.3 Frequency Counter

In addition to serving as an analog-to-digital converter, the TC820 internal counter can also function as a frequency counter (Figure 3-3). In the Counter mode, pulses at the RANGE/FREQ input will be counted and displayed. The frequency counter derives its time-base from the clock oscillator. The counter time-base is:

#### **EQUATION 3-5:**

toouwr=	F <sub>OSC</sub>
•COUNT =	40,000

Thus, the counter will operate with a 1-second timebase when a 40 kHz oscillator is used. The frequency counter accuracy is determined by the oscillator accuracy. For accurate frequency measurements, a crystal oscillator is recommended.

The frequency counter will automatically select the proper range. Auto-range operation extends over four decades, from 3.999 kHz to 3.999 MHz. Decimal points are set automatically in the Frequency mode (Figure 3-2). The logic switching levels of the RANGE/FREQ input are CMOS levels. For best counter operation, an external buffer is recommended. See the applications section for details.

#### 3.4 Logic Probe

The TC820 can also function as a simple logic probe (Figure 3-5). This mode is selected when the LOGIC input is high. Two dual purpose pins, which normally control the decimal points, are used as logic inputs. Connecting either input to a logic high level will turn on the corresponding LCD annunciator. When the "low" annunciator is on, the buzzer will be on. As with the frequency counter input, external level shifters/buffers are recommended for the logic probe inputs.



FIGURE 3-3: TC820 Counter Operation.



FIGURE 3-4:

Auto-range Decimal Point Selection vs. Frequency Counter Input.



FIGURE 3-5: Logic Probe Simplified Schematic.

When the logic probe function is selected while FREQ/ VOLTS is low (A/D mode), the ADC will remain in the Auto-Zero mode. The LCD will read "OL" and all decimal points will be off (Figure ).



If the logic probe is active while FREQ/VOLTS is high (Counter mode), the frequency counter will continue to operate. The display will read "OL" but the decimal points will be visible. If the logic probe input is also connected to the RANGE/FREQ input, bringing the LOGIC input low will immediately display the frequency at the logic probe input.

#### 3.5 Analog Pin Functional Description

## 3.5.1 DIFFERENTIAL SIGNAL INPUTS $(V_{IN}+), (V_{IN}-)$

The TC820 is designed with true differential inputs, and accepts input signals within the Input Stage Common mode voltage ( $V_{CM}$ ) range. The typical range is  $V_{DD} - 1V$  to  $V_{SS} + 1.5V$ . Common mode voltages are removed from the system when the TC820 operates from a battery or floating power source (isolated from measured system) and  $V_{SS}$  is connected to analog common (see Figure 3-5).

In systems where Common mode voltages exist, the 86 dB Common mode rejection ratio minimizes error. Common mode voltages do, however, affect the integrator output level. A worst case condition exists if a large, positive  $V_{CM}$  exists in conjunction with a full scale, negative differential signal. The negative signal drives the integrator output positive along with  $V_{CM}$  (Figure 3-6). For such applications, the integrator output swing can be reduced below the recommended 2V full scale swing. The integrator output will swing within 0.3V of  $V_{DD}$ , or  $V_{DD}$  without increased linearity error.

#### 3.5.2 REFERENCE (V<sub>DD</sub>, V<sub>SS</sub>)

The TC820 reference, like the analog signal input, has true differential inputs. In addition, the reference voltage can be generated anywhere within the power supply voltage of the converter. The differential reference inputs permit ratiometric measurements and simplify interfacing with sensors, such as load cells and temperature sensors. To prevent rollover type errors from being induced by large Common mode voltages,  $C_{REF}$  should be large compared to stray node capacitance. A 0.1  $\mu$ F capacitor is typical.

The TC820 offers a significantly improved analog common temperature coefficient, providing a very stable voltage suitable for use as a voltage reference. The temperature coefficient of analog common is typically 35 ppm/°C.

#### 3.5.3 ANALOG COMMON

The analog common pin is set at a voltage potential approximately 3.3V below V<sub>DD</sub>. This potential is between 3.15V and 3.45V below V<sub>DD</sub>. Analog common is tied internally to an N-channel FET capable of sinking 3 mA. This FET will hold the common line at 3.3V below V<sub>DD</sub> should an external load attempt to pull the common line toward V<sub>DD</sub>. Analog common source current is limited to 12  $\mu$ A, and is, therefore, easily pulled to a more negative voltage (i.e., below V<sub>DD</sub> – 3.3V).

The TC820 connects the internal V<sub>IN</sub>+ and V<sub>IN</sub>- inputs to analog common during the auto-zero cycle. During the reference integrate phase, V<sub>IN</sub>- is connected to analog common. If V<sub>IN</sub>- is not externally connected to analog common, a Common mode voltage exists.

This is rejected by the converter's 86 dB Common mode rejection ratio. In battery powered applications, analog common and  $V_{IN}$ - are usually connected, removing Common mode voltage concerns. In systems where  $V_{IN}$ - is connected to the power supply ground or to a given voltage, analog common should be connected to  $V_{IN}$ -.

The analog common pin serves to set the analog section reference or common point. The TC820 is specifically designed to operate from a battery, or in any "measurement" system where input signals are not referenced (float), with respect to the TC820 power source. The analog common potential of  $V_{DD} - 3.3V$  gives a 7V end of battery life voltage. The analog common potential has a voltage coefficient of 0.001%.

With a sufficiently high total supply voltage  $(V_{DD} - V_{SS} > 7V)$ , analog common is a very stable potential with excellent temperature stability (typically 35ppm/°C). This potential can be used to generate the TC820 reference voltage. An external voltage reference will be unnecessary in most cases, because of the 35 ppm/°C temperature coefficient. See the applications section for details.



**FIGURE 3-7:** Common Mode Voltage Removed In Battery Operation With V<sub>IN</sub> = Analog Common.



**FIGURE 3-8:** Common Mode Voltage Reduces Available Integrator Swing ( $V_{COM} \neq V_{IN}$ ).

#### 4.0 FUNCTION CONTROL INPUTS PIN

#### 4.1 Functional Description

The TC820 Operating modes are selected with the function control inputs. See the control input truth, Table 4-1. The high logic threshold is  $\ge V_{DD} - 1.5V$  and the low logic level is  $\le DGND + 1.5V$ .

## TABLE 4-1:TC820 CONTROL INPUTTRUTH TABLE

Logic Input					
FREQ/ VOLTS	RANGE/ FREQ	LOGIC	TC820 Function		
Х	Х	1	Logic Probe		
0	0	0	A/D Converter, V <sub>FULL SCALE</sub> = 2 x V <sub>REF</sub>		
0	1	0	A/D Converter, V <sub>FULL SCALE</sub> = 20 x V <sub>REF</sub>		
1	Frequency Counter Input	0	Frequency Counter		
Note 1: 2:	Logic "0" Logic "1"	= DGND = V <sub>DD</sub> -			

#### 4.1.1 FREQ/VOLTS

This input determines whether the TC820 is in the Analog-to-Digital Conversion mode, or in the Frequency Counter mode. When FREQ/VOLTS is connected to  $V_{DD}$ , the TC820 will measure frequency at the RANGE/FREQ input. When unconnected, or connected to DGND, the TC820 will operate as an analog-to-digital converter. This input has an internal 5  $\mu$ A pull-down to DGND.

#### 4.1.2 LOGIC

The LOGIC input is used to activate the logic probe function. When connected to  $V_{DD}$ , the TC820 will enter the Logic Probe mode. The LCD will show "OL" and all decimal points will be off. The decimal point inputs directly control "high" and "low" display annunciators. When LOGIC is unconnected, or connected to DGND, the TC820 will perform analog-to-digital or frequency measurements, as selected by the FREQ/VOLTS input. The LOGIC input has an internal 5  $\mu$ A pull-down to DGND.

#### 4.1.3 RANGE/FREQ

The function of this dual purpose pin is determined by the FREQ/VOLTS input. When FREQ/VOLTS is connected to V<sub>DD</sub>, RANGE/FREQ is the input for the frequency counter function. Pulses at this input are counted with a time-base equal to  $F_{OSC}$ /40,000. Since this input has CMOS input levels (V<sub>DD</sub> – 1.5V and DGND +1.5V), an external buffer is recommended.

When the TC820 analog-to-digital converter function is selected, connecting RANGE/FREQ to  $V_{DD}$  will divide the integration time by 10. Therefore, the RANGE/FREQ input can be used to perform a 10:1 range change without changing external components.

#### 4.1.4 DP0/LO, DP1/HI

The function of these dual purpose pins is determined by the LOGIC input. When the TC820 is in the Analogto-Digital Converter mode, these inputs control the LCD decimal points. See the decimal point truth, Table 4-1. These inputs have internal 5  $\mu$ A pull-downs to DGND when the Voltage/Frequency Measurement mode is active.

#### TABLE 4-1: TC820 DECIMAL POINT TRUTH TABLE

DP1	DP0	LCD
0	0	3999
0	1	399.9
1	0	39.99
1	1	3.999

Connecting the LOGIC input to  $V_{DD}$  places the TC820 in the Logic Probe mode. In this mode, the DP0/LO and DP1/HI inputs control the LCD "low" and "high" annunciators directly. When DP1/HI is connected to  $V_{DD}$ , the "high" annunciator will turn on. When DP0/LO is connected to  $V_{DD}$ , the "low" annunciator and the buzzer will turn on. The internal pull-downs on these pins are disabled when the logic probe function is selected.

These inputs have CMOS logic switching thresholds. For optimum performance as a logic probe, external level shifters are recommended. See the applications section for details.

#### 4.1.5 BUZIN

This input controls the TC820 on-chip buzzer driver. Connecting BUZIN to  $V_{DD}$  will turn the buzzer on. There is an external pull-down to DGND. BUZIN can be used with external circuitry to provide additional functions, such as a fast, audible continuity indication.

#### 4.2 Additional Features

The TC820 is available in 40-pin and 44-pin packages. Several additional features are available in the 44-pin package.

#### 4.2.1 EOC/HOLD

EOC/HOLD is a dual purpose, bi-directional pin. As an output, this pin goes low for 10 clock cycles at the end of each conversion. This pulse latches the conversion data into the display driver section of the TC820.

 $\overline{\text{EOC}}$ /HOLD can be used to hold (or "FREEZE") the display. Connecting this pin to V<sub>DD</sub> inhibits the display update process. Conversions will continue, but the display will not change.  $\overline{\text{EOC}}$ /HOLD will hold the display reading for either analog-to-digital, or frequency measurements.

The input/output structure of the EOC/HOLD pin is shown in Figure 4-2. The output drive current is only a few microAmps, so EOC/HOLD can easily be overdriven by an open collector logic gate, as well as a FET, bipolar transistor, or mechanical switch. When used as an output, EOC/HOLD will have a slow rise and fall time due to the limited output current drive. A CMOS Schmitt trigger buffer is recommended.



FIGURE 4-2: EOC/HOLD Pin.

#### 4.2.2 OVER RANGE (OR), UNDER RANGE (UR)

The OR output will be high when the analog input signal is greater than full scale (3999 counts). The UR output will be high when the display reading is 380 counts or less.

The OR and UR outputs can be used to provide an auto-ranging meter function. By logically ANDing these outputs with the inverted  $\overline{EOC}$ /HOLD output, a single pulse will be generated each time an under ranged or over ranged conversion occurs (Figure 4-2).



FIGURE 4-3: Generating Under Range And Over Range Pulses.

#### 4.2.3 V<sub>DISP</sub>

The V<sub>DISP</sub> input sets the peak-to-peak LCD drive voltage. In the 40-pin package, V<sub>DISP</sub> is connected internally to DGND, providing a typical LCD drive voltage of 5V<sub>P-P</sub>. The 44-pin package includes a separate V<sub>DISP</sub> input for applications requiring a variable or temperature compensated LCD drive voltage. See the applications information for suggested circuits.

#### 5.0 TYPICAL APPLICATIONS

#### 5.1 Power Supplies

The TC820 is designed to operate from a single power supply such as a 9V battery (Figure 5-1). The converter will operate over a range of 7V to 15V. For battery operation, analog common (COM) provides a Common mode bias voltage (see analog common discussion in the theory of operation section). However, measurements cannot be referenced to battery ground. To do so will exceed the Negative Common mode voltage limit.



FIGURE 5-1: Powering the TC820 from a Single 9V Battery.

A battery with voltage between 3.5V and 7V can be used to power the TC820, when used with a voltage doubler, as shown in Figure 5-2. The voltage doubler uses the TC7660 and two external capacitors. With this configuration, measurements can be referenced either to analog common or to battery ground.



FIGURE 5-2: Powering the TC820 from a Low Voltage Battery.

#### 5.2 Digital Ground (DGND)

Digital ground is generated from an internal zener diode (Figure 5-3). The voltage between  $V_{DD}$  and DGND is the internal supply voltage for the digital section of the TC820. DGND will sink a minimum of 3 mA.

DGND establishes the low logic level reference for the TC820 mode select inputs, and for the frequency and logic probe inputs. The DGND pin can be used as the negative supply for external logic gates, such as the logic probe buffers. To ensure correct counter operation at high frequency, connect a 1  $\mu$ F capacitor from DGND to V<sub>DD</sub>.

DGND also provides the drive voltage for the LCD. The TC820 40-pin package internally connects the LCD  $V_{DISP}$  pin to DGND, and provides an LCD drive voltage of about  $5V_{P-P}$ . In the 44-pin package, connecting the  $V_{DISP}$  pin to DGND will provide a 5V LCD drive voltage.



FIGURE 5-3: DGND and Com Outputs.

#### 5.3 Digital Input Logic Levels

Logic levels for the TC820 digital inputs are referenced to  $V_{DD}$  and DGND. The high level threshold is  $V_{DD}$  – 1.5V, and the low logic level is DGND + 1.5V. In most cases, digital inputs will be connected directly to  $V_{DD}$  with a mechanical switch. CMOS gates can also be used to control the logic inputs, as shown in the logic probe inputs section.

#### 5.4 Clock Oscillator

The TC820 oscillator can be controlled with either a crystal, or with an inexpensive resistor capacitor combination. The crystal circuit, shown in Figure 5-4, is recommended when high accuracy is required in the Frequency Counter mode. The 40 kHz crystal is a standard frequency for ultrasonic alarms, and will provide a 1-second time-base for the counter or 2.5 analog-to-digital conversions per second. Consult the crystal manufacturer for detailed applications information.



FIGURE 5-4: Circuit.

Suggested Crystal Oscillator

Where low cost is important, the RC circuit of Figure 5-5 can be used. The frequency of this circuit will be approximately:

#### **EQUATION 5-1:**



FIGURE 5-5:

RC Oscillator Circuit.

Typical values are R = 10 k $\Omega$  and C = 68pF. The resistor value should be  $\geq$  100 k $\Omega$ . For accurate frequency measurement, an RC oscillator frequency of 40 kHz is required.

#### 5.5 System Timing

All system timing is derived from the clock oscillator. The clock oscillator is divided by 2 prior to clocking the A/D counters. The clock is also divided by 8 to drive the buzzer, by 240 to generate the LCD backplane frequency, and by 40,000 for the frequency counter time-base. A simplified diagram of the system clock is shown in Figure 5-6.



FIGURE 5-6: System Clock Generation.

#### 5.6 Component Value Selection

#### 5.6.1 AUTO-ZERO CAPACITOR - C<sub>AZ</sub>

The value of the auto-zero capacitor ( $C_{AZ}$ ) has some influence on system noise. A 0.47  $\mu$ F capacitor is recommended; a low dielectric absorption capacitor (Mylar) is required.

#### 5.6.2 REFERENCE VOLTAGE CAPACITOR - C<sub>REF</sub>

The reference voltage capacitor used to ramp the integrator output voltage back to zero during the reference integrate cycle is stored on  $C_{REF}$ . A 0.1  $\mu$ F capacitor is typical. A good quality, low leakage capacitor (such as Mylar) should be used.

#### 5.6.3 INTEGRATING CAPACITOR - CINT

 $C_{INT}$  should be selected to maximize integrator output voltage swing without causing output saturation. Analog common will normally supply the differential voltage reference. For this case, a  $\pm 2V$  integrator output swing is optimum when the analog input is near full scale. For 2.5 readings/second ( $F_{OSC}$  = 40 kHz) and  $V_{FS}$  = 400 mV, a 0.22  $\mu F$  value is suggested. If a different oscillator frequency is used,  $C_{INT}$  must be changed in inverse proportion to maintain the nominal  $\pm 2V$  integrator swing.

An exact expression for C<sub>INT</sub> is:

#### **EQUATION 5-2:**

Where:	C <sub>IN</sub>	$T = \frac{4000 V_{FS}}{V_{INT} R_{INT} F_{OSC}}$		
_				
FOSC	=	Clock Frequency		
$V_{FS}$	=	Full-Scale Input Voltage		
R <sub>INT</sub>	=	Integrating Resistor		
V <sub>INT</sub>	=	Desired Full-Scale Integrator Output Swing		

C<sub>INT</sub> must have low dielectric absorption to minimize rollover error. A polypropylene capacitor is recommended.

#### 5.6.4 INTEGRATING RESISTOR - RINT

The input buffer amplifier and integrator are designed with class A output stages. The integrator and buffer can supply 40  $\mu$ A drive currents with negligible linearity errors. R<sub>INT</sub> is chosen to remain in the output stage linear drive region, but not so large that printed circuit board leakage currents induce errors. For a 400 mV full-scale, R<sub>INT</sub> should be about 100 k $\Omega$ .

#### 5.7 Reference Voltage Selection

A full-scale reading (4000 counts for TC820) requires the input signal be twice the reference voltage. See Reference Voltage Selection, Table 5-1 below.

#### TABLE 5-1: REFERENCE VOLTAGE SELECTION

Full Scale Input Voltage (V <sub>FS</sub> ) (Note 1)	V <sub>REF</sub>	Resolution	
200 mV	(Note 2)	—	
400 mV	200 mV	10 µV	
1V	500 mV	250 μV	
2V (Notes 3, 4)	1V	500 µV	

- Note 1: TC820 in A/D Converter mode, RANGE/ FREQ = logic low.
  - 2: Not recommended.
  - V<sub>FS</sub> > 2V may exceed the Input Common mode range. See Section 3.2.7 "10:1 Range Change".
  - Full-scale voltage values are not limited to the values shown. For example, TC820
    V<sub>FS</sub> can be any value from 400 mV to 2V.

In some applications, a scale factor other than unity may exist between a transducer output voltage and the required digital reading. Assume, for example, that a pressure transducer output is 800 mV for 4000 lb/in<sup>2</sup>. Rather than dividing the input voltage by two, the reference voltage should be set to 400 mV. This permits the transducer input to be used directly.

The internal voltage reference potential available at analog common will normally be used to supply the converter's reference voltage. This potential is stable whenever the supply potential is greater than approximately 7V. The low battery detection circuit and analog common operate from the same internal reference. This ensures that the low battery annunciator will turn on at the time the internal reference begins to lose regulation.

The TC820 can also operate with an external reference. Figure 5-7 shows internal and external reference applications.



#### 5.8 Ratiometric Resistance Measurements

The TC820 true differential input and differential reference make ratiometric readings possible. In ratiometric operation, an unknown resistance is measured with respect to a known standard resistance. No accurately defined reference voltage is needed.

The unknown resistance is put in series with a known standard and a current is passed through the pair (Figure 5-8). The voltage developed across the unknown is applied to the input and voltages across the known resistor applied to the reference input. If the unknown equals the standard, the input voltage will equal the reference voltage and the display will read 2000. The displayed reading can be determined from the following expression:

#### **EQUATION 5-3:**



The display will over range for values of  $R_{UNKNOWN} \geq 2 \; x \; R_{STANDARD}.$ 



FIGURE 5-8: Low Parts Count Ratiometric Resistance Measurement.

#### 5.9 Buffering the FREQ Input

When the FREQ/VOLTS input is high and the LOGIC input is low, the TC820 will count pulses at the RANGE/ FREQ input. The time-base will be  $F_{OSC}/40,000$ , or 1 second with a 40kHz clock. The signal to be measured should swing from V<sub>DD</sub> to DGND. The RANGE/FREQ input has CMOS input levels without hysteresis. For best results, especially with low frequency sine-wave inputs, an external buffer with hysteresis should be added. A typical circuit is shown in Figure 5-9.



FIGURE 5-9: Frequency Counter External Buffer.

#### 5.10 Logic Probe Inputs

The DP0/LO and DP1/HI inputs provide the logic probe inputs when the LOGIC input is high. Driving either DP0/LO or DP1/HI to a logic high will turn on the appropriate LCD annunciator. When DP0/LO is high, the buzzer will be on.

To provide a "single input" logic probe function, external buffers should be used. A simple circuit is shown in Figure 5-10. This circuit will turn the appropriate annunciator on for high and low level inputs.





If carefully controlled logic thresholds are required, a window comparator can be used. Figure 5-11 shows a typical circuit. This circuit will turn on the high or low annunciators when the logic thresholds are exceeded, but the resistors connected from DP0/LO and DP1/HI to DGND will turn both annunciators off when the logic probe is unconnected.

The TC820 logic inputs are not latched internally, so pulses of short duration will usually be difficult or impossible to see. To display short pulses properly, the input pulse should be "stretched." The circuit of Figure 5-11 shows capacitors added across the input pull-down resistors to stretch the input pulse and permit viewing short duration input pulses.



FIGURE 5-11: Window Comparator Logic Probe.

#### 5.11 External Peak Detection

The TC820 will hold the highest A/D conversion or frequency reading indefinitely when the PKHOLD input is connected to  $V_{DD}$ . However, the analog peak input must be present during the A/D converter's signal integrate period. For slowly changing signals, such as temperature, the peak reading will be properly converted and held.

If rapidly changing analog signals must be held, an external peak detector should be added. An inexpensive circuit can be made from an op amp and a few discrete components, as shown in Figure 5-12. The droop rate of the external peak detector should be adjusted so that the held voltage will not decay below the desired accuracy level during the converter's 400 ms conversion time.



FIGURE 5-12: External Peak Detector.

#### 5.12 Liquid Crystal Display (LCD)

The TC820 drives a triplex (multiplexed 3:1) LCD with three backplanes. The LCD can include decimal points, polarity sign, and annunciators for over range, peak hold, high and low logic levels, and low battery. Table 5-2 shows the assignment of the display segments to the backplanes and segment drive lines. The backplane drive frequency is obtained by dividing the oscillator frequency by 240.

Backplane waveforms are shown in Figure 5-13. These appear on outputs BP1, BP2, and BP3. They remain the same, regardless of the segments being driven.



FIGURE 5-13: Backplane Waveforms.

Other display output lines have waveforms that vary depending on the displays values. Figure 5-13 shows a set of waveforms for the a, g, d outputs of one digit for several combinations of "on" segments.



FIGURE 5-14: Typical Display Output Waveforms.

TABLE 5-2:LCD BACKPLANE AND<br/>SEGMENT ASSIGNMENTS

40-Pin (PDIP)	44-Pin (PQFP)	LCD Display Pin Number	BP1	BP2	BP3
1	40	3	LOW		
2	41	4	A4	""	
3	42	5	B4	G4	E4
4	43	6	HIGH	C4	D4
5	44	7	A3	F3	DP3
6	1	8	B3	G3	E3
7	2	9	OVER	C3	D3
8	3	10	A2	F2	DP2
9	4	11	B2	G2	E2
10	5	12	PEAK	C2	D2
11	6	13	A1	F1	DP1
12	7	14	B1	G1	E1
13	8	2,16*	_	C1	D1
14	9	1	BP1		BATT
15	10	15	LOW	BP2	BP3

Connect both pins 2 and 16 of LCD to TC820 BP3 of output.

#### 5.13 LCD Source

Although most users will design their own custom LCD, a standard display for the TC820 (Figure 5-15), Part No. ST-1355-M1, is available from the following sources:

Crystaloid (USA) Crystaloid Electronics P.O. Box 628 5282 Hudson Drive Hudson, OH 44238 Phone: 216-655-2429

Crystaloid (Europe) Rep. France 102, rue des Nouvelles F92150 Suresnes France Phone: 33-1-42-04-29-25 Fax: 33-1-45-06-46-99



FIGURE 5-15:

Typical TC820 LCD.

#### 5.14 Annunciator Output

The annunciator output is a square wave running at the backplane frequency (for example, 167Hz when  $F_{OSC} = 40$ kHz). The peak-to-peak amplitude is equal to  $(V_{DD} - V_{DISP})$ . Connecting an annunciator of the LCD to the annunciator output turns it on; connecting it to its backplane turns it off.

#### 5.15 LCD Drive Voltage (V<sub>DISP</sub>)

The peak-to-peak LCD drive voltage is equal to ( $V_{DD} - V_{DISP}$ ). In the 40-pin dual in-line package (DIP),  $V_{DISP}$  is internally connected to DGND, providing a typical LCD drive voltage of  $5V_{P-P}$ 

For applications with a wide temperature range, some LCDs require that the drive levels vary with temperature to maintain good viewing angle and display contrast. In this case, the TC820 44-pin package provides a pin connection for V<sub>DISP</sub> Figure 5-16 shows TC820 circuits that can be adjusted to give a temperature compensation of about 10mV/°C between V<sub>DD</sub> and V<sub>DISP</sub> The diode between GND and V<sub>DISP</sub> should have a low turn on voltage because V<sub>DISP</sub> cannot exceed 0.3V below GND.

#### 5.16 Crystal Source

Two sources of the 40kHz crystal are:

Statek Corp. 512 N. Main St. Orange, CA 92668 Phone: 714-639-7810 Fax: 714-997-1256 Part #: CX-1V-40.0

SPK Electronics 2F-1, No. 312, Sec, 4, Jen Ai Rd. Taipei, Taiwan R.O.C. Phone: (02) 754-2677 Fax: 886-2-708-4124 Part #: QRT-38-40.0kHz





#### 6.0 PACKAGING INFORMATION

#### 6.1 Package Marking Information





Legend	: XXX	Customer-specific information			
	Y	Year code (last digit of calendar year)			
	ΥY	/ear code (last 2 digits of calendar year)			
	WW	Week code (week of January 1 is week '01')			
	MNN	Alphanumeric traceability code			
	(e3)	Pb-free JEDEC designator for Matte Tin (Sn)			
	*	This package is Pb-free. The Pb-free JEDEC designator (e3)			
		can be found on the outer packaging for this package.			
Note:	In the ever	nt the full Microchip part number cannot be marked on one line, it will			
	be carried over to the next line, thus limiting the number of available				
	characters	for customer-specific information.			

TC820CKW

@30743256

#### 44-Lead Plastic Leaded Chip Carrier (LW) – Square [PLCC]

**Note:** For the most current package drawings, please see the Microchip Packaging Specification located at http://www.microchip.com/packaging



Units		INCHES			
	<b>Dimension Limits</b>	MIN	NOM	MAX	
Number of Pins	N		44		
Pitch	е		.050		
Overall Height	A	.165	.172	.180	
Contact Height	A1	.090	.105	.120	
Molded Package to Contact	A2	.062	_	.083	
Standoff §	A3	.020	_	_	
Corner Chamfer	CH1	.042	_	.048	
Chamfers	CH2	_	_	.020	
Side Chamfer	CH3	.042	_	.056	
Overall Width	E	.685	.690	.695	
Overall Length	D	.685	.690	.695	
Molded Package Width	E1	.650	.653	.656	
Molded Package Length	D1	.650	.653	.656	
Footprint Width	E2	.582	.610	.638	
Footprint Length	D2	.582	.610	.638	
Lead Thickness	С	.0075	_	.0125	
Upper Lead Width	b1	.026	_	.032	
Lower Lead Width	b	.013	_	.021	

#### Notes:

1. Pin 1 visual index feature may vary, but must be located within the hatched area.

2. § Significant Characteristic.

3. Dimensions D1 and E1 do not include mold flash or protrusions. Mold flash or protrusions shall not exceed .010" per side.

4. Dimensioning and tolerancing per ASME Y14.5M.

Microchip Technology Drawing C04-048B

#### 40-Lead Plastic Dual In-Line (PL) – 600 mil Body [PDIP]

**Note:** For the most current package drawings, please see the Microchip Packaging Specification located at http://www.microchip.com/packaging



	Units		INCHES		
Dimension	n Limits	MIN	NOM	MAX	
Number of Pins	N		40		
Pitch	е		.100 BSC		
Top to Seating Plane	A	-	—	.250	
Molded Package Thickness	A2	.125	_	.195	
Base to Seating Plane	A1	.015	_	_	
Shoulder to Shoulder Width	E	.590	_	.625	
Molded Package Width	E1	.485	_	.580	
Overall Length	D	1.980	_	2.095	
Tip to Seating Plane	L	.115	_	.200	
Lead Thickness	с	.008	_	.015	
Upper Lead Width	b1	.030	_	.070	
Lower Lead Width	b	.014	_	.023	
Overall Row Spacing §	eB	—	_	.700	

#### Notes:

1. Pin 1 visual index feature may vary, but must be located within the hatched area.

- 2. § Significant Characteristic.
- 3. Dimensions D and E1 do not include mold flash or protrusions. Mold flash or protrusions shall not exceed .010" per side.
- 4. Dimensioning and tolerancing per ASME Y14.5M.

BSC: Basic Dimension. Theoretically exact value shown without tolerances.

Microchip Technology Drawing C04-016B

#### 44-Lead Plastic Metric Quad Flatpack (KW) – 10x10x2 mm Body, 3.20 mm [MQFP]

**Note:** For the most current package drawings, please see the Microchip Packaging Specification located at http://www.microchip.com/packaging



	Units			MILLIMETERS			
1	Dimension Limits	MIN NOM MAX					
Number of Leads	N		44				
Lead Pitch	е		0.80 BSC				
Overall Height	A	-	-	2.45			
Molded Package Thickness	A2	1.80	2.00	2.20			
Standoff §	A1	0.00	-	0.25			
Foot Length	L	0.73 0.88 1.03					
Footprint	L1	1.60 REF					
Foot Angle	¢	0° – 7°					
Overall Width	E	13.20 BSC					
Overall Length	D	13.20 BSC					
Molded Package Width	E1	10.00 BSC					
Molded Package Length	D1	10.00 BSC					
Lead Thickness	С	0.11 – 0.23					
Lead Width	b	0.29 – 0.45					
Mold Draft Angle Top	α	5° – 16°					
Mold Draft Angle Bottom	β	5° – 16°					

#### Notes:

1. Pin 1 visual index feature may vary, but must be located within the hatched area.

2. Chamfers at corners are optional; size may vary.

3. Dimensions D1 and E1 do not include mold flash or protrusions. Mold flash or protrusions shall not exceed 0.25 mm per side.

Dimensioning and tolerancing per ASME Y14.5M.
BSC: Basic Dimension. Theoretically exact value shown without tolerances.
REF: Reference Dimension, usually without tolerance, for information purposes only.

5. § Significant Characteristic.

Microchip Technology Drawing C04-071B

## TC820

NOTES:

### APPENDIX A: REVISION HISTORY

#### **Revision C (November 2007)**

The following is the list of modifications:

- 1. Changed status of document to EOL.
- 2. Updated Package Marking Information
- 3. Added Package Outline Drawings
- 4. Added Appendix A History page
- 5. Added Product Identification System page

#### Revision B (May 2002)

The following is the list of modifications:

1. Undocumented Changes

#### **Revision A (April 2002)**

• Original Release of this Document.

## TC820

NOTES:

#### **PRODUCT IDENTIFICATION SYSTEM**

To order or obtain information, e.g., on pricing or delivery, refer to the factory or the listed sales office.

PART NO.	x <u>/xx</u>	Ex	amples:	
Device Tem R	perature Package ange	a)	TC820CLI:	3-3/4 A/D Converter, 44LD PLCC package.
<b></b>		b)	TC820CPI:	3-3/4 A/D Converter, 40LD PDIP package.
Device	TC820: 3-3/4 Digit A/D, with Frequency Counter and Probe	c)	TC820CBU:	3-3/4 A/D Converter, 44LD MQFP package.
Temperature Range	$C = 0^{\circ}C \text{ to } +70^{\circ}C$			
Package	LW = Plastic Leaded Chip Carrier (PLCC), 44-lead PL = Plastic DIP, (600 mil Body), 40-lead KW = Plastic Metric Quad Flatpack, (MQFP), 44-lead			

## TC820

NOTES:

#### Note the following details of the code protection feature on Microchip devices:

- Microchip products meet the specification contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is one of the most secure families of its kind on the market today, when used in the intended manner and under normal conditions.
- There are dishonest and possibly illegal methods used to breach the code protection feature. All of these methods, to our knowledge, require using the Microchip products in a manner outside the operating specifications contained in Microchip's Data Sheets. Most likely, the person doing so is engaged in theft of intellectual property.
- Microchip is willing to work with the customer who is concerned about the integrity of their code.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of their code. Code protection does not mean that we are guaranteeing the product as "unbreakable."

Code protection is constantly evolving. We at Microchip are committed to continuously improving the code protection features of our products. Attempts to break Microchip's code protection feature may be a violation of the Digital Millennium Copyright Act. If such acts allow unauthorized access to your software or other copyrighted work, you may have a right to sue for relief under that Act.

Information contained in this publication regarding device applications and the like is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION, INCLUDING BUT NOT LIMITED TO ITS CONDITION, QUALITY, PERFORMANCE, MERCHANTABILITY OR FITNESS FOR PURPOSE. Microchip disclaims all liability arising from this information and its use. Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights.

## QUALITY MANAGEMENT SYSTEM CERTIFIED BY DNV ISO/TS 16949:2002

#### Trademarks

The Microchip name and logo, the Microchip logo, Accuron, dsPIC, KEELOQ, KEELOQ logo, microID, MPLAB, PIC, PICmicro, PICSTART, PRO MATE, rfPIC and SmartShunt are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

AmpLab, FilterLab, Linear Active Thermistor, Migratable Memory, MXDEV, MXLAB, SEEVAL, SmartSensor and The Embedded Control Solutions Company are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Analog-for-the-Digital Age, Application Maestro, CodeGuard, dsPICDEM, dsPICDEM.net, dsPICworks, dsSPEAK, ECAN, ECONOMONITOR, FanSense, FlexROM, fuzzyLAB, In-Circuit Serial Programming, ICSP, ICEPIC, Mindi, MiWi, MPASM, MPLAB Certified logo, MPLIB, MPLINK, PICkit, PICDEM, PICDEM.net, PICLAB, PICtail, PowerCal, PowerInfo, PowerMate, PowerTool, REAL ICE, rfLAB, Select Mode, Smart Serial, SmartTel, Total Endurance, UNI/O, WiperLock and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

All other trademarks mentioned herein are property of their respective companies.

 $\ensuremath{\textcircled{\sc 0}}$  2007, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.



Microchip received ISO/TS-16949:2002 certification for its worldwide headquarters, design and wafer fabrication facilities in Chandler and Tempe, Arizona; Gresham, Oregon and design centers in California and India. The Company's quality system processes and procedures are for its PIC® MCUs and dsPIC® DSCs, KEELOQ® code hopping devices, Serial EEPROMs, microperipherals, nonvolatile memory and analog products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001:2000 certified.



## WORLDWIDE SALES AND SERVICE

#### AMERICAS

Corporate Office 2355 West Chandler Blvd. Chandler, AZ 85224-6199 Tel: 480-792-7200 Fax: 480-792-7277 Technical Support: http://support.microchip.com Web Address: www.microchip.com

Atlanta Duluth, GA Tel: 678-957-9614 Fax: 678-957-1455

Boston Westborough, MA Tel: 774-760-0087 Fax: 774-760-0088

Chicago Itasca, IL Tel: 630-285-0071 Fax: 630-285-0075

**Dallas** Addison, TX Tel: 972-818-7423 Fax: 972-818-2924

Detroit Farmington Hills, MI Tel: 248-538-2250 Fax: 248-538-2260

Kokomo Kokomo, IN Tel: 765-864-8360 Fax: 765-864-8387

Los Angeles Mission Viejo, CA Tel: 949-462-9523 Fax: 949-462-9608

Santa Clara Santa Clara, CA Tel: 408-961-6444 Fax: 408-961-6445

Toronto Mississauga, Ontario, Canada Tel: 905-673-0699 Fax: 905-673-6509

#### ASIA/PACIFIC

Asia Pacific Office Suites 3707-14, 37th Floor Tower 6, The Gateway Harbour City, Kowloon Hong Kong Tel: 852-2401-1200 Fax: 852-2401-3431 Australia - Sydney

Tel: 61-2-9868-6733 Fax: 61-2-9868-6755

**China - Beijing** Tel: 86-10-8528-2100 Fax: 86-10-8528-2104

**China - Chengdu** Tel: 86-28-8665-5511 Fax: 86-28-8665-7889

**China - Fuzhou** Tel: 86-591-8750-3506 Fax: 86-591-8750-3521

**China - Hong Kong SAR** Tel: 852-2401-1200 Fax: 852-2401-3431

China - Nanjing Tel: 86-25-8473-2460 Fax: 86-25-8473-2470

**China - Qingdao** Tel: 86-532-8502-7355 Fax: 86-532-8502-7205

**China - Shanghai** Tel: 86-21-5407-5533 Fax: 86-21-5407-5066

**China - Shenyang** Tel: 86-24-2334-2829 Fax: 86-24-2334-2393

**China - Shenzhen** Tel: 86-755-8203-2660 Fax: 86-755-8203-1760

**China - Shunde** Tel: 86-757-2839-5507 Fax: 86-757-2839-5571

**China - Wuhan** Tel: 86-27-5980-5300 Fax: 86-27-5980-5118

**China - Xian** Tel: 86-29-8833-7252 Fax: 86-29-8833-7256

#### ASIA/PACIFIC

India - Bangalore Tel: 91-80-4182-8400 Fax: 91-80-4182-8422

**India - New Delhi** Tel: 91-11-4160-8631 Fax: 91-11-4160-8632

India - Pune Tel: 91-20-2566-1512 Fax: 91-20-2566-1513

**Japan - Yokohama** Tel: 81-45-471- 6166 Fax: 81-45-471-6122

**Korea - Daegu** Tel: 82-53-744-4301 Fax: 82-53-744-4302

Korea - Seoul Tel: 82-2-554-7200 Fax: 82-2-558-5932 or 82-2-558-5934

Malaysia - Kuala Lumpur Tel: 60-3-6201-9857 Fax: 60-3-6201-9859

**Malaysia - Penang** Tel: 60-4-227-8870 Fax: 60-4-227-4068

Philippines - Manila Tel: 63-2-634-9065 Fax: 63-2-634-9069

**Singapore** Tel: 65-6334-8870 Fax: 65-6334-8850

**Taiwan - Hsin Chu** Tel: 886-3-572-9526 Fax: 886-3-572-6459

**Taiwan - Kaohsiung** Tel: 886-7-536-4818 Fax: 886-7-536-4803

**Taiwan - Taipei** Tel: 886-2-2500-6610 Fax: 886-2-2508-0102

**Thailand - Bangkok** Tel: 66-2-694-1351 Fax: 66-2-694-1350

#### EUROPE

Austria - Wels Tel: 43-7242-2244-39 Fax: 43-7242-2244-393 Denmark - Copenhagen Tel: 45-4450-2828 Fax: 45-4485-2829

France - Paris Tel: 33-1-69-53-63-20 Fax: 33-1-69-30-90-79

**Germany - Munich** Tel: 49-89-627-144-0 Fax: 49-89-627-144-44

**Italy - Milan** Tel: 39-0331-742611 Fax: 39-0331-466781

**Netherlands - Drunen** Tel: 31-416-690399 Fax: 31-416-690340

**Spain - Madrid** Tel: 34-91-708-08-90 Fax: 34-91-708-08-91

**UK - Wokingham** Tel: 44-118-921-5869 Fax: 44-118-921-5820