6-Channel LED Driver with I²C[™] Interface

Description

The CAT3626 is a high efficiency 1x/1.5x fractional charge pump with programmable dimming current in six LED channels. To ensure uniform brightness in LCD backlight applications, each LED channel delivers an accurate regulated current.

Low noise and input ripple is achieved by operating at a constant switching frequency of 1 MHz which allows the use of small external ceramic capacitors. The 1x/1.5x fractional charge pump supports a wide range of input voltages from 3 V to 5.5 V with efficiency up to 91%, and is ideal for Li–Ion battery powered devices.

The LED channels are configured into three independent pairs, each containing 2 matched channels. Each pair can be separately programmed from zero to 32 mA, in 0.5 mA resolution steps, using the I^2C serial interface. Any individual channel can be disabled while others remain active. When the enable input (EN) is low, the device is in shutdown mode drawing zero current.

The device is available in a 16-pad TQFN package with a max height of 0.8 mm.

Features

- Drives 6 LED Channels
- Independent Current on 3 Pairs of LEDs
- I²C Serial Interface Programming
- Adjustable Current to 32 mA in 0.5 mA Step
- Power Efficiency up to 91%
- Fractional Pump 1x/1.5x
- Low Noise Input Ripple
- Fixed High Frequency Operation 1 MHz
- "Zero" Current Shutdown Mode
- Soft Start and Current Limiting
- Short Circuit Protection
- Thermal Shutdown Protection
- These Devices are Pb–Free, Halogen Free/BFR Free and are RoHS Compliant

Applications

- RGB LEDs
- LCD and Keypad Backlighting
- Cellular Phones, PDAs
- Digital Cameras



ON Semiconductor®

http://onsemi.com



TQFN-16 HV4 SUFFIX CASE 510AE



(4 x 4 mm) (Top View)

MARKING DIAGRAMS



G626 = CAT3626HV4-T2 CDAJ = CAT3626HV4-GT2 A = Assembly Location XXX = Last Three Digits of Assembly Lot Number Y = Production Year (Last Digit) M = Production Month (1-9, A, B, C) CC = Country of Origin (Two Digit)

ORDERING INFORMATION

Device	Package	Shipping
CAT3626HV4-T2 (Note 1)	TQFN-16 (Pb-Free)	2,000/
CAT3626HV4-GT2 (Note 2)	TQFN-16 (Pb-Free)	Tape & Reel

1. Matte-Tin Plated Finish (RoHS-compliant).

2. NiPdAu Plated Finish (RoHS-compliant).



Figure 1. Typical Application Circuit

Table 1. ABSOLUTE MAXIMUM RATINGS

Parameters	Ratings	Units
VIN, LEDxx voltage	6	V
VOUT, C1±, C2± voltage	7	V
EN, SDA, SCL voltage	VIN + 0.7 V	V
Storage Temperature Range	-65 to +160	°C
Junction Temperature Range	-40 to +150	°C
Lead Temperature	300	°C

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

Table 2. RECOMMENDED OPERATING CONDITIONS

Parameter	Range	Units
VIN	3 to 5.5	V
Ambient Temperature Range	-40 to +85	°C
LED forward voltage	Up to 4.2	V
I _{LED} per LED pin	0 to 32	mA

NOTE: Typical application circuit with external components is shown above.

 $\label{eq:constraint} \begin{array}{l} \textbf{Table 3. ELECTRICAL OPERATING CHARACTERISTICS} \\ V_{\text{IN}} = 3.6 \text{ V}, \text{ EN} = \text{High, ambient temperature of } 25^{\circ}\text{C} \text{ (over recommended operating conditions unless specified otherwise)} \end{array}$

Symbol	Parameter	Test Conditions	Min	Тур	Max	Units
l _Q	Quiescent Current	1x mode, all LEDs Off 1x mode, all LEDs On 1.5x mode, all LEDs Off		0.5 2.2 3.5		mA
I _{QSHDN}	Shutdown Current	V _{EN} = 0 V		0	1	μΑ
I _{LED}	LED Current Range with 6 LEDs		0		32	mA
I _{LED-ACC}	LED Current Accuracy	$1 \text{ mA} \leq I_{\text{LED}} \leq 31 \text{ mA}$		±3		%
I _{LED-DEV}	LED Channel Matching	(I _{LED} – I _{LEDAVG}) / I _{LEDAVG}		±3		%
R _{OUT}	Output Resistance (open loop)	1x mode, I _{OUT} = 120 mA 1.5x mode, I _{OUT} = 120 mA		0.5 2.8		Ω
F _{OSC}	Charge Pump Frequency		0.8	1	1.3	MHz
I _{SC_MAX}	Output short circuit Current Limit	V _{OUT} < 0.5 V		60		mA
I _{IN_MAX}	Input Current Limit	1x mode, V _{OUT} > 1 V		300		mA
I _{EN} V _{HI-EN} V _{LO-EN}	EN Pin – Input Leakage – Logic High Level – Logic Low Level		-1 1.3		1 0.4	μA V V
V _{HI} V _{LO}	I ² C SDA, SCL – High Level Input Voltage – Low Level Input Voltage		$0.7 \times V_{IN}$		0.3 x V _{IN}	V V
T _{SD}	Thermal Shutdown			165		°C
T _{HYS}	Thermal Hysteresis			20		°C
V _{UVLO}	Under-voltage lock out (UVLO) threshold			2		V

Symbol	Parameter	Min	Тур	Max	Unit
f _{SCL}	Clock Frequency			400	kHz
t _{AA}	SCL Low to SDA Data Out and ACK Out			0.9	μs
t _{BUF}	Bus Free Time Before a New Transmission Can Start	1.2			μs
t _{HD:STA}	Start Condition Hold Time	0.6			μs
t _{LOW}	Clock Low Period	1.2			μs
t _{HIGH}	Clock High Period	0.6			μs
t _{SU:STA}	Start Condition Setup Time (For a Repeated Condition)	0.6			μs
t _{HD:DAT}	Data In Hold Time	0			ns
t _{SU:DAT}	Data In Setup Time	100			ns
t _R	SDA and SCL Rise Time			0.3	μs
t _F	SDA and SCL Fall Time			300	ns
t _{SU:STO}	Stop Condition Setup Time	0.6			μs
t _{DH}	Data Out Hold Time	50			ns

Table 4. A.C. CHARACTERISTICSFor 3 V \leq V_{IN} \leq 5.5 V, over full ambient temperature range -40°C to +125°C(over recommended operating conditions unless specified otherwise).



Figure 2. I²C Bus Timing Characteristics

TYPICAL CHARACTERISTICS

(V_{IN} = 3.6 V, I_{OUT} = 90 mA (6 LEDs at 15 mA), EN = V_{IN}, $C_{IN} = C_1 = C_2 = C_{OUT} = 1 \mu$ F, $T_{AMB} = 25^{\circ}$ C, unless otherwise specified.)



TYPICAL CHARACTERISTICS

(V_{IN} = 3.6 V, I_{OUT} = 90 mA (6 LEDs at 15 mA), EN = V_{IN}, $C_{IN} = C_1 = C_2 = C_{OUT} = 1 \ \mu$ F, $T_{AMB} = 25^{\circ}$ C, unless otherwise specified.)



TYPICAL CHARACTERISTICS

(V_{IN} = 3.6 V, I_{OUT} = 90 mA (6 LEDs at 15 mA), EN = V_{IN}, $C_{IN} = C_1 = C_2 = C_{OUT} = 1 \mu$ F, $T_{AMB} = 25^{\circ}$ C, unless otherwise specified.)







Figure 16. Power Up with 6 LEDs at 15 mA (1.5x Mode)







Figure 20. Operating Waveforms in 1x Mode



Figure 17. Enable Power Down (1x Mode)



Figure 19. Switching Waveforms in 1.5x Mode

TYPICAL CHARACTERISTICS

 $(V_{IN} = 3.6 \text{ V}, I_{OUT} = 90 \text{ mA} \text{ (6 LEDs at 15 mA)}, \text{ EN} = V_{IN}, C_{IN} = C_1 = C_2 = C_{OUT} = 1 \text{ } \mu\text{F}, T_{AMB} = 25^{\circ}\text{C}, \text{ unless otherwise specified.})$





Figure 23. SDA, SCL V_{IH} vs. Supply Voltage

Figure 24. SDA, SCL VIL vs. Supply Voltage

Pin #	Name	Function
1	LEDA1	Cathode terminal of LED A1
2	SDA	I ² C Serial data input/output
3	SCL	I ² C Serial clock input
4	EN	Enable input
5	VOUT	Charge pump output connected to the LED anodes
6	VIN	Supply voltage
7	C1-	Bucket capacitor 1 terminal
8	C1+	Bucket capacitor 1 terminal
9	C2-	Bucket capacitor 2 terminal
10	C2+	Bucket capacitor 2 terminal
11	GND	Ground reference
12	LEDC2	Cathode terminal of LED C2
13	LEDC1	Cathode terminal of LED C1
14	LEDB2	Cathode terminal of LED B2
15	LEDB1	Cathode terminal of LED B1
16	LEDA2	Cathode terminal of LED A2
	TAB	Connect to Ground on PCB

Table 5. PIN DESCRIPTIONS

Pin Function

VIN is the supply pin for the charge pump. A small $1 \mu F$ ceramic bypass capacitor is required between the VIN pin and ground near the device. The operating input voltage range is from 2.2 V to 5.5 V. Whenever the input supply falls below the undervoltage threshold (2 V), all LEDs channels will be automatically disabled.

EN is the enable logic input for the driver. Guaranteed levels of logic high and logic low are set at 1.3 V and 0.4 V respectively. When EN is initially taken high, the device becomes enabled and all LED currents remain at 0 mA. To place the device into zero current shutdown mode, the EN pin must be held low.

SDA is the I²C serial data line. This is a bidirectional line allowing data to be written into and read from the four registers in the driver. Registers RegA/B/C set the LED current in each pair of channels, while RegEn sets the On/Off state independently of each channel.

SCL is the I^2C serial clock input.

VOUT is the charge pump output that is connected to the LED anodes. A small 1 μ F ceramic bypass capacitor is required between the VOUT pin and ground near the device.

GND is the ground reference for the charge pump. The pin must be connected to the ground plane on the PCB.

C1+, C1– are connected to each side of the 1 μ F ceramic bucket capacitor C1.

C2+, C2– are connected to each side of the 1 μ F ceramic bucket capacitor C2.

LEDxx provide the internally regulated current to the six LED cathodes. These pins enter a high-impedance zero-current state whenever the device is placed in shutdown mode. In applications using less than six LEDs, the unused channels should be disabled through the RegEn register.

TAB is the exposed pad underneath the package. For best thermal performance, the tab should be soldered to the PCB and connected to the ground plane.

Block Diagram



Figure 25. CAT3626 Functional Block Diagram

Basic Operation

At power–up, the CAT3626 starts operating in 1x mode where the output will be approximately equal to the input supply voltage (less any internal voltage losses). If the output voltage is sufficient to regulate all LEDs currents the device remains in 1x operating mode.

If the input voltage is insufficient or falls to a level where the regulated currents cannot be maintained, the device automatically switches (after a fixed time of 400 μ s) into 1.5x mode.

In 1.5x mode, the output is approximately equal to 1.5 times the input supply voltage (less any internal voltage losses).

The above sequence is repeated each and every time the chip is either powered-up or taken out of shutdown (via EN pin), or the RegEn register is accessed by write cycle.

LED Current Setting

The LED current setting is programmed via the I²C serial interface and is stored in four 8–bit registers RegA, RegB, RegC and RegEn as follows:

- RegA stores the LED current for group A (LEDA1 and LEDA2 channels),
- RegB stores the LED current for group B (LEDB1 and LEDB2 channels),
- RegC stores the LED current for group C (LEDC1 and LEDC2 channels),
- RegEn selects the on/off state of each of the 6 LED channels.

At each write access to RegEn, the driver automatically reconfigures to the mode (1x or 1.5x) that provides the highest efficiency.

Begister	Begister		Bit Pattern									
Name	Address	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0			
RegA	0	Х	х									
RegB	1	х	Х			See Table 7	for values					
RegC	2	х	Х									
				LEDC2 LEDC1 LEDB2 LEDB1 LEDA2 LEDA								
RegEn	3	Х	Х	On = 1 Off = 0	On = 1 Off = 0	On = 1 Off = 0	On = 1 Off = 0	On = 1 Off = 0	On = 1 Off = 0			

Table 6. REGISTER ADDRESS AND DATA CONFIGURATION (Note 3)

3. X = not used, 1 = logic high, 0 = logic low

The Table 7 lists the various LED currents with the associated RegA, RegB, and RegC register values.

LED Current (mA)	D7	D6	D5	D4	D3	D2	D1	D0	Dec
0.5	Х	Х	0	0	0	0	0	0	0
1.0	Х	Х	0	0	0	0	0	1	1
1.5	х	х	0	0	0	0	1	0	2
2.0	х	х	0	0	0	0	1	1	3
2.5	х	х	0	0	0	1	0	0	4
3.0	х	х	0	0	0	1	0	1	5
3.5	х	х	0	0	0	1	1	0	6
4.0	х	х	0	0	0	1	1	1	7
4.5	х	х	0	0	1	0	0	0	8
5.0	х	х	0	0	1	0	0	1	9
5.5	х	х	0	0	1	0	1	0	10
6.0	х	х	0	0	1	0	1	1	11
6.5	х	х	0	0	1	1	0	0	12
7.0	х	х	0	0	1	1	0	1	13
7.5	х	х	0	0	1	1	1	0	14
8.0	х	х	0	0	1	1	1	1	15
8.5	х	х	0	1	0	0	0	0	16
9.0	х	х	0	1	0	0	0	1	17
9.5	х	х	0	1	0	0	1	0	18
10.0	х	х	0	1	0	0	1	1	19
10.5	х	х	0	1	0	1	0	0	20
11.0	х	х	0	1	0	1	0	1	21
11.5	х	х	0	1	0	1	1	0	22
12.0	х	х	0	1	0	1	1	1	23
12.5	х	х	0	1	1	0	0	0	24
13.0	х	х	0	1	1	0	0	1	25
13.5	Х	Х	0	1	1	0	1	0	26
14.0	Х	Х	0	1	1	0	1	1	27
14.5	Х	Х	0	1	1	1	0	0	28
15.0	Х	Х	0	1	1	1	0	1	29
15.5	Х	Х	0	1	1	1	1	0	30
16.0	Х	х	0	1	1	1	1	1	31

Table 7. LED CURRENT SELECTION AND REGISTER VALUE (Note 4)

LED Current (mA)	D7	D6	D5	D4	D3	D2	D1	D0	Dec
16.5	Х	Х	1	0	0	0	0	0	32
17.0	х	х	1	0	0	0	0	1	33
17.5	х	х	1	0	0	0	1	0	34
18.0	х	х	1	0	0	0	1	1	35
18.5	х	х	1	0	0	1	0	0	36
19.0	х	х	1	0	0	1	0	1	37
19.5	х	х	1	0	0	1	1	0	38
20.0	х	х	1	0	0	1	1	1	39
20.5	х	х	1	0	1	0	0	0	40
21.0	х	х	1	0	1	0	0	1	41
21.5	х	х	1	0	1	0	1	0	42
22.0	х	х	1	0	1	0	1	1	43
22.5	х	х	1	0	1	1	0	0	44
23.0	х	х	1	0	1	1	0	1	45
23.5	х	х	1	0	1	1	1	0	46
24.0	х	х	1	0	1	1	1	1	47
24.5	х	х	1	1	0	0	0	0	48
25.0	х	х	1	1	0	0	0	1	49
25.5	х	х	1	1	0	0	1	0	50
26.0	х	х	1	1	0	0	1	1	51
26.5	х	х	1	1	0	1	0	0	52
27.0	х	х	1	1	0	1	0	1	53
27.5	х	х	1	1	0	1	1	0	54
28.0	х	х	1	1	0	1	1	1	55
28.5	х	х	1	1	1	0	0	0	56
29.0	х	х	1	1	1	0	0	1	57
29.5	х	х	1	1	1	0	1	0	58
30.0	х	х	1	1	1	0	1	1	59
30.5	Х	Х	1	1	1	1	0	0	60
31.0	Х	Х	1	1	1	1	0	1	61
31.5	Х	Х	1	1	1	1	1	0	62
32.0	Х	Х	1	1	1	1	1	1	63

4. X = not used, 1 = logic high, 0 = logic low

I²C Interface

The LED driver is interfaced through a 2-wire serial I^2C -bus in order to control the state and the current in each of the six LED channels. The SDA and SCL lines comply with the I^2C electrical specification and should be terminated with pull-up resistors. When the bus is not used, both lines are high. The device supports the maximum bus speed of 400 kbit/s. The serial bit sequence is shown below

for read and write operations into the registers. Read and write instructions are initiated by the master controller/CPU and acknowledged by the slave LED driver. The I²C address of the driver is internally fixed to the binary value 1100110. The protocol requires that the start bit and the device address are both repeated. For further details on the I²C protocol, please refer to the I²C–Bus Specification, document number 9398 393 40011, from Philips Semiconductors.

• Read operation:

	uu operation.	r	<u> </u>		<u> </u>									r
S	Slave address	W	А	Register address	A	S	Slave	addre	ess	R	A	Data	A*	Р
• W	rite operation:													
S	Slave address	W	А	Register address	А	D)ata	А	Р					
	Slav Registe	F e addr er addr E	S: A, W: A: A*: P: ress: ress: Data:	Start condition Read bit (1), Write b Acknowledge sent b Not Acknowledge se Stop condition Device address 7 bit Device register addr Data to read or write	it (0) y the s ent by t ts (MSI ess 8 b e 8 bits	lave Ll he ma B first, bits	ED driver ster micro slave ad	[·] (SDA ocontro dress i	high) bller (S s 1100	DA lov 1110).	v)			
	Slave Add:	ress 1 1		W Reg	gister Ad A4 A3	Idress A2	A1 A0		7 D6	D5 I	Data D4 D3	D2 D1 D0		
STAR		1 1	. .			<u></u>	04 V 00 V			V DEV			⊐ ີ∿ດທ∎	STOP
									<u>, 100</u>					
SCL		56	7[8 9 1 2 3	4 5	6]7 18 _	9_1	L_2 L	_3	4 🛄 5 🛛	6 _7 _8 L	9	ł
				Figure 26. Writ	e Inst	ructio	on Sequ	ence						
STAF SDA SCL	Slave Adv 1 1 0 0	dress 1 1 1 1 5 6		W Register Add	dress = A4 A3 0 0	RegB = A2 0	1 <u>A1 A0]</u> _0 [1]. _78	D ACK [)	7 D6 (X	Data = : D5 [1	39 (20m)4 D3 0 0	IA) 1 D2 D1 D0 1 1 1 1] <u>]ackíl</u>	STOP
	Figure	27. \	Vrite I	nstruction Example	Setti	ng 20	mA Cu	rrent	in LE	DB1 a	and Ll	EDB2		
	SDA SCL START Condition	/ 1_7 DDRES	SS R	8 9 1-7 /W ACK A Figure 28	DDRES	8 8 35 Bus P	∫9 ACK rotocol		7 DA	X ATA		CK STOP Condition		

Typical Application

The CAT3626 is ideal for driving RGB (red green blue) LEDs with common anode configuration. The individual LED currents associated with the red, green and blue LEDs are programmable independently through the I²C interface, allowing to generate an accurate color mixing. Dimming while maintaining the same color can be done by reprogramming the RegEn register on and off with the appropriate duty cycle (PWM mode).



PACKAGE DIMENSIONS

TQFN16, 4x4 CASE 510AE-01 ISSUE A



SYMBOL	MIN	NOM	MAX
A	0.70	0.75	0.80
A1	0.00	0.02	0.05
A3		0.20 REF	
b	0.25	0.30	0.35
D	3.90	4.00	4.10
D2	2.00		2.25
E	3.90	4.00	4.10
E2	2.00		2.25
е		0.65 BSC	

Notes:

L

(1) All dimensions are in millimeters.

0.45

0.65

(2) Complies with JEDEC MO-220.





Example of Ordering Information (Note 7)



5. All packages are RoHS-compliant (Lead-free, Halogen-free).

6. The standard lead finish is NiPdAu.

7. The device used in the above example is a CAT3626HV4-GT2 (TQFN, NiPdAu Plated Finish, Tape & Reel, 2,000/Reel).

8. For Matte-Tin package option, please contact your nearest ON Semiconductor Sales office.

9. For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

I²C is a trademark of Philips Corporation. ON Semiconductor is licensed by Philips Corporation to carry the I²C Bus Protocol.

ON Semiconductor and IIII) are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability, are used to any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typical" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death applicaties to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support:

Phone: 421 33 790 2910 Japan Customer Focus Center Phone: 81–3–5773–3850 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative