

Modulation Transformers *2000 Series*



Features:

- Sealed “gapped” core modulation transformer design
- Minimum frequency response of 150- 7000 Hz.
- Range of secondary taps for a variety of tube types
- The tapped secondary winding carries full class C plate current



Parts

Part Number	Typical Modulation Push-Pull Tube Types	Primary Impedance Watts (ohms)	Secondary Impedance (ohms)	Max. Secondary Current (DC)
2013	6V6, 6L6, 807, 5881, EL34	25 10000 C.T.	3000, 5000, 6500, 8000	100 mA

Data subject to change without notice