



Solid Core CT for Branch Circuit Monitoring JCT023-XXX-V or A

3&1 AC CT



- Single Phase measuring current transformers.
- Ranges: 30 to 63A (333mV & 100mA Secondary)
- Cable aperture : Ø9
- JCT023 Series for use with our JCT035-XXX-V or A
- Panel / DIN Rail Mounting

JCT035-XXX-V or A



- Single Phase measuring current transformers.
- Ranges: 30 to 63A (333mV & 100mA Secondary)
- Cable aperture : Ø9
- RJ12 socket for use with our EASYWIRE multi channel meters
- Panel / DIN Rail Mounting

Dimensions

How to Order / Model Reference

eg **JCT023-000/333mV**
JCT023 100mA

Primary Current
Select code from ratio table

Secondary Voltage **333 mV**

Secondary Current **100 mA**

Current Transformer Ratios

Primary Current (A)	Metering Burden(VA)			Code
	cl. 0.2S	cl. 0.5S	cl. 1	
30			0.033	030
50			0.033	050
63			0.033	063

333mV / 100mA Secondary

Dimensions

How to Order / Model Reference

eg **JCT035-000/333mV**
JCT035 100mA

Primary Current
Select code from ratio table

Secondary Voltage **333 mV**

Secondary Current **100 mA**

Current Transformer Ratios

Primary Current (A)	Metering Burden(VA)			Code
	cl. 0.2S	cl. 0.5S	cl. 1	
30			0.033	030
50			0.033	050
63			0.033	063

333mV / 100mA Secondary