

SPECIFICATION SHEET

JFW MODEL 75SA-058

SWITCH ASSEMBLY

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range 20-1000 MHz

Configuration 1P16T self-terminating solid-state RF switch

Enclosure Type 19 inch rack mount @ 1RU high

Startup/Default States (configurable) RF switch off at startup (see SWITCH command)
DHCP enabled (see NET command)
4 Ethernet users (see NET command)
Prompts off (see PROMPT command)

Impedance 75 Ohms nominal

VSWR 1.6:1 maximum

Insertion Loss 2.5dB maximum

Isolation 55 dB minimum

RF Input Power +20 dBm

Switching Speed 50 microseconds
(after command is received and processed)
(3 milliseconds typical processing time)

Remote Control Ethernet (DHCP, TCP/IP, 10/100, up to 12 users)
RS-232 (up to 115200 Baud)

Remote Commands RF Switch Control Commands:
Switch, Set Switch, Read Switch

System Commands:
Help, Identification, Store, Recall, Pause, Net,
Serial, Close, Disconnect, MOTD, Date, Message,
Restrict, IDENT, Name, Show Users, Reboot, Uptime,
Prompt

AC Supply 100-240 VAC @ 47-63 Hz
2 Amp 5x20mm "Slo-Blo" AC fuse
Littelfuse #215-002, JFW #025-021

RF Connector F female

Operating Temperature Range 0° to +50° C

Physical Size See outline drawing 092-6808

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	12/03/2010		BAC 12/03/2010				
24759	12/03/2014	A	TRS 12/03/2014				