



# ■ビニル絶縁付角先開形端子(ストレート形)






















































A形

B形



UL E42024 SP LR20812


形番		規格	寸法(mm)							標準色	適用電線範囲	適用圧着工具			1箱 入数 (個)	
			d2	B	L	F	ℓ	φD	T			燃線(mm <sup>2</sup> )	手動	空気圧式		油圧式
A形	V1.25-B3A	 	3.2	5.8	20.0	6.3	9.0	3.2	0.8	赤	※ 0.25~1.65 ※ 0.3 (AWG#22) 0.5 (AWG#20) 0.75 (AWG#18) 0.9 1.25 (AWG#16)	YNT-2216	YA-1 YA-2 YAT-1A YAT-2A YAD-1A YAD-2A YA-4 YAT-4A YAD-4A	BCT-0514L	1,000	
	V1.25-YS3A	 		6.4	19.6											
	V1.25-S3A	 		7.2												
	V1.25-N3A	 		6.2	20.0											
	V1.25-C3.5A	 		5.6												
	V1.25-YS4A	 		6.4	19.6	7.0										
	V1.25-S4A	 	4.3	7.2												
	V1.25-4A	 		8.5	20.0											
	V1.25-5A	 	5.3	9.5												
	V1.25-6A	 	6.4	12.0	26.2											11.0
A形	V2-N3A	 	3.2	5.9	20.0	6.3	9.0	3.9	0.8	青	1.04~2.63 1.25 (AWG#16) 2.0 (AWG#14)	YNT-1614	YA-1 YA-2 YAT-1A YAT-2A YAD-1A YAD-2A YA-4 YAT-4A YAD-4A	BCT-0514L	1,000	
	V2-YS3A	 		6.4	19.6											
	V2-S3A	 	3.7	7.2	20.2	6.5										
	V2-YS4A	 		6.4	19.6	6.3										
	V2-S4A	 	4.3	7.2	20.2	6.5										
	V2-4A	 		8.5	21.0	7.3										
	V2-5A	 	5.3	9.5		11.0										
	V2-6A	 	6.4	12.0	26.2											
	A形	V5.5-S3A	 	3.7	7.2	26.2	7.5	13.5	5.4	1.0	黄	2.63~6.64 3.5 (AWG#12) 5.5 (AWG#10)	YNT-1210S	YA-4 YAT-4A YAD-4A	BCT-0514L	500
		V5.5-3A	 		9.5											
V5.5-S4A		 	4.3	8.5												
V5.5-4A		 		9.5												
V5.5-5A		 	5.3													
V5.5-6A		 	6.4	13.5	32.2	12.2										
B形	V1.25-S3B	 	3.7	7.5	17.3	5.1	9.0	3.2	0.8	赤	※0.25~1.65 ※0.3 (AWG#22) 0.5 (AWG#20) 0.75 (AWG#18) 0.9 1.25 (AWG#16)	YNT-2216	YA-1,YAD-1A YA-2,YAD-2A YAT-1A YAT-2A YA-4 YAT-4A YAD-4A	BCT-0514L	1,000	
	V1.25-3B	 			8.5	21.7										7.2
	V1.25-S4B	 	4.3	7.5	17.3	5.1										
	V1.25-4B	 			8.5	22.7									7.2	
	V1.25-5B		5.3			11.7										
	V1.25-6B		6.4	13.5	28.2											
	B形	V2-T3B		3.7	7.5	17.7	5.2	9.0	3.9	0.8	青	1.04~2.63 1.25 (AWG#16) 2.0 (AWG#14)	YNT-1614	YA-1,YAD-1A YA-2,YAD-2A YAT-1A YAT-2A YA-4 YAT-4A YAD-4A	BCT-0514L	1,000
		V2-3B				8.5	21.2									
		V2-T4B		4.3	7.5	17.7	5.2									
		V2-4B				8.5	21.2									7.3
V2-5B			5.3													
V2-6B			6.4	13.5	28.2	11.7										
B形	V5.5-S3B		3.7	7.6	24.7	6.2	13.5	5.4	1.0	黄	2.63~6.64 3.5 (AWG#12) 5.5 (AWG#10)	YNT-1210S	YA-4 YAT-4A YAD-4A	BCT-0514L	500	
	V5.5-3B				8.5	26.2										7.5
	V5.5-S4B		4.3	7.6	24.7	6.2										
	V5.5-4B				8.5	26.2									7.5	
	V5.5-5B		5.3													
	V5.5-6B		6.4	13.5	33.2	12.2										

注1) ※印は電線の合計断面積が0.5mm<sup>2</sup>以上となる様にして使用すればより確実になります。


(例:0.3mm<sup>2</sup>を2つ折りにして圧着、0.5mm<sup>2</sup>はそのまま圧着)

注2) ナイロン絶縁付仕様、また丸先開形端子(X形)、丸横開形端子(Y形)仕様も製作できます。詳細は弊社までお問い合わせください。

注3) 本製品の中には多少納期を要するものもあります。



## ■ビニル絶縁付角先開形端子(F形)



A形


B形























































































E42024



LR20812



形番		規格		寸法(mm)							標準色	適用電線範囲	適用圧着工具			1箱 入数 (個)								
				d2	B	L	F	ℓ	φD	T			燃線(mm <sup>2</sup> )	手動	空気圧式		油圧式							
A形	FV1.25-B3A	 	3.2	5.8	20.0	6.3	9.0	4.0	0.8	赤	※ 0.25~1.65 ※ {0.3 (AWG#22) 0.5 (AWG#20) 0.75 (AWG#18) 0.9 1.25 (AWG#16)}	YNT-2216	YA-1 YA-2 YAT-1A YAT-2A YAD-1A YAD-2A YA-4 YAT-4A YAD-4A	BCT-0514L	1,000									
	FV1.25-YS3A	 		6.4	19.6																			
	FV1.25-S3A	 	3.7	7.2	20.0																			
	FV1.25-N3A	 		6.2		7.0																		
	FV1.25-YS4A	 		6.4	19.6																			
	FV1.25-S4A	 	4.3	7.2																				
	FV1.25-4A	 		8.5	20.0																			
	FV1.25-5A	 	5.3	9.5																				
	FV1.25-6A	 	6.4	12.0	26.2	11.0																		
	FV2-N3A	 	3.2	5.9	20.0	6.3	9.0	4.5	0.8	青	1.04~2.63 {1.25 (AWG#16) 2.0 (AWG#14)}	YNT-1614	YA-1 YA-2 YAT-1A YAT-2A YAD-1A YAD-2A YA-4 YAT-4A YAD-4A	BCT-0514L	1,000									
	FV2-YS3A	 		6.4	19.6																			
	FV2-S3A	 	3.7	7.2	20.2	6.5																		
	FV2-YS4A	 		6.4		6.3																		
	FV2-YM4A	 		6.8																				
	FV2-S4A	 	4.3	7.2	20.2	6.5																		
	FV2-4A	 		8.5		7.3																		
	FV2-5A	 	5.3	9.5																				
	FV2-6A	 	6.4	12.0	26.2	11.0																		
	FV5.5-S3A	 	3.7	7.2		7.5	13.5	6.8	1.0	黄	2.63~6.64 {3.5 (AWG#12) 5.5 (AWG#10)}	YNT-1210S	YA-4 YAT-4A YAD-4A	BCT-0514L	500									
	FV5.5-3A	 		9.5																				
	FV5.5-S4A	 	4.3	8.5	26.2																			
	FV5.5-4A	 			9.5																			
	FV5.5-5A	 	5.3																					
	FV5.5-6A	 	6.4	13.5	32.2	12.2																		
B形	FV1.25-S3B	 	3.7	7.5	17.3	5.1										9.0	4.0	0.8	赤	※0.25~1.65 {※0.3 (AWG#22) 0.5 (AWG#20) 0.75 (AWG#18) 0.9 1.25 (AWG#16)}	YNT-2216	YA-1,YAD-1A YA-2,YAD-2A YAT-1A YAT-2A YA-4 YAT-4A YAD-4A	BCT-0514L	1,000
	FV1.25-3B	 			8.5	21.7																		
	FV1.25-S4B	 	4.3	7.5	17.3	5.1																		
	FV1.25-4B	 			8.5	22.7	7.2																	
	FV1.25-5B	 	5.3			11.7																		
	FV1.25-6B	 	6.4	13.5	28.2																			
	FV2-T3B	 	3.7	7.5	17.7	5.2	9.0	4.5	0.8	青	1.04~2.63 {1.25 (AWG#16) 2.0 (AWG#14)}	YNT-1614	YA-1,YAD-1A YA-2,YAD-2A YAT-1A YAT-2A YA-4 YAT-4A YAD-4A	BCT-0514L	1,000									
	FV2-3B	 			8.5	21.2										7.2								
	FV2-T4B	 	4.3	7.5	17.7	5.2																		
	FV2-4B	 			8.5	21.2										7.3								
	FV2-5B	 	5.3			11.7																		
	FV2-6B	 	6.4	13.5	28.2																			
	FV5.5-S3B	 	3.7	7.6	24.7	6.2	13.5	6.8	1.0	黄	2.63~6.64 {3.5 (AWG#12) 5.5 (AWG#10)}	YNT-1210S	YA-4 YAT-4A YAD-4A	BCT-0514L	500									
	FV5.5-3B	 			8.5	26.2										7.5								
	FV5.5-S4B	 	4.3	7.6	24.7	6.2																		
	FV5.5-4B	 			8.5	26.2										7.5								
	FV5.5-5B	 	5.3			12.2																		
	FV5.5-6B	 	6.4	13.5	33.2																			

注1) ※印は電線の合計断面積が0.5mm<sup>2</sup>以上となる様にして使用すればより確実になります。(例:0.3mm<sup>2</sup>を2つ折りにして圧着、0.5mm<sup>2</sup>はそのまま圧着)

注2) ナイロン絶縁付仕様、また丸先開形端子(X形)、丸横開形端子(Y形)仕様も製作できます。詳細は弊社までお問い合わせください。

注3) 本製品の中には多少納期を要するものもあります。