

The RadioRay® Model 2000 is designed to permanently attach to a vehicle. The 2-Speed Searchlight with Directional Flexibility is controlled by a wireless remote, which gives the operator a full 370° horizontal rotation and a 135° vertical tilt with fingertip control. The RadioRay® provides superior light penetration with the new C-5 Pentabeam technology.

The RadioRay® includes:

- RadioRay® Searchlight
- Remote Control
- (Must be kept clean and dry.)
- 2 Duracell MN21 batteries
- Rain Coat for remote
- Gasket for permanent mounting
- Screws and Caps for mounting

MOUNTING INSTRUCTIONS

- Determine the location for the light on your vehicle. The small arrow on the base indicates the normal forward direction of the light. The light will rotate to the left of this arrow approximately 190° and to the right approximately 190°. The beam will angle down about 45° and angles up to 90°, a full vertical. The location should take into consideration this beam movement to insure optimum usability.

- Once the position and orientation are decided upon—use the black rubber gasket as a footprint to mark the mounting of base to vehicle. Drill ¼ inch hole through mounting surface in the middle of the footprint for passage of the power cord. Use silicone sealant to fill opening around power cord.

IMPORTANT: Allow 3" of cord to remain under the light to insure full 370° rotation.

- You should choose screw or bolt fasteners appropriate to the surface to which you intend to attach the light. If you intend to use the four small plastic caps provided to cover the screw heads once installed, a #8 round head is recommended.

- The black gasket should be installed on the lamp base prior to attachment to the vehicle surface.

NOTE: The small drain hole in the edge of the gasket should normally face opposite the forward direction of the vehicle—opposite the arrow molded in the front of the base.

- The 12-volt DC power wire should be joined to the leads under the lamp with appropriate automotive wire attachments. It is critical that polarity be observed. The (+) lead of the RadioRay® is marked with a red tag. The power should be fused at 10 Amps and be on an ignition switched circuit if possible.

*PROGRAMMABLE REMOTE INSTRUCTIONS

The RadioRay® is controlled with a programmable remote with 6,561 different channels. This feature allows you the freedom to change the channel selection and the receiver re-learns the new selection.

PROGRAMMING THE TRANSMITTER *

IMPORTANT:

1. Disconnect power by removing fuse or disconnecting vehicle battery.
2. Remove battery cover from back of remote.
3. Set the 7 dip switches to a selection of your choice. There are 3 positions on each: positive, negative, and neutral. Use a small screwdriver and select a position for each dip switch.
4. Insert both MN21 Duracell batteries with the +/- in the same direction. Be sure batteries have adequate charge.
5. Replace battery cover.
 - a. Depress the on/off button and hold it down. The red LED will light.
 - b. While holding the on/off button down, reinstall the power (replace fuse or connect vehicle battery).
 - c. Keep your finger on the on/off button a few seconds, and then release. The light should now be programmed.

OPERATION OF RADIORAY®

1. Using the remote control, turn on the light using the on/off switch.
2. With the 4-way switch on the remote control, rotate your light to the desired location. Depending upon conditions, the remote may be used up to 100 feet from the RadioRay®.
3. The speed of the light rotation can be controlled by depressing the +/- button one time and by depressing it again to restore the original speed.

BULB REPLACEMENT

The RadioRay® utilizes a Philips H-9 bulb, which may be purchased through Golight, Inc. 308-278-3131 or 800-557-0098.

IMPORTANT SAFETY INFORMATION

^This symbol is to alert you to important operating or servicing instructions that appear in your instructions. Always follow basic safety precautions when using this product to reduce the risk of injury, fire or electric shock.

^This light is for off road and utility use only. It is not designed for road use as a driving light.

^The RadioRay® complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this light and remote may not cause harmful interference, and (2) this light and remote must accept any interference received, including interference that may cause undesired operation.

^FCC RULE Part. 15.21 Changes or modifications made by the user not expressly approved by Golight™, Inc. for compliance could void the user's authority to operate the equipment.

For safe and efficient operation of your RadioRay®, observe these guidelines:

Using your RadioRay® in icing conditions could damage the gear motors. (Optional dome available see accessory sheet)

Always keep the remote in the raincoat provided. The remote must be kept clean and dry to avoid damage to internal circuitry.

Your RadioRay is a radio transmitter and receiver operating at 433 MHz. Whenever the light is on, the internally mounted antenna sends out and receives radio frequency (RF) energy.

*Modern electronic equipment, i.e. Personal medical devices such as pacemakers, hearing aids, etc., is shielded from RF energy. However, RF energy may affect some electronic equipment.

*Vehicle electronic systems may be affected by RF energy. Check with your vehicle manufacturer representative to be sure that your RadioRay® will not affect the electronic system of your vehicle.