


# Installation Information

## LIPS<sup>®</sup> X112 GAUGE HEAD POSITION SENSOR

### INTRINSICALLY SAFE FOR HAZARDOUS GAS/VAPOUR ATMOSPHERES

**For certificate number and safety parameters information for product marked EX04, see next page.**

| ATEX /IECEx Qualified to Intrinsic Safety Standard<br>Certificate numbers SIRA 13ATEX2371X<br>IECEX SIR 13.0154X |                                                           | Ex II 1G<br>Ex ia IIC T4 Ga (Ta = -40°C to +80°C) |                  |
|------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------|---------------------------------------------------|------------------|
| Electronics Version                                                                                              | Output Description:                                       | Supply Voltage:<br>V <sub>s</sub> (tolerance)     | Load resistance: |
| <b>EX07</b>                                                                                                      | 0.5 - 4.5V (ratiometric with supply)<br>[Output code 'A'] | +5V (4.5 - 5.5V)                                  | 5kΩ min          |



**Putting Into Service:** The sensor must be used with a galvanic isolation barrier designed to supply the sensor with a nominal 5V and to transmit the sensor output to a safe area. The barrier parameters must not exceed:-

- U<sub>i</sub> = 11.4V**      **I<sub>i</sub> = 0.20A**      **P<sub>i</sub> = 0.51W**
- C<sub>i</sub> = 1.36µF\***    **Li = 860µH\*** ('Ixx' or 'Lxx' options)    \*Figures for 1km cable where: C<sub>i</sub> = 200pF/m & Li = 810nH/m
- C<sub>i</sub> = 1.16µF**      **Li = 50µH** ('J' or 'K' options)

The sensor is certified to be used with up to **1000m** of cable, cable characteristics must not exceed:-

- Capacitance: ≤ 200 pF/m for max. total of: 200 nF
- Inductance: ≤ 810 nH/m for max. total of: 810 µH

Approval only applies to specified ambient temperature range and atmospheric conditions in the range: 0.80 to 1.10 Bar, oxygen ≤ 21%.

The performance of the sensor may be affected by voltage drops associated with long cable lengths; For cable lengths exceeding 10 metres a five wire connection is recommended to eliminate errors introduced by cable resistance and associated temperature coefficients.

N.b. sensors supplied with cable, the free end must be appropriately terminated.

**Warning** - The M12 IEC 60947 connector may be rotated for purposes of convenient orientation of the connector and cable, however rotating the connector more than one complete revolution is not recommended.

**Repeated rotation of the connector will damage the internal wiring!**


**Use:** The sensor is designed to measure linear displacement and provide an analogue output signal.

**Assembly and Dismantling:** The unit is not to be serviced or dismantled and re-assembled by the user.

**Maintenance:** No maintenance is required. Any cleaning must be done with a damp cloth.

**Mechanical Mounting:** Via 1/2"x20 UNF mounting thread, adjust sensor position and lock in place using lock nuts provided. Maximum tightening torque: 10Nm.

**Output Characteristic:** Plunger is extended 3.3 mm from end of body at start of normal travel. The output increases as the plunger extends from the sensor body, the calibrated stroke is between 5 mm and 50 mm.



**Incorrect Connection Protection levels: Not protected** – the sensor is **not** protected against either reverse polarity or over-voltage. The risk of damage should be minimal where the supply current is limited to less than 50mA.

# Installation Information

## LIPS<sup>®</sup> X112 GAUGE HEAD POSITION SENSOR

### INTRINSICALLY SAFE FOR HAZARDOUS GAS/VAPOUR ATMOSPHERES

**For certificate number and safety parameters information for product marked EX07, see previous page.**

| ATEX Qualified to Intrinsic Safety Standard<br>Certificate numbers SIRA 00ATEX2076X |                                                           | Ex II 1G<br>EEx ia IIC T4 (Ta = -40°C to +80°C) |                  |
|-------------------------------------------------------------------------------------|-----------------------------------------------------------|-------------------------------------------------|------------------|
| Electronics Version                                                                 | Output Description:                                       | Supply Voltage:<br>V <sub>s</sub> (tolerance)   | Load resistance: |
| EX04                                                                                | 0.5 - 4.5V (ratiometric with supply)<br>[Output code 'A'] | +5V (4.5 - 5.5V)                                | 5kΩ min          |

The barrier parameters must not exceed:-

**U<sub>i</sub> = 11.4V**      **I<sub>i</sub> = 0.20A**      **P<sub>i</sub> = 0.51W**  
**C<sub>i</sub> = 1.36μF\***      **L<sub>i</sub> = 710μH\*** ('Ixx' or 'Lxx' options)      \*Figures for 1km cable where: C<sub>i</sub> = 200pF/m & L<sub>i</sub> = 660nH/m  
**C<sub>i</sub> = 1.16μF**      **L<sub>i</sub> = 50μH** ('J' or 'K' options)

The sensor is certified to be used with up to **1000m** of cable, cable characteristics must not exceed:-

Capacitance: ≤ 200 pF/m for max. total of: 200 nF  
 Inductance: ≤ 660 nH/m for max. total of: 660 μH

With the exception of the certificate number and safety parameters above, all other notes regarding Putting Into Service, Use, Assembly and Dismantling etc. on previous page apply to sensors marked EX04 or EX07.