

## 700 MHz LTE Bandpass Filter (CF = 716 MHz)

### 4C9-716-X36N11

Reactel is proud to present this bandpass filter as another member of the growing family of 700 MHz LTE units. This particular unit is suitable for the Lower A band and is centered at 716 MHz. Reactel has a large variety of 700 MHz LTE filters and diplexers, please contact the factory with your specifications.



### Specifications

CF	716 MHz
Passband	698 – 734 MHz, minimum
Insertion Loss	≤ 1.0 dB @ Passband
Return Loss	≥ 20 dB @ Passband
Rejection	≥ 30 dB @ 776 – 896 MHz
Connectors	Type N, SC, TNC, or 7/16
Size	2.5" high x 1.5" wide x 4.3" long, nominal excluding connectors



**Reactel, Incorporated - Reacting First to Your Filter Requirements**

8031 Cessna Avenue ▪ Gaithersburg, Maryland 20879

Phone: 301-519-3660 ▪ Fax: 301-519-2447 ▪ [reactel@reactel.com](mailto:reactel@reactel.com) ▪ [www.reactel.com](http://www.reactel.com)