

The Selective Monitoring Microphone AS11 offers:

- · Robust, flexible directional microphone
- · Headphone amplifier
- Working with internal battery
- · One-hand operation
- Tunable 1/3rd and 1 octave band pass filter

Application

- Airborne noise measurements
- · Machine diagnostics
- Sound source localization
- · Leakage detection

TECHNICAL DATA:

Frequency range of microphone: 30 Hz - 18 kHz Max. output voltage: 4 Vpp Distortion: <1% at 1 kHz und 4 Vpp Power supply: 4,8V rech. battery, operating 10 h Dimensions (DxL): 35Ø x 550 mm Weight incl. battery: 350 gr

handle. Amplifier and filter is integrated into the hand grip. There is only one single cable connection between microphone and headphones! This makes the device a fully integrated one hand operation detector.

After switching on, the green power LED indicates full battery charge. Below 3,5 volts, the brightness decreases very rapidly and at 3 volts it lights only extremely weak indicating the need for recharging or exchanging the battery pack.

There are 2 amplifier gain ranges; 30 and 60 dB. The volume on the headphones is adjusted with the integrated pot on the control panel (11 positions).

With the second pot on the control panel, the center frequency for the 1/3rd octave or 1/1octave band pass filter could be selected between 31Hz and 8.000Hz. The filtered signal then is amplified by 20dB. Signals, recorded by the directive microphone, are filtered and amplified on the headphones. The output jack allows connection to other signal analyzers or recorders. This signal is equal to the headphone signal.

ROGA-Instruments, Im Hasenacker 56, D-56412 Nentershausen Phone: +49 (0) 6485-8815803, E-Mail: info@roga-instruments.com