



Features

- 1 bay / 10 bay SMBus desktop charger (others on request)
- Constant Current and voltage regulation (CCCV)
- Charges Lithium- and Nickel-based batteries
- 30W maximum charging power
- 16.8V maximum charging voltage
- 3.3A maximum charging current
- Battery temperature monitoring
- Resistor based battery identification
- Battery identification/monitoring using single-wire battery fuel gauge and monitor ICs (HDQ or 1-wire) or SMBus

Applications

- Customized charging station for battery packs or mobile devices used in industry, medical and consumer areas

Specification

Input		
	MAC01	MAC10
Voltage range	90 - 264VAC	
Frequency range	47 - 63Hz	
Input power	tbd	tbd
Standby power	tbd	tbd
Input fuse	tbd	tbd

Output (per bay)		
	MACxxA	MACxxB
Voltage	0 - 8.4V	0 - 16.8V
Current	<3.3A	<1.7A
Power	30W max.	
Voltage tolerance	±1% max.	
Current tolerance	±5% max.	
Leakage current	< 1mA	
Ripple & Noise ⁽¹⁾	< 120mV _{pk-pk}	
Protection	Short circuit Over temperature shutdown Reverse polarity	

Environmental	
Cooling	convection cooled
Temperature	Operating: -20°C to 40°C Non-operating: -40°C to 85°C
Altitude	Operating: 1060hPa to 795hPa -382m to 2000m Non-operating: 1060hPa to 572hPa -382m to 4570m
Humidity	5 to 95% r.H., non-condensing

General		
Input connector	MAC01 IEC60320 C8 (2-pin)	MAC10 IEC60320 C14 (3-pin)
Efficiency ⁽²⁾	typical 80% at 100% load	
Green procurement MTBF	RoHS2002/95/EC WEEE 2002/96/EC > 250000h at 25°C and full load per MIL-HDBK 217F	
Indicator	Battery status LED (green/red) Power LED (green)	

Notes

- Datasheet subject to change without notice.
1. Measured with a 0.1µF ceramic and a 47µF tantalum capacitor across the output terminals. The oscilloscope bandwidth is set at 20MHz a co-axial cable will be used to measure it. The test condition is maximum load.
 2. Power losses of input and output cables are not considered here.
 3. The rms method is used for leakage current measurements.
 4. xx=number of bays

Charge phases and Indicators		Battery Status LED Indicator	
Charge phase	Description	Green	Red
Pre-charge	Until the battery voltage is lower than a specified threshold (deeply discharged) it is charged with a low current.	FLASHES	
Fast charge	When charging nickel based batteries, the charger delivers a constant current (CC) to the battery. When charging LiIon batteries the CC phase is followed by a constant voltage phase (CV). Once the battery voltage is close to the regulated charge voltage the charging current decreases.	FLASHES	
Top-off charge	Top-off charge completes the charging process. Selectable only for NiMH/NiCd batteries for achieving maximum capacity.	FLASHES	
Battery full		ON	
Failure			ON

Charge phases, battery dependent threshold values and LED patterns can be modified to fit a variety of specifications. Please contact RRC.

Charge termination methods		
NiCd	-ΔV	At the end of the charging process the battery voltage decreases slightly. Fast charging is terminated if the voltage drop is higher than a specified threshold
NiMH	d ² V/dt ²	This fast charge termination method detects the inflexion point of the charge voltage curve. Charging process is terminated if the rate at which the battery temperature increases during constant-current charging is higher than a specified threshold. Temperature gradient threshold is adjustable
	dT/dt	
LiIon LiPolymer	I _{cutoff}	If the charging current goes lower than a set threshold the battery charging process is terminated.
All chemistries	Timer	Terminate the charge process based on a safety timer
	TCO	Charge process stops if the temperature is out of a specified safety window.

Safety & EMC			
Insulation class		II	
Earth leakage current ⁽³⁾		NA	
Enclosure / Touch leakage current ⁽³⁾		<100μA	
Safety standards		ITE version IEC60950-1	Household version IEC60335-2-29
			Medical version IEC60601-1
Electromagnetic Emissions	Europe	EN55022, level B	
	USA	FCC15 class B	
	International	CISPR 22, level B	
Electromagnetic Immunity	ESD immunity	EN/IEC61000-4-2, 4/8kV, performance criteria B	
	Radiated immunity	EN/IEC61000-4-3, 3V/m, performance criteria A	
	EFT / Burst	EN/IEC61000-4-4, 1kV, performance criteria B	
	Surge	EN/IEC61000-4-5, 1kV, performance criteria B	
	Conducted Immunity	EN/IEC61000-4-6, 10V, performance criteria A	
	Magnetic Fields	EN/IEC61000-4-8, 1A/m, performance criteria A	
Regulatory approvals	Europe	CE	
	USA	cULus per UL60950	
	Japan	PSE	
	International	CB	

Mechanical Details	
Dimensions (LxWxH)	tbd
Weight	tbd

Germany/Headquarters	USA	Hong Kong	China
RRC power solutions GmbH Technologiepark 1 D-66424 Homburg / Saar	RRC power solutions Inc. 18340 Yorba Linda Blvd., Suite 107-437 Yorba Linda, CA 92886-4104	RRC power solutions Ltd. S-V,6/F, Valiant Industrial Centre 2-12 Au Pui Wan Street Fo Tan, N.T., Hong Kong	RRC power solutions Ltd. Room 520, Yuanlin Building, Aiguo Road No. 3066, Luohu District, Shenzhen 518021
Tel.: +49 6841 98090 Fax: +49 6841 9809280 Email: sales@rrc-ps.de Web: www.rrc-ps.de	Tel.: +1 714 777 3604 Fax: +1 714 777 3658 Email: usa@rrc-ps.com Web: www.rrc-ps.com	Tel.: +852 2376 0106 Fax: +852 2375 0107 Email: hkrrc@rrc-ps.cn Web: www.rrc-ps.com	Tel.: +86 755 8374 1908 Fax: +86 755 8374 1861 Email: hkrrc@rrc-ps.cn Web: www.rrc-ps.com