

## RECTIFIER DIODES

### FAST RECOVERY RECTIFIER DIODES < 100 A

Type	I <sub>O</sub> (A)	V <sub>RRM</sub> (V)	I <sub>FSM</sub> 10 ms (A)	V <sub>F</sub> / I <sub>F</sub> max (V) (A)	I <sub>R</sub> /V <sub>RRM</sub> max (mA)	t <sub>rr</sub> max (ns)	t <sub>rr</sub> @ I <sub>F</sub> = 0.5 A I <sub>R</sub> = 1 A (ns)	Package
PLQ 08 PLQ 1	1	80 100	20	1.1 1	0.5 T <sub>amb</sub> = 100°C	50 (1)	35	F 126
BYT 11-600 BYT 11-800 BYT 11-1000	1	600 800 1000	35	1.3 1	0.02	—	100	F 126
PFR 305 PFR 310	3	50 100	135	1.0 3	0.01	—	50	DO 27 A
PFR 850 PFR 851 PFR 852 PFR 854 PFR 856	3	50 100 200 400 600	150	1.25 3	0.01	150 (2) 150 (2) 150 (2) 150 (2) 200 (2)	75	DO 27 A
BYT 13-600 BYT 13-800 BYT 13-1000	3	600 800 1000	100	1.3 3	0.02	150 (3)	150	DO 27 A

(1) I<sub>F</sub> = 1 A — V<sub>R</sub> = 30 V — di<sub>F</sub>/dt = -50 A/μs — I<sub>rr</sub> = 0.2 I<sub>RM</sub>.  
 (2) I<sub>F</sub> = 1 A — V<sub>R</sub> = 30 V — di<sub>F</sub>/dt = -25 A/μs — I<sub>rr</sub> = 0.2 I<sub>RM</sub>.  
 (3) I<sub>F</sub> = 0.5 A — I<sub>R</sub> = 1 A — I<sub>rr</sub> = 0.25 A.

Type	I <sub>O</sub> (A)	V <sub>RRM</sub> (V)	I <sub>FSM</sub> 10 ms (A)	V <sub>F</sub> / I <sub>F</sub> max (V) (A)	I <sub>R</sub> /V <sub>RRM</sub> T <sub>j</sub> = 100°C max (mA)	t <sub>rr</sub> (1) max (ns)	Package
BYT 71-100 A BYT 71-400 A BYT 71-600 A BYT 71-800 A	6	100 400 600 800	90	1.4 6	1	300	DO 220
1N 3879, (R) 1N 3880, (R) 1N 3881, (R) 1N 3882, (R) 1N 3883, (R)	6	50 100 200 300 400	150	1.4 6	1	200	DO 4*
BY 233-200 A BY 233-400 A BY 233-600 A	8	200 400 600	100	1.5 8	1	150	DO 220
ESM 765-100 A ESM 765-200 A ESM 765-400 A ESM 765-600 A ESM 765-800 A	10	100 200 400 600 800	120	1.4 10	1	300	DO 220

(1) I<sub>F</sub> = 1 A V<sub>R</sub> = 30 V di<sub>F</sub>/dt = - 15 A / μs — I<sub>rr</sub> = 0.2 I<sub>RM</sub>  
 \* 10-32 UNF - M5 thread available on request → Type number + suffix M.  
 Type number : cathode to case.  
 Type number + suffix R : anode to case.