

# TC1028

## Linear Building Block – Dual Low Power Comparator and Voltage Reference with Shutdown

#### **Features**

- Combines Two Comparators and a Voltage Reference in a Single Package
- Optimized for Single Supply Operation
- Small Package: 8-Pin MSOP
- Ultra Low Input Bias Current: Less than 100pA
- Low Quiescent Current, Operating: 10μA (Typ.) Shutdown Mode: 0.05μA (Typ.)
- · Rail-to-Rail Inputs and Outputs
- Operates Down to V<sub>DD</sub> = 1.8V

## Applications

- Power Supply Circuits
- Battery Operated Equipment
- Consumer Products
- · Replacements for Discrete Components

#### **Device Selection Table**

Part Number	Package	Temperature Range	
TC1028CEUA	8-Pin MSOP	-40°C to +85°C	

#### Package Type



## **General Description**

The TC1028 is a mixed-function device combining two comparators and a voltage reference in a single 8-pin package. The inverting input of Comparator A and the non-inverting input of Comparator B are internally connected to the reference.

This increased integration allows the user to replace two packages, which saves space, lowers supply current and increases system performance. The TC1028 operates from two 1.5V alkaline cells down to  $V_{DD} = 1.8V$ . It requires only 10µA typical of supply current, which significantly extends battery life. A low power shutdown input (SHDN) disables the entire chip, placing all outputs in a high-impedance state. This mode saves battery power and allows comparator outputs to share common analog lines (multiplexing). Shutdown current is 0.05µA typical.

Rail-to-rail inputs and outputs allow operation from low supply voltages with large input and output signal swings.

Packaged in an 8-Pin MSOP, the TC1028 is ideal for applications requiring low power level detection.

#### **Functional Block Diagram**



## 1.0 ELECTRICAL CHARACTERISTICS

## **ABSOLUTE MAXIMUM RATINGS\***

Supply Voltage	6.0V
Voltage on Any Pin (V <sub>SS</sub> - 0.3)	/) to (V <sub>DD</sub> + 0.3V)
Junction Temperature	+150°C
Operating Temperature Range	40°C to +85°C
Storage Temperature Range	55°C to +150°C

**TC1028 ELECTRICAL SPECIFICATIONS** 

\*Stresses above those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions above those indicated in the operation sections of the specifications is not implied. Exposure to Absolute Maximum Rating conditions for extended periods may affect device reliability.

Electrical Cha +85°C, and Vr	aracteristics: Typical values apply = 1.8V to 5.5V, unless otherwise	at 25°C and specified.	V <sub>DD</sub> = 3.0	V. Minimum a	and maxir	num values apply for $T_A = -40^{\circ}$ to
Symbol	Parameter	Min	Тур	Max	Units	Test Conditions
V <sub>DD</sub>	Supply Voltage	1.8	_	5.5	V	
I <sub>Q</sub>	Supply Current Operating	_	10	15	μA	All outputs unloaded, SHDN = V <sub>DD</sub>
I <sub>SHDN</sub>	Supply Current, Shutdown	_	0.05	0.1	μA	SHDN = V <sub>SS</sub>
Shutdown Inp	put			•		-
V <sub>IH</sub>	Input High Threshold	80% V <sub>DD</sub>	_		V	
V <sub>IL</sub>	Input Low Threshold	_	_	20% V <sub>DD</sub>	V	
I <sub>SI</sub>	Shutdown Input Current	_	_	±100	nA	
Comparators	•			•		-
R <sub>OUT</sub>	Output Resistance in Shutdown	20	—	—	MΩ	SHDN = V <sub>SS</sub>
C <sub>OUT</sub>	Output Capacitance in Shutdown	_	_	5	pF	SHDN = V <sub>SS</sub>
T <sub>SEL</sub>	Select Time	_	20	_	μsec	$V_{OUT}$ Valid from $\overline{SHDN} = V_{IH}$
T <sub>DESEL</sub>	Deselect Time	—	500	_	nsec	$V_{OUT}$ Invalid from $\overline{SHDN} = V_{IL}$ R <sub>L</sub> =10k $\Omega$ to V <sub>SS</sub>
V <sub>IR</sub>	Input Voltage Range	V <sub>SS</sub> – 0.2		V <sub>DD</sub> + 0.2	V	
V <sub>OS</sub>	Input Offset Voltage	-5 -5		+5 +5	mV	$V_{DD} = 3V, T_A = 25^{\circ}C$ $T_A = -40^{\circ}C \text{ to } 85^{\circ}C$
IB	Input Bias Current	_	—	±100	pА	$T_A = 25^{\circ}C$ , INA+, INB- = $V_{DD}$ to $V_{SS}$
V <sub>OH</sub>	Output High Voltage	V <sub>DD</sub> – 0.3	—	—	V	$R_L = 10k\Omega$ to $V_{SS}$
V <sub>OL</sub>	Output Low Voltage	_	_	0.3	V	$R_{L} = 10k\Omega$ to $V_{DD}$
CMRR	Common Mode Rejection Ratio	66		—	dB	$T_A = 25^{\circ}C, V_{DD} = 5V$ $V_{CM} = V_{DD}$ to $V_{SS}$
PSRR	Power Supply Rejection Ratio	60	_	_	dB	$T_A = 25^{\circ}C, V_{DD} = 1.8V \text{ to } 5V$
I <sub>SRC</sub>	Output Source Current	1	_	-	mA	INA+ = $V_{DD}$ , INB- = $V_{SS}$ Output Shorted to $V_{SS}$ $V_{DD}$ = 1.8V
I <sub>SINK</sub>	Output Sink Current	2	_	_	mA	INA+ = $V_{SS}$ , INB- = $V_{DD}$ Output Shorted to $V_{DD}$ $V_{DD}$ = 1.8V
t <sub>PD1</sub>	Response Time	—	4	_	μsec	100mV Overdrive, C <sub>L</sub> = 100pF
t <sub>PD2</sub>	Response Time	—	6	—	μsec	10mV Overdrive, C <sub>L</sub> = 100pF
Voltage Refer	rence					
V <sub>REF</sub>	Reference Voltage	1.176	1.200	1.224	V	
IREF(SOURCE)	Source Current	50	_	_	μA	
IREF(SINK)	Sink Current	50	_	_	μA	
C <sub>L(REF)</sub>	Load Capacitance		_	100	pF	
R <sub>OUT</sub> (SD)	Output Resistance in Shutdown	20	_	_	MΩ	SHDN = V <sub>SS</sub>
C <sub>OUT</sub> (SD)	Output Capacitance in Shutdown	_	_	5	pF	SHDN = V <sub>SS</sub>

## TC1028 ELECTRICAL SPECIFICATIONS (CONTINUED)

**Electrical Characteristics:** Typical values apply at 25°C and  $V_{DD}$  = 3.0V. Minimum and maximum values apply for  $T_A$  = -40° to +85°C, and  $V_{DD}$  = 1.8V to 5.5V, unless otherwise specified.

Symbol	Parameter	Min	Тур	Max	Units	Test Conditions
T <sub>SEL</sub>	Select Time	—	200	_	µsec	REF Valid from $\overline{SHDN} = V_{IH}$ R <sub>L</sub> = 100kΩ to V <sub>SS</sub>
T <sub>DESEL</sub>	Deselect Time	—	10	_	μsec	REF Invalid from $\overline{SHDN} = V_{IL}$ R <sub>L</sub> = 100kΩ to V <sub>SS</sub>
C <sub>L(REF)</sub>	Load Capacitance	—	_	100	pF	
E <sub>VREF</sub>	Noise Voltage	_	20	_	$\mu V_{RMS}$	100Hz TO 100kHz
e <sub>VREF</sub>	Noise Voltage Density	_	1.0	_	μV/√Hz	1kHz

## 2.0 PIN DESCRIPTION

The description of the pins are listed in Table 2-1.

## TABLE 2-1: PIN FUNCTION TABLE

Pin No. (8-Pin MSOP)	Symbol	Description			
1	OUTA	Comparator output.			
2	V <sub>SS</sub>	Negative power supply.			
3	INA+	Non-inverting input to Comparator A.			
4	INB-	Inverting input to Comparator B.			
5	SHDN	Shutdown input.			
6	REF	Voltage reference.			
7	V <sub>DD</sub>	Positive power supply.			
8	OUTB	Comparator output.			

## 3.0 DETAILED DESCRIPTION

The TC1028 is one of a series of very low power, linear building block products targeted at low voltage, single supply applications. The TC1028 minimum operating voltage is 1.8V and typical supply current is only  $10\mu$ A (fully enabled). It combines two comparators and a voltage reference in a single package. The shutdown mode disables both comparators and the reference. All of the outputs are in a high impedance state during shutdown.

## 3.1 Comparators

The TC1028 contains two comparators. The comparator's input range extends beyond both supply voltages by 200mV and the outputs will swing to within several millivolts of the supplies depending on the load current being driven. The inverting input of Comparator A and the non-inverting input of Comparator B are internally connected the output of the voltage reference.

The comparators exhibit a propagation delay and supply current which are largely independent of supply voltage. The low input bias current and offset voltage make them suitable for high impedance precision applications. Both comparators are disabled during shutdown and have high impedance outputs.

## 3.2 Voltage Reference

A 2.0% tolerance, internally biased, 1.20V bandgap voltage reference is included in the TC1028. It has a push-pull output capable of sourcing and sinking  $50\mu$ A. The voltage reference is disabled during shutdown, with a high impedance output.

## 3.3 Shutdown Input

SHDN at  $V_{IL}$  disables the entire part. The SHDN input cannot be allowed to float; when not used, connect it to  $V_{DD}$ . All outputs are in a high impedance state when shutdown is active. The disabled comparators' inputs and outputs can be driven from rail-to-rail by an external voltage when the TC1028 is in shutdown. No latchup will occur when the device is driven to its enabled state when SHDN is set to  $V_{IH}$ .

## 4.0 TYPICAL APPLICATIONS

The TC1028 lends itself to a wide variety of applications, particularly in battery-powered systems. It typically finds application in power management, processor supervisory and interface circuitry.

## 4.1 Wake-Up Timer

Many microcontrollers have a low-power "sleep" mode that significantly reduces their supply current. Typically, the microcontroller is placed in this mode via a software instruction, and returns to a fully-enabled state upon reception of an external signal ("wake-up"). The wakeup signal is usually supplied by a hardware timer. Most system applications demand that this timer have a long duration (typically seconds or minutes), and consume as little supply current as possible.

The circuit shown in Figure 4-1 is a wake-up timer made from Comparator A. Capacitor C1 charges through R1 until a voltage equal to V is reached, at which point the "wake-up" is driven active. Upon wake-up, the microcontroller resets the timer by forcing a logic low on a dedicated, open drain I/O port pin. This discharges C1 through R4 (the value of R4 is chosen to limit maximum current sunk by the I/O port pin). With a 3V supply, the circuit as shown consumes typically  $10\mu$ A and furnishes a nominal timer duration of 25 seconds.

#### FIGURE 4-1: WAKE-UP TIMER



## 4.2 Precision Battery Monitor

Figure 4-2 is a precision battery low/battery dead monitoring circuit. Typically, the battery low output warns the user that a battery dead condition is imminent. Battery dead typically initiates a forced shutdown to prevent operation at low internal supply voltages (which can cause unstable system operation).

The circuit in Figure 4-2 uses a single TC1028, a TC1034, and only six external resistors. COMPA and COMPB provide precision voltage detection using  $V_R$  as a reference. Resistors R2 and R4 set the detection threshold for BATT LOW, while resistors R1 and R3 set the detection threshold for BATT LOW at 2.2V (typical) and BATT FAIL at 2.0 (typical). Total current consumed by this circuit is typically 16µA at 3V. Resistors R5 and R6 provide hysteresis for comparators COMPA and COMPB, respectively.

## 4.3 External Hysteresis (Comparator)

Hysteresis can be set externally with two resistors using positive feedback techniques (see Figure 4-3). The design procedure for setting external comparator hysteresis is as follows:

- 1. Choose the feedback resistor  $R_C$ . Since the input bias current of the comparator is at most 100pA, the current through  $R_C$  can be set to 100nA (i.e., 1000 times the input bias current) and retain excellent accuracy. The current through  $R_C$  at the comparator's trip point is  $V_R / R_C$  where  $V_R$  is a stable reference voltage.
- 2. Determine the hysteresis voltage (V<sub>HY</sub>) between the upper and lower thresholds.

3. Calculate R<sub>A</sub> as follows:

#### **EQUATION 4-1:**

$$\mathsf{R}_{\mathsf{A}} = \mathsf{R}_{\mathsf{C}} \left( \frac{\mathsf{V}_{\mathsf{H}\mathsf{Y}}}{\mathsf{V}_{\mathsf{D}\mathsf{D}}} \right)$$

- 4. Choose the rising threshold voltage for  $V_{\mbox{SRC}}$   $(V_{\mbox{THR}}).$
- 5. Calculate R<sub>B</sub> as follows:

#### **EQUATION 4-2:**

R	1	
ite –		4 T
	$\left(\frac{1}{V}\right) - \frac{1}{D} - \frac{1}{D} - \frac{1}{D}$	<u>-</u>
	$V_R \times R_A / R_A$	R <sub>C</sub>

6. Verify the threshold voltages with these formulas:

V<sub>SRC</sub> rising:

#### **EQUATION 4-3:**

$$V_{THR} = (V_R)(R_A) \left[ \left( \frac{1}{R_A} \right) + \left( \frac{1}{R_B} \right) + \left( \frac{1}{R_C} \right) \right]$$

V<sub>SRC</sub> falling:

#### **EQUATION 4-4:**

$$V_{THF} = V_{THR} - \left[ \left( \frac{R_A \times V_{DD}}{R_C} \right) \right]$$







## 5.0 TYPICAL CHARACTERISTICS

**Note:** The graphs and tables provided following this note are a statistical summary based on a limited number of samples and are provided for informational purposes only. The performance characteristics listed herein are not tested or guaranteed. In some graphs or tables, the data presented may be outside the specified operating range (e.g., outside specified power supply range) and therefore outside the warranted range.







## 5.0 TYPICAL CHARACTERISTICS (CONTINUED)



## 6.0 PACKAGING INFORMATION

## 6.1 Package Marking Information

Package marking data not available at this time.

## 6.2 Taping Form



#### 6.3 Package Dimensions



#### Sales and Support

#### **Data Sheets**

Products supported by a preliminary Data Sheet may have an errata sheet describing minor operational differences and recommended workarounds. To determine if an errata sheet exists for a particular device, please contact one of the following:

- 1. Your local Microchip sales office
- 2. The Microchip Corporate Literature Center U.S. FAX: (480) 792-7277
- 3. The Microchip Worldwide Site (www.microchip.com)

Please specify which device, revision of silicon and Data Sheet (include Literature #) you are using.

#### New Customer Notification System

Register on our web site (www.microchip.com/cn) to receive the most current information on our products.

## TC1028

NOTES:

Information contained in this publication regarding device applications and the like is intended through suggestion only and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. No representation or warranty is given and no liability is assumed by Microchip Technology Incorporated with respect to the accuracy or use of such information, or infringement of patents or other intellectual property rights arising from such use or otherwise. Use of Microchip's products as critical components in life support systems is not authorized except with express written approval by Microchip. No licenses are conveyed, implicitly or otherwise, under any intellectual property rights.

#### Trademarks

The Microchip name and logo, the Microchip logo, FilterLab, KEELOQ, microID, MPLAB, PIC, PICmicro, PICMASTER, PICSTART, PRO MATE, SEEVAL and The Embedded Control Solutions Company are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

dsPIC, ECONOMONITOR, FanSense, FlexROM, fuzzyLAB, In-Circuit Serial Programming, ICSP, ICEPIC, microPort, Migratable Memory, MPASM, MPLIB, MPLINK, MPSIM, MXDEV, PICC, PICDEM, PICDEM.net, rfPIC, Select Mode and Total Endurance are trademarks of Microchip Technology Incorporated in the U.S.A.

Serialized Quick Turn Programming (SQTP) is a service mark of Microchip Technology Incorporated in the U.S.A.

All other trademarks mentioned herein are property of their respective companies.

© 2002, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.





Microchip received QS-9000 quality system certification for its worldwide headquarters, design and wafer fabrication facilities in Chandler and Tempe, Arizona in July 1999 and Mountain View, California in March 2002. The Company's quality system processes and procedures are QS-9000 compliant for its PlCmicro® 8-bit MCUs, KEELoq® code hopping devices, Serial EEPROMs, microperipherals, non-volatile memory and analog products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001 certified.



## WORLDWIDE SALES AND SERVICE

#### AMERICAS

Corporate Office 2355 West Chandler Blvd. Chandler, AZ 85224-6199 Tel: 480-792-7200 Fax: 480-792-7277 Technical Support: 480-792-7627 Web Address: http://www.microchip.com

#### **Rocky Mountain**

2355 West Chandler Blvd. Chandler, AZ 85224-6199 Tel: 480-792-7966 Fax: 480-792-7456

#### Atlanta

500 Sugar Mill Road, Suite 200B Atlanta, GA 30350 Tel: 770-640-0034 Fax: 770-640-0307

Boston

2 Lan Drive, Suite 120 Westford, MA 01886 Tel: 978-692-3848 Fax: 978-692-3821

Chicago

333 Pierce Road, Suite 180 Itasca, IL 60143 Tel: 630-285-0071 Fax: 630-285-0075

Dallas

4570 Westgrove Drive, Suite 160 Addison, TX 75001 Tel: 972-818-7423 Fax: 972-818-2924

Detroit

Tri-Atria Office Building 32255 Northwestern Highway, Suite 190 Farmington Hills, MI 48334 Tel: 248-538-2250 Fax: 248-538-2260

Kokomo

2767 S. Albright Road Kokomo, Indiana 46902 Tel: 765-864-8360 Fax: 765-864-8387

Los Angeles 18201 Von Karman, Suite 1090

Irvine, CA 92612 Tel: 949-263-1888 Fax: 949-263-1338 New York

150 Motor Parkway, Suite 202 Hauppauge, NY 11788 Tel: 631-273-5305 Fax: 631-273-5335

#### San Jose

Microchip Technology Inc. 2107 North First Street, Suite 590 San Jose, CA 95131 Tel: 408-436-7950 Fax: 408-436-7955

Toronto

6285 Northam Drive, Suite 108 Mississauga, Ontario L4V 1X5, Canada Tel: 905-673-0699 Fax: 905-673-6509

#### ASIA/PACIFIC

Australia

Microchip Technology Australia Pty Ltd Suite 22, 41 Rawson Street Epping 2121, NSW Australia

Tel: 61-2-9868-6733 Fax: 61-2-9868-6755

China - Beijing Microchip Technology Consulting (Shanghai) Co., Ltd., Beijing Liaison Office Unit 915 Bei Hai Wan Tai Bldg. No. 6 Chaoyangmen Beidajie Beijing, 100027, No. China Tel: 86-10-85282100 Fax: 86-10-85282104

#### China - Chengdu

Microchip Technology Consulting (Shanghai) Co., Ltd., Chengdu Liaison Office Rm. 2401, 24th Floor, Ming Xing Financial Tower No. 88 TIDU Street Chengdu 610016, China Tel: 86-28-6766200 Fax: 86-28-6766599

#### China - Fuzhou

Microchip Technology Consulting (Shanghai) Co., Ltd., Fuzhou Liaison Office Unit 28F, World Trade Plaza No. 71 Wusi Road Fuzhou 350001, China Tel: 86-591-7503506 Fax: 86-591-7503521

China - Shanghai Microchip Technology Consulting (Shanghai) Co., Ltd.

Room 701, Bldg. B Far East International Plaza No. 317 Xian Xia Road Shanghai, 200051 Tel: 86-21-6275-5700 Fax: 86-21-6275-5060

#### China - Shenzhen

Microchip Technology Consulting (Shanghai) Co., Ltd., Shenzhen Liaison Office Rm. 1315, 13/F, Shenzhen Kerry Centre, Renminnan Lu Shenzhen 518001, China Tel: 86-755-2350361 Fax: 86-755-2366086 Hong Kong

Microchip Technology Hongkong Ltd. Unit 901-6, Tower 2, Metroplaza 223 Hing Fong Road Kwai Fong, N.T., Hong Kong Tel: 852-2401-1200 Fax: 852-2401-3431

#### India

Microchip Technology Inc. India Liaison Office Divyasree Chambers 1 Floor, Wing A (A3/A4) No. 11, O'Shaugnessey Road Bangalore, 560 025, India Tel: 91-80-2290061 Fax: 91-80-2290062

#### Japan

Microchip Technology Japan K.K. Benex S-1 6F 3-18-20, Shinyokohama Kohoku-Ku, Yokohama-shi Kanagawa, 222-0033, Japan Tel: 81-45-471-6166 Fax: 81-45-471-6122 Korea Microchip Technology Korea 168-1, Youngbo Bldg. 3 Floor Samsung-Dong, Kangnam-Ku Seoul, Korea 135-882 Tel: 82-2-554-7200 Fax: 82-2-558-5934 Singapore Microchip Technology Singapore Pte Ltd. 200 Middle Road #07-02 Prime Centre Singapore, 188980 Tel: 65-6334-8870 Fax: 65-6334-8850

Taiwan

Microchip Technology Taiwan 11F-3, No. 207 Tung Hua North Road Taipei, 105, Taiwan Tel: 886-2-2717-7175 Fax: 886-2-2545-0139

#### EUROPE

Denmark

Microchip Technology Nordic ApS Regus Business Centre Lautrup hoj 1-3 Ballerup DK-2750 Denmark Tel: 45 4420 9895 Fax: 45 4420 9910

France

Microchip Technology SARL Parc d'Activite du Moulin de Massy 43 Rue du Saule Trapu Batiment A - ler Etage 91300 Massy, France Tel: 33-1-69-53-63-20 Fax: 33-1-69-30-90-79 **Germany** 

Microchip Technology GmbH Gustav-Heinemann Ring 125 D-81739 Munich, Germany Tel: 49-89-627-144 0 Fax: 49-89-627-144-44

Italy

Microchip Technology SRL Centro Direzionale Colleoni Palazzo Taurus 1 V. Le Colleoni 1 20041 Agrate Brianza Milan, Italy Tel: 39-039-65791-1 Fax: 39-039-6899883

United Kingdom

Arizona Microchip Technology Ltd. 505 Eskdale Road Winnersh Triangle Wokingham Berkshire, England RG41 5TU Tel: 44 118 921 5869 Fax: 44-118 921-5820

03/01/02

