tuco

Electronics

Amplifier, Power, 1.6W 12.75-15.35 GHz

Features

- 1.6 Watt Saturated Output Power Level
- Variable Drain Voltage (6-10V) Operation
- ♦ MSAG[™] Process

Description

The MAAP-000071-PKG0003 is a 4-stage 1.6 W power amplifier with on-chip bias networks in a 20 lead MLP package, allowing easy assembly. This product is fully matched to 50 ohms on both the input and output. It can be used as a power amplifier stage or as a driver stage in high power applications.

Each device is 100% RF tested to ensure performance compliance. The part is fabricated using M/A-COM's GaAs Multifunction Self-Aligned Gate (MSAG) Process.

M/A-COM's MSAG™ process features robust silicon-like manufacturing processes, planar processing of ion implanted transistors and multiple implant capability enabling power, low-noise, switch and digital FETs on a single chip. The use of refractory metals and the absence of platinum in the gate metal formulation prevents hydrogen poisoning when employed in hermetic packaging.

Also Available in:					
Description	Die	Ceramic Package	Die Sample Board	Die Mechanical Sample	Packaged Sample Board
Part Number	MAAPGM0071-DIE	MAAPGM0071	MAAP-000071-SMB004	MAAP-000071-MCH000	MAAP-000071-SMB003 (Lead Free)

Electrical Characteristics: $T_B = 30^{\circ}C^1$, $Z_0 = 50 \Omega$, $V_{DD} = 8V$, $I_{DQ} = 900 \text{mA}^2$, $P_{in} = 10 \text{ dBm}$, $R_G = 100 \Omega$

Parameter	Symbol	Typical	Units
Bandwidth	f	12.75-15.35	GHz
Output Power	P _{OUT}	32	dBm
1-dB Compression Point	P1dB	31	dBm
Power Added Efficiency	PAE	19	%
Small Signal Gain	G	24	dB
Input VSWR	VSWR	1.4:1	
Output VSWR	VSWR	2.7:1	
Gate Current	I _{GG}	10	mA
Drain Current	I _{DD}	1400	mA
Output Third Order Intercept	TOI	40	dBm
Third Order Intermod, Pout = 26 dBm (DCL)	IM3	33	dBc

T_B = MMIC Base Temperature 1.

Adjust V_{GG} between –2.6 and –1.2V to achieve specified Idq. 2.

M/A-COM Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. M/A-COM makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does M/A-COM assume any liability whatsoever arising out of the use or application of any product(s) or information.

• Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300

• Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298

Visit www.macom.com for additional data sheets and product information.

MAAP-000071-PKG003 Rev -

Advance Information



Primary Applications

- Point-to-Point Radios
 - 13 and 15 GHz Bands



RoHS Compliant

[•] North America Tel: 800.366.2266 / Fax: 978.366.2266



RoHS Compliant



Amplifier, Power, 1.6W 12.75-15.35 GHz

MAAP-000071-PKG003 Rev — Advance Information

Maximum Ratings³

Parameter	Symbol	Absolute Maximum	Units
Input Power	P _{IN}	15.0	dBm
Drain Supply Voltage	V _{DD}	+12.0	V
Gate Supply Voltage	V _{GG}	-3.0	V
Quiescent Drain Current (No RF)	I _{DQ}	1.42	А
Quiescent DC Power Dissipated (No RF)	P _{DISS}	14.2	W
Junction Temperature	ature T _J 170		°C
Storage Temperature	T _{STG}	-55 to +150	°C

3. Operation beyond these limits may result in permanent damage to the part.

Recommended Operating Conditions⁴

Characteristic	Symbol	Min	Тур	Max	Unit
Drain Voltage	V _{DD}	6.0	8.0	10.0	V
Gate Voltage	V_{GG}	-2.6	-2.0	-1.2	V
Input Power	P _{IN}		10.0	14.0	dBm
Thermal Resistance	Θ_{JC}		10.8		°C/W
MMIC Base Temperature	Τ _B			Note 5	°C

4. Operation outside of these ranges may reduce product reliability.

5. MMIC Base Temperature = $170^{\circ}C - \Theta_{JC} V_{DD} * I_{DQ}$

Operating Instructions

This device is static sensitive. Please handle with care. To operate the device, follow these steps.

- 1. Apply $V_{GG} = -2.7 \text{ V}, V_{DD} = 0 \text{ V}.$
- 2. Ramp V_{DD} to desired voltage, typically 8.0 V.
- 3. Adjust V_{GG} to set I_{DQ} , (approximately @ -2.0 V).
- 4. Set RF input.
- 5. Power down sequence in reverse. Turn V_{GG} off last.



- North America Tel: 800.366.2266 / Fax: 978.366.2266
- Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
- Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298

Visit www.macom.com for additional data sheets and product information.

M/A-COM Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. M/A-COM makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does M/A-COM assume any liability whatsoever arising out of the use or application of any product(s) or information.



Electronics

RoHS Compliant



MAAP-000071-PKG003 Rev – Advance Information

Amplifier, Power, 1.6W 12.75-15.35 GHz



Note: The exposed pad centered on the package bottom must be connected to RF and dc ground for proper electrical and thermal operation.

Refer to M/A-COM Application Note Surface Mounting Instructions for PQFN Packages #S2083* for assembly guidelines.

Additional Precaution: All parts must receive a bake-out of 125°C for 24 hours prior to any solder reflow operation.

*Application Notes can be found by going to the Site Search Page of M/A-COM's web page (http://www.macom.com/Application%20Notes/ index.htm) and searching for the required Application Note.

3

- M/A-COM Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. M/A-COM makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does M/A-COM assume any liability whatsoever arising out of the use or application of any product(s) or information.
- North America Tel: 800.366.2266 / Fax: 978.366.2266
- Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
- Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298

Visit www.macom.com for additional data sheets and product information.



Electronics

RoHS Compliant



Amplifier, Power, 1.6W 12.75-15.35 GHz

MAAP-000071-PKG003 Rev – Advance Information



Figure 3. Demonstration Board PN MAAP-000071-SMB003 (available upon request).

4

M/A-COM Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. M/A-COM makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does M/A-COM assume any liability whatsoever arising out of the use or application of any product(s) or information. • North America Tel: 800.366.2266 / Fax: 978.366.2266

- Europe Tel: 44.1908.574.200 / Fax: 44.1908.574.300
- Asia/Pacific Tel: 81.44.844.8296 / Fax: 81.44.844.8298

Visit www.macom.com for additional data sheets and product information.