### INTEGRATED CIRCUITS

# DATA SHEET

# 74ALVT162827

20-bit buffer/line driver, non-inverting, with  $30\Omega$  termination resistors (3-State)

Product specification Supersedes data of 1997 May 01 IC23 Data Handbook





# 2.5V/3.3V 20-bit buffer/line driver, non-inverting, with 30 $\Omega$ termination resistors (3-State)

### 74ALVT162827

#### **FEATURES**

- Multiple V<sub>CC</sub> and GND pins minimize switching noise
- 5V I/O Compatible
- Live insertion/extraction permitted
- 3-State output buffers
- Outputs include series resistance of 30Ω making external termination resistors unnecessary
- Power-up 3-State
- Output capability: +12mA/-12mA
- Latch-up protection exceeds 500mA per Jedec Std 17
- ESD protection exceeds 2000 V per MIL STD 883 Method 3015 and 200 V per Machine Model
- Bus hold data inputs eliminate the need for external pull-up resistors to hold unused inputs

#### **DESCRIPTION**

The 74ALVT162827 high-performance BiCMOS device combines low static and dynamic power dissipation with high speed and high output drive. It is designed for  $V_{CC}$  operation at 2.5V or 3.3V with I/O compatibility to 5V.

The 74ALVT162827 20-bit buffers provide high performance bus interface buffering for wide data/address paths or buses carrying parity. They have NOR Output Enables (nOE1, nOE2) for maximum control flexibility.

The 74ALVT162827 is designed with  $30\Omega$  series resistance in both the pull-up and pull-down output structures. This design reduces line noise in applications such as memory address drivers, clock drivers and bus receivers/transmitters.

#### **QUICK REFERENCE DATA**

SYMBOL	PARAMETER	CONDITIONS	TYPI	UNIT		
STWBOL	PANAMETER	T <sub>amb</sub> = 25°C	2.5V	3.3V	ONT	
t <sub>PLH</sub> t <sub>PHL</sub>	Propagation delay nAx to nBx or nBx to nAx	C <sub>L</sub> = 50pF	2.7 2.3	2.2 2.0	ns	
C <sub>IN</sub>	Input capacitance DIR, OE	V <sub>I</sub> = 0V or V <sub>CC</sub>	3	3	pF	
C <sub>Out</sub>	Output capacitance	$V_{I/O} = 0V \text{ or } V_{CC}$	9	9	pF	
I <sub>CCZ</sub>	Total supply current	Outputs disabled	40	70	μΑ	

#### ORDERING INFORMATION

PACKAGES	TEMPERATURE RANGE	OUTSIDE NORTH AMERICA	NORTH AMERICA	DWG NUMBER
56-Pin Plastic SSOP Type III	-40°C to +85°C	74ALVT162827 DL	AV162827 DL	SOT371-1
56-Pin Plastic TSSOP Type II	–40°C to +85°C	74ALVT162827 DGG	AV162827 DGG	SOT364-1


#### PIN DESCRIPTION

PIN NUMBER	SYMBOL	FUNCTION
55, 54, 52, 51, 49, 48, 47, 45, 44, 43, 42, 41, 40, 38, 37, 36, 34, 33, 31, 30	1A0 - 1A9 2A0 - 2A9	Data inputs
2, 3, 5, 6, 8, 9, 10, 12, 13, 14, 15, 16, 17, 19, 20, 21, 23, 24, 26, 27	1Y0 - 1Y9 2Y0 - 2Y9	Data outputs
1, 56, 28, 29	1 <u>0</u> E0, 1 <u>0</u> E1 2 <u>0</u> E0, 2 <u>0</u> E1	Output enable inputs (active-Low)
4, 11, 18, 25, 32, 39, 46, 53	GND	Ground (0V)
7, 22, 35, 50	V <sub>CC</sub>	Positive supply voltage


# 2.5V/3.3V 20-bit buffer/line driver, non-inverting, with $30\Omega$ termination resistors (3-State)

### 74ALVT162827


#### PIN CONFIGURATION



#### LOGIC SYMBOL



### LOGIC SYMBOL (IEEE/IEC)



#### **FUNCTION TABLE**


INPU	JTS	OUTPUTS	OPERATING MODE
nOEx	nAx	nYx	OF ERATING MODE
L	L	L	Transparent
L	Н	Н	Transparent
Н	Х	Z	High impedance

Don't care

Ζ High impedance "off" state

High voltage level L = Low voltage level


#### SCHEMATIC OF EACH OUTPUT



# 2.5V/3.3V 20-bit buffer/line driver, non-inverting, with $30\Omega$ termination resistors (3-State)

74ALVT162827

#### **LOGIC DIAGRAM**



#### ABSOLUTE MAXIMUM RATINGS1, 2

SYMBOL	PARAMETER	CONDITIONS	RATING	UNIT
V <sub>CC</sub>	DC supply voltage		-0.5 to +7.0	V
I <sub>IK</sub>	DC input diode current	V <sub>1</sub> < 0	-18	mA
VI	DC input voltage <sup>3</sup>		-1.2 to +7.0	V
I <sub>OK</sub>	DC output diode current	V <sub>O</sub> < 0	-50	mA
V <sub>OUT</sub>	DC output voltage <sup>3</sup>	output in Off or High state	-0.5 to +5.5	V
I <sub>OUT</sub>	DC output current	output in Low state	128	mA
T <sub>stg</sub>	Storage temperature range		-65 to 150	°C

#### NOTES:

- 1. Stresses beyond those listed may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
- The performance capability of a high-performance integrated circuit in conjunction with its thermal environment can create junction temperatures which are detrimental to reliability. The maximum junction temperature of this integrated circuit should not exceed 150°C.
- 3. The input and output voltage ratings may be exceeded if the input and output current ratings are observed.

#### **RECOMMENDED OPERATING CONDITIONS**

SYMBOL	PARAMETER	2.5V RANG	2.5V RANGE LIMITS		3.3V RANGE LIMITS	
STWBOL	FARAMETER	MIN	MAX	MIN	MAX	UNIT
V <sub>CC</sub>	DC supply voltage	2.3	2.7	3.0	3.6	V
V <sub>I</sub>	Input voltage	0	5.5	0	5.5	V
V <sub>IH</sub>	High-level input voltage	1.7		2.0		V
V <sub>IL</sub>	Input voltage		0.7		0.8	V
Іон	High-level output current		-8		-12	mA
I <sub>OL</sub>	Low-level output current		12		12	mA
Δt/Δν	Input transition rise or fall rate; Outputs enabled		10	·	10	ns/V
T <sub>amb</sub>	Operating free-air temperature range	-40	+85	-40	+85	°C

## 2.5V/3.3V 20-bit buffer/line driver, non-inverting, with $30\Omega$ termination resistors (3-State)

74ALVT162827

### DC ELECTRICAL CHARACTERISTICS (3.3V $\pm$ 0.3V RANGE)

SYMBOL PARAMETER		TEST CONDITIONS		LIMITS			
				Temp = -40°C to +8		+85°C	UNIT
				MIN	TYP <sup>1</sup>	MAX	1
V <sub>IK</sub>	Input clamp voltage	$V_{CC} = 3.0V; I_{IK} = -18mA$			-0.85	-1.2	V
V <sub>OH</sub>	High-level output voltage	$V_{CC} = 3.0V; I_{OH} = -12mA$		2.0	2.3		V
V <sub>OL</sub>	Low-level output voltage	V <sub>CC</sub> = 3.0V; I <sub>OL</sub> = 12mA			0.5	0.8	V
		$V_{CC} = 3.6V$ ; $V_I = V_{CC}$ or GND	Control pins		0.1	±1	
	land to the second	V <sub>CC</sub> = 0 or 3.6V; V <sub>I</sub> = 5.5V			0.1	10	1 .
H	Input leakage current	V <sub>CC</sub> = 3.6V; V <sub>I</sub> = V <sub>CC</sub>	5		0.5	1	μΑ
		V <sub>CC</sub> = 3.6V; V <sub>I</sub> = 0	Data pins <sup>4</sup>		0.1	-5	
I <sub>OFF</sub>	Off current	$V_{CC} = 0V$ ; $V_I$ or $V_O = 0$ to 4.5V	•		0.1	±100	μΑ
	Due Hold current	$V_{CC} = 3V; V_I = 0.8V$		75	130		μΑ
$I_{HOLD}$	Bus Hold current  Data inputs <sup>6</sup>	V <sub>CC</sub> = 3V; V <sub>I</sub> = 2.0V		-75	-140		μΑ
	Data inputs	$V_{CC} = 0V \text{ to } 3.6V; V_{CC} = 3.6V$		±500			μΑ
I <sub>EX</sub>	Current into an output in the High state when V <sub>O</sub> > V <sub>CC</sub>	V <sub>O</sub> = 5.5V; V <sub>CC</sub> = 3.0V			10	125	μА
I <sub>PU/PD</sub>	Power up/down 3-State output current <sup>3</sup>	$V_{CC} \le 1.2V$ ; $V_O = 0.5V$ to $V_{CC}$ ; $V_I = GNI$ OE/OE = Don't care	O or V <sub>CC</sub>		1	±100	μΑ
I <sub>OZH</sub>	3-State output High current	$V_{CC} = 3.6V$ ; $V_{O} = 3.0V$ ; $V_{I} = V_{IL}$ or $V_{IH}$			0.5	5	μΑ
I <sub>OZL</sub>	3-State output Low current	$V_{CC} = 3.6V; V_O = 0.5V; V_I = V_{IL} \text{ or } V_{IH}$			0.5	<b>-</b> 5	μΑ
I <sub>CCH</sub>		$V_{CC} = 3.6V$ ; Outputs High, $V_I = GND$ or $V_{CC}$ , $I_{O} = 0$			0.07	0.1	
I <sub>CCL</sub>	Quiescent supply current	$V_{CC} = 3.6V$ ; Outputs Low, $V_I = GND$ or $V_{CC}$ , $I_{O} = 0$			3.9	5.5	mA
I <sub>CCZ</sub>	1	$V_{CC}$ = 3.6V; Outputs Disabled; $V_I$ = GND or $V_{CC}$ , $I_O$ = $0^5$			0.07	0.1	1
Δl <sub>CC</sub>	Additional supply current per input pin <sup>2</sup>	$V_{CC}$ = 3V to 3.6V; One input at $V_{CC}$ -0.6V, Other inputs at $V_{CC}$ or GND			0.04	0.4	mA

- All typical values are at V<sub>CC</sub> = 3.3V and T<sub>amb</sub> = 25°C.
   This is the increase in supply current for each input at the specified voltage level other than V<sub>CC</sub> or GND
   This parameter is valid for any V<sub>CC</sub> between 0V and 1.2V with a transition time of up to 10msec. From V<sub>CC</sub> = 1.2V to V<sub>CC</sub> = 3.3V ± 0.3V a transition time of 100µsec is permitted. This parameter is valid for T<sub>amb</sub> = 25°C only.
- 4. Unused pins at V<sub>CC</sub> or GND.
  5. I<sub>CCZ</sub> is measured with outputs pulled up to V<sub>CC</sub> or pulled down to ground.
- 6. This is the bus hold overdrive current required to force the input to the opposite logic state.

### AC CHARACTERISTICS (3.3V $\pm$ 0.3V RANGE)

GND = 0V,  $t_R = t_F = 2.5 \text{ns}$ ,  $C_L = 50 \text{pF}$ ,  $R_L = 500 \Omega$ 

SYMBOL PARAMETER		WAVEFORM	T <sub>an</sub> V <sub>C</sub>	UNIT		
			MIN	TYP	MAX	
t <sub>PLH</sub> t <sub>PHL</sub>	Propagation delay nAx to nYx	1	1.0 1.0	2.2 2.0	3.3 3.0	ns
t <sub>PZH</sub> t <sub>PZL</sub>	Output enable time to High and Low level	2	1.5 1.0	3.4 2.4	5.6 3.7	ns
t <sub>PHZ</sub> t <sub>PLZ</sub>	Output disable time from High and Low level	2	1.5 1.0	3.4 2.7	5.2 4.5	ns

# 2.5V/3.3V 20-bit buffer/line driver, non-inverting, with $30\Omega$ termination resistors (3-State)

74ALVT162827

#### DC ELECTRICAL CHARACTERISTICS (2.5V $\pm$ 0.2V RANGE)

SYMBOL PARAMETER		TEST CONDITIONS		LIMITS			
				Temp = -40°C to +8		+85°C	UNIT
				MIN	TYP <sup>1</sup>	MAX	
V <sub>IK</sub>	Input clamp voltage	$V_{CC} = 2.3V; I_{IK} = -18mA$			-0.85	-1.2	V
V <sub>OH</sub>	High-level output voltage	$V_{CC} = 2.3V; I_{OH} = -8mA$		1.7	2.3		V
V <sub>OL</sub>	Low-level output voltage	V <sub>CC</sub> = 2.3V; I <sub>OL</sub> = 12mA			0.5	0.7	V
		$V_{CC} = 2.7V$ ; $V_I = V_{CC}$ or GND	Control pins		0.1	±1	
l <sub>1</sub>	Input leakage current	$V_{CC} = 0 \text{ or } 2.7V; V_I = 5.5V$			0.1	10	μА
Ц	Imput leakage current	$V_{CC} = 2.7V; V_I = V_{CC}$	Data pins <sup>4</sup>		0.1	1	μΑ
		$V_{CC} = 2.7V; V_I = 0$	Data pins		0.1	-5	1
I <sub>OFF</sub>	Off current	$V_{CC} = 0V$ ; $V_I$ or $V_O = 0$ to 4.5V	•		0.1	±100	μΑ
I <sub>HOLD</sub>	Bus Hold current	$V_{CC} = 2.3V; V_{I} = 0.7V$			115		
HOLD	Data inputs <sup>6</sup>	V <sub>CC</sub> = 2.3V; V <sub>I</sub> = 1.7V			-10		μΑ
I <sub>EX</sub>	Current into an output in the High state when V <sub>O</sub> > V <sub>CC</sub>	V <sub>O</sub> = 5.5V; V <sub>CC</sub> = 2.3V			10	125	μΑ
I <sub>PU/PD</sub>	Power up/down 3-State output current <sup>3</sup>	$V_{CC} \le 1.2V$ ; $V_O = 0.5V$ to $V_{CC}$ ; $V_I = GNE$ OE/OE = Don't care	or V <sub>CC</sub> ;		1	100	μΑ
I <sub>OZH</sub>	3-State output High current	$V_{CC} = 2.7V; V_{O} = 2.3V; V_{I} = V_{IL} \text{ or } V_{IH}$			0.5	5	μΑ
I <sub>OZL</sub>	3-State output Low current	$V_{CC} = 2.7V$ ; $V_O = 0.5V$ ; $V_I = V_{IL}$ or $V_{IH}$	$V_{CC} = 2.7V; V_{O} = 0.5V; V_{I} = V_{IL} \text{ or } V_{IH}$		0.5	-5	μΑ
Icch		$V_{CC} = 2.7V$ ; Outputs High, $V_I = GND$ or $V_{CC}$ , $I_{O} = 0$			0.04	0.1	
I <sub>CCL</sub>	Quiescent supply current	$V_{CC}$ = 2.7V; Outputs Low, $V_I$ = GND or $V_{CC}$ , $I_{O}$ = 0			3.5	5.0	mA
I <sub>CCZ</sub>	1	$V_{CC}$ = 2.7V; Outputs Disabled; $V_I$ = GND or $V_{CC}$ , $I_O$ = $0^5$			0.04	0.1	1
Δl <sub>CC</sub>	Additional supply current per input pin <sup>2</sup>	$V_{CC}$ = 2.3V to 2.7V; One input at $V_{CC}$ -0 Other inputs at $V_{CC}$ or GND	.6V,		0.04	0.4	mA

- All typical values are at V<sub>CC</sub> = 2.5V and T<sub>amb</sub> = 25°C.
   This is the increase in supply current for each input at the specified voltage level other than V<sub>CC</sub> or GND
- 3. This parameter is valid for any  $V_{CC}$  between 0V and 1.2V with a transition time of up to 10msec. From  $V_{CC}$  = 1.2V to  $V_{CC}$  = 2.5V  $\pm$  0.2V a transition time of 100 $\mu$ sec is permitted. This parameter is valid for  $T_{amb}$  = 25°C only.
- 4. Unused pins at V<sub>CC</sub> or GND.
- 5. I<sub>CCZ</sub> is measured with outputs pulled up to V<sub>CC</sub> or pulled down to ground.
- 6. Not guaranteed.

### AC CHARACTERISTICS (2.5V $\pm$ 0.2V RANGE)

GND = 0V,  $t_R = t_F = 2.5$ ns,  $C_L = 50$ pF,  $R_L = 500\Omega$ 


SYMBOL PARAMETER		WAVEFORM	T <sub>an</sub> V <sub>C</sub>	UNIT		
			MIN	TYP	MAX	
t <sub>PLH</sub> t <sub>PHL</sub>	Propagation delay nAx to nYx	1	1.5 1.5	2.7 2.3	4.5 3.5	ns
t <sub>PZH</sub> t <sub>PZL</sub>	Output enable time to High and Low level	2	2.5 1.5	4.7 2.9	7.5 4.7	ns
t <sub>PHZ</sub> t <sub>PLZ</sub>	Output disable time from High and Low level	2	1.5 1.0	3.2 2.4	5.2 4.0	ns

# 2.5V/3.3V 20-bit buffer/line driver, non-inverting, with $30\Omega$ termination resistors (3-State)


74ALVT162827

#### **AC WAVEFORMS**

 $\begin{array}{l} V_{M} = 1.5 V \; for \; V_{CC} \geq 3.0 V; \; V_{M} = V_{CC} / 2 \; for \; V_{CC} \leq 2.7 V \\ V_{X} = V_{OL} + 0.3 V \; for \; V_{CC} \geq 3.0 V; \; V_{X} = V_{OL} + 0.15 V \; for \; V_{CC} \leq 2.7 V \\ V_{Y} = V_{OH} - 0.3 V \; for \; V_{CC} \geq 3.0 V; \; V_{Y} = V_{OH} - 0.15 V \; for \; V_{CC} \leq 2.7 V \end{array}$ 




Waveform 1. Input (nAx) to Output (nYx) Propagation Delays



Waveform 2. 3-State Output Enable and Disable Times

#### **TEST CIRCUIT AND WAVEFORM**



#### **SWITCH POSITION**

TEST	SWITCH
t <sub>PLZ</sub> /t <sub>PZL</sub>	6V or V <sub>CC x 2</sub>
t <sub>PLH</sub> /t <sub>PHL</sub>	Open
t <sub>PHZ</sub> /t <sub>PZH</sub>	GND

#### **DEFINITIONS**

R<sub>L</sub> = Load resistor; see AC CHARACTERISTICS for value.

 $C_L = Load$  capacitance includes jig and probe capacitance: See AC CHARACTERISTICS for value.

 $R_T$  = Termination resistance should be equal to  $Z_{OUT}$  of pulse generators.

FARALLY	INPUT PULSE REQUIREMENTS						
FAMILY	Amplitude	Rep. Rate	t <sub>W</sub>	t <sub>R</sub>	t <sub>F</sub>		
74ALVT16	3.0V or V <sub>CC</sub> whichever is less	≤10MHz	500ns	≤2.5ns	≤2.5ns		

V<sub>M</sub> = 1.5V or V<sub>CC</sub>/2 whichever is less Input Pulse Definition

SW00025


1998 Feb 13 7

# 20-bit buffer/line driver, non-inverting, with $30\Omega$ termination resistors (3-State)

### 74ALVT162827

### SSOP56: plastic shrink small outline package; 56 leads; body width 7.5 mm

SOT371-1



UNIT	A max.	Α <sub>1</sub>	A <sub>2</sub>	A <sub>3</sub>	рb	С	D <sup>(1)</sup>	E <sup>(1)</sup>	е	HE	L	Lp	Q	v	w	у	Z <sup>(1)</sup>	θ
mm	2.8	0.4 0.2	2.35 2.20	0.25	0.3 0.2	0.22 0.13	18.55 18.30	7.6 7.4	0.635	10.4 10.1	1.4	1.0 0.6	1.2 1.0	0.25	0.18	0.1	0.85 0.40	8° 0°


#### Note

1. Plastic or metal protrusions of 0.25 mm maximum per side are not included.

OUTLINE		REFER	EUROPEAN	ISSUE DATE			
VERSION	IEC	JEDEC	EIAJ		PROJECTION	ISSUE DATE	
SOT371-1		MO-118AB				<del>93-11-02</del> 95-02-04	

TSSOP56: plastic thin shrink small outline package; 56 leads; body width 6.1mm

SOT364-1



# 20-bit buffer/line driver, non-inverting, with $30\Omega$ termination resistors (3-State)

74ALVT162827

#### Data sheet status

Data sheet status	Product status	Definition [1]
Objective specification	Development	This data sheet contains the design target or goal specifications for product development. Specification may change in any manner without notice.
Preliminary specification	Qualification	This data sheet contains preliminary data, and supplementary data will be published at a later date. Philips Semiconductors reserves the right to make chages at any time without notice in order to improve design and supply the best possible product.
Product specification	Production	This data sheet contains final specifications. Philips Semiconductors reserves the right to make changes at any time without notice in order to improve design and supply the best possible product.

<sup>[1]</sup> Please consult the most recently issued datasheet before initiating or completing a design.

#### **Definitions**

**Short-form specification** — The data in a short-form specification is extracted from a full data sheet with the same type number and title. For detailed information see the relevant data sheet or data handbook.

Limiting values definition — Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.

**Application information** — Applications that are described herein for any of these products are for illustrative purposes only. Philips Semiconductors make no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

#### **Disclaimers**

**Life support** — These products are not designed for use in life support appliances, devices or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips Semiconductors customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips Semiconductors for any damages resulting from such application.

Right to make changes — Philips Semiconductors reserves the right to make changes, without notice, in the products, including circuits, standard cells, and/or software, described or contained herein in order to improve design and/or performance. Philips Semiconductors assumes no responsibility or liability for the use of any of these products, conveys no license or title under any patent, copyright, or mask work right to these products, and makes no representations or warranties that these products are free from patent, copyright, or mask work right infringement, unless otherwise specified.

Philips Semiconductors 811 East Arques Avenue P.O. Box 3409 Sunnyvale, California 94088–3409 Telephone 800-234-7381 © Copyright Philips Electronics North America Corporation 1998 All rights reserved. Printed in U.S.A.

print code Date of release: 05-96

Document order number: 9397-750-03651

Let's make things better.

Philips Semiconductors



