



Is Now Part of



ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at

www.onsemi.com

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

Application Note 1032

July, 1999

Performance Restrictions Associated with 3.5 Watts SO-8 Power MOSFETs

Alan Li, Sr. Applications Engineer

In applications requiring high current and small footprint electronic switches, a Power MOSFET packaged in an SO-8 is usually the best choice. This is because the combination offers low on-resistance and reasonable power handling. A second benefit is the numerous suppliers for this product. As a result, SO-8 Power MOSFETs are commonly found in applications such as notebook computer DC-DC converters, battery chargers, and disk drive motor controls.

SO-8 packaged Power MOSFETs handle about one Watt under "typical" conditions (Figure 1), regardless of the silicon size. The thermal capability of any semiconductor is strongly related to the operating conditions, however users often overlook the importance of such criteria. In addition, the lack of an industry standard means that MOSFET manufacturers may mislead the power handling of SO-8 Power MOSFETs by two to four times their typical thermal capability. Users should also remember that current handling is proportional to power handling. By simply manipulating the power rating conditions, MOSFET manufacturers can tailor any current rating to any "non-typical" condition.

Of particular concern is a claim circulating that 3.5 Watt SO-8 Power MOSFETs exist in the industry. This is another twist in addition to the existing ill-defined 2.5 Watt power rating. If users carefully read the fine print of the disclaimer on the datasheets, it reveals that 3.5 Watt power handling can only be achieved "when mounted on a 1 inch square copper board; $t < 10$ sec." Such conditions are not only unrealistic, but also pose a potential hazard for those who design parts with this information. As a result, it is not uncommon to see SO-8 Power MOSFETs being destroyed when they smoke during lab experiments.

The disclaimers are technically correct but unrealistic for two reasons. First, one square inch of board space is somewhat equivalent to the size of a typical CPU, (Figure 2). Realistically, no one can afford such precious space for a MOSFET switch in any portable electronics. Secondly, SO-8 Power MOSFETs reach thermal equilibrium in a few minutes. That means a 10 second operation is far from the worst case condition. As a general rule, SO-8 Power MOSFETs handle about one Watt under "typical" conditions (Figure 1).

In order to calculate power handling rather than rely on datasheet specifications, users should be familiar with the parameter $R_{\theta JA}$. Since $T_J - T_A = P_D * R_{\theta JA}$ (Equation 1), power handling can be calculated assuming the maximum allowable temperature, ambient temperature, and $R_{\theta JA}$ at a given condition are known. To facilitate users in proper thermal design, Fairchild Semiconductor publishes different $R_{\theta JA}$ specifications at various conditions.




Figure 1. Typical Condition

$$R_{\theta JA} = 125 \text{ }^\circ\text{C/W} \rightarrow P_D = 1 \text{ W}$$




Figure 2. 1 in² 2oz Copper PAD

$$R_{\theta JA} (10\text{sec}) = 36 \text{ }^\circ\text{C/W} \rightarrow P_D(10\text{sec}) = 3.5 \text{ W}$$

$$R_{\theta JA} = 50 \text{ }^\circ\text{C/W} \rightarrow P_D = 2.5 \text{ W}$$

Equation 1.

$$T_J - T_A = P_D * R_{\theta JA}$$

where:

T_J = Junction Temperature

T_A = Ambient Temperature

P_D = Power Dissipation

Be Aware That Under "Typical" Conditions, SO-8 Power MOSFETs Only Handle About One Watt.

TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx™	ISOPLANAR™	UHC™
CoolFET™	MICROWIRE™	VCX™
CROSSVOLT™	POP™	
E ² CMOS™	PowerTrench™	
FACT™	QST™	
FACT Quiet Series™	Quiet Series™	
FAST®	SuperSOT™-3	
FASTr™	SuperSOT™-6	
GTO™	SuperSOT™-8	
HiSeC™	TinyLogic™	

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

ON Semiconductor and  are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor
19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada
Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free
USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81-3-5817-1050

ON Semiconductor Website: www.onsemi.com
Order Literature: <http://www.onsemi.com/orderlit>
For additional information, please contact your local
Sales Representative