

WIDE BAND CHOKE 宽带扼流电感

R6H/RH/RID 系列


FEATURES

- Low DC resistance.
- High impedance over a wide frequency range.

APPLICATIONS

- Used in PC boards to filter the EMI from the outside. For radio, Telephone, and TV, PC, A/V equipments, etc.

DIMENSIONS (mm)



ITEM	A(±0.15)	B(±0.30)	C(±2.0)	D(±0.05)	E(±0.5)	F(±0.5)	G(±0.5)
RH 3.5×4.7×0.8	3.5	4.7	64	0.65	52	6.0	5.0
RH 3.5×6.0×0.8	3.5	6.0	64	0.65	52	6.0	5.0
RH 3.5×9.0×0.8	3.5	9.0	64	0.65	52	6.0	5.0
RID230575-0.5TS	2.3	6.0	8.0	0.60	5.0		
R6H0610-SERIES	6.0	10.0					

ELECTRICAL CHARACTERISTICS

PART NO.	WINDING	WIRE SIZE (T.C.W)	IMPEDANCE(Ω) (min)			FIG
			10 MHz	25 MHz	100MHz	
R6H0610-1.5TS	1.5TS	0.50	150	250	390	1
R6H0610-2.0TS	2.0TS	0.50	200	350	480	2
R6H0610-2.5TS	2.5TS	0.50	280	495	540	3
R6H0610-3.0TS	3.0TS	0.50	355	640	535	4
R6H0610-2×1.5TS	2×1.5TS	0.50	150	250	380	5
RID230575-0.5TS	0.5TS	0.60		65		6
RH 3.5×4.7×0.8	0.5TS	0.50		47	64	7
RH 3.5×6.0×0.8	0.5TS	0.50		57	84	7
RH 3.5×9.0×0.8	0.5TS	0.50		92	140	7

特 征

- 低直流电阻；
- 在较宽得频率范围内有较高的阻抗。

用 途

- 适用于电路板的 EMI 滤波电路。如收音机，电话机，电视机，电脑，影音设备等。