# Thin type / Surface Mount type 4 Direction Detector





	Parameter	Symbol	Limits	Unit
Input (LED)	Forward current	lF	50	mA
	Reverse voltage	VR	5	V
	Power dissipation	Po	80	mW
Output (photo- (transistor)	Collector-emitter voltage	Vceo	30	V
	Emitter-collector voltage	Veco	4.5	V
	Collector current	lc	30	mA
	Collector power dissipation	Pc	80	mW
Operating temperature		Topr	-25 to +85	°C
	Storage temperature	Tstg	-30 to +85	°C

## **Applications**

DSC(Digital steal camera) DVC(Digital video camera) Digital handy phone, Fan herater,

### **Features**

- 2) Optical Sensor3) 4 Pirection Detector4) Noise less type

### Electrical and optical characteristics (Ta=25°C)

			Symbol	Min.	Тур.	Max.	Unit	Conditions
Input charac- teristics	Forward voltage		VF	-	1.1	1.3	V	I <sub>F</sub> =5mA
Inpu chai teris	Reverse current		IR	-	-	10	μΑ	V <sub>R</sub> =10V
Output charac- teristics	Dark current		Iceo	-	-	0.5	μА	Vce=10V
Transfer characteristics	Collector current		Ic	50	80	-	μА	Vce=5V, Ir=5mA
	DC leakage current		Ileak	-	10	20	μΑ	Vce=5V, Ir=5mA
	Collector-emitter saturation voltage		VcE(sat)	_	_	0.4	V	I <sub>F</sub> =5mA, I <sub>C</sub> =0.05mA
	Response time	Rise time	tr	-	10	-	μs	V 5V L 0.05 A B 4000
		Fall time	tf	-	10	-	μs	Vcc=5V, Ic=0.05mA, RL=100Ω
Infrared light emitter diode	Peak light emitting wavelength		λР	-	950	-	nm	I==50mA  * Non-coherent Infrared light emitting diode used.
Photo transistor	Maximum sensitivity wavelength		λР	-	800	-	nm	-

### Electrical and optical characteristics curves




Fig.1 Forward current falloff




Fig.4 Relative output vs. ambient




Fig.2 Forward current vs. forward




Fig.5 Collector current vs. forward current




Fig.3 Power dissipation / collector power dissipation vs. ambient temperature







Fig.6 DC leakage current vs. forward current











Fig.9 Output characteristics



#### Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.



Thank you for your accessing to ROHM product informations. More detail product informations and catalogs are available, please contact us.

## ROHM Customer Support System

http://www.rohm.com/contact/