

Hard Ceiling Mount for PEAR M5542i Pigtail

Hard Ceiling Installation

DESCRIPTION:

Galtronics hard ceiling mount offers an easy installation solution to mount Galtronics' PEAR M5542i antenna to hard ceilings not requiring a second access hole. Mounting hardware is not included, make sure the selected fasteners are appropriate based on the ceiling material to which the hard ceiling mount is attached to.

ADDITIONAL INFORMATION:

* Hard ceiling mounting kit can be painted with recommended paint "Krylon Fusion for Plastic".


MOUNTING & ANTENNA OPTIONS

02121261-05542U PEAR M5542i Pigtail Antenna

62-31-09 Hard Ceiling Mounting Kit


A

- Cut a hole with a diameter of Ø4.5" (115 mm) to the ceiling and mark holes for countersunk head screws Ø3.5 mm / 0.137"




B

- Thread the antenna Pigtail through the ceiling adapter and connect the antenna to the DAS system coax cable



C

- Place the hard ceiling Adapter in the center hole and attach it with 3 countersunk head screws Ø3.5 mm / 0.137" suitable for the ceiling material (not provided)



- Insert the antenna into the hard ceiling adapter, push it towards the ceiling and lock it. ("a click sound should be heard") as shown in below illustration

