

PEAR™ S5591i

Outdoor/In-Building Directional Antenna

[380-470/698-960/1695-2700 MHz]



Description:

Directional wall mount antenna for outdoor and in-building applications such as DAS. The antenna is vertically polarized and operates at 380-2700 MHz covering also the public safety frequency band for TETRA.



Ordering & Antenna Options			
Part Number	Connector	Description	Environmental
02121312-05591	N-Type (F)	PEAR™ S5591i	Indoor / Outdoor
02125312-05591	4.1-9.5 DIN (F)	PEAR™ S5591i	Indoor / Outdoor
02130312-05591	4.3-10 DIN (F)	PEAR™ S5591i	Indoor / Outdoor
62-29-03		2-Axis Swivel Mounting Bracket	

Electrical Specifications					
Frequency Band [MHz]	380-470	698-790	790-960	1695-2180	2180-2700
Input Connector Type	N-Type or 4.3-10 DIN or 4.1-9.5 DIN Connector (F) with cable (12"/30cm length)				
Polarization	Vertical				
Impedance	50 Ω				
VSWR/Return Loss	<3.7:1/4.8 dB	<2.5:1/7.3 dB		<1.8:1/10.9 dB	
Gain	2.0 dBi	5.0 dBi		7.0 dBi	
Vertical Beamwidth	>120°	80°	110°	70°	70°
Horizontal Beamwidth	>120°	100°	100°	75°	75°
PIM @ 2x43 dBm	<-153 dBc for 4.3-10 DIN <-150 dBc for N-Type or 4.1-9.5 DIN				
Input Power	50 W at ambient temperature of 77° F (25° C)				



Mechanical Specifications			
Operating Temperature	-67° to 158 °F (-55° to +70°C)		
Environmental Conditions	Outdoor / Indoor		
Antenna Weight	13.22 lbs (600g)		
Antenna Dimensions (H x W x D)	10.2" x 8.0" x 2.5" (256 x 200 x 65 mm)		
Flammability rating	UL 94-V0		
RoHS	Compliant		
Radome Color	RAL 9016 (white)*		
Outdoor Ingress Protection	IP65		
Cable	Plenum Rated		
Shipping Dimensions	15.7" x 10.6" x 5.3" / 400 x 270 x 135 mm		
Shipping Weight (Gross Weight)	3.52 lbs (1.6 Kg)		

^{*} Radome can be painted with recommended paint "Krylon fusion for plastic"

Mounting Options

This antenna can be mounted using any of the following mounting brackets. Optional mounting brackets need to be ordered as a separate line item. See Ordering Options for details (see page 1).

Mounting Plate Installation (Standard)

After affixing the mounting plate to the wall, then mount the antenna on to the mounting plate by sliding it into the slots and securing it with the provided fasteners.

Included with antenna



Optional Swivel Mounting Bracket

Video Clip

Galtronics swivel mounting bracket offers an easy installation solution to mount Galtronics' PEAR panel antennas to either a pole or a wall. The mounting bracket allows a tilt of up to +/-45deg in the horizontal as well as in the vertical plane.

P/N: 62-29-03





