

SPECIFICATION SHEET

JFW MODEL 50PD-136

5 WAY RESISTIVE POWER DIVIDER

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	DC-2000 MHz
Impedance	50 Ohms nominal
VSWR	1.2:1 maximum to 500 MHz 1.3:1 maximum to 1000 MHz 1.4:1 maximum to 2000 MHz
Insertion Loss	14 dB ± 0.7 dB
Amplitude Tracking	± 0.5 dB
RF Input Power	2 Watts average @ 25°C 100 Watts peak (1 microsecond)
Operating Temperature Range	-40°C to +85°C
RF Connector	N or BNC female
Physical Size	See outline drawing 092-2328-05 (N) 092-6646-05 (BNC)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	04/15/1997			14297	07/02/2003	C	CLV 07/02/2003
874	11/03/1997	A		18885	07/15/2010	D	TRS 07/15/2010
9999	11/16/2002	B	SL 11/27/2002				