

SPECIFICATION SHEET

JFW MODEL 50PD-335

2 WAY RESISTIVE POWER DIVIDER

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	DC-3000 MHz
Impedance	50 Ohms nominal
VSWR	1.2:1 maximum to 500 MHz 1.3:1 maximum to 1000 MHz 1.4:1 maximum to 3000 MHz
Insertion Loss	6 dB \pm 0.5 dB DC-2000 MHz 6 dB \pm 0.75 dB 2000-3000 MHz
Amplitude Tracking	\pm 0.4 dB
RF Input Power	2 Watts average (divider) 1 Watt average (combiner)
RF Connector	BNC, TNC, or N female
Physical Size	See outline drawing 092-2328-02 (N) 092-6646-02 (BNC)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	06/08/2000			16950	03/12/2009	C	TRS 03/12/2009
9999	12/17/2002	A	SL 12/19/2002	18885	07/15/2010	D	TRS 07/15/2010
15752	03/24/2008	B	TRS 04/24/2008				