



MA-WD35-DS15

3.3-3.8 GHz Dual Slant WiMAX Base Station Antenna, 90°

MARS Dual Slant Base Station Antenna is light-weight yet has a robust and durable construction.

Additional Features:

- Specially designed for WiMAX applications.
- · Quick and easy installation.
- · Easy mounting allowing obtaining required down tilt.
- Suitable for harsh environment installations.
- DC grounded.

Applications:

- WiMAX licensed band applications.
- · Point-to-Multi Point Applications.
- WLL applications.



Specifications

_		-	-		
_	ıΔ	ct	rı	ca	

Frequency range	3.3-3.8 GHz
GAIN, typ.	15 dBi
VSWR, max.	1.7 : 1
Polarization	Dual Polarized ±45°
3 dB Beam-Width, H-Plane, typ.	90°
3 dB Beam-Width, E-Plane, typ.	8°
Down tilt, E-Plane	2°
Front to Back Ratio.	-20 dB
Port to Port Isolation	-30 dB
Input power, max.	50 Watt
Input Impedance	50 Ohm
Lightning Protection	DC Grounded

Mechanical

Dimensions (HxWxD)	600 x 225 x 40 mm (23.6" x 8.9" x 1.6")
Weight	1.8 kg.
Connector	2 x N-Type, Female (bottom)
Back Plane	Aluminum protected through chemical passivation
Radome	UV Protected Plastic
Mount	See ordering options

Environmental

Operating Temperature Range	-40°C to +65°C
Vibration	According to IEC 60721-3-4
Wind Load	200 km/h (survival)
Flammability	UL94
Water Proofing	IP-65
Humidity	ETS 300 019-1-4, EN 302 085 (annex A.1.1)
Salt Fog	According to IEC 68-2-11
Ice and Snow	25mm radial (survival)

Standard Compliance

ETSI EN 30	2 085 V1	.2.3 - CS1
------------	----------	------------

Ordering Options	
MA-WD35-DS15	Antenna Suited for MNT-22 (optional wall/pole adjustable mount)
MA-WD35-DS15B	Antenna with MNT-22 mount

Patterns are available on our website

MARS Antennas & RF Systems proprietary information

MARS reserves the right to make technical changes or modifications to any of its products and specifications without prior notice and without implementing such changes to prior supplied products. Product images are representative and indicative only. Warranty terms and general conditions of sale are applicable on any purchase of any product, available on MARS website.

Tel: +972-3-5599661 • Fax: +972-3-5599677 • e-mail: mars@marsant.co.il • web: www.mars-antennas.com