

2 SC 1326	Mat	Si-N	VHF Drv.Out, 55/30V, 0.4A, PQ=1W(400MHz/28V)	2a	~TO-5			BFS 23, BFW 47, BLY 34, 2N3553, 2N5160
2 SC 1327	Mat, Mic	Si-N	Uni, In, 35/35V, 50/100mA, 0.15W, 250MHz (2SA721	7c	TO-92	BC 550	7a	BC 169, BC 184, BC 239, BC 549, 2SC2675+
2 SC 1328		Si-N	=2SC1327: 55/55V (2SA722	7c	TO-92	BC 550	7a	BC 414, BC 550, 2SC2240, 2SC2390, ++
2 SC 1329	Nec	Si-N	FM P, 50/25V, 8A, >100MHz, PQ=32W(70MHz/12V)	55s				2SC2313
2 SC 1330	Nec, Mic	Si-N	Uni, 50/40V, 0.1A, 0.4W, 250MHz	7c°	TO-92°	BC 546	7a	BC 167, BC 182, BC 237, BC 547, 2SD767, +
2 SC 1331	Nec	Si-N	IF,UHF, 20/20V, 20mA, 750MHz	5g	TO-72	2SC2570 A	7f	BF 377...378, BF 689, BF 763, 2N2857, ++
2 SC 1333	Nec	Si-N	UHF Drv.Out, 45/25V, 1A, 1200MHz, Gp=5dB(1GHz)	55s				BLW 33...34, 2N4430, 2SC3140
2 SC 1334	Nec	Si-N	UHF Drv.Out, 50/30V, 1A, 1200MHz, Gp=4dB(1GHz)	55s	~SOT-48			BLW 98, BLX 98, 2N4431, 2SC3141
2 SC 1335	Hit	Si-N	Uni, In, 30/30V, 0.1A, 0.2W, 230MHz, F<6dB(120Hz)	9b		BC 550	7a	BC 169, BC 184, BC 239, BC 549, ++
2 SC 1336	Nec	Si-N	UHF, In, 20/15V, 0.03A, 4.5GHz, F=3/Gp=11dB(2GHz)	51s				BFO 71, BFO 85, BFR 14, 2SC1119
2 SC 1337(A)	Mit	Si-N	UHF P, 35/17V, 2A, 1GHz, PQ=8.5W(485MHz/13.5V)	55r				BLW 14, BLW 44, 2N5946
2 SC 1338(A)	Mit	Si-N	UHF P, 35/17V, 3A, 1GHz, PQ=16W(485MHz/13.5V)	55r				BLW 15, BLX 69
2 SC 1339	Mit	Si-N	UHF P, 35/17V, 5A, 1GHz, PQ=28W(485MHz/13.5V)	55r				BLW 15, BLX 69
2 SC 1340	Mit	Si-N	UHF Drv.Out, 35/25V, 1A, 5W, 1GHz, GP=19dB(220MHz)	55r				BLU 97, BLW 43, BLW 80, BLX 68, BLY 53
2 SC 1342	Hit	Si-N	FM Imp,Mx,Os, 30/20V, 30mA, 320MHz, Gp=17dB(100M)	9b, 7c	-, TO-92	BF 255	7d	BF 240...241, BF 254...255, BF 594...595,++
2 SC 1343	Hit	Si-N	P, 150/110V, 10/12A, 100W, 14MHz (2SA753	23a	TO-3	2SC3263	18j	BD 245D, 2SD551, 2SD733, 2SD1047, ++
2 SC 1344	Hit	Si-N	LF, In, 30/30V, 0.1A, 0.2W, 230MHz, F<1dB(1kHz)	9b, 7c	-, TO-92	BC 550	7a	BC 169, BC 184, BC 239, BC 549, ++
2 SC 1345		Si-N	=2SC1344: 55/50V	9b, 7c	-, TO-92	BC 550	7a	BC 414, BC 550, 2SC2240, 2SC2459, ++
2 SC 1346		Si-N	=2SC1317: 0.6W (2SA730	7c°	TO-92°	BC 639	7c	+2SC1317
2 SC 1347		Si-N	=2SC1318: 0.6W (2SA731	7c°	TO-92°	BC 639	7c	+2SC1318
2 SC 1348(-1....-3)	Son	Si-N	TV-HA, 1000...1200V, 4A, 125V, 5MHz	23a	TO-3			(BU 207...209, BU 508, 2SC2928, 2SD954++)
2 SC 1349	Fui	Si-N	SS, 20/15V, 0.2A, 0.2W, -/15ns	2a	TO-46			BSS 11, BSX 19...20, 2N2369...69(A), ++
2 SC 1350	Fui	Si-N	S, 25/20V, 0.3A, 0.3W, -/60ns	2a	TO-18			BSS 11, BSX 19...20, 2N2369...69(A), ++
2 SC 1351	Fui	Si-N	S, 80/65V, 1A, 0.8W, <50/85ns	2a	TO-39			BSV 95, 2N3735, 2SC1069
2 SC 1352	Fui	Si-N	S, 25/15V, 0.8A, 0.6W, <15/20ns	2a	~TO-5			BSS 28...29, BSV 69, BSX 12, 2N3426, ++
2 SC 1353	Fui	Si-N	S, 90/70V, 0.7A, 0.65W, 45/95ns	2a	TO-39			BSW 39, 2SC1069
2 SC 1354	Mat	Si-N	VHF P, 55/35V, 5/10A, 220MHz, PQ=37W(175MHz/24V)	60c				-
2 SC 1355	Fui	Si-N	UHF Drv.Out, 40V, 0.7A, 1800MHz, PQ=2W(700MHz/18V)	55r				BLU 99
2 SC 1356	Fui	Si-N	UHF Drv.Out, 40V, 1A, 1800MHz, PQ=6W(700MHz/18V)	55r				-
2 SC 1358(A)	Nec	Si-N	TV-HA (90°), 1400/500V, 4.5/10A, 50W, sat<10V(4A) A: sat<5V(4.5A)	23a	TO-3	BU 208 A	23a	BU 208...209, BU 508(A), 2SD783, 2SD954++
2 SC 1359	Mat, Mic	Si-N	AM/FM,Uni, 30/20V, 0.03A, 0.4W, 250MHz (2SA838	7c	TO-92	BC 546, BF 255	7a, 7d	BC237, BC548, BF240...241, BF254...255, ++
2 SC 1360(A)	Mat	Si-N	TV IF, 50(A=60)V, 0.05A, >300MHz, Gp=22dB(58MHz)	7c(9mm)	TO-92L	BF 959	7d	BF 370, BF 920...921(S), BF 959
2 SC 1361	Son	Si-N	Uni, In, 25/25V, 0.2A, 0.25W, 140MHz	7c	TO-92	BC 550	7a	BC 169, BC 184, BC 239, BC 549, ++
2 SC 1362		Si-N	=2SC1361: 50/50V	7c	TO-92	BC 550	7a	BC 414, BC 550, 2SC2240, 2SC2459, ++
2 SC 1363	Son	Si-N	Uni, 25/25V, 0.2A, 0.25W, 140MHz	7c	TO-92	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 SC 1364		Si-N	=2SC1363: 50/50V	7c	TO-92	BC 546	7a	BC 167, BC 182, BC 237, BC 547, ++
2 SC 1365	Nec	Si-N	UHF A,Drv, 45/25V, 0.3A, 1.7GHz, F<4/Gp=17dB(200M)	2a	TO-39			2SC1199, 2SC1252...1253, 2SC2852
2 SC 1366		Si-N	=2SC1365: 2GHz, F=3/Gp=18dB(200MHz)	2a	TO-39			2SC1253, 2SC2852
2 SC 1367(A)	Hit	Si-N	TV-VA, 1000/600(A=1000/700)V, 1A, 50W, 6MHz	23a	TO-3	(2SC1413)*	23a	BU 204...206, 2SC1101, 2SC1167, 2SD1095++
2 SC 1368	Hit	Si-N	P, 25/25V, 1.5/3A, 8W, 180MHz (2SA738	14h	TO-126	BD 139	14h	BD 135, BD 226, BD 375, 2SD1380, ++
2 SC 1372	Fui	Si-N	Uni, 30/20V, 0.2A, 0.2W, 250MHz	7c	TO-92	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 SC 1373	Hit	Si-N	Uni, 25/10V, 0.1A, 0.3W, <100/325ns	2a	TO-18	BC 546	7a	BC 238, BC 548, BSV 62...63, 2N706A, ++
2 SC 1374	Hit	Si-N	SS, 25/13V, 0.1A, 0.3W, >600MHz, <13/16ns	2a	TO-18			BSV 89...92, BSX 92...93, 2N2368...69(A),++
2 SC 1375	Hit	Si-N	SS, 25/10V, 0.1A, 0.3W, <45/60ns	2a	TO-18			BSV 89...92, BSX 92...93, 2N2368...69(A),++
2 SC 1376	Hit	Si-N	SS, 40/15V, 0.5A, 0.3W, 590MHz, <25/40ns	2a	TO-18			BSS 10, BSX 26, BSX 39, 2N3261
2 SC 1377	Tos	Si-N	AM SSB P, 90/55V, 6A, 100MHz, PQ=8W(27MHz/12V)	17j	TO-220	2SC1969	17j	2SC1307, 2SC1944, 2SC1969, 2SC2098
2 SC 1378	Tos	Si-N	VHF P, 40/20V, 4A, 150MHz, PQ=25W(175MHz/13.5V)	55r				BLY 89, MRF 209, 2N5591, 2N6082,
2 SC 1379	Tos	Si-N	VHF P, 40/20V, 7A, 150MHz, PQ=40W(175MHz/13.5V)	60c				-
2 SC 1380	Tos	Si-N	Uni, 55/50V, 0.1A, 0.2W, 80MHz	2a	TO-18	BC 546	7a	BC 167, BC 182, BC 237, BC 547, ++
2 SC 1380 A		Si-N	=2SC1380: In, F<2dB(100Hz)	2a	TO-18	BC 550	7a	BC 414, BC 550, 2SC2240, 2SC2459, ++
2 SC 1381	Tos	Si-N	P, 100/100V, 1A, 5W, 50MHz (2SA681	14h	TO-126	BD 139	14h	BD 139, BD 180, BD 379, 2SC3421, ++
2 SC 1382	Tos	Si-N	P, 80/80V, 0.75A, 5W, 100MHz (2SA682	14h	TO-126	BD 139	14h	BD 139, BD 230, BD 379, 2SA3421, ++
2 SC 1383	Mat	Si-N	Uni, 30/25V, 1/1.5A, 1W, 200MHz (2SA683	7c(9mm)	TO-92L	2SD1207	7c(9mm)	2SC2236, 2SD863, 2SD1207, 2SD1331, ++
2 SC 1384		Si-N	=2SC1383: 60/50V (2SA684	7c(9mm)	TO-92L	2SD1207	7c(9mm)	2SC3328, 2SC4145, 2SD863, 2SD1207
2 SC 1385	Hit	Si-N	S, 60/30V, 0.5A, 0.8W, 800MHz, <40/60ns	2a	~TO-5			BSS 27, BSV 77, 2N5189, 2SC1072, ++
2 SC 1386	Hit	Si-N	S, 70/52V, 1A, 0.8W, 800MHz, <30/55ns	2a	~TO-5			BSS 27, BSV 95, 2N3735, 2SC1069, ++
2 SC 1387	Fui	Si-N	UHF, CATV, 25/20V, 0.15A, 0.5W, 1.6GHz	2a	TO-39			BFR 36, BFW 16, 2SC1068, 2SC1324
2 SC 1388	Fui	Si-N	S, 100/80V, 1A, 0.8W, <50/110ns	2a	TO-39			2SC1069
2 SC 1390	Hit	Si-N	Uni, In, 20/20V, 0.05A, 0.2W, 230MHz, F=0.5dB(1k)	7c	TO-92	BC 546	7a	BC 169, BC 184, BC 239, BC 549, ++
2 SC 1391	Hit	Si-N	Vid P, 300V, 0.1A, 6.5W, 25MHz	22a	TO-66	2SC1505	17j	2SC1505...1507, 2SC1749, 2SC1819, ++
2 SC 1393	Nec	Si-N	VHF Imp In, 30/30V, 20mA, 700MHz, F<3dB(200MHz)	7f	TO-92	2SC2570 A	7f	BF 225, BF 310, BF 314, BF 502, BF 505++
2 SC 1394	Nec	Si-N	VHF Mx, 30/30V, 20mA, 700MHz, <3.5/Gp>20dB(200MHz)	7f	TO-92	2SC2570 A	7f	BF 224, BF 310, BF 314, BF 505, BF 507++
2 SC 1395	Nec	Si-N	VHF Os, 30/15V, 20mA, >600MHz	7c	TO-92	2SC2570 A	7f	BF 377...378, BF 689, BF 763, 2N2857, ++
2 SC 1396		Si-N	=2SC1395: >800MHz	7c	TO-92	2SC2570 A	7f	BF 377...378, BF 689, BF 763, 2N2857, ++
2 SC 1398(A)	Mat	Si-N	P, 70/50(A=70/70)V, 2/3A, 15W, 120MHz (2SA748	17j	TO-220	2SC1398	17j	2SC2528, 2SC3252
2 SC 1399	Nec	Si-N	Uni, 100/80V, 0.05A, 0.25W, 100MHz	7c	TO-92	2SC2632	7c(9mm)	2SCS1890A, 2SC2363, 2SC3245, 2SD756(A)++
2 SC 1400		Si-N	=2SC1399: In, F<3dB(1kHz)	7c	TO-92	2SC2632	7c(9mm)	2SC1775A, 2SC2088, 2SC2240, 2SC2459, ++
2 SC 1401	Fui	Si-N	S P, 400/350V, 30A, 200W, 20MHz, <4/6.5µs	68a				2SC1302, 2SC1470, 2SC2250, 2SD542...543
2 SC 1402	Sak	Si-N	P, 140/80V, 8A, 70W, 10MHz (2SA744	23a	TO-3	2SC3263	18j	BD 245D, 2N3442, 2SD551, 2SD1047, ++
2 SC 1403		Si-N	=2SC1402: 160/100V (2SA745	23a	TO-3	2SC3263	18j	BD 245D, 2N3442, 2SD551, 2SD1047, ++
2 SC 1403 A		Si-N	=2SC1402: 180/120V	23a	TO-3	(2SC3281)*	=16j	BD 245E, BDW 16, 2SC2261...62, 2SD751, ++
2 SC 1404	Mat	Si-N	UHF P, 36/18V, 3.5A, 1GHz, PQ=18W(470MHz/12.5V)	55r	SOT-48/2			BLX 69, 2SC1338
2 SC 1405	Mat	Si-N	VHF Drv.Out, 36/18V, 0.75A, PQ=3.5W(175MHz/13.5V)	51r	TO-131			BLW 17, 2SC1011
2 SC 1406	Mat	Si-N	Uni, 30/25V, 1/1.5A, 1W, 200MHz (2SA751	7c°	TO-92°	BC 639	7c	BC 337...338, BC 635, BC 637, BC 639, ++
2 SC 1407		Si-N	=2SC1406: 60/50V (2SA752	7c°	TO-92L	BC 639	7c	BC 337A, BC 637, BC 639, 2SD667, ++
2 SC 1409(A)	Hit	Si-N	LF P,TV-VA, 200/120V, 2A, 12.5W, 20MHz	17j	TO-220AA	2SD1138	17j	BD 239F, 2SC2660, 2SD 760, 2SD1138, ++
2 SC 1410(A)		Si-N	=2SC1409:	17j	TO-220AB	2SD1138	17j	BD 239F, 2SC2660, 2SD 760, 2SD1138, ++
2 SC 1411		Si-N	Chopper, 6/6/4V, 0.05A, 0.2W, -/1100ns	2a	TO-18			-
2 SC 1412	Fui	Si-N	UHF A,Drv, 45/40V, 0.15A, 0.6W, 1.5GHz	2a	TO-39			BFR 36, BFW 16, 2SC1068, 2SC1324
2 SC 1413	Hit	Si-N	TV-HA, 1200/500V, 5/16A, 50W, 4MHz, sat<10V(5A)	23a	TO-3	BU 208 A	23a	BU 207...209, BU 508, 2SD1099, 2SD1103,++
2 SC 1413 A		Si-N	=2SC1413: 1500/500V	23a	TO-3	BU 208 A	23a	BU 208...209, BU 508, 2SC2928, 2SD954, ++
2 SC 1414	Fui	Si-N	UHF P, 40V, 2A, 1.5GHz, PQ=10W(700MHz/18V)	55r				2SC1087
2 SC 1415	Fui	Si-N	UHF P, 40V, 3A, 1.2GHz, PQ=16W(700MHz/18V)	55r				2SC1087
2 SC 1416(A)	Tos	Si-N	Uni, In, 55/50V, 0.05A, 0.2W, 100MHz	2a		BC 550	7a	BC 414, BC 550, 2SC2240, 2SC2390, ++
2 SC 1417	Hit	Si-N	HF, 20/15V, 0.03A, 300MHz	9b		BF 255	7d	BF 240...241, BF 254...255, BF 594...595,++
2 SC 1418	Hit	Si-N	P, 50/50V, 2A, 20W, 5MHz (2SA754	17j	TO-220AA	2SC1398	17j	BD 239, 2SC1398, 2SC2528, 2SC3252, ++
2 SC 1419		Si-N	=2SC1418:	17j	TO-220AB	2SC1398	17j	BD 239, 2SC1398, 2SC2528, 2SC3252, ++
2 SC 1420	Fui	Si-N	UHF, 15/10V, 0.07A, 0.3W, 66Hz, F=6dB(2GHz)	51r				2SC2876, 2SC3603
2 SC 1421	Fui	Si-N	UHF, 15/10V, 0.03A, 0.25W, 5GHz	51r				BFG 91, BFP 91, BFQ 57...58, BFO 74
2 SC 1422	Fui	Si-N	UHF, 15/10V, 0.04A, 0.25W, 5.5GHz	51r				BFG 91, BFP 91, BFQ 57...58, BFO 74
2 SC 1423	Fui	Si-N	UHF, 15/10V, 0.03A, 0.25W, 7GHz, F=6dB(2GHz)	51r				BFG 65, BFQ 66, 2SC3062, 2SC3276
2 SC 1424	Nec	Si-N	VHF/UHF Imp In, 30/14V, 0.05A, 2GHz, F<4dB(500MHz)	5g	TO-72	2SC2570 A	7f	BF 377...378, BFR 37, BFF 55, BFW 30, ++